VHF Receiver Parts List — (Continued)

Quantity	Part Number	Description	Symbol
3		Resistor, fixed comp., 51K, 1/4w 5%	R18, R19
		Resistor, fixed comp., 51K, 1/4w 5%	R30
2		Resistor, fixed comp., 68 ohm, 1/4w 5%	R12, R15
1		Resistor, fixed comp., 150 ohm, 1/4w 5%	R8
1		Resistor, fixed comp., 470K, 1/4w 5%	R4
6		Resistor, fixed comp., 100K, 1/4w 5%	R3, R26
		Resistor, fixed comp., 100K, 1/4w 5%	R27, R29
		Resistor, fixed comp., 100K, 1/4w 5%	R31, R32
1		Resistor, fixed comp., 100 ohm, 1/4w 5%	R2
3		Resistor, fixed comp., 47K, 1/4w 5%	R1, R7
		Resistor, fixed comp., 47K, 1/4w 5%	R9
1	12AU7	Tube, electron, RCA*	V10
1	6J6	Tube, electron, RCA*	V9
1	6AL5	Tube, electron, RCA*	V8
1	6BN6	Tube, electron, RCA*	V7
2	6BA6	Tube, electron, RCA*	V5, V6
3	6CW4	Tube, electron, RCA*	V1, V2
		Tube, electron, RCA*	V3
1	1464-PC	Transformer, disctr, 10.7 MHz, J.W. Miller*	T8
3	1463-PC	Transformer, I.F., 10.7 MHz, J.W. Miller*	T5, T6
		Transformer, I.F., 10.7 MHz, J.W. Miller*	T7
1	MST-115D	Switch, miniature toggle, SPDT, Alco*	S2
1		Inductor, per Figure 27	L10
1		Inductor, per Figure 27	L9
1		Inductor, per Figure 27	L8
1		Inductor, per Figure 27	L4
1		Inductor, per Figure 25	L7
1		Inductor, per Figure 25	L6
1		Inductor, per Figure 25	L5
1		Inductor, per Figure 25	L2
1		Inductor, per Figure 25	L1
1	20A337RB1	Inductor, J.W. Miller*	L3
1	IN751	Diode, zener, 5. 1v Motorola*	CR3
1	IN270	Diode, germanium, Sylvania*	CR2
1	V47E/947	Diode, volt. var. cap., 4-7pf/14V, TRW*	CR1
21	DD-222	Capacitor, 0.0022μf/1000v (GMV), Centralab*	C28, C29
		Capacitor, 0.0022μf/1000v (GMV), Centralab*	C30, C32
		Capacitor, 0.0022μf/1000v (GMV), Centralab*	C33, C35
		Capacitor, 0.0022μf/1000v (GMV), Centralab*	C36
		Capacitor, 0.0022μf/1000v (GMV), Centralab*	C39, C42
		Capacitor, 0.0022μf/1000v (GMV), Centralab*	C49-C58
1	DD-502	Capacitor, 0.005μf/1000v (GMV), Centralab*	C47
1	DA-503	Capacitor, 0.05 μf/30v 100-20%, Centralab*	C46
1	DM-221	Capacitor, 220 pf/1000v 10%, Centralab*	C44
1	DM-10-100J	Capacitor, 10 pf 500v 5%, Elemenco*	C37
5	DD-6-103	Capacitor, 0.01μf/600v (GMV), Centralab*	C27
		Capacitor, 0.01μf/600v (GMV), Centralab*	C31
		Capacitor, 0.01μf/600v (GMV), Centralab*	C34
		Capacitor, 0.01μf/600v (GMV), Centralab*	C38
		Capacitor, 0.01μf/600v (GMV), Centralab*	C48
1	DD-302	Capacitor, 0.003μf/1000v (GMV), Centralab*	C25
1	DM-10-121G	Capacitor, 120 pf/500v 2%, Elemenco*	C22
1	VC-4-G	Capacitor, Variable, .8-18.0 pf, J.F.D.*	C24

*Other equivalent brands can be used.