P Methun
192412021

ULTRA-HIGH-SPEED PHOTONIC TRANSPORT LINK: TECHNOLOGY EVALUATION, IMPAIRMENT MITIGATION, AND INTEGRATED SYSTEM DESIGN

1. INTRODUCTION

Optical fiber communication is widely used in modern telecommunication networks because it provides high bandwidth, low transmission loss, and reliable long-distance data transmission.

With the rapid growth of cloud computing, artificial intelligence, video streaming, and 5G communication, the demand for high-speed optical networks has increased significantly.

Dense Wavelength Division Multiplexing (DWDM) is an advanced optical communication technology that allows multiple optical signals with different wavelengths to travel through a single optical fiber.

This investigation focuses on designing a high-capacity DWDM optical communication system consisting of 32 channels, each transmitting data at 200 Gb/s.

The proposed system uses advanced modulation techniques, optical amplifiers, photonic integrated circuits, and Digital Signal Processing (DSP) to improve transmission performance.

The main objective is to achieve high spectral efficiency, low Bit Error Rate (BER), improved Optical Signal-to-Noise Ratio (OSNR), and reliable long-distance optical communication.

2. OBJECTIVES

1. To design a 32-channel DWDM optical communication system.
2. To achieve a data transmission rate of 200 Gb/s per channel.
3. To investigate different optical modulation formats.
4. To select suitable high-speed optical modulators.
5. To compare different optical amplification techniques.
6. To analyze optical fiber transmission impairments.

7. To implement DSP techniques for signal compensation.
8. To evaluate the performance of the integrated DWDM system.

STAGE 1 – INTERPRET THE COMMUNICATION REQUIREMENT

1.1 System Requirements

The proposed optical communication network must provide high-speed data transmission with minimum signal degradation.

The system consists of 32 DWDM channels, each supporting a transmission capacity of 200 Gb/s.

Important requirements include:

- High aggregate transmission capacity.
- High spectral efficiency.
- Low optical transmission loss.
- Low Bit Error Rate.
- High Optical Signal-to-Noise Ratio.
- Reliable optical amplification.
- Effective dispersion compensation.
- Low power consumption.
- Compact photonic integration.

1.2 Calculation of Total Transmission Capacity

Given:

Number of DWDM channels:

$N = 32$

Data rate per channel:

$R = 200$ Gb/s

Formula:

Total Capacity = Number of Channels × Data Rate per Channel

Substitution:

Total Capacity = 32×200

Total Capacity = 6400 Gb/s

Therefore,

Total DWDM Capacity = 6.4 Tb/s

The proposed optical communication system can transmit 6.4 terabits of data per second across 32 optical channels.

1.3 Spectral Efficiency

Spectral efficiency represents the amount of information transmitted per unit optical bandwidth.

Formula:

Spectral Efficiency = Data Rate / Channel Bandwidth

Assume a DWDM channel spacing of 50 GHz.

Given:

Data Rate = 200 Gb/s

Channel Spacing = 50 GHz

Spectral Efficiency = 200 / 50

Spectral Efficiency = 4 bits/s/Hz

This indicates that the proposed system can transmit four bits per second for every hertz of allocated channel spacing.

1.4 Important Performance Parameters

Parameter	**Description**
Data Rate	200 Gb/s per channel
Number of Channels	32
Aggregate Capacity	6.4 Tb/s
Channel Spacing	50 GHz
Spectral Efficiency	4 bits/s/Hz
Optical Fiber	Single-Mode Fiber
Modulation	DP-16QAM

Optical Amplification	Hybrid Raman-EDFA
Signal Processing	Coherent DSP

1.5 Major Optical Transmission Impairments

Chromatic Dispersion

Chromatic dispersion occurs when different wavelength components of an optical signal travel at different velocities.

This causes pulse broadening and inter-symbol interference.

Polarization Mode Dispersion

Polarization mode dispersion occurs because different polarization components travel at slightly different speeds through the optical fiber.

This produces signal distortion at high data rates.

Nonlinear Effects

Optical fiber nonlinearities occur when high optical power changes the refractive index of the fiber.

Major nonlinear effects include:

- Self-Phase Modulation (SPM)
- Cross-Phase Modulation (XPM)
- Four-Wave Mixing (FWM)

Amplified Spontaneous Emission Noise

Optical amplifiers introduce noise during signal amplification.

This reduces OSNR and can increase BER.

1.6 Investigation Requirement Statement

The proposed system must provide an aggregate transmission capacity of 6.4 Tb/s using 32 DWDM channels operating at 200 Gb/s each.

The system should use spectrally efficient modulation, high-speed optical modulators, lownoise amplification, and coherent DSP techniques.

The final architecture must minimize optical impairments while maintaining reliable performance and practical implementation complexity.

STAGE 2 – INVESTIGATE AND SELECT THE MODULATION / MODULATOR CONFIGURATION

2.1 Introduction

Optical modulation is the process of converting electrical information into optical signals.

The modulation technique determines transmission speed, spectral efficiency, signal quality, and receiver complexity.

Different modulation techniques are investigated to identify the most suitable method for 200 Gb/s DWDM communication.

2.2 Comparison of Modulation Techniques

Modulation Technique	**Bits per Symbol**	**Advantages**	**Limitations**
NRZ-OOK	1	Simple implementation	Low spectral efficiency
PAM4	2	Higher data rate than OOK	Sensitive to noise
DPSK	1	Improved phase-based detection	Requires differential detection
DQPSK	2	Better spectral efficiency	Complex receiver
16-QAM	4	High spectral efficiency	Higher SNR requirement
DP-16QAM	8	High capacity and bandwidth efficiency	Requires coherent DSP
DP-64QAM	12	Very high spectral efficiency	Greater OSNR sensitivity

2.3 Selection of DP-16QAM

Dual-Polarization 16-Quadrature Amplitude Modulation (DP-16QAM) is selected for the proposed DWDM system.

DP-16QAM combines amplitude and phase modulation to transmit multiple bits using each optical symbol.

It also uses two orthogonal polarization states to double the information capacity.

Advantages:

1. High spectral efficiency.
2. Reduced symbol rate for a given bit rate.
3. Suitable for coherent optical communication.
4. Supports high-capacity DWDM transmission.
5. Compatible with advanced DSP compensation. **2.4 Baud Rate**

Calculation

For DP-16QAM:

Number of bits per symbol per polarization: $\log_2(16)$

= 4 bits

Number of polarizations = 2

Total bits per dual-polarization symbol:

4 × 2 = 8 bits

Given:

Bit Rate = 200 Gb/s

Formula:

Symbol Rate = Bit Rate / Bits per Symbol

Symbol Rate = 200 / 8

Symbol Rate = 25 GBaud

Therefore, a DP-16QAM system requires a symbol rate of 25 GBaud to transmit a gross data rate of 200 Gb/s.

PAM4 Calculation

PAM4 transmits two bits per symbol.

Symbol Rate = 200 / 2

Symbol Rate = 100 GBaud

Comparison

Parameter	PAM4	DP-16QAM
Gross Data Rate	200 Gb/s	200 Gb/s
Bits per Symbol	2	8
Symbol Rate	100 GBaud	25 GBaud
Receiver	Direct Detection	Coherent Detection
Spectral Efficiency	Lower	Higher

The DP-16QAM technique requires a significantly lower symbol rate than single-polarization PAM4 for the same gross data rate.

These calculations exclude forward error correction overhead and framing overhead.

2.5 Investigation of Optical Modulation Mechanisms

Electro-Optic Modulation

Electro-optic modulation changes the optical properties of a material using an applied electric field.

It provides high-speed modulation and is suitable for optical communication systems.

Acousto-Optic Modulation

Acousto-optic modulation uses acoustic waves to control light.

It is commonly used for optical switching and frequency shifting but is generally unsuitable for directly generating very-high-speed communication symbols.

Thermo-Optic Modulation

Thermo-optic modulation changes the refractive index of a material through temperature variation.

It is useful for optical tuning but has a relatively slow response.

Magneto-Optic Modulation

Magneto-optic modulation uses magnetic fields to modify optical polarization.

It is commonly used in optical isolators and Faraday rotators.

Kerr Effect

The optical Kerr effect causes the refractive index of a material to change with optical intensity.

It is important in nonlinear optical processing and fiber transmission analysis.

2.6 Comparison of Optical Modulator Architectures

Parameter	**Mach-Zehnder Modulator**	**Micro-Ring Resonator**
Operating Principle	Optical interference	Optical resonance
Modulation Bandwidth	High	High, design-dependent
Device Size	Relatively larger	Compact
Thermal Sensitivity	Moderate	High
Optical Bandwidth	Relatively broad	Resonance-limited
Application	Coherent modulation	Compact optical integration

2.7 Selected Modulator

A high-speed Mach-Zehnder Modulator (MZM) is selected.

The Mach-Zehnder Modulator controls optical intensity and phase by changing the phase difference between two optical paths.

For coherent DP-16QAM, a dual-polarization IQ modulator using nested Mach-Zehnder structures is proposed.

Advantages:

1. High modulation speed.
2. Supports amplitude and phase modulation.
3. Suitable for coherent optical communication.
4. Compatible with advanced modulation formats.

5. Provides relatively broad optical operating bandwidth.

DESIGN DECISION 1

I recommend DP-16QAM modulation using a high-speed electro-optic Mach-Zehnder IQ modulator because it supports 200 Gb/s gross transmission at 25 GBaud, provides high spectral efficiency, and is suitable for coherent DWDM optical communication.

STAGE 3 – DEVELOP AND EVALUATE THE OPTICAL AMPLIFICATION CONFIGURATION

3.1 Introduction

Optical signals experience attenuation while traveling through optical fiber.

Optical amplifiers increase signal power without requiring optical-to-electrical conversion.

Amplification is essential for maintaining adequate signal power in long-distance DWDM communication systems.

3.2 Types of Optical Amplifiers

Erbium-Doped Fiber Amplifier (EDFA)

An EDFA uses erbium-doped optical fiber to amplify signals.

It is commonly used in C-band optical communication systems.

Advantages:

- High optical gain.
- Suitable for DWDM systems.
- Good output power capability.
- Mature and reliable technology.

Semiconductor Optical Amplifier (SOA)

An SOA uses semiconductor material to amplify optical signals.

Advantages:

- Compact structure.
- Suitable for photonic integration.
- Electrically pumped operation.

Limitations include nonlinear distortion and inter-channel interactions.

Raman Optical Amplifier

Raman amplification uses stimulated Raman scattering to amplify optical signals.

Advantages:

- Distributed amplification capability.
- Flexible gain spectrum.
- Can improve effective noise performance.

Hybrid Raman-EDFA Amplifier

A hybrid amplifier combines Raman amplification and EDFA amplification.

The Raman amplifier provides distributed gain along the optical fiber, while the EDFA provides additional lumped amplification.

This combination can improve long-distance transmission performance. **3.3**

Comparison of Optical Amplifiers

Amplifier	Gain Characteristics	Noise Performance	Application
EDFA	High gain in erbium bands	Good	Long-distance DWDM
SOA	Broad, device-dependent	Generally higher noise	Integrated optical systems
Raman	Flexible gain spectrum	Low effective noise possible	Long-distance links
Hybrid Raman-EDFA	Combined distributed and lumped gain	Potentially improved OSNR	High-capacity DWDM

3.4 Optical Amplifier Power Calculation

The uploaded assignment requests an amplifier power calculation, but the numerical input and output power values are missing from the provided question.

Therefore, the following values are assumed for an illustrative calculation.

Given:

Number of channels = 32

Input power per channel = −20 dBm

Required output power per channel = 0 dBm

Step 1: Calculate Required Gain

Formula:

Gain (dB) = Output Power (dBm) − Input Power (dBm)

Gain = 0 − (−20)

Required Gain = 20 dB

Step 2: Convert Output Power to Watts

Formula:

P(W) = 10^((P(dBm) − 30)/10)

For 0 dBm:

P = 0.001 W

Therefore,

Output power per channel = 1 mW

Step 3: Calculate Total Output Power

Total Power = Number of Channels × Power per Channel

Total Power = 32 × 0.001

Total Output Power = 0.032 W

Therefore,

Total Output Power = 32 mW

Step 4: Convert Total Output Power to dBm

Formula:

$P(dBm) = 10 \log_{10}(P(mW))$

$P = 10 \log_{10}(32)$

Total Output Power = 15.05 dBm

Final Results

Parameter	**Calculated Value**
Input Power per Channel	−20 dBm

Output Power per Channel	0 dBm
Required Gain	20 dB
Total Output Power	32 mW
Total Output Power	15.05 dBm

These results represent the assumed amplifier operating point, not measured system performance.

3.5 Gain Flattening Filter

A Gain Flattening Filter (GFF) is used to maintain approximately equal amplifier gain across different DWDM wavelengths.

Without gain flattening, some channels may receive more amplification than others.

This can cause unequal signal powers and different OSNR values across the DWDM spectrum.

A gain flattening filter improves channel power uniformity and supports stable WDM operation.

3.6 ASE Noise

Amplified Spontaneous Emission (ASE) is unwanted optical noise produced during amplification.

ASE noise accumulates when multiple optical amplifiers are connected in series.

Higher ASE noise reduces OSNR and increases the probability of bit errors.

The proposed hybrid amplifier configuration is intended to reduce effective noise accumulation while maintaining the required optical signal power.

DESIGN DECISION 2

I recommend a hybrid Raman-EDFA optical amplifier with gain flattening because it combines distributed and lumped amplification, supports long-distance DWDM transmission, and can provide improved OSNR performance compared with a conventional EDFA-only design.

The final gain and noise performance must be confirmed through simulation.

STAGE 4 – INVESTIGATE AND SELECT THE WDM IMPAIRMENT / DSP COMPENSATION CONFIGURATION

4.1 Introduction

Optical fiber communication systems experience signal distortion due to dispersion, nonlinear effects, polarization changes, and noise.

These impairments become more significant in high-speed and long-distance communication systems.

Digital Signal Processing is used in coherent optical receivers to compensate for transmission impairments and recover transmitted information.

4.2 Chromatic Dispersion

Chromatic dispersion occurs because different wavelength components propagate at different group velocities.

This causes optical pulse broadening and interference between adjacent symbols.

A common approximate relation is:

$\Delta T = D \times L \times \Delta\lambda$

Where:

D = Chromatic dispersion coefficient

L = Fiber length

$\Delta\lambda$ = Optical spectral width

Assume:

D = 17 ps/(nm·km)

L = 80 km

$\Delta\lambda$ = 0.1 nm

Calculation:

$\Delta T = 17 \times 80 \times 0.1$

ΔT = 136 ps

The calculated differential group delay across the assumed optical spectral width is 136 ps.

Digital chromatic dispersion equalization is used to compensate for the resulting waveform distortion.

4.3 Polarization Mode Dispersion

Polarization Mode Dispersion occurs when two orthogonal polarization components propagate at different speeds.

PMD can cause pulse distortion and reduce receiver performance.

Adaptive polarization demultiplexing and MIMO equalization are used to compensate for polarization mixing and differential delay.

4.4 Self-Phase Modulation

Self-Phase Modulation occurs when an optical signal changes its own phase through the Kerr nonlinear effect.

SPM can produce spectral broadening and phase distortion.

4.5 Cross-Phase Modulation

Cross-Phase Modulation occurs when the optical power of one wavelength channel affects the phase of another channel.

It is particularly important in multi-channel DWDM systems.

4.6 Four-Wave Mixing

Four-Wave Mixing occurs when multiple optical frequencies interact through fiber nonlinearity and generate new frequency components.

These unwanted components may overlap with existing DWDM channels.

4.7 Optical and Digital Compensation

Compensation Method	**Advantages**	**Limitations**
Dispersion Compensating Fiber	Optical-domain CD compensation	Additional loss and nonlinear effects
Optical Phase Conjugation	Can compensate selected dispersion and nonlinear effects	Requires suitable optical link design

Digital Equalization	Flexible CD and PMD compensation	Requires DSP processing
Digital Backpropagation	Can reduce nonlinear distortion	High computational complexity

4.8 Coherent DSP Processing Techniques

Chromatic Dispersion Equalization

Digital filters are used to compensate for chromatic dispersion.

Frequency-domain equalization is particularly useful for processing large accumulated dispersion.

Polarization Demultiplexing

Polarization demultiplexing separates the two transmitted polarization channels.

A 2 × 2 MIMO adaptive equalizer can recover the original signals and compensate for PMD.

Carrier Phase Estimation

Carrier phase estimation compensates for phase variations caused by laser phase noise and other phase disturbances.

It is especially important for QAM modulation.

Digital Backpropagation

Digital Backpropagation estimates and reverses optical fiber propagation effects using a numerical model.

It can compensate for selected nonlinear distortions, but requires significant processing resources.

4.9 Proposed DSP Receiver Chain

The proposed coherent DSP processing sequence is:

1. Analog-to-Digital Conversion
2. Signal Resampling and Normalization
3. Chromatic Dispersion Compensation
4. Adaptive Polarization Demultiplexing
5. Frequency Offset Estimation

6. Carrier Phase Recovery
7. Symbol Detection
8. Forward Error Correction
9. Recovered Data Output

Digital backpropagation may be added as an optional nonlinear compensation stage.

4.10 Benefits of DSP Compensation

- Reduces chromatic dispersion distortion.
- Compensates for polarization mixing and PMD.
- Improves signal recovery.
- Reduces bit errors.
- Improves tolerance to transmission impairments.
- Supports longer transmission distances.
- Enables advanced coherent modulation formats.

DESIGN DECISION 3

I recommend coherent DSP using chromatic dispersion equalization, adaptive MIMO polarization demultiplexing, carrier phase recovery, and optional digital backpropagation because these techniques provide flexible compensation for major optical transmission impairments.

STAGE 5 – EVALUATE THE INTEGRATED WDM TRANSMISSION STRATEGY

5.1 Proposed Integrated DWDM System

The proposed optical communication system combines 32 high-speed optical transmitters, wavelength multiplexing, optical amplification, single-mode fiber transmission, coherent receivers, and digital signal processing.

Each transmitter generates a 200 Gb/s optical signal using DP-16QAM modulation.

The signals are combined using an Arrayed Waveguide Grating (AWG) multiplexer.

The combined optical signal travels through single-mode fiber and is amplified using a hybrid Raman-EDFA amplification system.

At the receiver, an AWG demultiplexer separates the individual wavelength channels.

Coherent receivers and DSP blocks recover the transmitted data.

5.2 Major System Components

Optical Transmitter

The transmitter converts electrical information into modulated optical signals.

It includes:

- Laser source
- Electrical data generator
- High-speed IQ modulator
- Polarization multiplexing components

AWG Multiplexer

The AWG multiplexer combines multiple wavelength channels into one optical fiber.

Optical Isolator

An optical isolator prevents unwanted reflected light from traveling backward into sensitive optical devices.

Optical Fiber

Single-mode optical fiber provides the transmission medium for high-speed optical communication.

Hybrid Optical Amplifier

The hybrid Raman-EDFA amplifier compensates for optical transmission losses.

AWG Demultiplexer

The AWG demultiplexer separates the received wavelength channels.

Coherent Receiver

The coherent receiver detects the amplitude and phase information of the optical signal using a local oscillator.

Digital Signal Processor

The DSP unit compensates for optical impairments and recovers the transmitted data.

5.4 Working Principle

1. Electrical data is generated at a rate of 200 Gb/s for each channel.
2. Laser sources generate optical carriers at different wavelengths.
3. DP-16QAM modulators encode the electrical information onto optical signals.
4. An AWG multiplexer combines the 32 wavelength channels.
5. The combined signal is transmitted through single-mode optical fiber.
6. Hybrid Raman-EDFA amplification compensates for optical power loss.
7. An AWG demultiplexer separates the received wavelength channels.
8. Coherent optical receivers detect the amplitude and phase of the received signals.
9. DSP algorithms compensate for dispersion, polarization distortion, and phase noise.
10. Forward error correction and data recovery reconstruct the transmitted information.

5.5 Overall System Performance

Parameter	Proposed Value

Number of Channels	32
Data Rate per Channel	200 Gb/s gross
Aggregate Data Rate	6.4 Tb/s gross
Modulation Format	DP-16QAM
Symbol Rate	25 GBaud
Channel Spacing	50 GHz
Nominal Spectral Efficiency	4 bits/s/Hz
Optical Amplifier	Hybrid Raman-EDFA
Transmission Medium	Single-Mode Fiber
Receiver	Coherent Optical Receiver
Compensation	Digital Signal Processing

5.6 Advantages of the Proposed System

1. Provides high transmission capacity.
2. Improves spectral efficiency.
3. Supports long-distance optical communication.
4. Enables advanced signal processing.
5. Supports wavelength-based network scalability.
6. Reduces the need for separate optical fibers.
7. Allows photonic component integration.

5.7 Limitations

1. High implementation cost.
2. Complex coherent receiver architecture.
3. High DSP computational requirements.
4. Increased power consumption.

5. Sensitivity to nonlinear optical impairments.
6. Need for precise laser frequency control.

DESIGN DECISION 4

I recommend the proposed 32-channel DP-16QAM DWDM architecture for further development because it provides a gross aggregate capacity of 6.4 Tb/s, achieves a nominal spectral efficiency of 4 bits/s/Hz with 50 GHz spacing, and supports coherent impairment compensation.

Deployment should depend on successful OSNR, BER, power, and interoperability verification.

STAGE 6 – VERIFY AND CRITICALLY EVALUATE THE COMPLETE WDM SYSTEM

6.1 Verification of Design Requirements

The proposed system must be evaluated to determine whether it satisfies the communication requirements.

Verification includes transmission capacity, spectral efficiency, modulation performance, amplifier operation, DSP compensation, and standards compliance. **6.2 System Verification Table**

Performance Parameter	**Target Value**	**Design / Evidence Value**
Aggregate Capacity	6.4 Tb/s	6.4 Tb/s gross, analytically calculated
Number of Channels	32	32 selected
Channel Data Rate	200 Gb/s	200 Gb/s gross
Modulation Format	High spectral efficiency	DP-16QAM selected
Symbol Rate	Suitable for 200 Gb/s	25 GBaud calculated
Spectral Efficiency	High	4 bits/s/Hz nominal

Modulator	High-speed operation	EO Mach-Zehnder IQ modulator proposed
Amplifier Gain	Meet power budget	20 dB illustrative requirement
Total Amplifier Output	Meet channel power target	15.05 dBm illustrative
OSNR	Meet receiver/FEC threshold	Simulation required
BER	Meet selected FEC requirement	Simulation required
Dispersion Compensation	CD and PMD mitigation	Coherent DSP proposed
Nonlinear Compensation	Improved nonlinear tolerance	Optional DBP proposed

6.3 Proposed Simulation Method

The proposed system can be simulated using OptiSystem, OptSim, or MATLAB.

Step 1: Transmitter Design

Create 32 optical transmitters with different wavelengths.

Configure each transmitter for 200 Gb/s gross data transmission using DP-16QAM modulation.

Step 2: Wavelength Multiplexing

Combine the optical channels using a DWDM multiplexer.

Configure a nominal channel spacing of 50 GHz.

Step 3: Optical Fiber Transmission

Connect the multiplexer output to a single-mode optical fiber model.

Include attenuation, chromatic dispersion, polarization effects, and nonlinear propagation.

Step 4: Optical Amplification

Insert a hybrid Raman-EDFA amplification model.

Evaluate amplifier gain, ASE noise, and output power.

Step 5: Optical Receiver

Use a coherent receiver to detect the transmitted optical signal.

Convert the received analog signals into digital samples.

Step 6: DSP Compensation

Apply chromatic dispersion compensation, polarization demultiplexing, frequency correction, and carrier phase recovery.

Step 7: Performance Evaluation

Measure:

- Optical Signal-to-Noise Ratio
- Bit Error Rate
- Q-factor
- Optical spectrum
- Received constellation
- Signal power

6.4 Expected Simulation Observations

Optical Spectrum

The optical spectrum should display 32 wavelength channels with approximately uniform channel spacing.

Constellation Diagram

The DP-16QAM constellation should contain 16 symbol positions for each polarization.

Noise and transmission impairments will cause the received symbols to spread around their ideal positions.

BER Performance

The BER is expected to decrease as the received signal quality improves.

However, the exact BER depends on OSNR, nonlinear impairments, DSP performance, and receiver design.

Q-Factor

The Q-factor provides an indication of signal quality.

Higher signal quality generally corresponds to improved Q-factor and reduced error probability.

Launch Power

Increasing optical launch power initially improves received signal strength.

However, excessive launch power increases nonlinear fiber distortion.

Therefore, an optimum launch power must be determined through simulation.

7. FINAL SYSTEM DESIGN PARAMETERS

The following values are proposed starting parameters for simulation rather than experimentally verified results.

Parameter	**Proposed Value**
System Type	DWDM Optical Communication
Number of Channels	32
Gross Data Rate	200 Gb/s/channel
Aggregate Gross Capacity	6.4 Tb/s
Modulation	DP-16QAM
Symbol Rate	25 GBaud
Channel Spacing	50 GHz
Approximate Operating Band	C-band

Center Reference Wavelength	Approximately 1550 nm
Laser Linewidth	100 kHz target
Optical Modulator	EO Mach-Zehnder IQ Modulator
Modulator Vπ	3 V design target
Optical Fiber	SMF-28-type Single-Mode Fiber
Fiber Attenuation	0.2 dB/km assumed
Chromatic Dispersion	17 ps/(nm·km) assumed
Example Fiber Span	80 km
Amplifier	Hybrid Raman-EDFA
Amplifier Gain	20 dB illustrative target
Gain Flattening	GFF
Receiver	Coherent Optical Receiver
DSP	CD, PMD, phase recovery, optional DBP

8. FINAL ENGINEERING DECISION

WOULD YOU DEPLOY THE INVESTIGATED AND DESIGNED WDM SYSTEM?

Decision: YES – CONDITIONALLY, AFTER SUCCESSFUL VALIDATION

The proposed 32-channel DWDM optical communication system is technically promising for high-capacity optical transport applications.

The system provides a calculated gross aggregate transmission capacity of 6.4 Tb/s using 32 channels operating at 200 Gb/s each.

DP-16QAM modulation provides high spectral efficiency while reducing the required symbol rate compared with simpler modulation formats.

The Mach-Zehnder IQ modulator supports the amplitude and phase modulation required for coherent optical transmission.

The hybrid Raman-EDFA amplification architecture is proposed to compensate for optical fiber attenuation while improving noise performance.

Coherent DSP provides flexible compensation for chromatic dispersion, polarization mode dispersion, and carrier phase disturbances.

Digital backpropagation may provide additional nonlinear compensation when its performance benefit justifies its computational cost.

However, the system should not be deployed commercially until simulation and experimental verification demonstrate acceptable BER, OSNR margin, nonlinear tolerance, power consumption, and standards compliance.

Therefore, the proposed architecture is recommended for simulation-based development and prototype evaluation, followed by deployment only after the required performance targets are achieved.

9. CONCLUSION

This investigative assignment examined the design and performance of an ultra-high-speed DWDM optical communication system.

The proposed system uses 32 optical channels, each supporting a gross data rate of 200 Gb/s, providing a total gross capacity of 6.4 Tb/s.

Different modulation techniques, optical modulators, amplifier technologies, and signal compensation methods were investigated.

DP-16QAM was selected because of its high spectral efficiency and suitability for coherent optical transmission.

A Mach-Zehnder IQ modulator was selected for high-speed optical modulation.

Hybrid Raman-EDFA amplification was proposed to compensate for fiber attenuation and support long-distance transmission.

Coherent DSP techniques were recommended to compensate for chromatic dispersion, polarization distortion, and phase noise.

The investigation demonstrates that the proposed DWDM architecture is a suitable candidate for next-generation high-capacity optical communication networks.

Further simulation and experimental validation are required before confirming deployment feasibility.

10. REFERENCES

1. G. P. Agrawal, *Fiber-Optic Communication Systems*, Wiley.
2. G. Keiser, *Optical Fiber Communications*, McGraw-Hill.
3. J. M. Kahn and K.-P. Ho, “Spectral Efficiency Limits and Modulation/Detection Techniques for DWDM Systems,” IEEE Journal of Selected Topics in Quantum Electronics.
4. ITU-T G.698 Series – Multichannel DWDM Optical Interfaces.
5. IEEE 802.3ct – Ethernet Physical Layer Specifications.
6. IEEE 802.3ck – Electrical Interfaces for High-Speed Ethernet.
7. OIF – Common Electrical Interface Implementation Agreements.
8. Optiwave – OptiSystem Optical Communication System Simulation Software.