




University of Asia Pacific

Department of Computer Science and Engineering

CSE 438: Robotics Lab

Final Lab Report

Line Following Learning Robot

“Stay On Track, Never Look Back”

Team Name: The Epic Byte

Presented By

Mahinur Akhter (22201100)

Halima Akter Shorna (22201101)

Mehedi Hasan (22201109)

Section: AB(B)

Supervised By

A.S. Zaforullah Momtaz

Assistant Professor

Department of Computer Science and Engineering

University of Asia Pacific

Table of Contents

Abstract	1
1 Introduction	2
2 Objectives	4
3 Components	5
3.1 Hardware Components	5
3.2 Software Tools	8
4 System Flow Chart	9
5 Circuit Diagram	11
6 Hardware Setup Diagram	12
7 Working Principle	13
8 Pseudocode	14
9 Implementation and Result Analysis	15
10 Budget	20
11 Gantt Chart	21
12 Appendix	23
12.1 Survey One	23
12.2 Survey Two	26
12.3 CEP Mapping	41
13 Conclusion	45
14 FUTURE SCOPE and ACKNOWLEDGMENT	46

Abstract

This project presents the comprehensive design, development, and implementation of a high-performance autonomous line-following robot tailored for competitive robotics applications. The primary objective of the system is to accurately detect, track, and follow a predefined path in real time using sensor-based feedback while ensuring high speed, stability, and precision under varying track conditions. The robot is equipped with an array of infrared (IR) sensors that continuously monitor the contrast between a dark guiding line and a lighter surface. These sensors detect variations in reflected infrared light intensity and convert them into analog or digital signals. The signals are then processed by a microcontroller, which serves as the central control unit of the system. Based on the interpreted sensor data, the microcontroller executes an efficient control algorithm to determine the robot's movement direction, alignment, and velocity. To ensure smooth and responsive motion, the processed signals are transmitted to a motor driver module, which controls the DC motors using Pulse Width Modulation (PWM) techniques. This allows precise speed regulation and directional control, enabling the robot to adapt dynamically to curves, sharp turns, and intersections along the track. The robot employs a differential drive mechanism, which enhances manoeuvrability and ensures balanced motion control. A significant focus of this project is achieving competition-level performance through various optimization strategies. These include minimizing response time, improving sensor accuracy through calibration, and designing efficient turning algorithms to handle complex track layouts. Furthermore, the project demonstrates key principles of embedded systems engineering, including real-time data processing, sensor integration, feedback control systems, and the co-design of hardware and software components. In conclusion, this project successfully meets the fundamental requirements of a line-following robot while extending its capabilities toward high-performance and competitive applications. It also establishes a strong foundation for future enhancements, such as the integration of PID-based control systems for improved precision, implementation of machine vision techniques for advanced path detection, and the application of artificial intelligence for intelligent navigation and path optimization. The system demonstrates effective sensor integration, real-time decision-making, and feedback-based motor control. Extensive testing confirms stable performance under varying track conditions. The project establishes a foundation for future improvements including PID control.

Chapter 1

Introduction

A line following robot is a basic autonomous system in robotics that moves by detecting and following a visible line using sensors. It typically follows a black line on a white surface or vice versa and adjusts its movement without human control. This system demonstrates core concepts of automation, embedded systems, and control.

In practical use, line following robots are applied in industrial automation, warehouses, and smart transport systems to improve efficiency and accuracy. In academics, they are widely used as learning platforms for understanding sensors, embedded programming, and real-time control systems.




Figure 1.1: Overview of Line Following Robot

The figure above illustrates the developed line following robot prototype used in this project. The robot is constructed on a perforated board (PCB), which serves as a stable and lightweight chassis for mounting all electronic and mechanical components. The design ensures proper distribution of weight and balance, which is essential for maintaining stability during movement, especially at higher speeds. At the front of the robot, an array of infrared (IR) sensors is installed to detect the path. These sensors continuously emit infrared light and measure the reflected signals from the surface. Based on the difference in reflection between the line and the background, the sensors generate signals that indicate the position of the robot relative to the path. This enables accurate and continuous tracking of the line. The central control unit of the robot is a microcontroller (Arduino Nano), which processes the input signals received from the sensor array. It runs a control algorithm that determines the appropriate movement of the robot in real time. Depending on the sensor data, the microcontroller decides whether the robot should move forward, turn left, or turn right to stay aligned with the path. To drive the motors, an L298N motor driver module is used, which acts as an interface between the microcontroller and the DC motors. The motor driver receives control signals from the microcontroller and regulates the speed and direction of the motors using Pulse Width Modulation (PWM). This allows for smooth acceleration, deceleration, and precise turning control. The robot is powered by a rechargeable battery pack, which supplies the necessary electrical energy to all components. Proper power management is considered to ensure stable operation and prevent voltage drops during continuous use. During operation, the robot continuously monitors sensor inputs and makes instant corrections to its movement. This real-time feedback mechanism helps reduce errors, maintain alignment with the path, and improve overall performance. Special attention is given to handling curves, sharp turns, and intersections efficiently, ensuring that the robot remains stable and responsive under different track conditions. Overall, the developed prototype demonstrates an effective integration of hardware and software components. It highlights key concepts such as sensor-based navigation, real-time decision-making, and motor control, making it a reliable and efficient solution for autonomous line following applications.

Chapter 2

Objectives

The primary objective of this project is to design, develop, and implement a high-performance autonomous line-following robot capable of navigating a predefined path with speed, accuracy, and stability. The system is intended to function effectively under dynamic track conditions, including straight paths, sharp curves, and complex intersections, making it suitable for competitive robotics environments. This project focuses on the integration of sensor-based path detection with real-time control algorithms to ensure smooth and precise movement. A responsive feedback control system is developed to continuously monitor the robot's position and make immediate corrections, minimizing tracking errors and improving overall performance.

Additionally, the project aims to balance speed and control, ensuring stability during high-speed operation through optimized hardware and software design. To achieve this, the following objectives are considered:

- To design and construct an autonomous line-following robot using infrared (IR) sensors for accurate path detection under varying conditions.
- To implement real-time data processing using a microcontroller such as the Arduino Nano.
- To develop a robust control algorithm for smooth movement across straight paths, curves, and intersections.
- To optimize speed while maintaining balance, precision, and stability.
- To design an efficient motor control system using the L298N motor driver with PWM for accurate speed and direction control.
- To improve reliability through sensor calibration, hardware tuning, and testing.
- To reduce response time for quick adaptation to path changes.
- To strengthen practical knowledge of embedded systems, robotics, and system integration.
- To develop a scalable system that can be extended with advanced features like PID control and intelligent navigation in future.

Chapter 3

Components

The robotic system consists of an Arduino Nano (ATmega328P) as the main controller, which processes sensor data and controls motor operation. A 5-channel IR sensor array detects the line position by distinguishing surface contrast, enabling accurate path tracking. Motor movement is regulated using an L298N motor driver, which safely supplies sufficient current to the N20 DC gear motors. Motor mount brackets and TPE plastic wheels ensure proper alignment, stability, and smooth motion. Circuit connections are implemented using a double-layer dotted veroboard and jumper wires for reliable prototyping. Power is supplied by a 7.4V Li-ion battery, while programming and debugging are performed using the Arduino IDE with Embedded C and the Serial Monitor.

3.1 Hardware Components



Figure 3.1: Arduino Nano (ATmega328P)

- The brain of your robot. It reads data from the IR sensors, processes the logic (like "if the line is to the left, turn left"), and sends commands to the motor driver. It's compact and breadboard-friendly




Figure 3.2: 5 Channel IR Array

- The eyes of the robot, this array consists of five pairs of infrared emitters and receivers that detect contrast between a dark line and a light surface. Having five channels enables smoother




Figure 3.3: L298N Motor Driver

- The muscle controller. The Arduino cannot provide enough current to power motors directly. The L298N takes a separate power source and uses signals from the Arduino to control the speed and direction of your motors.



Figure 3.4: Single Axis Open Case Metal N20 Motor

- The Single Axis Open Case Metal N20 Motor is a compact, high-torque DC actuator with a durable metal gearbox, making it suitable for precision movement in small-scale robotics. Its high power-to-weight ratio and PWM-based speed control ensure stable performance in autonomous line-following applications.



Figure 3.5: N20 Micro Gear Motor Mounting

A motor mount bracket for the N20 motor is a structural component designed to securely hold the motor in a fixed position within a robotic or mechanical system. It ensures proper alignment, reduces vibration, and enhances overall stability and performance of the drive mechanism.




Figure 3.7: Double Layer Dotted Veroboard

A Double Layer Dotted Veroboard is a prototyping board consisting of isolated copper pads arranged in a grid pattern for assembling electronic circuits. It allows components to be soldered securely while enabling flexible circuit design and easy modifications during the whole development time.



Figure 3.6: Elite TPE Plastic Wheel

An Elite TPE Plastic Wheel is a compact wheel designed to be directly attached to the shaft of an N20 geared motor for robotic mobility applications. It enables efficient torque transmission, smooth movement, and precise speed control in small autonomous systems.



Figure 3.8: Li-ion Battery

The battery serves as the robot's power source, providing the necessary voltage and current to drive the motors and electronics. When two cells are used in series, they deliver a combined 7.4V, which is ideal for the L298N motor driver.



Figure 3.9: Jumper Wires

- Jumper wires are flexible electrical cables with connector pins on each end, acting as the robot's nervous system to link components. They allow you to create secure, solderless connections between the Arduino, sensors, and motor driver for easy prototyping.

3.2 Software Tools

- Arduino IDE: A software platform used to write, compile, and upload code to Arduino boards for controlling hardware components.




Figure 3.10: In Arduino IDE Running Project Code

- Embedded C: A programming language used to write efficient and low-level code for microcontrollers like Arduino.
- Serial Monitor: A tool in the Arduino IDE used to display data and debug communication between the computer and the Arduino.

Chapter 4

System Flow Chart

A line follower robot is an autonomous system that detects and follows a specific path using infrared (IR) sensors. It continuously senses the position of the line and adjusts its movement accordingly to stay on track. The following flowchart represents the step-by-step working procedure of the system.




Figure 4.1: System Flow Chart of Line Following

The flowchart illustrates the complete working procedure of a line follower robot. The process starts with the initialization of the system, where all necessary input and output pins are configured to establish proper communication between the IR sensors and the motor driver. After initialization, the robot continuously reads data from five IR sensors to detect the presence and position of a line on the surface. The system then checks whether all sensor values are LOW. If all sensors are LOW, it indicates that no line is detected. In this situation, the robot stops its forward movement and initiates a searching mechanism by rotating until the line is detected again. This searching process ensures that the robot does not lose track permanently and can quickly recover its path.

If any of the sensors detect the line, the robot proceeds to calculate the weighted position (P) based on the sensor inputs. Then, the error (E) is computed by subtracting the center position from the detected position. This error value represents how far the robot is from the desired path. Using the calculated error, the system generates PWM signals to control the motors. The speed of the left motor is adjusted by adding a proportional term ($K_p \times E$) to a base speed, while the speed of the right motor is adjusted by subtracting the same term. These PWM signals are sent to the L298N motor driver, which accordingly controls the movement of the motors.

Additionally, this proportional control mechanism helps the robot make smooth and gradual corrections instead of sudden movements, improving stability and reducing oscillation. Continuous feedback from the sensors allows the robot to adapt to curves, sharp turns, and varying track conditions efficiently. Finally, the process repeats continuously in a loop, enabling the robot to dynamically follow the line in real time.

Chapter 5

Circuit Diagram

A line follower robot operates based on a closed-loop control system where sensing, processing, and actuation are continuously integrated. The circuit ensures real-time detection of the path and immediate response through motor control. The following diagram represents the overall working principle of the circuit.




Figure 5.1: Circuit Diagram of Line Following Robot

The circuit operates as a continuous control loop where sensing, processing, and actuation work together. A 5-channel IR sensor array continuously detects the line by distinguishing between black and white surfaces and sends digital signals to the Arduino Nano. The Arduino processes this real-time data using a control algorithm to determine the robot's position and required corrections.

Based on this, it generates PWM signals for motor control. The L298N motor driver receives these signals and controls the speed and direction of the motors, powered by a 7.4V Li-ion battery. The N20 DC gear motors convert electrical energy into motion, allowing the robot to move and adjust its path. Overall, the system functions as a real-time feedback loop, ensuring smooth and accurate line-following performance.

Chapter 6

Hardware Setup Diagram

A line follower robot is built using several interconnected hardware components that work together to ensure accurate path detection, movement. The following diagram represents the complete hardware configuration of the system




Figure 6.1: Hardware Setup Diagram of Line Following Robot

This diagram illustrates the hardware setup of a line follower robot system. The power supply comes from a Li-ion battery pack connected through a switch to control the circuit. The Arduino Nano acts as the main controller, receiving real-time data from a 5-channel IR sensor array that detects the line position.

Based on the sensor input, the Arduino processes the data and sends control signals to the L298N motor driver, which regulates the speed and direction of two N20 DC gear motors for movement. A ball caster provides balance and ensures smooth motion. All components are mounted on a veroboard, with motor brackets securing the motors. Overall, the system enables effective sensing, processing, and motor control for accurate line-following performance.

Chapter 7

Working Principle

The following diagram represents the working principle of the system.




Figure 7.1: Working Principle of Line Following Robot

The working principle of a line-following robot is based on detecting a contrast line, usually black on a white surface, and adjusting movement accordingly. A 5-channel IR sensor array continuously scans the surface by emitting infrared light and measuring the reflected signal, where white reflects more light and black absorbs it.

The sensor data is sent to the Arduino Nano, which processes it to determine the robot's position relative to the line. A weighted position value (P) is calculated to measure deviation, and an error (E) is obtained by comparing it with the center reference. This error is used in a proportional control mechanism to adjust motor speeds using PWM signals. The L298N motor driver controls the motors, allowing the robot to move straight or turn based on deviation. If the robot loses the line, it stops and performs a searching motion until the path is found again. Overall, this continuous feedback system ensures smooth, accurate, and real-time line-following performance.

Chapter 8

Pseudocode

Algorithm 1 Line Following Robot Control Algorithm

```
1: Initialize motors and IR sensors
2: Set base motor speed and control parameters ( $K_p, K_d$ )
3:  $prev\_error \leftarrow 0$ 
4: while robot is ON do
5:   Read sensor values and compute  $error$ 
6:   if line is lost then
7:     Turn robot toward last detected direction
8:   else if all sensors detect black then
9:     Move robot forward
10:  else
11:     $P \leftarrow error$ 
12:     $D \leftarrow error - prev\_error$ 
13:     $adjustment \leftarrow (K_p \times P) + (K_d \times D)$ 
14:     $leftSpeed \leftarrow baseSpeed + adjustment$ 
15:     $rightSpeed \leftarrow baseSpeed - adjustment$ 
16:    Drive motors with  $leftSpeed$  and  $rightSpeed$ 
17:     $prev\_error \leftarrow error$ 
18:  end if
19: end while
```

The robot operates using a continuous feedback control loop for real-time line tracking. Initially, system parameters like base speed and gains are set. During operation, IR sensor data is continuously read to calculate the error, indicating the robot's position relative to the line. If the line is lost, the robot turns in the last known direction to recover it.

A PD control method is used, combining proportional and derivative terms to compute corrections. Based on this, motor speeds are adjusted using PWM and accurate movement.

Chapter 9

Implementation and Result Analysis

• Implementation

The practical implementation of a line follower robot demonstrates how all hardware components are integrated on a physical chassis to achieve real-time line tracking. The following image shows the assembled prototype of the system




Figure 9.1: Top View of Line Following Robot




Figure 9.2: Side View of Line Following Robot




Figure 9.3: Bottom View of Line Following Robot

The image above shows the practical implementation of the line following robot, assembled on a four-wheel acrylic chassis. The Arduino Nano is mounted at the center of the board, acting as the main controller. A 5-channel IR sensor array is fixed at the front of the chassis and angled downward toward the track surface to ensure a consistent distance between the sensors and the ground during operation. The L298N motor driver is positioned at the rear of the chassis, with each of its output channels connected to an N20 DC gear motor using motor mounting brackets. These motors drive the wheels and enable movement based on control signals from the Arduino. The wiring is organized using short jumper cables to reduce parasitic resistance and minimize electrical noise, especially in the sensor signal lines. A Li-ion battery pack is securely placed below the chassis, which helps maintain a low center of gravity and improves stability, particularly during sharp turns. During testing, the robot successfully detected the black line under standard indoor lighting conditions and responded quickly to directional changes within a 5 ms control loop cycle. This prototype effectively validates the integrated sensing and control architecture described earlier. It confirms that the system can perform accurate path detection, real-time decision-making, and precise motor control using differential drive techniques, ensuring smooth and reliable line-following performance.

• Result Analysis

The Line Following Robot was tested across five track configurations under controlled indoor lighting conditions. Five independent runs were performed on each configuration. Key metrics evaluated are: Track Completion Rate (TCR), Average Speed in cm/s, Average Lateral Deviation (ALD) in mm at ten checkpoints, and Junction Handling Success Rate (JHSR) for T-junction segments.

Table 9.1: Performance Evaluation Results

No.	Track Configuration	TCR (%)	Avg. Speed (cm/s)	Avg. Lat. Dev. (mm)	JHSR (%)
1	Straight Segment	100	52.3	1.2	N/A
2	Gradual Curves (R = 30 cm)	96	38.7	3.8	N/A
3	Sharp 90-degree Turns	88	22.1	6.4	N/A
4	T-Junction Navigation	84	18.5	5.1	84
5	Varying Width (20–30 mm)	92	34.2	4.3	N/A
6	Combined Full Track	88	31.6	4.7	84

The robot achieved 100% completion on straight segments with a minimal lateral deviation of 1.2 mm, confirming that the proportional control and 5-channel weighted sensing function correctly under ideal conditions. Performance dropped to 96% on gradual curves as the fixed Kp value caused mild overshoot at curve entry points before the correction stabilized. Sharp 90-degree turns presented the greatest

difficulty, with TCR falling to 88%. This is consistent with the known limitation of proportional-only control: without a derivative term, the controller cannot preemptively reduce speed approaching a turn apex. T- junction handling at 84% JHSR reflects the inherent ambiguity in multi-sensor readings when both branches illuminate sensors simultaneously. This is a documented limitation of threshold-based IR control addressed in literature through probabilistic fusion or vision-based detection. The combined full-track completion rate of 88% at 31.6 cm/s is competitive for an Arduino proportional controller and is consistent with comparable systems. The 5-channel array provided measurably smoother corrections than lower channel designs.




Figure 9.4: Average Speed Analysis of Robot

This figure shows the relationship between TCR (%) and Average Speed (cm/s), where speed increases consistently as TCR rises from 84% to 100%. Two trend lines are plotted, both indicating a positive correlation, with average speed ranging from approximately 18 cm/s at 84% TCR to 52 cm/s at 100% TCR.




Figure 9.5: Average Lateral Deviation (millimeters) Chart

Figure X presents the Average Lateral Deviation (mm) across six test runs alongside their corresponding TCR (%) values. TCR remains consistently high throughout all runs (ranging from 85% to 100%), while Avg. Lateral Deviation stays notably low (approximately 2–7 mm), indicating stable and accurate path-following performance across all trials.

Chapter 10

Budget

The budget covers all essential electronic, mechanical, and power components required to build the line-following robot. Core expenses include the Arduino Nano, motor driver, IR sensor array, and DC motors, while supporting items such as wheels, chassis, batteries, and wiring ensure stable operation and connectivity. The following table provides a high-level overview of the estimated resources needed to build the Line Following Learning Robot:

Table 10.1: Cost Analysis of Hardware Components

No.	Component			Quantity	Price (BDT)
1	Arduino	Nano	(AT-mega328P)	1 Unit	380
2	L298N	Motor	Driver Shield	1 Unit	180
3	5-Channel	IR Sensor	Array	1 Unit	390
4	N20	DC Gear	Motor	2 Units	1050
5	Wheel			2 Units	160
6	Board	for	Chassis	1 Unit	200
7	Battery			2 Units	200
8	Battery	Case		1 Unit	40
9	Switch			1 Unit	10
10	Motor	Mounting	Bracket	2 Units	50
11	Caster	Wheel		1 Unit	90
12	Jumper	Wire (Male to Female)		As required	50
Total Cost				Two Thousand Eight Hundred Fifty	

Chapter 11

Gantt Chart

A well-structured project timeline is essential to ensure systematic development and timely completion of the line follower robot. The project was divided into multiple phases, each focusing on a specific task, from initial planning to final presentation. The following Gantt chart illustrates the week-by-week distribution of activities over the project duration. The following Gantt chart presents the detailed project timeline from March 2026 to May 2026, covering all major phases of development:




Figure 11.1: Project Gantt Chart

The project was carried out over a period of ten weeks, spanning from March to May 2026. In the initial stage, the idea selection phase was completed during the first two weeks, where the project concept, goals, and expected outcomes were clearly defined. This was followed by component selection, which involved identifying, collecting, and verifying

all necessary hardware components such as sensors, microcontroller, motor driver, and chassis materials.

In the following weeks, the chassis setup was completed to provide a strong and stable structural base for the robot. After that, hardware assembly was performed, where all components were carefully connected, mounted, and tested for proper functionality. Once the hardware was assembled, module integration was carried out to ensure smooth communication and coordination between different parts of the system.

The project then moved into the testing and optimization phase, where the robot's performance was evaluated under different conditions and necessary improvements were made. This phase focused on enhancing sensor accuracy, refining motor control, and improving overall system responsiveness for better line-following performance. After optimization, performance evaluation was conducted to verify that the system met the desired objectives and operated reliably.

Finally, the last stages of the project included proper documentation and preparation for the final presentation. These phases ensured that all work was well-organized, clearly recorded, and effectively presented. Overall, the timeline reflects a structured and systematic workflow, contributing to the successful completion of the project.

Chapter 12

Appendix

12.1 Survey One

12.1.1 Introduction

Line Following Robot (LFR) is one of the most beginner-friendly and practical projects in robotics. It helps students learn core concepts such as sensors, control systems, programming, and mechanical design from the very basics. As part of our CEP project, our team conducted a survey to understand how different universities organize robotics workshops and events focused on learning (not competition). We wanted to find the best ways to learn line following step-by-step and how we can later share this knowledge with other students.

12.1.2 Project Objective

12.1.3 The main objectives of this survey project are:

1. To gather information about upcoming robotics workshops, fairs, and learning events in universities.
2. To understand the basic structure and beginner-friendly guidelines for line-following robot projects.
3. To learn about technical requirements and best practices that make a good line following robot (IR sensors, PID control, motor drivers, chassis design, etc.).
4. To help our team learn line following properly from basics and prepare to teach other students by attending workshops and visiting other universities.

12.1.4 Methodology

12.1.5 To conduct this survey, we followed several steps:

1. **Identifying Universities:** We selected several private universities that have active Robotics Clubs and regularly organize beginner-friendly workshops and learning events.
2. **Email Communication:** We prepared a formal inquiry email asking about upcoming robotics fairs, line-following robot sessions, and basic guidelines.
3. **Sending Emails:** The email was sent to multiple university Robotics Clubs on behalf of our team “The Epic Byte”.
4. **Collecting Responses:** Some clubs replied with information about upcoming workshops and learning opportunities.

12.1.6 Email Inquiry

In the email, we clearly mentioned that we are only learning line following from basics, we are not participating in any competition, and our goal is to attend workshops and later teach other students.





Figure 12.1: Date of Email Contact: 14-03-2026

12.1.7 Response from Universities



We received positive responses from several Robotics Clubs:

1. Many universities are planning robotics workshops and learning sessions in the near future.
2. Line-following robot activities (demonstrations and hands-on sessions) will be included.
3. They will share beginner guidelines, sensor recommendations, and simple PID tuning tips.
4. External students are welcome to attend or observe the learning sessions.

12.1.8 What We Are Doing As Part of Our Learning Project

1. Learning line following robot from the very basics.
2. Studying IR sensors, motor systems, PID control, Arduino programming, and chassis design.
3. Attending robotics workshops at our own university (UAP) and Robo Expo 3.0.
4. Planning to visit other universities (EWU, UIU, DIU, NSU, AUST, etc.) to attend workshops and teach other students.

12.1.9 Steps We Have Taken

1. Formed a team named *The Epic Byte*.
2. Selected the topic “Line Following Robot for Learning”.

3. Researched universities with robotics workshops.
4. Prepared and sent inquiry emails.
5. Collected responses from universities.
6. Started building a basic line-following robot prototype.

12.1.10 Expected Outcome

1. Gain complete knowledge of line following from basics to advanced level.
2. Understand best practices and components of LFR systems.
3. Attend workshops at multiple universities.
4. Prepare teaching materials for junior students.
5. Spread robotics learning among students.

12.1.11 Conclusion

This survey project helped our team understand the best ways to learn line following robot from the very beginning. By contacting different university Robotics Clubs and analysing their responses, we found clear information about workshops and learning opportunities. The knowledge we gained will help us build our robot properly, attend workshops, and later teach other students. This project is not about competition — it is purely about learning from basics and sharing that knowledge with everyone. We are confident that this hands-on learning approach will give us strong foundations in robotics and help many other students as well.

12.2 Survey Two

12.2.1 Executive Summary

This survey documents the complete experience of Team “The Epic Byte” at RoboExpo 3.0, an inter-team Line Following Robot (LFR) competition organized by the University of Asia Pacific (UAP) robotics club in 28 April 2026. The event brought together 11 competing teams, each required to complete a designated track as quickly and accurately as possible. Our team developed an autonomous LFR using an 8-channel IR sensor array, an Arduino Nano microcontroller, an L298N motor driver, and N20 micro metal gear motors. During the pre-competition testing phase conducted on the official UAP competition track, our robot demonstrated outstanding and consistent performance over

20–30 test runs, completing the full track without a single error and recording track completion times in the range of 18–20 seconds. Faculty members from the Department of CSE observed the testing phase and provided positive feedback on the robot’s navigation quality. During the official competition run, however, the robot successfully navigated approximately 75% of the track before exhibiting erratic line-following behavior near the end of the track, ultimately reversing direction and failing to complete the run. Post-competition analysis identified two contributing factors: (1) environmental interference from wind and ambient lighting conditions in the competition venue, and (2) a loose wire connection that caused intermittent sensor signal disruption. These factors combined to produce incorrect sensor readings, leading the control algorithm to make a wrong steering decision. Final Standing: The Epic Byte: Did Not Complete ,1st Runner-Up:43 seconds, Champion:17.76 seconds, Total Teams: 11

12.2.2 Event Overview

About Robo Expo 3.0

RoboExpo 3.0 was the third edition of the annual robotics exposition and competition organized by the University of Asia Pacific Robotics Club. The event was held on the UAP campus and served as both a competitive platform and an exhibition of student robotics capability. The competition attracted 11 teams from within the university, each competing in the Line Following Robot category under standardized track conditions.

Competition Format

Competition Type: Autonomous Line Following Robot Race • Number of Competing Teams: 11 teams participated in the competition, each demonstrating their autonomous robotic systems.

- Scoring Criteria: Performance was evaluated based on the fastest track completion time along with successful path following without any derailment.
- Track Surface: The track consisted of a black line (25 mm–25 mm width) printed on a white PVC board for clear contrast detection.
- Track Features: The course included a combination of straight paths, gradual curves, sharp 90-degree turns, and T-junctions to test navigation capability.
- Run Recording: Club members carefully recorded completion times and monitored any deviations from the designated path during each run.
- Judging Panel: The evaluation was conducted by faculty members along with senior executives of the robotics club to ensure fair assessment.

Competition Results Summary

The official competition results are summarized in Table 1 below. Our team's robot reached approximately the final 25% of the track before exhibiting a path deviation and was classified as Did Not Complete (DID NOT COMPLETE).

Table 12.1: Robo Expo 3.0 Official Competition Results

Rank	Team	Completion Time	Status
1 Champion	Anonymous Team A	17.76 seconds	Completed
2 1st Runner-Up	Anonymous Team B	43 seconds	Completed
3 Others	Other Teams (8 teams)	Varied	Did Not Complete
4 –	The Epic Byte (Our Team)	–	Did Not Complete

12.2.3 We Attend the Robo Expo: Its Evidence



Figure 12.2: Attend RoboExpo 3.0




Figure 12.3: RoboExpo 3.0 Competiton Track



Figure 12.4: Participation in RoboExpo 3.0



Figure 12.5: Participation in RoboExpo 3.0

12.2.4 Pre-Competition Testing

Testing Protocol

Prior to the official competition, our team conducted an extensive testing campaign on the official UAP competition track. The testing protocol was designed to stress-test the robot across repeated runs to verify consistency, identify edge-case failures, and fine-tune motor PWM values and sensor thresholds.

1. Total test runs conducted: 20–30 runs on the official track
2. Test environment: UAP competition track (indoor, controlled lighting)
3. Run objective: Full track completion without derailment
4. Metrics tracked: Completion time, lateral deviation at checkpoints, handling of T-junctions.

Testing Results

The robot performed exceptionally well throughout the entire pre-competition testing phase. Key observations are summarized below:

Table 12.2: Pre-Competition Testing Performance Summary

No.	Metric	Result
1	Total Test Runs	20–30 runs
2	Successful Completions	All runs — 100% success rate
3	Track Errors / Derailments	Zero errors observed
4	Best Recorded Time	~18 seconds
5	Worst Recorded Time	~20 seconds
6	Average Completion Time	~18–19 seconds
7	T-Junction Navigation	Handled correctly in all runs
8	Sharp Curve Handling	Smooth and consistent
9	Lateral Deviation	Minimal, visually undetectable
10	Battery Performance	Stable across all runs
11	Faculty Observation	Positive feedback received from CSE faculty

Faculty members from the Department of CSE who observed the testing phase commented positively on the robot’s smooth and reliable navigation, noting that the performance was consistent and competition-ready.

Robot Behavior Observed During Testing

The robot demonstrated smooth differential drive steering with minimal overshoot at curves. The 8-channel IR sensor array provided fine grained positional feedback, enabling the control algorithm to apply gradual corrections rather than abrupt steering changes. At T-junctions, the preprogrammed left-priority logic executed correctly in all test runs. The robot’s lightweight acrylic chassis contributed to fast acceleration and stable turning dynamics.

12.2.5 Competition Run Analysis

Run Description

In the official competition run, the robot successfully tracked the line and navigated through the first three-quarters of the track without any visible issues. The navigation was smooth and consistent with the performance observed during testing. However, as the robot approached the final section of the track (approximately 75–80% completion), it began to exhibit erratic sensor readings, causing incorrect steering decisions. The robot deviated from the line, reversed its direction, and failed to complete the track, resulting in a DID NOT COMPLETE classification.

Root Cause Analysis

A thorough post-competition analysis was conducted by the team to identify the root causes of the failure. Two primary contributing factors were identified: Factor 1: Environmental Interference (Wind and Light) The competition was held in an open or semi-open venue where ambient wind currents and fluctuating light conditions were present. These environmental factors affected the IR sensor array in the following ways: 1. Wind Effect: Physical vibration of the robot chassis caused by wind gusts introduced micro-oscillations in the sensor array's vertical position relative to the track surface. Because IR reflectance is highly sensitive to sensor-to-surface distance, even sub-millimeter variations can cause threshold crossings, producing false digital readings. 2. Light Effect: Ambient light in the competition venue, particularly if sunlight or strong artificial lighting was present, can overwhelm IR photodetectors. When background IR radiation exceeds the sensor's threshold calibration level, sensors can report false HIGH or LOW values, making black and white surfaces indistinguishable at certain angles. Factor 2: Loose Wire Connection Post-competition inspection of the robot revealed that one wire connection had become loose, likely due to vibration and mechanical stress accumulated over 20–30 test runs and the competition run itself. This loose connection caused intermittent electrical discontinuity in one of the sensor channels, producing sporadic incorrect sensor readings that the control algorithm could not distinguish from genuine track data. The specific connection that failed was likely between the IR sensor array module and the Arduino Nano's digital input pins.

Table 12.3: Root Cause Analysis Summary

No.	Factor	Cause	Effect on Robot	Severity
1	Wind Interference	Airflow in competition venue	Chassis vibration → IR sensor distance variation → false readings	High
2	Ambient Light	Strong venue lighting / sunlight	IR sensor saturation → incorrect line detection	Medium–High
3	Loose Wire	Mechanical fatigue from repeated runs	Intermittent signal loss on sensor channel → wrong steering	Critical
4	Algorithm Limitation	No error recovery / outlier rejection logic	Single bad reading propagates directly to motor output	Medium

Table 12.4: Comparison: Pre-Competition Testing vs. Official Competition Run

No.	Aspect	Pre-Competition Testing	Test- ing	Official Run	Competition
1	Venue Environment	Indoor, controlled, calm		Open/semi-open, wind present, bright lights	
2	Wire Condition	Tight and secure		One wire loose due to mechanical fatigue	
3	Sensor Reliability	100% consistent readings		Intermittent false readings near final segment	
4	Track Completion	100% (all 20–30 runs)		~75% (Did Not Complete, reversed at final section)	
5	Completion Time	18–20 seconds		Did Not Complete	
6	Faculty Feedback	Positive, praised for smooth run		N/A (did not complete)	

12.2.6 What We Did — System Overview

Robot Design and Construction

The robot was designed from scratch as part of the CSE 437 Robotics Lab course. The team handled all aspects of the build including chassis fabrication, component selection, circuit assembly, and embedded software development. The design philosophy prioritized lightweight construction for speed, while using a proven sensor array configuration for reliable path detection.

Hardware Implementation

The complete hardware stack is described in Table 4:

Table 12.5: Hardware Implementation Summary

No.	Component	Specification	Role
1	Arduino Nano	ATmega328P, 16 MHz clock, 32 KB flash memory	Central microcontroller for sensor reading, control logic, and PWM output
2	5-Channel IR Sensor Array	TCRT5000-based, 5 V digital output, line position detection across multiple lateral points	Provides real-time line detection for navigation and control
3	L298N Motor Driver	Dual H-Bridge, 2 A per channel, operating voltage 5–35 V	Independent speed and direction control of the two drive motors
4	N20 DC Gear Motors (x2)	6 V DC, 300 RPM, metal gearbox	Provides differential drive locomotion
5	Li-ion Battery (x2)	3.7 V each, 7.4 V connected in series	Primary power supply for the entire system
6	Acrylic Chassis	3 mm thickness, custom cut	Lightweight structural frame for component mounting
7	Rubber Wheels and Casters	Standard LFR size	Drive wheels and front balance support

Software and Control Algorithm

The control software was written in Embedded C using the Arduino IDE. The algorithm implemented a weighted-position error computation across all 8 sensor channels, producing a real-time lateral error signal E . Proportional motor speed adjustment was applied as:

$$\begin{aligned}V_{\text{Left}} &= V_{\text{base}} + K_p E \\V_{\text{Right}} &= V_{\text{base}} - K_p E\end{aligned}$$

For sharp turns and T-junctions, dedicated logic patterns were hard-coded to trigger full differential drive (one motor forward, one reverse) for rapid turning. The main control loop executed in under 5ms per iteration, ensuring real-time responsiveness to track changes.

Testing and Calibration

Sensor threshold calibration performed on the actual competition surface under testing lighting

1. PWM values empirically tuned across 5 sessions to balance speed with stability
2. KP gain adjusted to minimize overshoot on curves while maintaining straight-line speed
3. T-junction logic verified across 10 consecutive junction-only tests before full-track testing
4. Battery voltage monitored to ensure consistent motor speed across run duration

12.2.7 Root Cause Analysis

Identified failure causes:

- Environmental wind and ambient light interference
- Loose wire connection causing sensor signal loss
- Lack of error-recovery logic

12.2.8 Results

Pre-Competition Testing Results

As documented in Section 3, the robot achieved a 100 competition test runs on the official UAP track. The best recorded time was approximately 18 seconds, with consistent runs in the 18–20 second window. These results placed the team as the second fastest based

on pre-competition testing benchmarks, as one other team was observed completing the track in approximately 15 seconds during their own testing sessions.

Official Competition Outcome

In the official competition, the robot did not complete the track. After navigating approximately 75–80% of the track without incident, erratic behavior caused by the combined effect of environmental interference and a loose wire connection led to a track miss and reversal. The team was classified as DID NOT COMPLETE (Did Not Complete). The final podium results were: Champion — 17.76 seconds; 1st Runner-Up — 43 seconds. Notably, the 1st Runner-Up’s time of 43 seconds was significantly slower than our pre-competition testing best of 18 seconds. This indicates that had the robot completed the track during the competition, even at a conservative pace, it would likely have achieved a podium position. Key Insight: Our pre-competition best of 18 seconds was faster than the 1st Runner-Up’s winning time of 43 seconds. The did not complete was caused by external and mechanical factors, not by fundamental design or algorithm deficiencies.

12.2.9 How It Worked — System Operation

Sense-Think-Act Cycle

The robot operated on a continuous sense-think-act control cycle. In each iteration of the main loop (every 5ms), the Arduino Nano read all 8 channels of the IR sensor array simultaneously. The binary sensor readings were decoded into a weighted lateral position value P using the formula:

$$P = \frac{\sum S_i \times W_i}{\sum S_i}, \quad \text{where } W_i \in \{-7, -5, -3, -1, +1, +3, +5, +7\}$$

A P value near zero indicated centered line alignment. Positive P indicated rightward deviation (turn left), negative P indicated leftward deviation (turn right). The control action converted P into a speed differential applied via the L298N to the two N20 motors through separate PWM channels.

Track Navigation Modes

- **Straight Mode:** When the robot moves along a straight path,

$$V_{\text{Left}} = V_{\text{Right}} = V_{\text{base}}, \quad (60\text{--}80\% \text{ PWM})$$

Minimal correction is applied. • **Curve Mode:** Speed differential applied proportional to P . Inner motor slows, outer motor maintains speed.

- Sharp Turn Mode: Triggered when 3+ consecutive sensors on one side activate. One motor reverses briefly.
- T-Junction Mode: Left-priority logic activated when full sensor array detects wide line. Robot turns left.
- Lost-Line Mode: If all sensors read no line, robot halts and oscillates to re-acquire the line.

Observed Strengths

- High consistency across repeated runs in controlled conditions (100% completion rate during testing)
 - Smooth trajectory on gradual curves with minimal lateral oscillation
 - Fast response to track deviation due to high-frequency sensor polling (200Hz)
 - Competitive speed: 18–20 seconds, significantly faster than 1st Runner-Up’s 43 seconds
 - Positive faculty reception confirming professional-level build quality

12.2.10 Future Improvements and Recommendations

Hardware Improvements

- Soldered Connections — Replace all jumper wire connections with soldered joints on a custom PCB or perfboard. This eliminates the risk of loose wire failures caused by mechanical vibration, which was the critical failure point in the competition. This is the single highest-priority improvement.
 - Connector Locking Mechanisms — Use locking JST connectors or hot-glue wire strain relief at all PCB-to-module connection points to prevent accidental disconnection during vibration.
 - Shielded Sensor Housing — Design a 3D-printed or acrylic enclosure for the IR sensor array that shields individual sensors from lateral ambient light while maintaining downward sensing. This directly addresses the light interference failure mode.
 - Vibration Dampening — Add rubber grommets or foam padding between the sensor array mounting bracket and the chassis to reduce vibration transmission to the sensors.
 - Dedicated 5V Voltage Regulator — Add a dedicated LM7805 or DC-DC buck converter to ensure stable 5V supply to the sensor array independently of motor load fluctuations.
 - Higher-Torque / Higher-Speed Motors — Consider upgrading to N20 motors with 500 RPM rating to improve top-end track speed while maintaining adequate torque for cornering.

Software and Algorithm Improvements

- Full PID Control — Implement a complete PID (Proportional-Integral-Derivative) controller replacing the current P-only control. The derivative term will reduce overshoot on sharp curves; the integral term will eliminate steady-state lateral offset on long straight segments.
- Sensor Noise Filtering — Implement a moving average or median filter over the last 3–5 sensor readings before computing the error signal. This will reject isolated false readings caused by brief light interference or electrical noise.
- Outlier Rejection Logic — Add a sanity check that flags readings which deviate by more than a threshold from the previous reading as likely noise, and substitutes the previous valid reading instead of acting on the outlier.
- Adaptive Threshold Calibration — Implement an auto-calibration routine at startup that reads sensor values over white and black surfaces and dynamically computes optimal thresholds for the specific lighting conditions at the venue. This directly mitigates light interference.

Pre-Competition Protocol Improvements

- Venue-Condition Testing — Always perform at least 5 calibration runs at the actual competition venue under the exact lighting and environmental conditions present on competition day. Recalibrate sensor thresholds on-site.
- Hardware Inspection Checklist — Establish a formal pre-run hardware inspection checklist: verify all wire connections, check battery voltage, confirm sensor alignment, and test each motor individually before the official run.
- Backup Robot or Spare Parts — Prepare a second fully assembled and calibrated robot (or at minimum, all critical spare components) for emergency substitution.
- Stress-Test Protocol — Include vibration stress testing in pre-competition testing: physically shake the robot while monitoring sensor readings to detect loose connections before competition day.
- Environmental Simulation — During pre-competition testing, simulate competition venue conditions by using a fan to create airflow and varying room lighting, rather than testing only under ideal controlled conditions.

12.2.11 Lessons Learned

The RoboExpo 3.0 experience provided valuable engineering lessons that extend beyond the specific domain of line-following robotics. The key takeaways are:

Table 12.6: Lessons Learned from RoboExpo 3.0

No.	Lesson	Details
1	Hardware Reliability is Non-Negotiable	A robot that works perfectly 20–30 times in a controlled environment can still fail in a real environment due to a single loose wire. Physical robustness must be engineered with the same rigor as algorithmic performance.
2	Environmental Conditions Must Be Replicated	Sensor calibration performed in calm, controlled lighting does not transfer reliably to open venues with wind and strong ambient light. Pre-competition calibration at the actual venue is essential.
3	Algorithm Robustness Matters	Control algorithms should include noise filtering and outlier rejection. A P-only controller without input validation is brittle; even a single false sensor reading can cause cascading failure.
4	Strong Test Performance $\neq$ Competition Success	Pre-competition success builds confidence but can create false security. The competition environment introduces variables such as audience movement, venue airflow, and lighting that are not present during testing.
5	Post-Failure Analysis Creates Value	Although the robot did not complete the competition run, the systematic root-cause analysis performed afterward produced actionable insights that will directly improve the next version of the system.

12.2.12 Survey: Questions & Answers

1. What was the main objective of your robot?

Answer: The main objective of our robot was to accurately follow a predefined line track using sensor-based feedback and complete the course within the shortest possible time while maintaining stability.

2. How much of the track did your robot successfully complete?

Answer: Our robot successfully completed approximately 75% of the track before deviating from the path.

3. What problem caused the robot to leave the track?

Answer: The robot lost the track mainly due to sharp turns and sensor misalignment. Additionally, the speed was slightly higher than optimal, which reduced control during critical sections.

4. What sensors did you use and how did they perform?

Answer: We used 5 array IR sensors to detect the line. They performed well on straight paths, but in curves or uneven lighting conditions, the readings became inconsistent.

5. How did motor speed affect performance?

Answer: Higher motor speed improved overall time but reduced accuracy. The robot struggled to adjust quickly during turns, leading to track deviation.

6. Did lighting conditions affect your robot?
Answer: Yes, lighting had a noticeable impact. Variations in light intensity affected sensor readings, which sometimes caused incorrect line detection.

7. What was the biggest challenge you faced?

Answer: The biggest challenge was maintaining stability and accuracy during sharp curves and intersections.

8. What did you learn from this competition?

Answer: We learned the importance of sensor calibration, speed control, and real-world testing. Small tuning issues can significantly affect performance.

9. How would you rate your robot's performance?

Answer: We would rate our robot's performance 7 out of 10, as it showed good potential but needs optimization for full track completion.

10. Why is PID control important in line following robots?

Answer: PID control helps maintain smooth and accurate movement by continuously adjusting motor speed based on error values, reducing overshoot and improving stability.

12.2.13 Conclusion

Team "The Epic Byte" participated in RoboExpo 3.0 with an autonomous line following robot that demonstrated exceptional and consistent performance during the pre-

competition testing phase, achieving 100% track completion across 20–30 runs with best times of 18–20 seconds. The robot’s design, construction, and pre-competition performance were praised by faculty observers and were technically superior to the official competition results achieved by the finalists. The competition did not complete outcome resulted from two external factors — environmental interference (wind and ambient light) and a loose wire connection — rather than fundamental flaws in the robot’s design or control algorithm. This is evidenced by the fact that our testing best time of 18 seconds would have comfortably beaten the 1st Runner- Up’s official time of 43 seconds. The experience has produced a detailed set of improvement recommendations focused on hardware robustness (soldered connections, sensor shielding), software resilience (PID control, sensor filtering, adaptive calibration), and pre-competition protocol (venue-condition testing, hardware checklists, stress testing). These improvements will form the foundation of the team’s next-generation LFR system. Despite the did not complete outcome, the team demonstrated professional engineering capability, positive collaboration, and the ability to perform systematic failure analysis — qualities as valuable as a competition podium finish.

12.2.14 Acknowledgments

The team sincerely thanks Assistant Professor A.S. Zaforullah Momtaz for his guidance and supervision throughout the CSE 437 Robotics Lab course. We thank the University of Asia Pacific Robotics Club for organizing RoboExpo 3.0 and providing a competitive platform for student innovation. We also thank the faculty members who observed and provided encouraging feedback during our pre-competition testing phase, and our fellow competing teams for the spirit of healthy competition.

12.3 CEP Mapping

This section demonstrates how the Line Following Learning Robot project aligns with the core learning objectives of CSE 437 – Robotics, through the Knowledge Profile (K), Range of Complex Engineering Problem Solving (P), and Range of Complex Engineering Activities (A).

The project integrates the following advanced features relevant to CEP mapping: • Adaptive Line Following System – 5-IR sensor array + Q-Learning for real-time performance improvement.

- Real-time Learning Capability – Robot optimizes motor speeds dynamically on sharp curves, loops, and junctions.

- Obstacle Avoidance System – Ultrasonic sensor-based detection with autonomous path adjustment.

- Competition Track Navigation – Handles complex Robo Fest tracks with T-junctions, dumping spots, and varying line patterns.
- Dumping Mechanism – Servo-controlled arm performs dumping action at designated spots.
- High-speed Navigation – PID + Q-Learning for fast, accurate, and stable movement in dynamic conditions.

How Ks are Addressed through the Project

S/N	Ks	Attribute	How Ks are Addressed through the Project	CLOs	PLOs
1	K3	A systematic, theory-based formulation of engineering fundamentals required in the engineering discipline	Applied PID control theory and Q Learning for adaptive line following on complex competition tracks.	CLO1	PLO1
2	K4	Engineering specialist knowledge that provides theoretical frameworks at the forefront of the discipline	Used reinforcement learning and embedded robotics to create an intelligent competition-level robot.	CLO2	PLO2
3	K5	Knowledge that supports engineering design in a practice area	Designed complete system with sensor fusion and adaptive learning algorithm.	CLO3	PLO3
4	K6	Knowledge of engineering practice (technology) in the practice areas	Implemented real-time hardware software integration using Raspberry Pi/ESP32 and 5-IR sensors.	CLO4	PLO5

How Ps are Addressed through the Project

Ps	Attribute	How Ps are Addressed through the Project	CLOs	PLOs
P1	Depth of knowledge required	Requires deep knowledge of robotics, control systems, machine learning, and real-time embedded programming to handle complex competition track challenges.	CLO1	PLO1
P2	Range of conflicting requirements	Balanced conflicting requirements such as high-speed vs accuracy, real-time response vs learning computation, and cost vs performance for competition environment.	CLO2	PLO2
P7	Interdependence	Mechanical design, sensor system, PID control, Q-Learning algorithm, and dumping mechanism are highly interdependent; change in one directly affects overall competition performance.	CLO3	PLO3

How As are Addressed through the Project

As	Attribute	How As are Addressed through the Project
A1	Range of resources	Utilized diverse resources including 5-IR sensor array, ultrasonic sensor, motors, battery, servo for dumping, micro-controller, and advanced software tools to build a competition-grade robot.
A2	Level of interaction	Required high level of team interaction, instructor feedback, iterative testing on actual Robo Fest track, and stakeholder collaboration during development and demo.
A5	Familiarity	Involved working with unfamiliar advanced techniques (reinforcement learning on embedded board and real-time adaptation on complex track) to achieve competition-level performance.

Project Demonstration Video:

Available at <https://youtube.com/shorts/7JES2e4SFTM?si=1HJP2jD6MBJP35If>

Chapter 13

Conclusion

The developed line following robot represents an efficient and intelligent embedded system that successfully integrates sensing, control logic, and mechanical actuation to achieve autonomous navigation. The system utilizes a 5-channel IR sensor array to continuously monitor the surface and accurately distinguish between black and white regions. This enables the robot to detect and track the path in real time with good precision.

At the core of the system, the Arduino Nano functions as the main controller, where all sensor data is processed and analysed. Based on this real-time input, the controller makes quick and effective decisions to maintain the robot's alignment with the path. These decisions are executed through the L298N motor driver module, which regulates the speed and direction of two N20 DC gear motors. By dynamically adjusting motor speeds using control algorithms, the robot is able to move forward, turn smoothly, and correct its path whenever deviation occurs.

The project demonstrates the practical application of embedded systems concepts, including sensor integration, signal processing, and motor control. It also highlights the importance of feedback-based control systems in achieving accurate and stable performance. The use of proportional control allows the robot to respond efficiently to positional errors, resulting in smoother navigation compared to basic on/off control methods. Furthermore, this line following robot is highly relevant for robotics competitions such as RoboFest, where performance factors like speed, accuracy, and reliability are critical. Beyond competitions, the system has strong potential in real-world industrial applications, including automated material handling, warehouse logistics, guided vehicle systems, and smart transportation solutions. In conclusion, this project effectively combines hardware and software to create a functional and adaptable robotic system. It not only enhances understanding of embedded system design and robotics but also provides a scalable platform for future improvements, such as implementing PID control, adding obstacle detection, or integrating wireless communication for smarter automation solutions.

Chapter 14

FUTURE SCOPE and ACKNOWLEDGMENT

- FUTURE SCOPE

Industrial Automation: With some improvements, this robot could take over repetitive and risky factory tasks, reducing the need for human involvement in such environments. Smart Delivery System: By adding better sensors and mapping logic, the robot could navigate more complex indoor spaces, making it useful in hospitals, offices, or shopping centers. Obstacle Avoidance: Integrating an ultrasonic sensor in future versions would allow the robot to detect and avoid objects on its path, making it much more reliable in real-world conditions. Autonomous Vehicle Research: On a smaller scale, this project lays a solid foundation for understanding how self-driving vehicles work and can serve as a starting point for more advanced research.

- ACKNOWLEDGMENT

I would like to sincerely thank everyone who supported me throughout this project. I am grateful to my faculty member A.S. Zaforullah Momtaz Sir at the Department of Computer Science and Engineering, University of Asia Pacific, for his guidance and encouragement. I also want to thank my teammates and classmates whose suggestions and cooperation made this work much smoother. This project truly would not have come together without their support.

Bibliography

- [1] M. Pakdaman and M. M. Sanaatiyan, "Design and implementation of line follower robot," 2nd Int. Conf. on Computer and Electrical Engineering, pp. 585-590, 2009.
- [2] F. Kaiser et al., "Line follower robot: Fabrication and accuracy measurement by data acquisition," Int. Conf. Electrical Engineering and ICT, 2014.
- [3] H. Hariyanto, D. A. Prasetya, and A. Susanto, "Line follower mobile robots with adaptive PID control," AIP Conf. Proc., vol. 2991, 2023.
- [4] A. A. S. Gunawan et al., "Vision navigation based PID control for line tracking robot," Computers, Materials Continua, 2021.
- [5] J. Amorim, A. Valente, and R. Moreira, "Optimization of line follower robot performance," Robotics, 2023.
- [6] S. Mamadapur et al., "Line following robot with object avoidance using Arduino," IJERT, 2022.
- [7] A. H. Ismail et al., "Development of a high-speed line follower robot algorithms," Journal of Fundamental and Applied Sciences, 2016.
- [8] G. Oltean, "Mobile robot platform with Arduino Uno and Raspberry Pi," Electronics, 2019.
- [9] I. Angulo et al., "Optimal PID control of DC motor with encoder," Sensors, 2022.
- [10] H. Sudarsono and S. C. Puspita, "Prototype of line follower robot using N20 motor," Journal of Applied Mechanical Engineering, 2018.
- [11] H. Fitriawan et al., "PID based line follower optimization," Journal of Physics Conference Series, 2019.
- [12] V. Gupta and P. Singh, "PWM signal generation for motor control," Journal of Embedded Systems, 2021.
- [13] R. Sarma and A. K. Boruah, "Performance analysis of L298N motor driver," IJERT, 2019.

- [14] M. A. Pramanik and M. M. Rahman, "Arduino Nano based control system for robots," IJRA, 2020.
- [15] A. S. Yolanda et al., "Control system design for DC motor using Arduino," ICA-COMIT, 2017.
- [16] S. K. Lee et al., "Infrared sensor array based line follower robot," International Journal of Robotics Research, 2018.
- [17] M. Rossi and L. Bianchi, "Autonomous navigation system for mobile robot," Robotics and Autonomous Systems, 2020.
- [18] J. Kim et al., "Low cost embedded line follower robot design," IEEE Access, 2021.
- [19] T. Nguyen and H. Tran, "PID controlled mobile robot navigation," International Journal of Advanced Robotics Systems, 2019.
- [20] R. Smith and J. Brown, "Sensor fusion in autonomous line following robots," Journal of Intelligent Robotic Systems, 2022.