

适配LTDC驱动RGB LCD屏

工程参考: [DshanMCU_H7R/project/App/DshanMCU_H7R_LVGL_Desktop](#)

添加代码:

```
// 注意关闭 DCache(Data) 和 ICache(Instruction)

void LTDC_LCD_Fill(uint16_t * fb, uint16_t color, uint32_t length)
{
    uint16_t * tmp_fb = fb;
    for(uint32_t i = 0; i < length; i++)
    {
        *(tmp_fb + i) = color;
    }
}

{
    rgb_lcd_init();

    uint16_t * fb_addr = (uint16_t *)((uint32_t)0xC0000000);
    while (1)
    {
        SCB_CleanInvalidateDCache();
        while (!(LTDC->CDSR & LTDC_CDSR_VSYNCS));
        LTDC_LCD_Fill(fb_addr, (uint16_t)0xF800, (uint32_t)480*480*2);
        ux_device_cdc_acm_printf("%s\n", "LCD COLOR RED!");
        HAL_Delay(1000);

        SCB_CleanInvalidateDCache();
        while (!(LTDC->CDSR & LTDC_CDSR_VSYNCS));
        LTDC_LCD_Fill(fb_addr, (uint16_t)0x07E0, (uint32_t)480*480*2);
        ux_device_cdc_acm_printf("%s\n", "LCD COLOR GREEN!");
        HAL_Delay(1000);

        SCB_CleanInvalidateDCache();
        while (!(LTDC->CDSR & LTDC_CDSR_VSYNCS));
        LTDC_LCD_Fill(fb_addr, (uint16_t)0x001F, (uint32_t)480*480*2);
        ux_device_cdc_acm_printf("%s\n", "LCD COLOR BLUE!");
        HAL_Delay(1000);

        SCB_CleanInvalidateDCache();
        while (!(LTDC->CDSR & LTDC_CDSR_VSYNCS));
        LTDC_LCD_Fill(fb_addr, (uint16_t)0xFFFF, (uint32_t)480*480*2);
        ux_device_cdc_acm_printf("%s\n", "LCD COLOR WHITE!");
        HAL_Delay(1000);

        SCB_CleanInvalidateDCache();
        while (!(LTDC->CDSR & LTDC_CDSR_VSYNCS));
        LTDC_LCD_Fill(fb_addr, (uint16_t)0x0000, (uint32_t)480*480*2);
        ux_device_cdc_acm_printf("%s\n", "LCD COLOR BLACK!");
    }
}
```

```
HAL_Delay(1000);

/* USER CODE END WHILE */

/* USER CODE BEGIN 3 */
}
}
```

技术交流学习

欢迎加入讨论：

- 社区交流： <https://forums.100ask.net>
- QQ技术交流群（如群满，请加qq：401684796 验证备注：LVGL）：962138234
- 微信交流群：添加微信： baiwenkeji_fae 验证备注：LVGL