

**Aim:**

The `addNodes()` function creates a new list and adds elements to the list until delimiter `-1` is occurred.

Fill in the missing code in the below functions `addNodes(NODE first, int x)` and `traverseList(NODE first)` in the file `CreateAndAddNodes.c`.

**Source Code:**SingleLL1.c

```
#include<stdio.h>
#include<stdlib.h>

#include "CreateAndAddNodes.c"

void main() {
    NODE first = NULL;
    int x;
    printf("Enter elements up to -1 : ");
    scanf("%d", &x);
    while (x != -1) {
        first = addNodes(first, x);
        scanf("%d", &x);
    }
    if (first == NULL) {
        printf("Single Linked List is empty\n");
    } else {
        printf("The elements in SLL are : ");
        traverseList(first);
    }
}
```

CreateAndAddNodes.c

```
struct node {
    int data;
    struct node *next;
};
typedef struct node *NODE;

NODE createNode() {
    NODE temp;
    temp=(NODE)malloc(sizeof(struct node));
    temp->next=NULL;
    return temp;
}

NODE first=NULL;
NODE addNodes(NODE first, int x){
    NODE temp;
    temp=createNode();
    temp->data=x;
    if(first==NULL)
```

```

    {
        first=temp;
    }
    else
    {
        NODE lastNode = first;
        while(lastNode->next!=NULL)
        {
            lastNode=lastNode->next;
        }
        lastNode->next=temp;
    }
    return first;
}
void traverseList(NODE first) {
    if(first==NULL)
    {
        printf("List is empty");
    }
    else
    {
        NODE temp=first;
        while(temp!=NULL)
        {
            printf("%d --> ",temp->data);
            temp=temp->next;
        }
        printf("NULL\n");
    }
}
}

```

### Execution Results - All test cases have succeeded!

Test Case - 1
User Output
Enter elements up to -1 : 9 18 27 36 45 -1
The elements in SLL are : 9 --> 18 --> 27 --> 36 --> 45 --> NULL

Test Case - 2
User Output
Enter elements up to -1 : 12 14 19 23 -1
The elements in SLL are : 12 --> 14 --> 19 --> 23 --> NULL