WEBENCH® Design Report

LMR50410XDBVR 10V-32V to 3.30V @ 0.6A

VinMin = 10.0V
VinMax = 32.0V
Vout = 3.3V
Iout = 0.6A

Device = LMR50410XDBVR
Topology = Buck
Created = 2020-06-09 06:44:20.101
BOM Cost = $1.49
BOM Count = 9
Total Pd = 0.27W



Electrical BOM

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cboot	MuRata	GRM155R71C104KA88D Series= X7R	Cap= 100.0 nF ESR= 1.0 mOhm VDC= 16.0 V IRMS= 0.0 A	1	$0.01	0402 3 mm^2
2.	Cin	TDK	C1608X5R1H105K080AB Series= X5R	Cap= 1.0 uF ESR= 5.522 mOhm VDC= 50.0 V IRMS= 2.2162 A	1	$0.04	0603 5 mm^2
3.	Cinx	MuRata	GRM188R71H104KA93D Series= X7R	Cap= 100.0 nF ESR= 20.0 mOhm VDC= 50.0 V IRMS= 3.8 A	1	$0.02	0603 5 mm^2
4.	Cout	MuRata	GRM21BD70J226ME44L Series= X7T	Cap= 22.0 uF ESR= 1.0 mOhm VDC= 6.3 V IRMS= 6.0 A	2	$0.10	0805 7 mm^2
5.	L1	Bourns	SRR1260-120M	L= 12.0 µH DCR= 23.0 mOhm	1	$0.50	 SRR1260 210 mm^2
6.	Rfbb	Vishay-Dale	CRCW040222K1FKED Series= CRCW..e3	Res= 22100.0Ohm Power= 63.0 mW Tolerance= 1.0%	1	$0.01	0402 3 mm^2
7.	Rfbt	Yageo	RC0603FR-0751KL Series= ?	Res= 51000.0Ohm Power= 100.0 mW Tolerance= 1.0%	1	$0.01	0603 5 mm^2

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
8.	U1	Texas Instruments	LMR50410XDBVR	Switcher	1	$0.70	DBV0006A 15 mm²









IC Tj



Cin Pd



Cin IRMS



Iin Avg



Pout



Cout IRMS















Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	178.568 mA	Capacitor	Input capacitor RMS ripple current
2.	Cin Pd	176.08 µW	Capacitor	Input capacitor power dissipation
3.	Cinx IRMS	13.159 mA	Capacitor	Bulk capacitor RMS ripple current
4.	Cinx Pd	3.463 µW	Capacitor	Bulk capacitor power dissipation
5.	Cout IRMS	108.086 mA	Capacitor	Output capacitor RMS ripple current
6.	Cout Pd	5.841 µW	Capacitor	Output capacitor power dissipation
7.	IC Ipk	787.21 mA	IC	Peak switch current in IC
8.	IC Pd	264.97 mW	IC	IC power dissipation
9.	IC Tj	51.198 degC	IC	IC junction temperature
10.	IC Tolerance	15.0 mV	IC	IC Feedback Tolerance
11.	ICThetaJA Effective	80.0 degC/W	IC	Effective IC Junction-to-Ambient Thermal Resistance

#	Name	Value	Category	Description
12.	Iin Avg	70.433 mA	IC	Average input current
13.	Ipp percentage	62.403 %	Inductor	Inductor ripple current percentage (with respect to average inductor current)
14.	L Ipp	374.42 mA	Inductor	Peak-to-peak inductor ripple current
15.	L Pd	8.549 mW	Inductor	Inductor power dissipation
16.	Cin Pd	176.08 µW	Power	Input capacitor power dissipation
17.	Cinx Pd	3.463 µW	Power	Bulk capacitor power dissipation
18.	Cout Pd	5.841 µW	Power	Output capacitor power dissipation
19.	IC Pd	264.97 mW	Power	IC power dissipation
20.	L Pd	8.549 mW	Power	Inductor power dissipation
21.	Total Pd	273.844 mW	Power	Total Power Dissipation
22.	BOM Count	9	System Information	Total Design BOM count
23.	Cross Freq	38.534 kHz	System Information	Bode plot crossover frequency
24.	Duty Cycle	11.079 %	System Information	Duty cycle
25.	Efficiency	87.85 %	System Information	Steady state efficiency
26.	FootPrint	259.0 mm^2	System Information	Total Foot Print Area of BOM components
27.	Frequency	700.0 kHz	System Information	Switching frequency
28.	Gain Marg	-18.108 dB	System Information	Bode Plot Gain Margin
29.	Iout	600.0 mA	System Information	Iout operating point
30.	Low Freq Gain	69.167 dB	System Information	Gain at 1Hz
31.	Mode	CCM	System Information	Conduction Mode
32.	Phase Marg	69.526 deg	System Information	Bode Plot Phase Margin
33.	Pout	1.98 W	System Information	Total output power
34.	Total BOM	$1.49	System Information	Total BOM Cost
35.	Vin	32.0 V	System Information	Vin operating point
36.	Vin p-p	82.694 mV	System Information	Peak-to-peak input voltage
37.	Vout	3.3 V	System Information	Operational Output Voltage
38.	Vout Actual	3.308 V	System Information	Vout Actual calculated based on selected voltage divider resistors
39.	Vout Tolerance	2.931 %	System Information	Vout Tolerance based on IC Tolerance (no load) and voltage divider resistors if applicable
40.	Vout p-p	2.257 mV	System Information	Peak-to-peak output ripple voltage

Design Inputs

#	Name	Value	Description
1.	Iout	600.0 m	Maximum Output Current
2.	VinMax	32.0	Maximum input voltage
3.	VinMin	10.0	Minimum input voltage
4.	Vout	3.3	Output Voltage
5.	acFrequency	60.0	AC Frequency
6.	base_pn	LMR50410X	Base Product Number
7.	source	DC	Input Source Type
8.	Ta	30.0	Ambient temperature

Design Assistance

1. **LMR50410X** Product Folder : http://www.ti.com/product/LMR50410 : contains the data sheet and other resources.

