

1 - Recon

1. ¿Cuál es el canal que utiliza actualmente el Punto de Acceso wifi-global?

Antes de empezar, necesitamos poner nuestra tarjeta en modo monitor

```
sudo airmog-ng start wlan0
```

- `sudo` Ejecuta el comando como administrador
- `airmon-ng` Herramienta para gestionar interfaces WiFi
- `start` Inicia el modo monitor
- `wlan0` Interfaz de red inalámbrica

```
sudo airodump-ng wlan0mon --band abg
```

- `airodump-ng` Escanea redes WiFi y muestra información
- `wlan0mon` Interfaz en modo monitor

- band abg Escanea todas las bandas (2.4GHz y algunas 5GHz)

user@WiFiChallengeLab: ~/wifi

CH 136][Elapsed: 5 mins][2025-08-12 23:06][WPA handshake: F0:9F:C2:7A:33:28

BSSID	PWR	Beacons	#Data, #/s	CH	MB	ENC	CIPHER	AUTH	ESSID
F0:9F:C2:71:22:15	-28	102	14	0	44	54e	WPA2	CCMP	MGT wifi-corp
F0:9F:C2:7A:33:28	-28	102	19	0	44	54e	WPA2	CCMP	MGT wifi-regional-tablets
F0:9F:C2:71:22:16	-28	102	32	0	44	54e	WPA2	CCMP	MGT wifi-regional
F0:9F:C2:71:22:1A	-28	102	7	0	44	54e	WPA2	CCMP	MGT wifi-corp
F0:9F:C2:71:22:17	-28	102	403	0	54	54e	WPA2	CCMP	MGT wifi-global
F0:9F:C2:71:22:12	-28	53	32	0	6	54	WPA2	CCMP	PSK wifi-mobile
06:04:B7:BF:32:96	-28	53	0	0	6	54	WPA2	CCMP	PSK WIFI-JUAN
72:4B:B0:6F:A5:F4	-28	53	0	0	6	54	WPA2	CCMP	PSK MiFibra-5-D6G3
F0:9F:C2:71:22:10	-28	53	42	0	6	54	OPN		wifi-guest
F0:9F:C2:6A:88:26	-28	50	0	0	11	54	OPN		<length: 9>
F0:9F:C2:11:0A:24	-28	50	0	0	11	54e	WPA3	CCMP	SAE wifi-management
F0:9F:C2:1A:CA:25	-28	50	0	0	11	54e	WPA3	CCMP	SAE wifi-IT
7A:B4:B1:70:2A:00	-28	52	0	0	9	54	WPA2	TKIP	PSK vodafone7123
4E:43:C3:23:CA:E7	-28	103	0	0	3	54	WPA2	CCMP	PSK MOVISTAR_JYG2
F0:9F:C2:71:22:11	-28	103	3941	0	3	54	WEP	WEP	wifi-old

BSSID	STATION	PWR	Rate	Lost	Frames	Notes	Probes
F0:9F:C2:71:22:15	64:32:A8:07:6C:40	-29	48e- 1e	0	26		AP_router,wifi-corp
F0:9F:C2:7A:33:28	64:32:A8:BD:64:54	-29	6e- 6e	0	42	PMKID	wifi-regional-tablets
F0:9F:C2:71:22:16	64:32:A8:AC:53:50	-29	24e- 6e	0	53	PMKID	wifi-regional
F0:9F:C2:71:22:17	64:32:A8:BC:53:51	-29	48e-18e	0	177		open-wifi,home-WiFi,WiFi-Restaurant
F0:9F:C2:71:22:17	64:32:A8:BA:18:42	-29	18e- 9e	0	235		
F0:9F:C2:71:22:12	28:6C:07:6F:F9:44	-29	24 -54	0	32		
F0:9F:C2:71:22:10	B0:72:BF:44:B0:49	-29	18 -11	0	10		
F0:9F:C2:71:22:10	B0:72:BF:B0:78:48	-29	48 -54	0	10		
F0:9F:C2:71:22:10	80:18:44:BF:72:47	-29	54 -54	0	22		
(not associated)	64:32:A8:A9:DE:55	-29	0 - 6	0	10		wifi-regional-tablets
(not associated)	02:00:00:00:06:00	-49	0 - 6	0	7		
(not associated)	02:00:00:00:02:00	-49	0 - 6	0	7		
(not associated)	02:00:00:00:01:00	-49	0 - 6	0	7		
(not associated)	02:00:00:00:03:00	-49	0 - 6	0	7		
(not associated)	02:00:00:00:04:00	-49	0 - 1	0	6		
(not associated)	02:00:00:00:05:00	-49	0 - 1	0	6		
(not associated)	B4:99:BA:6F:F9:45	-49	0 - 1	0	180		wifi-offices,Jason
(not associated)	64:32:A8:AD:AB:53	-49	0 - 1	0	130		wifi-corp-legacy
(not associated)	78:C1:A7:BF:72:46	-49	0 - 1	0	180		wifi-offices,Jason
F0:9F:C2:71:22:11	4E:85:29:30:88:D8	-29	54 - 9	0	3927		

2. ¿Cuál es la MAC del cliente wifi-IT?

```
sudo airodump-ng wlan0mon --wps -c11
```

CH 11][Elapsed: 24 s][2025-08-12 23:13][enabled AP selection

BSSID	PWR	RXQ	Beacons	#Data, #/s	CH	MB	ENC	CIPHER	AUTH	WPS	ESSID
F0:9F:C2:6A:88:26	-28	100	252	0	0	11	54	OPN		0.0	<length: 9>
F0:9F:C2:11:0A:24	-28	0	252	0	0	11	54e	WPA3	CCMP	SAE	wifi-management
F0:9F:C2:1A:CA:25	-28	0	252	30	0	11	54e	WPA3	CCMP	SAE	wifi-IT

BSSID	STATION	PWR	Rate	Lost	Frames	Notes	Probes
(not associated)	02:00:00:00:04:00	-49	0 - 1	0	1		
(not associated)	02:00:00:00:05:00	-49	0 - 1	0	1		
(not associated)	B4:99:BA:6F:F9:45	-49	0 - 1	0	18		wifi-offices,Jason
(not associated)	78:C1:A7:BF:72:46	-49	0 - 1	0	18		wifi-offices,Jason
(not associated)	64:32:A8:AD:AB:53	-49	0 - 1	42	14		wifi-corp-legacy
F0:9F:C2:1A:CA:25		-29	1e- 6e	0	30		

3. ¿Cuál es la probe de 78:C1:A7:BF:72:46?

```
sudo airodump-ng wlan0mon --band abg
```

```
(not associated) 02:00:00:00:00:00 -49 0 - 1 0 20
(not associated) 02:00:00:00:00:00 -49 0 - 6 0 20
(not associated) 02:00:00:00:00:00 -49 0 - 6 0 19
(not associated) 84:99:BA:6F:F9:45 -49 0 - 1 66 456 wifi-offices,Jason
(not associated) 78:C1:A7:BF:72:46 -49 0 - 1 66 462
(not associated) 64:32:A8:AD:AB:53 -49 0 - 1 0 300 wifi-corp-legacy
F0:9F:C2:71:22:12 28:6C:07:6F:F9:44 -29 12 - 9 0 26
F0:9F:C2:71:22:10 80:18:44:BF:72:47 -29 54 -54 0 28
```

4. ¿Cuál es el ESSID del AP oculto (mac F0:9F:C2:6A:88:26)?

```
F0:9F:C2:71:22:10 -28 39 8 0 6 54 OPN wifi-guest
F0:9F:C2:6A:88:26 -28 36 0 0 11 54 OPN <length: 9>
F0:9F:C2:11:0A:24 -28 36 0 0 11 54e WPA3 CCMP SAE wifi-management
```

```
cat ../Descargas/rockyou.txt | awk '{print "wifi-" $1}' > wifi-rockyou.txt
```

creamos un nuevo diccionario con el formato wifi-nombre

cambiamos el canal de nuestra interfaz de red a 11:

```
iwconfig wlan0mon channel 11
```

ahora usando mdk4 forzaremos que el AP nos de el nombre

```
sudo mdk4 wlan0mon p -t F0:9F:C2:6A:88:26 -f wifi-rockyou.txt
```

```
root@WiFiChallengeLab:~# sudo mdk4 wlan0mon p -t F0:9F:C2:6A:88:26 -f wifi-rockyou.txt
Waiting for a beacon frame from target to get its SSID length.
SSID length is 9
Trying SSID: wifi-love
Packets sent: 1 - Speed: 1 packets/sec
Trying SSID: wifi-lily
Packets sent: 131 - Speed: 130 packets/sec
Probe Response from target AP with SSID
Job's done, have a nice day :)
```