

# Media Samples Guide

---

## Overview

---

**Samples** work with **Intel® Media Server Studio 2017 for Linux**.

They demonstrate how to incorporate the **Intel® Media Server Studio – SDK** (hereinafter referred to as "**SDK**") API into various applications.

Some samples can work with **Intel® Media Server Studio – HEVC Decoder & Encoder** (hereinafter referred to as "**HEVC Encoder**", "**HEVC Decoder**", "**HEVC**").

Not all of the samples listed below might be applicable and supported for a particular product. Make sure to check the respective release notes document for potential limitations.

## What's New

---

- Transcoding sample (sample\_multi\_transcode) is extended with new options:
  - QSV-FF mode
  - New deinterlace mode (ADI\_SCD and BOB)
- Sample decode now writes data to the file using the color format received from decoder. Previously I420 format was used by default, now you have to specify it explicitly if you want to use it (-i420 option).
- New options are added to sample\_encode:
  - YUY2 input format
  - QSV-FF mode
  - GOP size, IDR Interval
  - I to P frames distance
  - Number of reference frames
  - B pyramid reference option
- V4L2 support is added to sample\_encode.
- sample\_h265\_gaa is not supported any more.

## Package contents

---

**Full list of available samples:**

- **Video Decoding Sample**

Console application which performs decoding of elementary compressed video stream to raw frames. Includes the following features:

- stereoscopic 3D (S3D) rendering of elementary MVC (Multi-View Video Coding) streams
- decoding of HEVC (High Efficiency Video Coding) video via **HEVC Decoder**
- decoding with video post processing (color conversion) of raw video sequences
- screen capturing via screen capture plugin

---

\* Other names and brands may be claimed as the property of others.

OpenCL and the OpenCL logo are trademarks of Apple Inc. used by permission by Khronos.

Copyright © 2016, Intel Corporation

- **Video Encoding Sample**

Console application which performs encoding of raw video frames into elementary compressed stream. Includes the following features:

- video resizing
- video rotation via User Plug-in Sample
- video rotation via User Plug-in Sample using OpenCL™
- encoding HEVC video via **HEVC Encoder**

- **Video Processing Sample**

Console application which performs various video processing algorithms on raw frames.

- **Video Transcoding Sample**

Console application which performs transcoding of elementary video stream from one compressed format to another. Includes the following features:

- multiple video streams transcoding
- video resizing, de-interlacing
- video rotation via User Plug-in Sample
- video rotation via User Plug-in Sample using OpenCL
- video processing using VPP algorithms

- **OpenCL Video Motion Estimation Sample and OpenCL Advanced Video Motion Estimation Samples**

Console application which provides step-by-step guidelines on the using Intel's motion estimation extension for OpenCL standard. The motion estimation extension includes a set of host-callable functions for frame-based Video Motion Estimation.

Each sample includes:

- a readme file for each sub-sample
- source and header files for each sub-sample

**Samples** package has one installer for all sub-samples.

## Software & Hardware Requirements

---

### Hardware:

- Hardware requirements are the same as described in Intel® Media Server Studio Release Notes or Intel® Media Software Development Kit Release Notes (whichever samples are used with)
- (Optional) HDMI\* 1.4, eDP\* 1.1 or similar based monitor/TV as primary display
- (Optional) Active shutter glasses

### Software:

- See <msdk\_install-folder>/media\_server\_studio\_sdk\_release\_notes.pdf for **SDK** general requirements. To build **Samples** you additionally need the following components to be installed and properly configured on the system:
- **For CentOS\*:**

```
$ sudo yum install gcc g++ make cmake perl libX11-devel mesa-libGL-devel
```

- Samples can be built with GCC/G++ compiler version 4.6 and CMake\* version 2.6.2 or higher.
- For samples with OpenCL (**Video Encoding, Video Transcoding, Video Motion Estimation, Interoperability**) it is required to install **Intel® Media Server Studio – Code Builder** and **Intel® Media Server Studio – Graphics Drivers**.

## Build Instructions

---

To build samples the following environment variable should be setup:

```
$ export MFX_HOME=/mediasdk/installation/folder
```

Go to the samples directory and execute `build.pl` script without arguments to see the help:

```
$ ./build.pl
Copyright (c) 2014 Intel® Corporation. All rights reserved.
This script performs Samples projects creation and build.
Usage: perl build.pl --cmake=ARCH,GENERATOR,CONFIG [--clean] [--build]
Possible variants:
  ARCH = intel64
  GENERATOR = make
  CONFIG = debug | release
Environment variables:
  MFX_HOME=/path/to/mediasdk/package # required
  MFX_VERSION="0.0.000.0000" # optional
Optional flags:
  --clean - clean build directory before projects generation / build
  --build - try to build projects before generation (requires
cmake>=2.8.0)
Examples:
  perl build.pl --cmake=intel64,make,debug [ only
generate projects ]
  perl build.pl --cmake=intel64,make,debug --build [ generate
and then build ]
  perl build.pl --cmake=intel64,make,debug --build --clean [ generate,
clean and build ]
```

Script invokes specified CMake\* projects generator and optionally builds them (option available for `cmake>=2.8.0`). At the moment only make files generator for UNIX-like systems is supported. Project files will be placed in the folder named by the requested configuration; for example:

```
/__cmake
intel64.make.release
intel64.make.debug
```

To build generated project files use generator-specific approaches. For example, to build samples from make files invoke:

```
$ make -C <install-folder>/__cmake/intel64.make.release
```

With CMake older than 2.8.0 all samples can be built at once with the following command:

```
$ ./build.pl --cmake=intel64,make,release --clean --build
```

Binaries will appear in the following folder:

```
$ ls -l __cmake/intel64.make.release/__bin/release/
sample_decode
sample_encode
sample_multi_transcode
sample_vpp
```

## Running the Software

---

DRM backend specific notes:

- For application to work thru DRM application should be authorized to access graphics card. VA-API DRM backend supports 2 authentication models:
  - The first model can be applied on the system with no installation of Graphic Server. In this case you need root privileges to run:

```
$ sudo LD_LIBRARY_PATH=$MEDIASDK_INSTALL_FOLDER/bin/x64 \
$ sample_decode h264 -i input.264 -o output.yuv -vaapi -hw
```

- The second model assumes that X server is installed and running. In this case DRM authentication will actually go thru LibVA X11 backend and, thus, thru X server which already has access to the graphic card. The only thing user should be sure in is that he is logged on to the X server (or has access) and DISPLAY environment variable is set properly. For example:

```
$ export DISPLAY=:0.0
$ sudo LD_LIBRARY_PATH=$MEDIASDK_INSTALL_FOLDER/bin/x64 \
$ sample_decode h264 -i input.264 -o output.yuv -vaapi -hw
```

- It can be noted that DRM-itself authentication can still be tried out even with running X server, but you need to remove DISPLAY environment variable and use root privileges:

```
$ export -n DISPLAY
$ sudo LD_LIBRARY_PATH=$MEDIASDK_INSTALL_FOLDER/bin/x64 \
$ sample_decode h264 -i input.264 -o output.yuv -vaapi -hw
```

X11 backend specific notes:

- To use this backend user should be sure that he is logged into X server or is allowed to make connections to the X server
- If user is allowed to use X and logged into machine remotely (thru SSH) he needs DISPLAY environment variable properly set. For example:

```
$ export DISPLAY=:0.0
$ sample_decode h264 -i input.264 -o output.yuv -vaapi -hw
```

## License

---

This software is distributed under the BSD-3 clause license, full text of license is reproduced below:

```
Copyright (c) 2005-2016, Intel Corporation
All rights reserved.
```

```
Redistribution and use in source and binary forms, with or without
modification, are permitted provided that the following conditions are met:
```

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. Neither the name of the copyright holder nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT HOLDER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

## Legal Information

---

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH INTEL PRODUCTS. NO LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT. EXCEPT AS PROVIDED IN INTEL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, INTEL ASSUMES NO LIABILITY WHATSOEVER AND INTEL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY, RELATING TO SALE AND/OR USE OF INTEL PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS OTHERWISE AGREED IN WRITING BY INTEL, THE INTEL PRODUCTS ARE NOT DESIGNED NOR INTENDED FOR ANY APPLICATION IN WHICH THE FAILURE OF THE INTEL PRODUCT COULD CREATE A SITUATION WHERE PERSONAL INJURY OR DEATH MAY OCCUR.

Intel may make changes to specifications and product descriptions at any time, without notice. Designers must not rely on the absence or characteristics of any features or instructions marked "reserved" or "undefined." Intel reserves these for future definition and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them. The information here is subject to change without notice. Do not finalize a design with this information.

The products described in this document may contain design defects or errors known as errata which may cause the product to deviate from published specifications. Current characterized errata are available on request.

Contact your local Intel sales office or your distributor to obtain the latest specifications and before placing your product order.

Copies of documents which have an order number and are referenced in this document, or other Intel literature, may be obtained by calling 1-800-548-4725, or by visiting [Intel's Web Site](#).

MPEG is an international standard for video compression/decompression promoted by ISO. Implementations of MPEG CODECs, or MPEG enabled platforms may require licenses from various entities, including Intel Corporation.

Intel, the Intel logo, Intel Core are trademarks or registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

### Optimization Notice

Intel's compilers may or may not optimize to the same degree for non-Intel microprocessors for optimizations that are not unique to Intel microprocessors. These optimizations include SSE2, SSE3, and SSE3 instruction sets and other optimizations. Intel does not guarantee the availability, functionality, or effectiveness of any optimization on microprocessors not manufactured by Intel.

Microprocessor-dependent optimizations in this product are intended for use with Intel microprocessors. Certain optimizations not specific to Intel microarchitecture are reserved for Intel microprocessors. Please refer to the applicable product User and Reference Guides for more information regarding the specific instruction sets covered by this notice.

Notice revision #20110804

---

\* Other names and brands may be claimed as the property of others.

OpenCL and the OpenCL logo are trademarks of Apple Inc. used by permission by Khronos.

Copyright © 2016, Intel Corporation