Technician Sheet

Installing an RFID cabinet. The SD card already contains all the software. You do not write images, open any software, or type commands.

Only three things to do

- Set the DIP switch to the cabinet number.
- Power on the cabinet.
- Wait until the Raspberry restarts by itself once, then check the status.

Steps

1. Make sure the SD card is in the Raspberry and the network cable is connected.
2. Set the **DIP switch** to the cabinet number (use your team's cabinet-number-to-switch table). Order does not matter: set the switch then power on, or the reverse.
3. **Power on cabinets one at a time.** Do not power on the next cabinet before this one is finished (step 4).
4. **Wait.** The Raspberry will **restart by itself once** - this is normal. Do not unplug or switch it off during this time. Expected: about ____ minutes (fill in after the master test).
5. Check the dashboard / MQTT: **the cabinet name and IP match the cabinet number**. If they do, this cabinet is done.

What is normal

- One restart after the switch is set (only on first power-on or after the switch is changed).
- After that, a power cut or an ordinary restart does not change the cabinet's name or IP.

If something is wrong

What happened	What to do
More than two restarts in a row	Switch the cabinet off, check the DIP switch, power on again. If it repeats, contact your team; change nothing except the switch.
Name or IP on the dashboard is wrong	Check the DIP switch. If it is correct, wait 5 minutes and check again. If still wrong, contact your team.
Cabinet does not appear on the dashboard	Check the network cable and power, wait 5 minutes. If still missing, contact your team.

Changing the cabinet number later

Just **change the DIP switch**. The Raspberry changes its IP and name by itself (and may restart once). No other steps.