# Technician Sheet

Installing an RFID cabinet. The SD card already contains all the software. You do not write images, open any software, or type commands.

**Only three things to do**

- Set the DIP switch to the cabinet number.
- Power on the cabinet.
- Wait until the Raspberry restarts by itself once, then check the status.

## Steps

1. Make sure the SD card is in the Raspberry and the network cable is connected.
2. Set the **DIP switch** to the cabinet number (use your team's cabinet-number-to-switch table). Order does not matter: set the switch then power on, or the reverse.
3. **Power on cabinets one at a time.** Do not power on the next cabinet before this one is finished (step 4).
4. **Wait.** The Raspberry will **restart by itself once** - this is normal. Do not unplug or switch it off during this time. Expected: about ____ minutes (fill in after the master test).
5. Check the dashboard / MQTT: **the cabinet name and IP match the cabinet number**. If they do, this cabinet is done.

## What is normal

- One restart after the switch is set (only on first power-on or after the switch is changed).
- After that, a power cut or an ordinary restart does not change the cabinet's name or IP.

## If something is wrong

| What happened | What to do |
|---|---|
| More than two restarts in a row | Switch the cabinet off, check the DIP switch, power on again. If it repeats, contact your team; change nothing except the switch. |
| Name or IP on the dashboard is wrong | Check the DIP switch. If it is correct, wait 5 minutes and check again. If still wrong, contact your team. |
| Cabinet does not appear on the dashboard | Check the network cable and power, wait 5 minutes. If still missing, contact your team. |

## Changing the cabinet number later

Just **change the DIP switch**. The Raspberry changes its IP and name by itself (and may restart once). No other steps.