

BCD TO EXCESS 3 IN VAMAN ESP

TOTLI VARSHA REDDY

varshareddy724@gmail.com

FWC22038

IITH Future Wireless Communication (FWC)

ASSIGNMENT-10

November 3, 2022

Contents

1 Components	1
2 Implementation	1
2.1 The steps for implementation:	2

Abstract

This manual shows how to represent the K-MAP for expressions for the function W,X,Y,Z shown in below truth table.

DECIMAL	BCD CODE	EXCESS3	
Digit	A B C D	W X Y Z	a b c d e f g
0	0 0 0 0	0 0 1 1	0 0 0 0 1 1 0
1	0 0 0 1	0 1 0 0	1 0 0 1 1 0 0
2	0 0 1 0	0 1 0 1	0 1 0 0 1 0 0
3	0 0 1 1	0 1 1 0	0 1 0 0 0 0 0
4	0 1 0 0	0 1 1 1	0 0 0 1 1 1 1
5	0 1 0 1	1 0 0 0	0 0 0 0 0 0 0
6	0 1 1 0	1 0 0 1	0 0 0 1 1 0 0
7	0 1 1 1	1 0 1 0	0 0 0 1 0 0 0
8	1 0 0 0	1 0 1 1	0 0 0 0 0 0 0
9	1 0 0 1	1 1 0 0	0 1 1 0 0 0 1

1 Components

Components	Values	Quantity
Vaman Board		1
JumperWires	M-F	5
Breadboard		1
USB-C Cable		1
USB-UART		1

2 Implementation

KMAP FOR EQUATIONS

CD \ AB	00	01	11	10
00	0	0	0	1
01	0	1	0	1
11	0	1	0	0
10	0	1	0	0

$$W = AB'C' + A'BD + A'BC$$

CD \ AB	00	01	11	10
00	0	1	0	0
01	1	0	0	1
11	1	0	0	0
10	1	0	0	0

$$X = A'B'D + A'B'C + A'BC'D' + AB'C'D \quad (1)$$

CD \ AB	00	01	11	10
00	1	1	0	1
01	0	0	0	0
11	1	1	0	0
10	0	0	0	0

$$Y = A'C'D' + A'C'D + AB'C'D' \quad (2)$$

AB \ CD				
	00	01	11	10
00	1	1	0	1
01	0	0	0	0
11	0	0	0	0
10	1	1	0	0

$$Z = A'D' + AB'C'D' \quad (3)$$

Karnugh Map : The code below realizes the Boolean logic for W,X,Y,Z using 5V,GND of Vaman Board. 2,3,4,5,6,7,8 GPIO Pins of Vaman Board are configured as input pins and the required Logic for U,V,W are drawn from 5V (Digital '1'),GND (Digital '0'). Built in led will glow based on G satisfying the Table

2.1 The steps for implementation:

1. Connect the USB-UART pins to the Vaman ESP32 pins according to Table

VAMAN LC PINS	UART PINS
GND	GND
ENB	ENB
TXD0	RXD
RXD0	TXD
0	IO0
5V	5V

2. Flash the following setup code through USB-UART using laptop

```
https://github.com/9705701645/FWC/blob/main/iot/codes/setup/src/main.cpp
```

```
svn co https://github.com/9705701645/FWC/trunk/iot/codes/setup
cd setup
pio run
pio run -t upload
```

after entering your wifi username and password (in quotes below)

```
#define STASSID "... " // Add your network
credentials
#define STAPSK "... "
```

in src/main.cpp file

3. You can notice that vaman will be connected to the network credentials provided above. Connect your laptop to the same network ,You should be able to find the ip address of your vaman-esp on laptop using

```
ifconfig
nmap -sn 192.168.6.1/24
```

where your computer's ip address is the output of ifconfig and given by 192.168.6.x

4. Login to termux-ubuntu on the android device and execute the following commands:

```
proot--distro login debian
cd /data/data/com.termux/files/home/
mkdir iot
svn co https://github.com/9705701645/FWC/trunk/iot/codes/ota
cd codes
```

5. Assuming that the username is krishna and password is 123, flash the following code wirelessly

```
https://github.com/9705701645/FWC/blob/main/iot/codes/ota/src/main.cpp
```

through

```
pio run
pio run -t nobuild -t upload --upload-port
ip_address_of_esp
```

where you may replace the above ip address with the ip address of your vaman-esp.