



PART K Quick Reference Cards

Seven one-page cards: rig layout, desk layout, DMX and network, specials and looks, system connections, first-time setup, and session start-up and shut-down.

Revision R13.1 · 28 September 2026

1 Rig layout

One FOH bar (C42s fixed), two stage bars (LX1, LX2) and a floor boom in each wing. Projector at LX1 centre, throwing upstage onto the screen.

Position	Fixtures (desk numbers)	Qty
FOH bar (fixed)	12 × Lightsky C42 #1–12 in number order from the SR end, cannot be moved · faces #1+4, #5+8, #9+12 · SP2 #2, V1 #3, SP1 #6, V2 #7, SP4 #10, SP3 #11	12
LX1 — downstage bar	6 × Zoom #13–18 colour wash	6
LX2 — upstage bar	2 × Zoom #19–20 (V3 Theodore, V4 Marina) · 6 × TourCOB #23–28 · 3 × PixBar · TourCOB #39 on the wall bracket	12
Pelmet front (fixed)	3 × PixBar — tabs/apron wash, cannot be moved	3
SR floor boom	Zoom #21 high · TourCOB #29 mid, #30 shin	3
SL floor boom	Zoom #22 high · TourCOB #31 mid, #32 shin	3
Floor, upstage	Hazer #40	1
Optional	Pinspots #41–42 on the FOH bar ends (mirror ball only)	(2)

THE RULES

Faces come from FOH (C42 cross pairs #1+4, #5+8, #9+12; the C42s are fixed, focus only). LX1 = colour top wash. LX2 = backlight + PixBars, focused downstage and never onto the screen (R-25). Booms = side colour across the stage (R-26). Every fixture keeps its desk number and address wherever it hangs. Proposed wet zone mid-stage audience-left — confirm at the site walk.

2 Desk layout

LSC Mantra Lite + 2 wings · TLM_SHOW_2026_R13_FLASHY_SCENE_SPLIT.mtr · QLab fires every cue — the desk is the backup.

Page	Purpose	Memories
P1	Venue / rig base	M1 STAGE WORK · M2 FULL WHITE · M3 WARM · M4 COOL · M5 BLUE · M6 RED · M9 PIXBAR WASH · M10 CURTAIN CALL
P2	Act One — scene sections	M1 Q1–11 · M2 Q12–17 · M3 ship/storm Q18–27.5 · M4 shore/duet Q28–30.5 · M5 bar/transformation Q31–37 · M6 interval Q38 · M9 WORK/FOCUS · M10 SAFE LIGHT
P3	Act Two — scene sections	M1 palace Q39–44 · M2 jellyfish Q45–49 · M3 lair/voice/haywire Q50–58.5 · M4 dry land Q59–59.7 · M5 wedding Q60–63.5 · M6 bows/end Q64–65
P4	Songs	M1 S1 Rock Lobster ... M10 S10 He's a Pirate
P5	FX / chases	M1 WARM CHASE · M2 COOL CHASE · M3 PARTY CHASE · M4 HAZE · M5 HAYWIRE · M6 JELLY PULSE
P6	Look library	M01 BLACKOUT ... M10 MAGIC
P7	Look library	M11 LAIR ... M16 BOWS · M7 = M17 SAFE LIGHT
P8	Backup / reference	M1 = the full 153-position list (BACKUP - 01 PRESHOW ...)
Control	Use	
P2 M10 SAFE LIGHT	Emergency face light (QLab E3 fires it too)	
Next Cue on a P2/P3/P4 memory	Backup only, if QLab or the network fails — press again after each flash	
P5 M4 HAZE	Hazer #40 on its fader (50 %, fan 50 %)	
P5 M5 HAYWIRE	QLab starts it at Q57 and stops it at Q57b	
P5 M6 JELLY PULSE	Bump for extra Q47 repeats	
O · A then L · T then S	All Cues Off · Clear All · Save	

NO LINK TIMES

No link times are set on the desk: QLab fires every flash return (Q21, Q23, Q25 +0.2 s · Q35 +0.3 s · Q47 +1 s · Q57b +0.3 s) and releases each memory as it leaves it.

3 DMX and network

Universe 1 on the desk XLR, universe 2 over Ethernet to a node. One chain per universe, terminated.

U	Addresses	Fixtures
U1	1–36	PixBars #33–38 (6 ch)
U1	37–38	Pinspots #41–42 (optional)
U1	301–420	Zooms #13–22 (12 ch)
U1	421–486	TourCOB #23–32, #39 (6 ch)
U1	487–488	Hazer #40 (2 ch)
U2	101–232	Lightsky C42 #1–12 (11 ch)
Item	Setting	
Desk	2.0.0.1 / 255.0.0.0, DHCP off · Art-Net + sACN on (turn off the unused one)	
U1 route	Desk XLR → LX1 → LX2 → SR boom → SL boom → hazer · terminate	
U2 route	Desk Ethernet → switch → node 2.0.0.10 → FOH C42 #1–12 · terminate	
Node	sACN universe 2, or Art-Net 0-0-1	
QLab → desk	OSC Play Memory, UDP 2.0.0.1 port 8000 (add the trigger on the desk)	

KEEP AT 0

Control, Strobe, Reset, Auto speed, Other, Default, Zoom (except in focus), CCT and Colour macro. Modes: C42 11 ch · Zoom 12 ch · COB 6 ch · PixBar 6 ch · hazer 2 ch.

4 Specials, looks and critical sequences

Special	Character	Fixture	Mark
SP1	Ariel	#6 C42 FOH	DSC
SP2	Spirit	#2 C42 FOH	DS audience-left
SP3	Octavia	#11 C42 FOH	US audience-right
SP4	Shell	#10 C42 FOH	Plinth
V1–V2	Dame, Flanders	#3, #7 C42 FOH	Voice marks 1–2
V3–V4	Theodore, Marina	#19–20 Zoom 13° LX2	Voice marks 3–4

Look	Desk	Colour
M01 BLACKOUT	P6 M1	
M02 HOUSE	P6 M2	
M03 UNDERWATER	P6 M3	
M04 COMEDY	P6 M4	
M05 ROYAL	P6 M5	
M06 SHIP	P6 M6	
M07 SHORE	P6 M7	
M08 STORM	P6 M8	
M09 LIGHTNING	P6 M9	

Look	Desk	Colour
M10 MAGIC	P6 M10	
M11 LAIR	P7 M1	
M12 VOICE SHELL	P7 M2	
M13 JELLYFISH	P7 M3	
M14 DRYLAND	P7 M4	
M15 WEDDING	P7 M5	
M16 BOWS	P7 M6	
M17 SAFE LIGHT	P7 M7	

Sequence	Cues	Desk	Note
Storm	Q20–27.5	P2 M3	Flashes 21/23/25 return +0.2 s (QLab)
Transformation	Q33–36	P2 M5	35 white hit → 35b +0.3 s
Voice transfer	Q52–57b	P3 M3	Shell → Dame → Flanders → Theodore → Marina; HAYWIRE Q57 → Q57b
Jellyfish	Q45–49	P3 M2	47 pulse returns +1 s; repeats on P5 M6

5 System connections

How QLab, the Mantra, the StudioLive, the node and the projector link. Subnet 255.0.0.0 for everything.

Device	IP	Settings
Mantra Lite	2.0.0.1	Art-Net + sACN · OSC Play Memory trigger port 8000
Art-Net / sACN node	2.0.0.10	Universe 2
QLab Mac	2.0.0.20	Manual IPv4 · Wi-Fi off · MANTRA patch → 2.0.0.1:8000 on the Ethernet interface
Backup Mac	2.0.0.21	Optional — songs as plain files (R-08)
StudioLive 16	2.0.0.30	Optional — iPad / UC Surface
Link	Carries	
QLab → StudioLive (USB)	Playback on ch 11–12 · backup playback ch 13–14 · radios ch 1–8	
QLab → projector (HDMI via HDBaseT)	Backdrops · VID-99 black	
Stream Deck → QLab (USB)	GO · Panic · F13/F14/F15 → E2/E3/E1	
Desk XLR / Ethernet	Universe 1 DMX · universe 2 Art-Net/sACN via node	

TEST IN THIS ORDER

1 Sound: any QLab cue — level on ch 11–12. 2 Lights: QLab E3 SAFE LIGHT — desk plays P2 M10; then Q4 — desk plays P2 M1 cue 4. 3 Universe 2: C42 #1 up. 4 Video: Q4 — BG-02 fades up; E2 → black.

6 First-time setup

Once, at the first venue session. About three hours with the rig hung.

1 Rig and patch

1. Hang and focus (card 1); booms weighted; projector on the bar with its bond.
2. Check modes and addresses (Part C); cable U1 and U2; terminate both.

2 Network

1. Mantra, node and QLab Mac on the show switch. No internet, no Wi-Fi.
2. Mac: Network > Ethernet > TCP/IP > Manually 2.0.0.20 / 255.0.0.0, router blank. Node 2.0.0.10.

3 Mantra

1. Tools > Export Show (venue backup).
2. Tools > Import Show > TLM_SHOW_2026_R13_FLASHY_SCENE_SPLIT.mtr. Check P2 Act One, P3 Act Two, P4 songs, P5 FX, P8 backup.
3. Tools > Setup > Remote Triggers > Add > OSC · Play Memory · port 8000. Turn off Art-Net or sACN (whichever the node doesn't use).
4. Save (T S) and set as Default Show. **No link times needed.**

4 QLab Mac

1. Harden the Mac (R-07); install QLab 5 and the licence.
2. Put TLM_R13_REBUILT_Show_Files on the Desktop (exact name). Open TLM_Show_R13_1.qlab5.
3. Workspace Settings: Audio → StudioLive USB · Video Stage 1 → projector · Network MANTRA → Ethernet interface. Save.
4. Check no red cues; select Q4's audio — target ends in _v2.wav.

5 StudioLive

1. USB to the Mac: ch 11–12 = USB (QLab), 13–14 = backup, radios 1–8.
2. Gains/EQ; principals on one DCA; save scene TLM SHOW.

6 Stream Deck

1. Import TLM QLab Show.streamDeckProfile.
2. In QLab give E2 hotkey F13, E3 F14, E1 F15 (Triggers tab); save.

7 Test and back up

1. Step through a cue-to-cue from Q1 (Part L); fix anything red.
2. Export the Mantra show to USB; copy the whole show folder to a second drive.

7 Start-up and shut-down — every session

When	Do
T-90 power up	Mains/RCDs → fixtures, node, switch → Mantra (loads the Default Show) → projector → StudioLive (scene TLM SHOW) → amps last
T-80 QLab Mac	Wi-Fi off, charger in. Open TLM_Show_R13_1.qlab5 from the Desktop folder. No red cues; Stream Deck profile; projector = Stage 1 (not mirrored)
T-70 system check	E3 SAFE LIGHT → desk plays P2 M10; ROW memories check every fixture; a QLab cue → ch 11–12; Q4 → BG-02; E2 → black
T-45 reset	Esc (Panic) in QLab; Mantra O (All Cues Off). Playhead on Q1; Show Mode. Haze check and detector isolation logged (R-13)
T-30 house open	SM calls Q1 → GO. From here every cue is one GO in QLab (Space or Stream Deck)
Shut-down	
1	QLab: Esc (Panic), then save
2	Amps / speakers off first
3	StudioLive off (save the scene if changed)
4	Projector standby — let the fan finish
5	Mantra: save if changed, export to USB, power off
6	Fixtures, node, switch off; Mac off; hazer off and clean

IF SOMETHING FAILS MID-SHOW

Lights: the matching Mantra P2/P3/P4 memory with Next Cue (again after each flash) · SAFE LIGHT = P2 M10. Sound: backup playback ch 13–14. Video: E2 black or AV-mute. Keep going — the SM decides on any hold.