# config_events

Command: `config_events`

## Description

Enables or disables specific device events. To apply the changes, a device reboot is required. For RFD4090 devices, only the following events are supported: terminalConnection, firmwareUpdate, network, exceptions, ntp, heartbeat, power, battery, and fileDownload.

## Request

### Request Fields

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
|---|---|---|---|---|
| `command` | string | Yes | Command issued to configure events & alert threshold values | `config_events` |
| `requestId` | string | Yes | A unique identifier for the request, allowing tracking and debugging of the operation. | `abc123` |
| `eventConfiguration` | object | No | | |
| `eventConfiguration.antenna` | boolean | No | set to true to enable antenna events | |
| `eventConfiguration.terminalConnection` | boolean | No | set to true to enable terminal connection/disconnection events | |
| `eventConfiguration.firmwareUpdate` | boolean | No | set to true to enable fw update events | |

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
|---|---|---|---|---|
| `eventConfiguration.gpi` | boolean | No | set to true to enable gpi events | |
| `eventConfiguration.network` | boolean | No | set to true to enable network events | |
| `eventConfiguration.exceptions` | boolean | No | set to true to enable exception events | |
| `eventConfiguration.ntp` | boolean | No | set to true to enable battery alerts | |
| `eventConfiguration.userApp` | boolean | No | set to true to enable user app events | |
| `eventConfiguration.heartbeat` | boolean | No | set to true to enable heart beat | |
| `eventConfiguration.power` | boolean | No | set to true to enable power source alerts | |
| `eventConfiguration.battery` | boolean | No | set to true to enable battery alerts | |
| `eventConfiguration.temperature` | boolean | No | set to true to enable temperature alerts | |
| `eventConfiguration.fileDownload` | boolean | No | set to true to enable file download alerts | |
| `eventConfiguration.cpuUsage` | boolean | No | set to true to enable cpu usage alerts | |
| `eventConfiguration.flashUsage` | boolean | No | set to true to enable flash usage alerts | |
| `eventConfiguration.ramUsage` | boolean | No | set to true to enable ram usage alerts | |

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
|---|---|---|---|---|
| `eventConfiguration.heartbeatConfiguration` | object | No | | |
| `eventConfiguration.heartbeatConfiguration.interval` | integer | No | heart beat interval in seconds | `100` |
| `eventConfiguration.heartbeatConfiguration.inventoryStatus` | boolean | No | set to true to enable inventory status as part of heartbeat message | |
| `eventConfiguration.heartbeatConfiguration.batteryStatus` | boolean | No | set to true to enable battery status as part of heartbeat message | |
| `eventConfiguration.heartbeatConfiguration.userApps` | boolean | No | set to true to enable user app status as part of heartbeat message | |
| `eventConfiguration.cpuThreshold` | integer | No | cpu usage value(%) above which alert will be triggered | |
| `eventConfiguration.ramThreshold` | integer | No | ram usage value(%) above which alert will be triggered | |
| `eventConfiguration.flashThreshold` | integer | No | flash usage value(%) above which alert will be triggered | |
| `eventConfiguration.temperatureThreshold` | integer | No | temperature treshold value above which alert will be triggered | |

## Request Examples

### Enable all events

```
{
  "command": "config_events",
  "requestId": "abc123",
  "eventConfiguration": {
    "antenna": true,
    "terminalConnection": true,
    "firmwareUpdate": true,
    "gpi": true,
    "network": true,
    "exceptions": true,
    "ntp": true,
    "userApp": true,
    "heartbeat": true,
    "power": true,
    "battery": true,
    "temperature": true,
    "fileDownload": true,
    "cpuUsage": true,
    "flashUsage": true,
    "ramUsage": true,
    "heartbeatConfiguration": {
      "interval": 100,
      "inventoryStatus": true,
      "batteryStatus": true,
      "userApps": true
    },
    "cpuThreshold": 80,
    "ramThreshold": 80,
    "flashThreshold": 80,
    "temperatureThreshold": 55
  }
}
```

**Selective events**

```
{
  "command": "config_events",
  "requestId": "abc123",
  "eventConfiguration": {
    "antenna": false,
    "terminalConnection": true,
    "firmwareUpdate": true,
    "gpi": false,
    "network": true,
```

```
    "exceptions": false,
    "ntp": false,
    "userApp": false,
    "heartbeat": false,
    "power": true,
    "battery": true,
    "temperature": true,
    "fileDownload": true,
    "cpuUsage": false,
    "flashUsage": false,
    "ramUsage": false
  }
}
```

## Response

### Response Fields

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
|---|---|---|---|---|
| `command` | string | Yes | | `config_events` |
| `requestId` | string | Yes | | `abc123` |
| `apiVersion` | string (enum) | Yes | | `V1.1` |
| `response` | object | Yes | Status of the command execution — check `code` to confirm success (0) or identify the error. | |

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
| --- | --- | --- | --- | --- |
| `response.code` | integer | Yes | Response code indicating success or failure.<br>• **0** — Success<br>• **1** — Command payload accepted<br>• **2** — Invalid payload<br>• **3** — Not able to retrieve information<br>• **4** — Firmware update in progress<br>• **5** — Can't reboot, inventory in progress<br>• **6** — Region is not configured<br>• **7** — Interface is not available<br>• **8** — Insufficient flash size<br>• **9** — File not found<br>• **10** — Configuration already exists<br>• **11** — Inventory in progress<br>• **12** — No radio operation in progress<br>• **13** — Firmware update failed<br>• **14** — Battery too low for firmware update<br>• **15** — WIFI: SSID not found | `0` |

| FIELD | TYPE | REQUIRED | DESCRIPTION | EXAMPLE |
|---|---|---|---|---|
| | | | • **16** — WIFI: Cannot delete active SSID<br>• **17** — WIFI: SSID missing<br>• **18** — WIFI: SSID already exists<br>• **19** — WIFI: SSID count overflow<br>• **20** — WiFi is not supported<br>• **21** — Certificate not found<br>• **22** — Advanced configuration not set<br>• **23** — Invalid enum value<br>• **24** — Max 32 prefilters limit exceeded<br>• **25** — Max 3 publish topics exceeded<br>• **26** — Max 1 subscribe topic exceeded<br>• **27** — Invalid tenant ID length<br>• **28** — Tag match pattern length exceeded | |
| `response.description` | string | Yes | Human-readable description of the response code (e.g. "Success", "Invalid payload"). | `Success` |

## Response Examples

### example1

```
{
  "command": "config_events",
  "requestId": "abc123",
  "apiVersion": "V1.1",
  "response": {
    "code": 0,
    "description": "Success"
  }
}
```