get_endpoint_config

Command: `get_endpoint_config`

Description

Command to get configured endpoints.If API does not included endpointName argument, then response includes all active endpoints detailed configuration & list of all saved endpoint names otherwise response includes interested endpoints configuration only

Download pdf: [Download get_endpoint_config as PDF](https://aa5123.github.io/zebra-rfd40-rfd90-iot-docs/command-pdfs/get_endpoint_config.pdf)

Request

Request Fields

Field	Type	Required	Description	Example
`command`	string	Yes	Specifies the operation being performed, in this case, retrieving the endpoint configuration.	
`requestId`	string	Yes	A unique identifier for the request, allowing tracking and debugging of the operation.	`123`
`endpointDetails`	object	No		
`endpointDetails.endpointName`	string	No		

Request Examples

Active endpoint config

```
{
  "command": "get_endpoint_config",
  "requestId": "abc123"
}
```

Specific endpoint config

```
{
  "command": "get_endpoint_config",
  "requestId": "def456",
  "endpointDetails": {
    "endpointName": "ctrl"
  }
}
```

Response

Response Fields

Field	Type	Required	Description	Example
`command`	string	No	The command indicating the type of operation or request being performed.	
`requestId`	string	No	A unique identifier for the request, used for tracking and correlation purposes.	`123`
`apiVersion`	string	No	The version of the API being used for the request.	`V1.1`
`epDetails`	object	No		
`epDetails.activeEndpoints`	object	No		
`epDetails.activeEndpoints.epConfig`	array	No	An array containing endpoint configurations.	
`epDetails.savedEndpoints`	object	No		
`epDetails.savedEndpoints.epNames`	array	No	An array containing endpoint configurations.	

Field	Type	Required	Description	Example
`response`	object	No	Status of the command execution — check `code` to confirm success (0) or identify the error.	

Field	Type	Required	Description	Example
`response.code`	integer	Yes	Response code indicating success or failure. • **0** — Success • **1** — Command payload accepted • **2** — Invalid payload • **3** — Not able to retrieve information • **4** — Firmware update in progress • **5** — Can't reboot, inventory in progress • **6** — Region is not configured • **7** — Interface is not available • **8** — Insufficient flash size • **9** — File not found • **10** — Configuration already exists • **11** — Inventory in progress • **12** — No radio operation in progress • **13** — Firmware update failed • **14** — Battery too low for firmware update • **15** — WIFI: SSID not found • **16** — WIFI: Cannot delete active SSID • **17** — WIFI: SSID missing	`0`

Field	Type	Required	Description	Example
			• **18** — WIFI: SSID already exists • **19** — WIFI: SSID count overflow • **20** — WiFi is not supported • **21** — Certificate not found • **22** — Advanced configuration not set • **23** — Invalid enum value • **24** — Max 32 prefilters limit exceeded • **25** — Max 3 publish topics exceeded • **26** — Max 1 subscribe topic exceeded • **27** — Invalid tenant ID length • **28** — Tag match pattern length exceeded	
`response.description`	string	Yes	Human-readable description of the response code (e.g. "Success", "Invalid payload").	`Success`

Response Examples

Active endpoint config

```
{
  "command": "get_endpoint_config",
  "requestId": "abc123",
  "apiVersion": "V1.1",
  "endpointResponse": {
    "activeEndpoints": {
      "epConfig": [
        {
          "configuration": {
```

```
            "endpointName": "mgmt3",
            "epType": "MGMT",
            "protocol": "MQTT",
            "activate": true,
            "url": "10.231.145.104",
            "verificationType": "VERIFY_NONE",
            "port": 1883,
            "qosCommon": 0,
            "tenantId": "zebra",
            "mqttParams": {
              "keepAlive": 96,
              "cleanSession": false,
              "reconnectDelayMin": 5,
              "reconnectDelayMax": 512,
              "username": "mqttuser",
              "password": "xxxxxx",
              "publishTopics": [
                {
                  "topic": "MGMT/clients/resp",
                  "qos": 0,
                  "retain": false
                },
                {
                  "topic": "MGMT/clients/rfid",
                  "qos": 0,
                  "retain": true
                }
              ],
              "subscribeTopics": [
                {
                  "topic": "MGMT/clients/cmnd",
                  "qos": 0,
                  "retain": false
                }
              ]
            },
            "securityParams": {
              "format": "PEM"
            },
            "eventConfiguration": {
              "terminalConnection": false,
              "firmwareUpdate": true,
              "network": true,
              "ntp": true,
              "heartbeat": false,
              "power": true,
              "battery": true,
```

```
              "fileDownload": true
            }
          }
        }
      ]
    },
    "savedEndpoints": {
      "epNames": [
        "ctrlEP",
        "ctrl",
        "gmdm",
        "dataEP",
        "mgmt3"
      ]
    }
  },
  "response": {
    "code": 0,
    "description": "Success"
  }
}
```

Specific endpoint config

```
{
  "command": "get_endpoint_config",
  "requestId": "abc123",
  "apiVersion": "V1.1",
  "endpointResponse": {
    "activeEndpoints": {
      "epConfig": [
        {
          "configuration": {
            "endpointName": "ctrl",
            "epType": "CTRL",
            "protocol": "MQTT",
            "activate": true,
            "url": "10.209.240.104",
            "verificationType": "VERIFY_NONE",
            "port": 1883,
            "qosCommon": 0,
            "tenantId": "zebra",
            "mqttParams": {
              "keepAlive": 96,
              "cleanSession": false,
              "reconnectDelayMin": 5,
              "reconnectDelayMax": 512,
```

```
            "username": "mqttuser",
            "password": "xxxxxx",
            "publishTopics": [
              {
                "topic": "CTRL/clients/resp",
                "qos": 0,
                "retain": false
              },
              {
                "topic": "CTRL/clients/event",
                "qos": 0,
                "retain": false
              },
              {
                "topic": "CTRL/clients/rfid",
                "qos": 0,
                "retain": true
              }
            ],
            "subscribeTopics": [
              {
                "topic": "CTRL/clients/cmnd",
                "qos": 0,
                "retain": false
              }
            ]
          },
          "securityParams": {
            "format": "PEM"
          },
          "eventConfiguration": {
            "terminalConnection": false,
            "firmwareUpdate": true,
            "network": true,
            "ntp": true,
            "heartbeat": false,
            "power": true,
            "battery": true,
            "fileDownload": true
          }
        }
      }
    ]
  }
},
"response": {
  "code": 0,
```

```
    "description": "Success"
  }
}
```