get_eth

Command: `get_eth`

Description

This API used to retrieve ethernet configuration details. Security features, static IP configuration, and IPv6 support are not available in the current API version.

Download pdf: [Download get_eth as PDF](https://aa5123.github.io/zebra-rfd40-rfd90-iot-docs/command-pdfs/get_eth.pdf)

Request

Request Fields

Field	Type	Required	Description	Example
`command`	string	Yes	Command issued to get the ethernet configuration	`get_eth`
`requestId`	string	Yes	A unique identifier for the request, allowing tracking and debugging of the operation.	`abc123`

Request Examples

Generated Example

```
{
  "command": "get_eth",
  "requestId": "abc123"
}
```

Response

Response Fields

Field	Type	Required	Description	Example
`command`	string	No		`get_eth`
`requestId`	string	No		`abc123`

Field	Type	Required	Description	Example
`apiVersion`	string (enum)	No		`V1.1`
`ethConfig`	object	No	Detailed schema for Ethernet configuration.	
`ethConfig.interfaceDetails`	object	No		
`ethConfig.interfaceDetails.interfaceName`	string	Yes	Name of the network interface.	`eth0`
`ethConfig.interfaceDetails.status`	string (enum)	Yes	Status of the network interface.	`enabled`
`ethConfig.interfaceDetails.hostname`	string	Yes	Hostname assigned to the device.	`RFD40AB03`
`ethConfig.interfaceDetails.macAddress`	string	Yes	MAC address of the network interface.	`E0-D0-45-3D-38-1D`
`ethConfig.interfaceDetails.linkStatus`	object	No		
`ethConfig.interfaceDetails.linkStatus.status`	string (enum)	Yes	Current status of the network link.	`up`
`ethConfig.interfaceDetails.linkStatus.linkSpeed`	string	Yes	Speed of the network link.	`100Mbps`
`ethConfig.interfaceDetails.ipv4Configuration`	object	No		
`ethConfig.interfaceDetails.ipv4Configuration.ipAddress`	string	No	IPv4 address of the network interface.	`192.168.1.81`
`ethConfig.interfaceDetails.ipv4Configuration.subnetMask`	string	No	Subnet mask for the IPv4 configuration.	`255.255.255.0`

Field	Type	Required	Description	Example
`ethConfig.interfaceDetails.ipv4Configuration.gateway`	string	No	Gateway address for the IPv4 configuration.	`192.168.1.144`
`ethConfig.interfaceDetails.ipv4Configuration.enableDhcp`	boolean (enum)	No	Indicates if DHCP is enabled for IPv4 configuration.	`enabled`
`ethConfig.interfaceDetails.ipv4Configuration.dnsServer`	string	No	DNS server address for the IPv4 configuration.	`192.168.1.78`
`ethConfig.interfaceDetails.ipv4Configuration.domainName`	string	No	Domain name for the IPv4 configuration.	`test.soti.com`
`ethConfig.interfaceDetails.ipv6Configuration`	object	No		``
`ethConfig.interfaceDetails.ipv6Configuration.ipAddress`	string	No	IPv6 address of the network interface.	`fe80::1643:8376:b32:4a16`
`ethConfig.interfaceDetails.ipv6Configuration.prefix`	integer	No	Prefix length for the IPv6 configuration.	`64`
`ethConfig.interfaceDetails.ipv6Configuration.gateway`	string	No	Gateway address for the IPv6 configuration.	`2a02:1234:420a:100b::99`
`ethConfig.interfaceDetails.ipv6Configuration.enableAuto`	boolean	No	Indicates if auto-configuration is enabled for IPv6.	`True`
`ethConfig.interfaceDetails.ipv6Configuration.dnsServer`	string	No	DNS server address for the IPv6 configuration.	`2001:4860:4860::9999`
`ethConfig.interfaceDetails.ipv6Configuration.domainName`	string	No	Domain name for the IPv6 configuration.	`test.soti.com`

Field	Type	Required	Description	Example
`ethConfig.interfaceDetails.security`	object	No		
`ethConfig.interfaceDetails.security.securityStatus`	boolean	No	Indicates if security features are enabled.	`True`
`ethConfig.interfaceDetails.security.EAP802_1X`	object	No		
`ethConfig.interfaceDetails.security.EAP802_1X.authentication`	string (enum)	No	Authentication method for 802.1X security.	`PEAP`
`ethConfig.interfaceDetails.security.EAP802_1X.innerAuthentication`	string (enum)	No	Inner authentication method for 802.1X security.	`EAP-MS-CHAPv2`
`ethConfig.interfaceDetails.security.EAP802_1X.certificate`	string	No	Certificate used for 802.1X authentication.	`client45`
`response`	object	No	Status of the command execution — check `code` to confirm success (0) or identify the error.	

Field	Type	Required	Description	Example
`response.code`	integer	Yes	Response code indicating success or failure. • **0** — Success • **1** — Command payload accepted • **2** — Invalid payload • **3** — Not able to retrieve information • **4** — Firmware update in progress • **5** — Can't reboot, inventory in progress • **6** — Region is not configured • **7** — Interface is not available • **8** — Insufficient flash size • **9** — File not found • **10** — Configuration already exists • **11** — Inventory in progress • **12** — No radio operation in progress • **13** — Firmware update failed • **14** — Battery too low for firmware update • **15** — WIFI: SSID not found • **16** — WIFI: Cannot delete active SSID • **17** — WIFI: SSID missing	`0`

Field	Type	Required	Description	Example
			• **18** — WIFI: SSID already exists • **19** — WIFI: SSID count overflow • **20** — WiFi is not supported • **21** — Certificate not found • **22** — Advanced configuration not set • **23** — Invalid enum value • **24** — Max 32 prefilters limit exceeded • **25** — Max 3 publish topics exceeded • **26** — Max 1 subscribe topic exceeded • **27** — Invalid tenant ID length • **28** — Tag match pattern length exceeded	
`response.description`	string	Yes	Human-readable description of the response code (e.g. "Success", "Invalid payload").	`Success`

Response Examples

Ethernet config info

```
{
  "command": "get_eth",
  "requestId": "abc123",
  "apiVersion": "V1.1",
  "ethconfig": {
    "InterfaceDetails": {
      "interfaceName": "eth0",
      "status": "Enabled",
      "hostName": "RFD40-211545201D0020",
```

```
      "macAddress": "AC:3F:A4:00:2C:89",
      "linkStatus": {
        "status": "Connected",
        "linkSpeed": "100Mbps"
      },
      "ipv4Configuration": {
        "ipAddress": "192.168.0.101",
        "subnetMask": "255.255.255.0",
        "gateway": "192.168.0.1",
        "enableDhcp": true,
        "dnsServer": "0.0.0.0",
        "domainName": "zebra.com"
      }
    }
  },
  "response": {
    "code": 0,
    "description": "Success"
  }
}
```