

I2C 1602LCD 使用说明

LCD Display (Blue and YELLOW) with I2C/TWI Interface



Note: Updated for the 4 line 20 character displays: see bottom.

These displays are Available [HERE](#):

NOTE! These displays are very clear bright white on dark blue (or Yellow) background: it is difficult to get a good digital photo due to polarization effects.

With limited pin resources, your project may be out of pins using a normal LCD shield. With this I2C interface LCD module, you only need 2 lines (I2C) to display information. If you already have I2C devices in your project, this LCD module actually uses no more pins at all. More information about I2C/TWI ([Wikipedia](#))

This unit connects with 4 wires including Vcc and Gnd. It is easiest with a 4-wire cable (supplied) that plugs into the Sensor Shield communications connector.

But you can wire it directly yourself if needed: There are 4 pins on the display.. (see photo below)





Top to bottom:

GND – GND

VCC - 5V

SDA - ANALOG Pin 4

SCL - ANALOG pin 5

On most Arduino boards, SDA (data line) is on analog input pin 4, and SCL (clock line) is on analog input pin 5. On the Arduino Mega, SDA is digital pin 20 and SCL is 21.

NOTE: The Blue Potentiometer (Photo) adjusts Contrast. If you don't see any characters, adjust it. Start clockwise and back down to where the characters are bright and the background does not have boxes behind the characters.

See this LCD used in Temperature-Humidity project.

Specifications:

Interface: I2C

I2C Address: 0x27

Back lit (Blue with white char color)

Supply voltage: 5V

Weight:40 gram

LiquidCrystal_I2C Library Support Functions

LiquidCrystal()

begin()

clear()

home()

setCursor(col,row)

write()

print()

cursor()

noCursor()

blink()

noBlink()

display()

noDisplay()
scrollDisplayLeft()
scrollDisplayRight()
autoscroll()
noAutoscroll()
leftToRight()
rightToLeft()
noBacklight()
backlight()
createChar(loc[0..7], Pixels Array[8])