control-systems: the Control Systems program — user guide

control-systems-ai999x 1.1.0, Rust build: command line, desktop app and browser. **Creator / engineer:** Ibnul Jaif Farabi · **Company:** AI999X · support@ai999x.com

Control Systems covers transfer functions, poles and zeros, step and frequency response, stability (Routh-Hurwitz, gain and phase margins, Nyquist), root locus, state space, controllability and observability, pole placement, LQR, Kalman filters, discretization and PID tuning. This guide is about `control-systems`, the model as a self-contained program for Windows and Linux: 97 capabilities in 16 topics, answered on your own computer with no network, no Python and nothing else to install. The same compiled model runs in the AI999X desktop app and in the browser on the model's page (https://www.ai999x.com/models/control-systems-ai999x/); the Python package (`pip install control-systems-ai999x`) has its own guide. Every command output printed here is what the program printed.

Contents

- 1. Get it: desktop app, command line, browser, Python
- 2. Quick start
- 3. Writing inputs
- 4. Outcomes and exit codes
- 5. Scripts and agents: batch and JSON
- 6. Figures
- 7. In a web page or Node.js: WebAssembly
- 8. Every capability

1. Get it

Version 1.4.0 of the AI999X desktop app and of the command-line bundle. Checksums for every file: https://downloads.ai999x.com/desktop/1.4.0/SHA256SUMS; the newest version is always under https://downloads.ai999x.com/desktop/latest/. Full instructions: https://www.ai999x.com/desktop-cli/

what	system	download
Desktop app: Control Systems	Windows x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-control-systems-1.4.0-windows-x86_64.zip
Desktop app: Control Systems	Linux x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-control-systems-1.4.0-linux-x86_64.tar.gz
Desktop app: all models	Windows x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-1.4.0-windows-x86_64.zip
Desktop app: all models	Linux x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-1.4.0-linux-x86_64.tar.gz
Command line	Windows x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-cli-1.4.0-windows-x86_64.zip
Command line	Linux x86-64	https://downloads.ai999x.com/desktop/1.4.0/ai999x-cli-1.4.0-linux-x86_64.tar.gz

Desktop app

Control Systems in its own app: search, questions in words, input forms, live figures and explanations. Windows: Download ai999x-control-systems-1.4.0-windows-x86_64.zip, right-click it → Extract All, then open the folder and start ai999x-control-systems.exe. If Windows SmartScreen asks, choose More info → Run anyway. Linux:

```
curl -LO https://downloads.ai999x.com/desktop/1.4.0/ai999x-control-systems-1.4.0-linux-
x86_64.tar.gz
curl -LO https://downloads.ai999x.com/desktop/1.4.0/SHA256SUMS
sha256sum -c --ignore-missing SHA256SUMS
tar xzf ai999x-control-systems-1.4.0-linux-x86_64.tar.gz
./ai999x-control-systems-1.4.0-linux-x86_64/ai999x-control-systems
```

It opens on this model: type a question or pick a capability, fill in the form and press Compute. The AI999X desktop app with every model works the same way (choose the model first). Windows: Download ai999x-1.4.0-windows-x86_64.zip, right-click it → Extract All, then open the folder and start ai999x.exe. If Windows SmartScreen asks, choose More info → Run anyway. Linux:

```
curl -LO https://downloads.ai999x.com/desktop/1.4.0/ai999x-1.4.0-linux-x86_64.tar.gz
curl -LO https://downloads.ai999x.com/desktop/1.4.0/SHA256SUMS
sha256sum -c --ignore-missing SHA256SUMS
tar xzf ai999x-1.4.0-linux-x86_64.tar.gz
./ai999x-1.4.0-linux-x86_64/ai999x
```

Command line — Linux

The bundle holds one program per model; `control-systems` is this one. The checksum line should print OK.

```
curl -LO https://downloads.ai999x.com/desktop/1.4.0/ai999x-cli-1.4.0-linux-x86_64.tar.gz
curl -LO https://downloads.ai999x.com/desktop/1.4.0/SHA256SUMS
sha256sum -c --ignore-missing SHA256SUMS
mkdir -p ~/.local/share && tar xzf ai999x-cli-1.4.0-linux-x86_64.tar.gz -C ~/.local/share
echo 'export PATH="$HOME/.local/share/ai999x-cli-1.4.0-linux-x86_64:$PATH"' >> ~/.bashrc && source
~/.bashrc
control-systems --version
```

Command line — Windows (PowerShell)

The fourth line should print True.

```
$F = "ai999x-cli-1.4.0-windows-x86_64.zip"
Invoke-WebRequest "https://downloads.ai999x.com/desktop/1.4.0/$F" -OutFile $F
Invoke-WebRequest "https://downloads.ai999x.com/desktop/1.4.0/SHA256SUMS" -OutFile SHA256SUMS
(Get-FileHash $F -Algorithm SHA256).Hash.ToLower() -eq ((Select-String -SimpleMatch $F
SHA256SUMS).Line -split ' ')[0]
Expand-Archive $F -DestinationPath "$env:LOCALAPPDATA\AI999X" -Force
$D = "$env:LOCALAPPDATA\AI999X\ai999x-cli-1.4.0-windows-x86_64"; $env:Path += ";$D"
[Environment]::SetEnvironmentVariable("Path", [Environment]::GetEnvironmentVariable("Path", "User")
+ ";$D", "User")
control-systems --version
```

In your browser

Open https://www.ai999x.com/models/control-systems-ai999x/, choose a capability and press Compute in your browser: the same program runs on your device as WebAssembly; nothing is sent anywhere.

Python

```
pip install control-systems-ai999x
```

2. Quick start

2.1 Check the install

Prints the model, its version and that this is the Rust build.

```
$ control-systems --version
control-systems-ai999x 1.0.0 (Rust build, ax-engine 0.1.0)
```

2.2 Ask in words

Write the question as you would say it: the program reads the quantities and their units, picks the capability and answers.

```
$ control-systems ask "stability margins: num = [10], den = [1, 3, 2, 0]"
Read as: Gain and phase margins
gm = 0.6
gm_db = -4.436974992
w_pc = 1.414213562 rad/s
pm_deg = -12.99720802
w_gc = 1.802203305 rad/s
  by: Gain and phase margins  (crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj
D(jw)), Newton-polished)
  assumes: exactly one gain crossover and one phase crossover
```

2.3 Find a capability

Search the capabilities by what you want to know; the first column is the id to pass to info and solve.

```
$ control-systems search "gain and phase margins"
ctrl_stability_margins               Gain and phase margins  (stability / margins)
ctrl_sensitivity_peak                Peak sensitivity Ms and modulus margin  (stability /
robustness)
ctrl_lead_max_phase                  Maximum phase lead of a lead compensator  (compensators /
lead)
ctrl_bode_point                      Bode magnitude and phase at one frequency  (frequency response
/ Bode)
ctrl_lead_design                     Lead compensator design for a required phase lead
(compensators / lead)
ctrl_lag_design                      Lag compensator placement  (compensators / lag)
ctrl_pole_stability                  Poles and stability of a characteristic polynomial  (stability
/ poles)
ctrl_poles_zeros                     Poles, zeros and gain of a transfer function  (transfer
functions / poles and zeros)
… 12 more
```

2.4 List the capabilities

Every capability the program answers: its id (what you pass to solve) and its name.

```
$ control-systems list
ctrl_ackermann                          Pole placement by Ackermann's formula
ctrl_arrival_angle                      Root-locus angle of arrival at a complex zero
ctrl_backward_euler                     Backward Euler (backward difference) discretization
ctrl_bandwidth                          -3 dB bandwidth of a transfer function
ctrl_bandwidth_second                   Bandwidth of a standard second-order system
ctrl_bode_point                         Bode magnitude and phase at one frequency
ctrl_breakaway_points                   Root-locus breakaway and break-in points
ctrl_c2d_foh                            First-order-hold (triangle-hold) discretization
… 89 more
```

2.5 What a capability needs

The equation or method, every input and output with its SI unit. Read this before solve: it tells you the input names.

```
$ control-systems info ctrl_stability_margins
Gain and phase margins
  crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj D(jw)), Newton-polished
  in   num      numerator of the open loop L(s) (vector) []
  in   den      denominator of L(s) (vector) []
  out  gm       gain margin (ratio) []
  out  gm_db    gain margin in dB []
  out  w_pc     phase-crossover frequency [rad/s]
  out  pm_deg   phase margin in degrees []
  out  w_gc     gain-crossover frequency [rad/s]
```

2.6 Solve

Inputs as name=value, each with any unit of the right kind. The answer lists every output, the method used, each input converted to SI, and the conditions the answer assumes.

```
$ control-systems solve ctrl_stability_margins "num=[10]" "den=[1, 3, 2, 0]"
gm = 0.6
gm_db = -4.436974992
w_pc = 1.414213562 rad/s
pm_deg = -12.99720802
w_gc = 1.802203305 rad/s
  by: Gain and phase margins  (crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj
D(jw)), Newton-polished)
  assumes: exactly one gain crossover and one phase crossover
```

2.7 Machine-readable answer

--json prints the same answer as one line of JSON (values in SI): for scripts and other programs.

```
$ control-systems solve ctrl_stability_margins "num=[10]" "den=[1, 3, 2, 0]" --json
{"outcome":"SOLVED","message":"","value":-12.9972080155,"unit":"","solved_for":"pm_deg","values":
[["gm",0.6,""],["gm_db",-4.43697499233,""],["w_pc",1.41421356237,"rad/s"],
["pm_deg",-12.9972080155,""],["w_gc",1.80220330461,"rad/s"]],"target":"pm_deg","phrase":"gain
margin (ratio)","assumptions":["exactly one gain crossover and one phase crossover"],"name":"Gain
and phase margins","equation":"crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj
D(jw)), Newton-polished"}
```

2.8 When an input is missing

No number is guessed: the answer names what is missing, shows a complete call, and the program exits with status 1.

```
$ control-systems solve ctrl_stability_margins "num=[10]"
NEEDS_INPUT: ctrl_stability_margins needs den (denominator of L(s)). Example:
solve('ctrl_stability_margins', num=[10], den=[1, 3, 2, 0]).
```

2.9 Draw the figures

The live figures for your own inputs, written as SVG files into the folder given with --out (here the current folder); open them in any browser. Without --out the SVG text comes back as JSON.

```
$ control-systems figures ctrl_stability_margins "num=[10]" "den=[1, 3, 2, 0]" --out .
[
  {
    "slug": "ctrl-stability-margins-live-1",
    "title": "The computed values side by side",
    "caption": "Every answer of one unit for your inputs: gm (gain margin (ratio)) = 0.6; gm_db
(gain margin in dB) = -4.437; pm_deg (phase margin in degrees) = -13. Your inputs: num = (list),
den = (list).",
    "file": ".\\ctrl-stability-margins-live-1.svg"
  }
]
```

2.10 Many questions at once

One JSON request per line in, one JSON answer per line out, in order: for scripts, notebooks and agents (the program starts once). In PowerShell: Get-Content cases.jsonl | control-systems batch

`cases.jsonl`:

```
{"key": "ctrl_stability_margins", "inputs": {"num": "[10]", "den": "[1, 3, 2, 0]"}}
{"key": "ctrl_routh_hurwitz", "inputs": {"coefficients": "[1, 2, 3, 4, 5]"}}
```

```
$ control-systems batch < cases.jsonl
{"outcome":"SOLVED","message":"","value":-12.9972080155,"unit":"","solved_for":"pm_deg","values":
[["gm",0.6,""],["gm_db",-4.43697499233,""],["w_pc",1.41421356237,"rad/s"],
["pm_deg",-12.9972080155,""],["w_gc",1.80220330461,"rad/s"]],"target":"pm_deg","phrase":"gain
margin (ratio)","assumptions":["exactly one gain crossover and one phase crossover"],"name":"Gain
and phase margins","equation":"crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj
D(jw)), Newton-polished"}
{"outcome":"SOLVED","message":"","value":2.0,"unit":"","solved_for":"rhp_roots","values":
[["first_column",[1.0,2.0,1.0,-6.0,5.0],""],["rhp_roots",2,""],
["stable",false,""]],"target":"rhp_roots","phrase":"first column of the Routh array","assumptions":
["no zero in the first column (special cases are refused)"],"name":"Routh-Hurwitz stability
test","equation":"Routh array in exact fractions; sign changes of the first column"}
```

3. Writing inputs

Inputs are written `name=value`, one per argument; `control-systems info <capability>` lists the names. Quote an argument that holds a space or brackets (bash, zsh and PowerShell all accept double quotes). The answer always states each input as it was read, converted to SI, so a misread unit is visible at once.

kind	example	how it is read
a number with a unit	`"R=0.128 nm"`	any unit of the same kind; converted to SI
a number in SI	`R=1.28e-10`	no unit means the SI unit shown by info
a choice	`structure=FCC`	one of the values info lists
a list or vector	`"v=[1, 2, 3]" or "v=1, 2, 3"`	brackets keep it a list
a matrix	`"A=[[1, 2], [3, 4]]"`	one list per row
true / false	`inclusive=true`	for yes/no options

An equation can be solved for any of its quantities: give the others and add `--target <symbol>`. Without `--target`, the program solves for the quantity the capability is named after.

4. Outcomes and exit codes

The program never guesses a number: when it cannot answer, it says why and exits with status 1, so a script can tell an answer from a refusal without reading the text.

outcome	meaning	exit status
SOLVED	the answer: every output with its unit, the method, the inputs in SI, the conditions assumed	0
NEEDS_INPUT	an input is missing; the message names it and shows a complete call	1
INVALID_INPUT	a value or unit of the wrong kind, an unknown input name, or a value outside the conditions	1
AMBIGUOUS	the inputs allow two different answers; say which one is meant	1
OUT_OF_SCOPE	the model has no capability for this, or the result would not be meaningful	1
(usage)	a command the program does not know: it prints its usage	2

5. Scripts and agents: batch and JSON

`control-systems solve ... --json` prints one answer as one line of JSON. `control-systems batch` reads one request per line on standard input and writes one JSON answer per line, in order, starting the program once for any number of requests. A request is `{"key": "<capability>", "inputs": {"name": "value", ...}, "target": null}`. In PowerShell, pipe the file in: `Get-Content cases.jsonl | control-systems batch`. `control-systems catalog` prints every capability with its inputs as JSON, to build forms or tool definitions.

answer field	meaning
outcome	one of the outcomes above
message	why there is no answer (empty when SOLVED)
value, unit	the main result in SI units
values	every output: [symbol, value, unit] (procedures)
target	the quantity solved for
si	each numeric input converted to SI: [symbol, value]
assumptions	the conditions the answer relies on
name, equation	the capability and its equation or method

```
import json, subprocess

reqs = [{"key": "<capability>", "inputs": {"name": "value"}}]
out = subprocess.run(["control-systems", "batch"], input="\n".join(map(json.dumps, reqs)),
                     capture_output=True, text=True, check=True).stdout
answers = [json.loads(line) for line in out.splitlines()]
```

6. Figures

`control-systems figures <capability> name=value ... --out DIR` draws the live figures for those inputs and writes each as an SVG file into DIR (an existing folder); without `--out` the SVG text comes back as JSON. The desktop app and the model page draw the same figures as soon as you press Compute.

```
$ control-systems figures ctrl_stability_margins "num=[10]" "den=[1, 3, 2, 0]" --out .
[
  {
    "slug": "ctrl-stability-margins-live-1",
    "title": "The computed values side by side",
    "caption": "Every answer of one unit for your inputs: gm (gain margin (ratio)) = 0.6; gm_db
(gain margin in dB) = -4.437; pm_deg (phase margin in degrees) = -13. Your inputs: num = (list),
den = (list).",
    "file": ".\\ctrl-stability-margins-live-1.svg"
  }
]
```

7. In a web page or Node.js: WebAssembly

The same model is a WebAssembly module, `control_systems_ai999x.wasm` (https://www.ai999x.com/compute/rust/control_systems_ai999x.wasm), with a small loader, `ax-wasm.js`

(https://www.ai999x.com/compute/rust/ax-wasm.js). It runs in a browser, a Web Worker or Node.js, with no server.

```
<script src="ax-wasm.js"></script>
<script>
  AXWasm.load("control_systems_ai999x.wasm").then(function (m) {
    var a = m.solve({key: "<capability>", inputs: {name: "value"}});
    console.log(a.outcome, a.values || a.value);
    console.log(m.catalog().capabilities.length + " capabilities");
  });
</script>
```

8. Every capability

By topic. For each: what it does, what it needs and gives, when it applies, and a command with what the program printed for it. `control-systems info <id>` shows the same inputs and outputs in the terminal.

Compensators (3)

Lag compensator placement — `ctrl_lag_design`

C(s) = (s + z)/(s + p) with z = w_c/ratio (default a decade below the crossover) and p = z/beta: zero, pole, DC gain beta, and the phase lag and gain it adds at w_c.

$$C(s) = \frac{s + z}{s + z/\beta}, \quad z = \omega_c/10$$

symbol		meaning	SI unit
`beta`	in	required low-frequency gain increase (> 1)	—
`w_c`	in	gain-crossover frequency in rad/s	—
`ratio`	in	w_c / zero (default 10) (optional)	—
`zero`	out	zero (rad/s)	—
`pole`	out	pole (rad/s)	—
`dc_gain`	out	DC gain z/p = beta	—
`phase_deg`	out	phase added at w_c in degrees (negative)	—
`magnitude_db`	out	gain added at w_c in dB	—

Applies when: beta > 1; ratio >= 2.

```
$ control-systems solve ctrl_lag_design beta=10 w_c=1
zero = 0.1
pole = 0.01
dc_gain = 10
phase_deg = -5.13765444
magnitude_db = 0.04277946506
  by: Lag compensator placement  (zero a decade below crossover, pole beta times lower)
  beta = 10
  w_c = 1
  assumes: beta > 1; ratio >= 2
```

In the worked example, beta = 10, w_c = 1 go through the equation above and give zero = 0.1, pole = 0.01, dc_gain = 10, phase_deg = -5.13765444. It applies only when beta > 1; ratio >= 2: outside that it says what is wrong instead of returning a number.

Lead compensator design for a required phase lead — `ctrl_lead_design`

alpha = (1 - sin phi)/(1 + sin phi) and T = 1/(w_m sqrt(alpha)) so that C(s) = (T s + 1)/(alpha T s + 1) adds the phase lead phi at w_m; its zero, pole and gain at w_m.

$$\alpha = \frac{1 - \sin\phi_m}{1 + \sin\phi_m}, \quad T = \frac{1}{\omega_m \sqrt{\alpha}}$$

symbol		meaning	SI unit
`phi_max_deg`	in	required maximum phase lead in degrees (0 to 90)	—
`w_m`	in	frequency of the maximum lead in rad/s	—
`alpha`	out	alpha (pole/zero ratio z/p)	—
`T`	out	time constant T	s
`zero`	out	zero corner 1/T (rad/s)	—
`pole`	out	pole corner 1/(alpha T) (rad/s)	—
`gain_db`	out	|C(j w_m)| in dB = -10 log10 alpha	—

Applies when: 0 < phi < 90 degrees; w_m > 0.

```
$ control-systems solve ctrl_lead_design phi_max_deg=30 w_m=1
alpha = 0.3333333333
T = 1.732050808 s
zero = 0.5773502692
pole = 1.732050808
gain_db = 4.771212547
  by: Lead compensator design for a required phase lead  (sin phi_max = (1 - alpha)/(1 + alpha),
w_m = 1/(T sqrt(alpha)))
  phi_max_deg = 30
  w_m = 1
  assumes: 0 < phi < 90 degrees; w_m > 0
```

In the worked example, phi_max_deg = 30, w_m = 1 go through the equation above and give alpha = 0.3333333333, T = 1.732050808 s, zero = 0.5773502692, pole = 1.732050808. It applies only when 0 < phi < 90 degrees; w_m > 0: outside that it says what is wrong instead of returning a number.

Maximum phase lead of a lead compensator — `ctrl_lead_max_phase`

For C(s) = (s + z)/(s + p) with z < p: the maximum phase lead asin((p - z)/(p + z)), the frequency sqrt(z p) where it occurs, alpha = z/p and the gain there, 10 log10(z/p) dB.

$$\sin\phi_{max} = \frac{p-z}{p+z} = \frac{1-\alpha}{1+\alpha}, \quad \omega_m = \sqrt{zp}$$

symbol		meaning	SI unit
`z`	in	zero corner frequency (rad/s)	—
`p`	in	pole corner frequency (rad/s), p > z	—
`phi_max_deg`	out	maximum phase lead in degrees	—
`w_max`	out	frequency of the maximum	rad/s
`alpha`	out	alpha = z/p	—
`magnitude_db`	out	|C(j w_max)| in dB	—

Applies when: 0 < z < p.

```
$ control-systems solve ctrl_lead_max_phase z=1 p=9
phi_max_deg = 53.13010235
w_max = 3 rad/s
alpha = 0.1111111111
magnitude_db = -9.542425094
  by: Maximum phase lead of a lead compensator  (stationary point of the phase)
  z = 1
  p = 9
  assumes: 0 < z < p
```

In the worked example, z = 1, p = 9 go through the equation above and give phi_max_deg = 53.13010235, w_max = 3 rad/s, alpha = 0.1111111111, magnitude_db = -9.542425094. It applies only when 0 < z < p: outside that it says what is wrong instead of returning a number.

Design (1)

Desired closed-loop poles from overshoot and settling time — `ctrl_specs_to_poles`

zeta from the overshoot, sigma = 4/Ts from the 2 % settling time, wn = sigma/zeta, the poles -sigma +/- j wd and the desired characteristic polynomial.

$$\zeta = \frac{-\ln OS}{\sqrt{\pi^2 + \ln^2 OS}}, \quad \sigma = \frac{4}{T_s}, \quad \omega_n = \frac{\sigma}{\zeta}$$

symbol		meaning	SI unit
`OS`	in	maximum overshoot (write 10% or 0.1)	—
`Ts`	in	2 % settling time in seconds	—
`zeta`	out	damping ratio	—
`wn`	out	natural frequency	rad/s

symbol		meaning	SI unit
`sigma`	out	real part magnitude 4/Ts	—
`wd`	out	imaginary part of the poles	rad/s
`char_poly`	out	s^2 + 2 sigma s + wn^2	—

Applies when: 0 < OS < 100 %; Ts > 0.

```
$ control-systems solve ctrl_specs_to_poles OS=0.1630335348 Ts=2
zeta = 0.5
wn = 4 rad/s
sigma = 2
wd = 3.464101615 rad/s
char_poly = [1.0,4.0,15.9999999982]
  by: Desired closed-loop poles from overshoot and settling time  (zeta from the overshoot formula;
sigma = 4/Ts)
  OS = 0.1630335348
  Ts = 2
  assumes: 0 < OS < 100 %; Ts > 0
```

In the worked example, OS = 0.1630335348, Ts = 2 go through the equation above and give zeta = 0.5, wn = 4 rad/s, sigma = 2, wd = 3.464101615 rad/s. It applies only when 0 < OS < 100 %; Ts > 0: outside that it says what is wrong instead of returning a number.

Discretization (12)

Backward Euler (backward difference) discretization — `ctrl_backward_euler`

The discrete transfer function obtained by substituting s = (z - 1)/(T z) into G(s).

$$s \leftarrow \frac{z-1}{Tz}$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); T > 0.

```
$ control-systems solve ctrl_backward_euler "num=[1]" "den=[1, 1]" T=0.1
numz = [0.0909090909091,0.0]
denz = [1.0,-0.909090909091]
  by: Backward Euler (backward difference) discretization  (polynomial substitution s = (z - 1)/(T
z))
  T = 0.1
  assumes: proper G(s); T > 0
```

In the worked example, num = [1], den = [1, 1], T = 0.1 go through the equation above and give numz = [0.09090909091, 0], denz = [1, -0.9090909091]. It applies only when proper G(s); T > 0: outside that it says what is wrong instead of returning a number.

Continuous equivalent of a discrete pole (s = ln z / T) — `ctrl_z_to_s_pole`

The s-plane pole s = ln(z)/T (principal branch) of a discrete pole z = z_re + j z_im, with its natural frequency and damping ratio.

$$s = \frac{\ln z}{T}$$

symbol		meaning	SI unit
`z_re`	in	real part of the discrete pole	—
`z_im`	in	imaginary part of the discrete pole (>= 0)	—
`T`	in	sampling period in seconds	—
`s_re`	out	real part of s (1/s)	—
`s_im`	out	imaginary part of s (rad/s)	—
`wn`	out	natural frequency	rad/s
`zeta`	out	damping ratio	—

Applies when: T > 0; z not on the negative real axis.

```
$ control-systems solve ctrl_z_to_s_pole z_re=0.5 z_im=0 T=0.1
s_re = -6.931471806
s_im = 0
wn = 6.931471806 rad/s
zeta = 1
  by: Continuous equivalent of a discrete pole (s = ln z / T)  (s = (ln|z| + j arg z)/T)
  z_re = 0.5
  z_im = 0
  T = 0.1
  assumes: T > 0; z not on the negative real axis
```

In the worked example, z_re = 0.5, z_im = 0, T = 0.1 go through the equation above and give s_re = -6.931471806, s_im = 0, wn = 6.931471806 rad/s, zeta = 1. It applies only when T > 0; z not on the negative real axis: outside that it says what is wrong instead of returning a number.

DC gain and final value of a discrete transfer function — `ctrl_discrete_dc_gain`

G(1) = sum(num)/sum(den) of a stable discrete transfer function G(z), and the final value of its response to a step of size A.

$$y(\infty) = A\,G(1)$$

symbol		meaning	SI unit
`num`	in	numerator coefficients in z, highest power first	—

symbol		meaning	SI unit
`den`	in	denominator coefficients in z, highest power first	—
`A`	in	step size (default 1) (optional)	—
`dc_gain`	out	DC gain G(1)	—
`final_value`	out	final value of the step response	—

Applies when: proper G(z); every pole inside the unit circle.

```
$ control-systems solve ctrl_discrete_dc_gain "num=[0.5]" "den=[1, -0.5]"
dc_gain = 1
final_value = 1
  by: DC gain and final value of a discrete transfer function  (G(1) after a stability check)
  assumes: proper G(z); every pole inside the unit circle
```

In the worked example, num = [0.5], den = [1, -0.5] go through the equation above and give dc_gain = 1, final_value = 1. It applies only when proper G(z); every pole inside the unit circle: outside that it says what is wrong instead of returning a number.

Discrete PID in velocity (incremental) form — `ctrl_discrete_pid`

Coefficients of u[k] = u[k-1] + q0 e[k] + q1 e[k-1] + q2 e[k-2] for a PID with backward-difference integral and derivative: q0 = Kp + Ki T + Kd/T, q1 = -Kp - 2 Kd/T, q2 = Kd/T.

$$\Delta u_k = (K_p + K_i T + \tfrac{K_d}{T})e_k - (K_p + \tfrac{2K_d}{T})e_{k-1} + \tfrac{K_d}{T}e_{k-2}$$

symbol		meaning	SI unit
`Kp`	in	proportional gain	—
`Ki`	in	integral gain	—
`Kd`	in	derivative gain	—
`T`	in	sampling period in seconds	—
`q0`	out	coefficient of e[k]	—
`q1`	out	coefficient of e[k-1]	—
`q2`	out	coefficient of e[k-2]	—

Applies when: T > 0; Ki, Kd >= 0.

```
$ control-systems solve ctrl_discrete_pid Kp=2 Ki=1 Kd=0.5 T=0.1
q0 = 7.1
q1 = -12
q2 = 5
  by: Discrete PID in velocity (incremental) form  (difference of the positional backward-
difference PID)
  Kp = 2
  Ki = 1
  Kd = 0.5
  T = 0.1
  assumes: T > 0; Ki, Kd >= 0
```

In the worked example, Kp = 2, Ki = 1, Kd = 0.5, T = 0.1 go through the equation above and give q0 = 7.1, q1 = -12, q2 = 5. It applies only when T > 0; Ki, Kd >= 0: outside that it says what is wrong instead of returning a number.

First-order-hold (triangle-hold) discretization — `ctrl_c2d_foh`

The ramp-invariant (triangle-hold, non-causal first-order hold) discrete equivalent of a proper G(s) sampled every T seconds.

$$B_d = \Gamma_1 - \Gamma_2 + \Phi\Gamma_2, \quad D_d = D + C\Gamma_2$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); T > 0.

```
$ control-systems solve ctrl_c2d_foh "num=[1]" "den=[1, 0]" T=1
numz = [0.5,0.5]
denz = [1.0,-1.0]
  by: First-order-hold (triangle-hold) discretization  (exponential of the augmented matrix [[A T,
B T, 0], [0, 0, 1], [0, 0, 0]])
  T = 1
  assumes: proper G(s); T > 0
```

In the worked example, num = [1], den = [1, 0], T = 1 go through the equation above and give numz = [0.5, 0.5], denz = [1, -1]. It applies only when proper G(s); T > 0: outside that it says what is wrong instead of returning a number.

Forward Euler (forward difference) discretization — `ctrl_forward_euler`

The discrete transfer function obtained by substituting s = (z - 1)/T into G(s).

$$s \leftarrow \frac{z-1}{T}$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); T > 0.

```
$ control-systems solve ctrl_forward_euler "num=[1]" "den=[1, 1]" T=0.1
numz = [0.0,0.1]
denz = [1.0,-0.9]
  by: Forward Euler (forward difference) discretization  (polynomial substitution s = (z - 1)/T)
  T = 0.1
  assumes: proper G(s); T > 0
```

In the worked example, num = [1], den = [1, 1], T = 0.1 go through the equation above and give numz = [0, 0.1], denz = [1, -0.9]. It applies only when proper G(s); T > 0: outside that it says what is wrong instead of returning a number.

Mapping an s-plane pole to the z-plane (z = e^{sT}) — `ctrl_s_to_z_pole`

The discrete pole z = e^{sT} of a continuous pole s = s_re + j s_im sampled with period T: real and imaginary parts, magnitude e^{s_re T} and angle s_im T.

$$z = e^{sT} = e^{\sigma T} \angle \omega T$$

symbol		meaning	SI unit
`s_re`	in	real part of the s-plane pole (1/s)	—
`s_im`	in	imaginary part of the pole, >= 0 (rad/s)	—
`T`	in	sampling period in seconds	—
`z_re`	out	real part of z	—
`z_im`	out	imaginary part of z	—
`z_mag`	out	|z| = e^{s_re T}	—
`z_angle`	out	angle of z in radians, s_im T	—

Applies when: T > 0; 0 <= s_im T < pi.

```
$ control-systems solve ctrl_s_to_z_pole s_re=-2 s_im=0 T=0.1
z_re = 0.8187307531
z_im = 0
z_mag = 0.8187307531
z_angle = 0
  by: Mapping an s-plane pole to the z-plane (z = e^{sT})  (z = e^{s_re T}(cos s_im T + j sin s_im
T))
  s_re = -2
  s_im = 0
  T = 0.1
  assumes: T > 0; 0 <= s_im T < pi
```

In the worked example, s_re = -2, s_im = 0, T = 0.1 go through the equation above and give z_re = 0.8187307531, z_im = 0, z_mag = 0.8187307531, z_angle = 0. It applies only when T > 0; 0 <= s_im T < pi: outside that it says what is wrong instead of returning a number.

Step response of a discrete transfer function at sample k — `ctrl_discrete_step`

y[k] of G(z) = numz/denz after a step of size A applied at k = 0, by the difference equation.

$$y[k] = \sum_i b_i u[k-i] - \sum_{i \geq 1} a_i y[k-i]$$

symbol		meaning	SI unit
`numz`	in	numerator in z, highest power first	—
`denz`	in	denominator in z, highest power first	—
`k`	in	sample index (0 to 500)	—
`A`	in	step size (default 1) (optional)	—
`y`	out	output at sample k	—

Applies when: proper (causal) G(z); 0 <= k <= 500.

```
$ control-systems solve ctrl_discrete_step "numz=[0.5]" "denz=[1, -0.5]" k=2
y = 0.75
  by: Step response of a discrete transfer function at sample k  (recursion y[j] = sum b_i u[j-i] -
sum a_i y[j-i])
  assumes: proper (causal) G(z); 0 <= k <= 500
```

In the worked example, numz = [0.5], denz = [1, -0.5], k = 2 go through the equation above and give y = 0.75. It applies only when proper (causal) G(z); 0 <= k <= 500: outside that it says what is wrong instead of returning a number.

Tustin (bilinear) discretization — `ctrl_tustin`

The discrete transfer function obtained by substituting s = (2/T)(z - 1)/(z + 1) into G(s).

$$s \leftarrow \frac{2}{T}\,\frac{z-1}{z+1}$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); T > 0.

```
$ control-systems solve ctrl_tustin "num=[1]" "den=[1, 1]" T=0.1
numz = [0.047619047619,0.047619047619]
denz = [1.0,-0.904761904762]
  by: Tustin (bilinear) discretization  (polynomial substitution, multiplied through by (z + 1)^n)
  T = 0.1
  assumes: proper G(s); T > 0
```

In the worked example, num = [1], den = [1, 1], T = 0.1 go through the equation above and give numz = [0.04761904762, 0.04761904762], denz = [1, -0.9047619048]. It applies only when proper G(s); T > 0: outside

that it says what is wrong instead of returning a number.

Tustin discretization with frequency prewarping — `ctrl_tustin_prewarp`

The bilinear transform s = (w/tan(w T/2)) (z - 1)/(z + 1), which matches the continuous frequency response exactly at the prewarping frequency w.

$$s \leftarrow \frac{\omega}{\tan(\omega T/2)} \frac{z-1}{z+1}$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`w`	in	prewarping frequency in rad/s	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); 0 < w T < pi.

```
$ control-systems solve ctrl_tustin_prewarp "num=[1]" "den=[1, 1]" T=1 w=1
numz = [0.353296003487,0.353296003487]
denz = [1.0,-0.293407993026]
  by: Tustin discretization with frequency prewarping  (polynomial substitution with the prewarped
constant)
  T = 1
  w = 1
  assumes: proper G(s); 0 < w T < pi
```

In the worked example, num = [1], den = [1, 1], T = 1, w = 1 go through the equation above and give numz = [0.3532960035, 0.3532960035], denz = [1, -0.293407993]. It applies only when proper G(s); 0 < w T < pi: outside that it says what is wrong instead of returning a number.

Zero-order-hold discretization of a first-order system — `ctrl_zoh_first_order`

G(z) = b/(z - a) with a = e^{-T/tau} and b = K (1 - a): the exact step-invariant (ZOH) equivalent of K/(tau s + 1) sampled every T seconds.

$$G(z) = \frac{K(1 - e^{-T/\tau})}{z - e^{-T/\tau}}$$

symbol		meaning	SI unit
`K`	in	DC gain	—
`tau`	in	time constant in seconds	—
`T`	in	sampling period in seconds	—
`b`	out	numerator coefficient b	—

symbol		meaning	SI unit
`a`	out	discrete pole a	—

Applies when: tau > 0; T > 0.

```
$ control-systems solve ctrl_zoh_first_order K=2 tau=1 T=0.5
b = 0.7869386806
a = 0.6065306597
  by: Zero-order-hold discretization of a first-order system  (a = exp(-T/tau), b = K (1 - a))
  K = 2
  tau = 1
  T = 0.5
  assumes: tau > 0; T > 0
```

In the worked example, K = 2, tau = 1, T = 0.5 go through the equation above and give b = 0.7869386806, a = 0.6065306597. It applies only when tau > 0; T > 0: outside that it says what is wrong instead of returning a number.

Zero-order-hold discretization of a transfer function — `ctrl_c2d_zoh`

The step-invariant (ZOH) discrete equivalent G(z) = (1 - z^{-1}) Z{G(s)/s} of a proper G(s) sampled every T seconds.

$$A_d = e^{AT},\ B_d = \int_0^T e^{A\tau} d\tau\, B$$

symbol		meaning	SI unit
`num`	in	numerator in s	—
`den`	in	denominator in s	—
`T`	in	sampling period in seconds	—
`numz`	out	numerator in z (padded, normalised)	—
`denz`	out	denominator in z (leading coefficient 1)	—

Applies when: proper G(s); T > 0.

```
$ control-systems solve ctrl_c2d_zoh "num=[1]" "den=[1, 1]" T=0.5
numz = [0.0,0.393469340287]
denz = [1.0,-0.606530659713]
  by: Zero-order-hold discretization of a transfer function  (exponential of [[A, B], [0, 0]] T in
state space, then Faddeev-LeVerrier)
  T = 0.5
  assumes: proper G(s); T > 0
```

In the worked example, num = [1], den = [1, 1], T = 0.5 go through the equation above and give numz = [0, 0.3934693403], denz = [1, -0.6065306597]. It applies only when proper G(s); T > 0: outside that it says what is wrong instead of returning a number.

Estimation (4)

One step of a scalar Kalman filter — `ctrl_kalman_scalar_step`

Predict (x- = a x, P- = a^2 P + q) and update with a measurement z of variance r (gain P-/(P- + r)) for x_k = a x_{k-1} + w, z_k = x_k + v.

$$K = \frac{P^-}{P^- + r}, \quad \hat{x} = \hat{x}^- + K(z - \hat{x}^-), \quad P = (1 - K)P^-$$

symbol		meaning	SI unit
`x`	in	previous estimate	—
`P`	in	previous error variance	—
`a`	in	state transition coefficient	—
`q`	in	process noise variance	—
`r`	in	measurement noise variance	—
`z`	in	new measurement	—
`x_pred`	out	predicted estimate	—
`P_pred`	out	predicted variance	—
`gain`	out	Kalman gain	—
`x_post`	out	updated estimate	—
`P_post`	out	updated variance	—

Applies when: P, q >= 0; r > 0.

```
$ control-systems solve ctrl_kalman_scalar_step x=0 P=1 a=1 q=1 r=2 z=4
x_pred = 0
P_pred = 2
gain = 0.5
x_post = 2
P_post = 1
  by: One step of a scalar Kalman filter  (Kalman predict and update equations)
  x = 0
  P = 1
  a = 1
  q = 1
  r = 2
  z = 4
  assumes: P, q >= 0; r > 0
```

In the worked example, x = 0, P = 1, a = 1, q = 1, r = 2, z = 4 go through the equation above and give x_pred = 0, P_pred = 2, gain = 0.5, x_post = 2. It applies only when P, q >= 0; r > 0: outside that it says what is wrong instead of returning a number.

Steady-state discrete Kalman filter gain — `ctrl_discrete_kalman_gain`

For x_{k+1} = A x_k + w (covariance Q), y_k = C x_k + v (variance R): the steady prior covariance P from the discrete filter Riccati equation and the measurement-update gain K = P C^T (C P C^T + R)^{-1}.

$$P = APA^T - APC^T(CPC^T + R)^{-1}CPA^T + Q, \quad K = PC^T(CPC^T + R)^{-1}$$

symbol		meaning	SI unit
`A`	in	discrete state matrix (n x n)	—
`C`	in	output vector	—
`Q`	in	process noise covariance (symmetric positive definite)	—
`R`	in	measurement noise variance (> 0)	—
`K`	out	steady Kalman gain	—
`P_prior`	out	steady prior error covariance	—

Applies when: (A, C) observable; Q positive definite; R > 0.

```
$ control-systems solve ctrl_discrete_kalman_gain A=1 C=1 Q=1 R=1
K = [0.61803398875]
P_prior = [[1.61803398875]]
  by: Steady-state discrete Kalman filter gain  (the dual discrete Riccati equation by Hewer's
iteration)
  R = 1
  assumes: (A, C) observable; Q positive definite; R > 0
```

In the worked example, A = [1], C = [1], Q = [1], R = 1 go through the equation above and give K = [0.6180339888], P_prior = [[1.618033989]]. It applies only when (A, C) observable; Q positive definite; R > 0: outside that it says what is wrong instead of returning a number.

Steady-state gain of a scalar Kalman filter — `ctrl_kalman_scalar_steady`

For x_k = a x_{k-1} + w (variance q) and z_k = c x_k + v (variance r): the steady prior variance P (discrete Riccati equation), the steady Kalman gain and the posterior variance.

$$P = a^2P - \frac{a^2c^2P^2}{c^2P + r} + q, \quad K = \frac{Pc}{c^2P + r}$$

symbol		meaning	SI unit
`a`	in	state transition coefficient	—
`c`	in	measurement coefficient	—
`q`	in	process noise variance	—
`r`	in	measurement noise variance	—
`P_prior`	out	steady prior error variance	—
`gain`	out	steady Kalman gain	—
`P_post`	out	steady posterior error variance	—

Applies when: c != 0; q, r > 0.

```
$ control-systems solve ctrl_kalman_scalar_steady a=1 c=1 q=1 r=1
P_prior = 1.618033989
gain = 0.6180339888
P_post = 0.6180339888
  by: Steady-state gain of a scalar Kalman filter  (positive root of c^2 P^2 + (r - a^2 r - q c^2)
P - q r = 0)
  a = 1
  c = 1
  q = 1
  r = 1
  assumes: c != 0; q, r > 0
```

In the worked example, a = 1, c = 1, q = 1, r = 1 go through the equation above and give P_prior = 1.618033989, gain = 0.6180339888, P_post = 0.6180339888. It applies only when c != 0; q, r > 0: outside that it says what is wrong instead of returning a number.

Steady-state Kalman-Bucy filter gain — `ctrl_kalman_bucy`

For x' = A x + w (covariance W), y = C x + v (variance V): the steady error covariance P from the filter Riccati equation A P + P A^T - P C^T V^{-1} C P + W = 0, the gain L = P C^T / V and the estimator poles (eigenvalues of A - L C).

$$AP + PA^T - PC^TV^{-1}CP + W = 0, \quad L = PC^TV^{-1}$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`C`	in	output vector	—
`W`	in	process noise covariance (symmetric positive definite)	—
`V`	in	measurement noise variance (> 0)	—
`L`	out	Kalman gain (column)	—
`P`	out	steady error covariance	—
`poles`	out	estimator poles	—

Applies when: (A, C) observable; W positive definite; V > 0.

```
$ control-systems solve ctrl_kalman_bucy "A=[[0, 1], [0, 0]]" "C=[1, 0]" "W=[[1, 0], [0, 1]]" V=1
L = [1.73205080757,1.0]
P = [[1.73205080757,1.0],[1.0,1.73205080757]]
poles = [{"re":-0.866025403784,"im":-0.5},{"re":-0.866025403784,"im":0.5}]
  by: Steady-state Kalman-Bucy filter gain  (the dual LQR problem (A^T, C^T, W, V) by Newton-
Kleinman iteration)
  V = 1
  assumes: (A, C) observable; W positive definite; V > 0
```

In the worked example, A = [0 1; 0 0], C = [1, 0], W = [1 0; 0 1], V = 1 go through the equation above and give L = [1.732050808, 1], P = [[1.732050808, 1], [1, 1.732050808]], poles = [-0.8660254038-0.5i, -0.8660254038+0.5i]. It applies only when (A, C) observable; W positive definite; V > 0: outside that it says what is wrong instead of returning a number.

Frequency response (8)

-3 dB bandwidth of a transfer function — `ctrl_bandwidth`

The lowest frequency at which |G(jw)| falls to |G(0)|/sqrt(2) for a stable, strictly proper G(s), and the DC gain.

$$|G(j\omega_B)| = \frac{|G(0)|}{\sqrt{2}}$$

symbol		meaning	SI unit
`num`	in	numerator	—
`den`	in	denominator	—
`wb`	out	-3 dB bandwidth	rad/s
`dc_gain`	out	DC gain	—

Applies when: stable; strictly proper; nonzero DC gain.

```
$ control-systems solve ctrl_bandwidth "num=[1]" "den=[1, 1]"
wb = 1 rad/s
dc_gain = 1
  by: -3 dB bandwidth of a transfer function  (smallest positive root of 2|N(jw)|^2 - G(0)^2
|D(jw)|^2)
  assumes: stable; strictly proper; nonzero DC gain
```

In the worked example, num = [1], den = [1, 1] go through the equation above and give wb = 1 rad/s, dc_gain = 1. It applies only when stable; strictly proper; nonzero DC gain: outside that it says what is wrong instead of returning a number.

Bandwidth of a standard second-order system — `ctrl_bandwidth_second`

The -3 dB bandwidth wn sqrt(1 - 2 zeta^2 + sqrt(4 zeta^4 - 4 zeta^2 + 2)) of wn^2/(s^2 + 2 zeta wn s + wn^2).

$$\omega_B = \omega_n \sqrt{1 - 2\zeta^2 + \sqrt{4\zeta^4 - 4\zeta^2 + 2}}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (> 0)	—
`wn`	in	natural frequency in rad/s	—
`wb`	out	-3 dB bandwidth	rad/s

Applies when: zeta > 0; wn > 0.

```
$ control-systems solve ctrl_bandwidth_second zeta=0.7071067812 wn=1
wb = 1 rad/s
  by: Bandwidth of a standard second-order system  (solve |G(jw)| = 1/sqrt(2))
  zeta = 0.7071067812
  wn = 1
  assumes: zeta > 0; wn > 0
```

In the worked example, zeta = 0.7071067812, wn = 1 go through the equation above and give wb = 1 rad/s. It applies only when zeta > 0; wn > 0: outside that it says what is wrong instead of returning a number.

Bode magnitude and phase at one frequency — `ctrl_bode_point`

|G(jw)|, 20 log10 |G(jw)| and the phase of G(jw) (principal value) of a transfer function at the angular frequency w.

$$|G(j\omega)|_{dB} = 20\log_{10}|G(j\omega)|$$

symbol		meaning	SI unit
`num`	in	numerator coefficients	—
`den`	in	denominator coefficients	—
`w`	in	angular frequency in rad/s	—
`magnitude`	out	|G(jw)|	—
`magnitude_db`	out	magnitude in dB	—
`phase_deg`	out	phase in degrees, (-180, 180]	—

Applies when: proper G(s); w > 0; not a pole on the imaginary axis.

```
$ control-systems solve ctrl_bode_point "num=[10]" "den=[1, 1, 0]" w=1
magnitude = 7.071067812
magnitude_db = 16.98970004
phase_deg = -135
  by: Bode magnitude and phase at one frequency  (G(jw) by complex evaluation)
  w = 1
  assumes: proper G(s); w > 0; not a pole on the imaginary axis
```

In the worked example, num = [10], den = [1, 1, 0], w = 1 go through the equation above and give magnitude = 7.071067812, magnitude_db = 16.98970004, phase_deg = -135. It applies only when proper G(s); w > 0; not a pole on the imaginary axis: outside that it says what is wrong instead of returning a number.

Frequency response of a first-order lag — `ctrl_first_order_freq`

Magnitude K/sqrt(1 + (w tau)^2), its value in dB and the phase -atan(w tau) of K/(tau s + 1) at the angular frequency w.

$$|G(j\omega)| = \frac{K}{\sqrt{1+\omega^2\tau^2}}, \quad \angle G = -\arctan(\omega\tau)$$

symbol		meaning	SI unit
`K`	in	DC gain (positive)	—
`tau`	in	time constant in seconds	—
`w`	in	angular frequency in rad/s	—
`magnitude`	out	gain |G(jw)|	—
`magnitude_db`	out	gain in dB	—
`phase_deg`	out	phase in degrees	—

Applies when: K > 0; tau > 0; w >= 0.

```
$ control-systems solve ctrl_first_order_freq K=10 tau=1 w=1
magnitude = 7.071067812
magnitude_db = 16.98970004
phase_deg = -45
  by: Frequency response of a first-order lag  (G(jw) = K/(1 + j w tau))
  K = 10
  tau = 1
  w = 1
  assumes: K > 0; tau > 0; w >= 0
```

In the worked example, K = 10, tau = 1, w = 1 go through the equation above and give magnitude = 7.071067812, magnitude_db = 16.98970004, phase_deg = -45. It applies only when K > 0; tau > 0; w >= 0: outside that it says what is wrong instead of returning a number.

Frequency response of a standard second-order system — `ctrl_second_order_freq`

Magnitude, dB gain and phase (between 0 and -180 degrees) of wn^2/(s^2 + 2 zeta wn s + wn^2) at the angular frequency w.

$$|G| = \frac{\omega_n^2}{\sqrt{(\omega_n^2 - \omega^2)^2 + (2\zeta\omega_n\omega)^2}}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio	—
`wn`	in	natural frequency in rad/s	—
`w`	in	angular frequency in rad/s	—
`magnitude`	out	|G(jw)|	—
`magnitude_db`	out	magnitude in dB	—
`phase_deg`	out	phase in degrees, [-180, 0]	—

Applies when: zeta >= 0; wn > 0; w > 0.

```
$ control-systems solve ctrl_second_order_freq zeta=0.5 wn=10 w=10
magnitude = 1
magnitude_db = 0
phase_deg = -90
  by: Frequency response of a standard second-order system  (G(jw) = wn^2/(wn^2 - w^2 + 2 j zeta wn
w))
  zeta = 0.5
  wn = 10
  w = 10
  assumes: zeta >= 0; wn > 0; w > 0
```

In the worked example, zeta = 0.5, wn = 10, w = 10 go through the equation above and give magnitude = 1, magnitude_db = 0, phase_deg = -90. It applies only when zeta >= 0; wn > 0; w > 0: outside that it says what is wrong instead of returning a number.

H-infinity norm (peak gain) of a stable transfer function — `ctrl_hinf_norm`

The peak gain sup_w |G(jw)| of a stable proper G(s), in ratio and dB, and the frequency where it occurs (0 when the peak is the DC gain).

$$\|G\|_\infty = \sup_\omega |G(j\omega)|$$

symbol		meaning	SI unit
`num`	in	numerator	—
`den`	in	denominator	—
`hinf`	out	H-infinity norm (peak gain)	—
`hinf_db`	out	peak gain in dB	—
`w_peak`	out	frequency of the peak	rad/s

Applies when: stable; proper; peak at a finite frequency.

```
$ control-systems solve ctrl_hinf_norm "num=[1]" "den=[1, 1]"
hinf = 1
hinf_db = 0
w_peak = 0 rad/s
  by: H-infinity norm (peak gain) of a stable transfer function  (stationary points of
|N(jw)|^2/|D(jw)|^2 (positive real roots of f' g - f g') and w = 0)
  assumes: stable; proper; peak at a finite frequency
```

In the worked example, num = [1], den = [1, 1] go through the equation above and give hinf = 1, hinf_db = 0, w_peak = 0 rad/s. It applies only when stable; proper; peak at a finite frequency: outside that it says what is wrong instead of returning a number.

H2 norm of a stable transfer function — `ctrl_h2_norm`

||G||_2 = sqrt((1/(2 pi)) integral of |G(jw)|^2 dw) of a stable, strictly proper G(s), computed exactly as B^T Wo B from the observability Gramian.

$$\|G\|_2^2 = \frac{1}{2\pi}\int_{-\infty}^{\infty} |G(j\omega)|^2 d\omega = B^T W_o B$$

symbol		meaning	SI unit
`num`	in	numerator	—
`den`	in	denominator	—
`h2`	out	H2 norm	—
`h2_squared`	out	squared H2 norm	—

Applies when: stable; strictly proper.

```
$ control-systems solve ctrl_h2_norm "num=[1]" "den=[1, 1]"
h2 = 0.7071067812
h2_squared = 0.5
  by: H2 norm of a stable transfer function  (Lyapunov equation of the controllable canonical form
in exact fractions)
  assumes: stable; strictly proper
```

In the worked example, num = [1], den = [1, 1] go through the equation above and give h2 = 0.7071067812, h2_squared = 0.5. It applies only when stable; strictly proper: outside that it says what is wrong instead of returning a number.

Resonant peak and resonant frequency — `ctrl_resonant_peak`

Peak magnitude Mr = 1/(2 zeta sqrt(1 - zeta^2)) and resonant frequency wr = wn sqrt(1 - 2 zeta^2) of a standard second-order system.

$$M_r = \frac{1}{2\zeta\sqrt{1-\zeta^2}}, \quad \omega_r = \omega_n\sqrt{1-2\zeta^2}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 < zeta < 0.7071)	—
`wn`	in	natural frequency in rad/s	—
`Mr`	out	resonant peak (ratio)	—
`Mr_db`	out	resonant peak in dB	—
`wr`	out	resonant frequency	rad/s

Applies when: 0 < zeta < 1/sqrt(2).

```
$ control-systems solve ctrl_resonant_peak zeta=0.5 wn=10
Mr = 1.154700538
Mr_db = 1.249387366
wr = 7.071067812 rad/s
  by: Resonant peak and resonant frequency  (maximum of |G(jw)|)
  zeta = 0.5
  wn = 10
  assumes: 0 < zeta < 1/sqrt(2)
```

In the worked example, zeta = 0.5, wn = 10 go through the equation above and give Mr = 1.154700538, Mr_db = 1.249387366, wr = 7.071067812 rad/s. It applies only when 0 < zeta < 1/sqrt(2): outside that it says what is wrong instead of returning a number.

Identification (3)

Damping ratio from the logarithmic decrement — `ctrl_log_decrement`

delta = ln(x1/xn)/n from two peak amplitudes n cycles apart, and zeta = delta/sqrt(4 pi^2 + delta^2).

$$\delta = \frac{1}{n}\ln\frac{x_1}{x_{n+1}}, \quad \zeta = \frac{\delta}{\sqrt{4\pi^2 + \delta^2}}$$

symbol		meaning	SI unit
`x1`	in	first peak amplitude (measured from the final value)	—
`xn`	in	peak amplitude n cycles later	—
`n`	in	number of cycles between the peaks	—
`delta`	out	logarithmic decrement per cycle	—
`zeta`	out	damping ratio	—

Applies when: 0 < xn < x1; n >= 1.

```
$ control-systems solve ctrl_log_decrement x1=1 xn=0.5 n=1
delta = 0.6931471806
zeta = 0.109652581
  by: Damping ratio from the logarithmic decrement  (ratio of successive peaks)
  x1 = 1
  xn = 0.5
  assumes: 0 < xn < x1; n >= 1
```

In the worked example, x1 = 1, xn = 0.5, n = 1 go through the equation above and give delta = 0.6931471806, zeta = 0.109652581. It applies only when 0 < xn < x1; n >= 1: outside that it says what is wrong instead of returning a number.

First-order-plus-dead-time fit by Smith's two-point method — `ctrl_fopdt_smith`

K = dy/du, tau = 1.5 (t63 - t28) and theta = t63 - tau from the times at which a step response reaches 28.3 % and 63.2 % of its change.

$$\tau = 1.5(t_{63} - t_{28}), \quad \theta = t_{63} - \tau$$

symbol		meaning	SI unit
`t28`	in	time to 28.3 % of the change (s)	—
`t63`	in	time to 63.2 % of the change (s)	—
`dy`	in	total output change	—
`du`	in	input step size	—
`K`	out	process gain	—

symbol		meaning	SI unit
`tau`	out	time constant	s
`theta`	out	dead time	s

Applies when: 0 < t28 < t63; theta >= 0.

```
$ control-systems solve ctrl_fopdt_smith t28=4 t63=10 dy=6 du=2
K = 3
tau = 9 s
theta = 1 s
  by: First-order-plus-dead-time fit by Smith's two-point method  (Smith's method)
  t28 = 4
  t63 = 10
  dy = 6
  du = 2
  assumes: 0 < t28 < t63; theta >= 0
```

In the worked example, t28 = 4, t63 = 10, dy = 6, du = 2 go through the equation above and give K = 3, tau = 9 s, theta = 1 s. It applies only when 0 < t28 < t63; theta >= 0: outside that it says what is wrong instead of returning a number.

Second-order model from a step response — `ctrl_identify_second_order`

Gain K = y_final/A, percent overshoot, zeta and wn of a standard second-order model from the peak value, the final value and the peak time of a measured step response.

$$\omega_n = \frac{\pi}{T_p\sqrt{1-\zeta^2}}$$

symbol		meaning	SI unit
`y_peak`	in	peak value of the response	—
`y_final`	in	final (steady) value	—
`t_peak`	in	time of the peak in seconds	—
`A`	in	step size (default 1) (optional)	—
`K`	out	DC gain	—
`PO`	out	percent overshoot (%)	—
`zeta`	out	damping ratio	—
`wn`	out	natural frequency	rad/s

Applies when: 0 < overshoot < 100 %; t_peak > 0.

```
$ control-systems solve ctrl_identify_second_order y_peak=1.163033535 y_final=1 t_peak=0.9068996821
K = 1
PO = 16.3033535
zeta = 0.4999999998
wn = 3.999999999 rad/s
  by: Second-order model from a step response  (zeta from the overshoot, wn = pi/(tp sqrt(1 -
zeta^2)))
  y_peak = 1.163033535
  y_final = 1
  t_peak = 0.9068996821
  assumes: 0 < overshoot < 100 %; t_peak > 0
```

In the worked example, y_peak = 1.163033535, y_final = 1, t_peak = 0.9068996821 go through the equation above and give K = 1, PO = 16.30335348, zeta = 0.5, wn = 4 rad/s. It applies only when 0 < overshoot < 100 %; t_peak > 0: outside that it says what is wrong instead of returning a number.

Modelling (1)

Speed transfer function of a DC motor — `ctrl_dc_motor`

omega(s)/V(s) = Kt/((J s + b)(L s + R) + Kt^2) of an armature-controlled DC motor (Ke = Kt in SI units): coefficients, DC gain and poles.

$$\frac{\Omega(s)}{V(s)} = \frac{K_t}{(Js+b)(Ls+R)+K_t^2}$$

symbol		meaning	SI unit
`J`	in	rotor inertia in kg*m^2	—
`b`	in	viscous friction in N*m*s	—
`Kt`	in	torque (= back-emf) constant in N*m/A	—
`R`	in	armature resistance in ohm	—
`L`	in	armature inductance in H	—
`num`	out	numerator	—
`den`	out	denominator [J L, b L + J R, b R + Kt^2]	—
`dc_gain`	out	speed per volt at steady state (rad/s per V)	—
`poles`	out	poles	—

Applies when: J, Kt, R, L > 0; b >= 0.

```
$ control-systems solve ctrl_dc_motor J=0.01 b=0.1 Kt=0.01 R=1 L=0.5
num = [0.01]
den = [0.005,0.06,0.1001]
dc_gain = 0.0999000999
poles = [-9.99749921826,-2.00250078174]
  by: Speed transfer function of a DC motor  (electrical and mechanical equations combined)
  J = 0.01
  b = 0.1
  Kt = 0.01
  R = 1
  L = 0.5
  assumes: J, Kt, R, L > 0; b >= 0
```

In the worked example, J = 0.01, b = 0.1, Kt = 0.01, R = 1, L = 0.5 go through the equation above and give num = [0.01], den = [0.005, 0.06, 0.1001], dc_gain = 0.0999000999, poles = [-9.997499218, -2.002500782]. It applies only when J, Kt, R, L > 0; b >= 0: outside that it says what is wrong instead of returning a number.

Optimal control (3)

Continuous-time LQR gain (Riccati equation) — `ctrl_lqr`

The optimal state feedback u = -K x minimising the integral of x^T Q x + R u^2 for x' = A x + B u: the Riccati solution P, K = R^{-1} B^T P and the closed-loop poles.

$$A^T P + PA - PBR^{-1}B^T P + Q = 0, \quad K = R^{-1}B^T P$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector	—
`Q`	in	state weight (symmetric positive definite)	—
`R`	in	input weight (> 0)	—
`K`	out	optimal gain	—
`P`	out	Riccati solution	—
`poles`	out	closed-loop poles	—

Applies when: (A, B) controllable; Q symmetric positive definite; R > 0.

```
$ control-systems solve ctrl_lqr "A=[[0, 1], [0, 0]]" "B=[0, 1]" "Q=[[1, 0], [0, 1]]" R=1
K = [1.0,1.73205080757]
P = [[1.73205080757,1.0],[1.0,1.73205080757]]
poles = [{"re":-0.866025403784,"im":-0.5},{"re":-0.866025403784,"im":0.5}]
  by: Continuous-time LQR gain (Riccati equation)  (Newton-Kleinman iteration (a Lyapunov equation
per step) from a stabilising Ackermann gain)
  R = 1
  assumes: (A, B) controllable; Q symmetric positive definite; R > 0
```

In the worked example, A = [0 1; 0 0], B = [0, 1], Q = [1 0; 0 1], R = 1 go through the equation above and give K = [1, 1.732050808], P = [[1.732050808, 1], [1, 1.732050808]], poles = [-0.8660254038-0.5i,

-0.8660254038+0.5i]. It applies only when (A, B) controllable; Q symmetric positive definite; R > 0: outside that it says what is wrong instead of returning a number.

Discrete-time LQR gain (discrete Riccati equation) — `ctrl_dlqr`

The optimal state feedback u_k = -K x_k minimising the sum of x^T Q x + R u^2 for x_{k+1} = A x_k + B u_k: P from the discrete Riccati equation, K = (R + B^T P B)^{-1} B^T P A and the closed-loop poles.

$$P = A^T P A - A^T P B (R + B^T P B)^{-1} B^T P A + Q$$

symbol		meaning	SI unit
`A`	in	discrete state matrix (n x n)	—
`B`	in	input vector	—
`Q`	in	state weight (symmetric positive definite)	—
`R`	in	input weight (> 0)	—
`K`	out	optimal gain	—
`P`	out	Riccati solution	—
`poles`	out	closed-loop poles	—

Applies when: (A, B) controllable; Q symmetric positive definite; R > 0.

```
$ control-systems solve ctrl_dlqr "A=[[1, 1], [0, 1]]" "B=[0, 1]" "Q=[[1, 0], [0, 1]]" R=1
K = [0.422082440385,1.2439288539]
P = [[2.94712296671,2.36920540709],[2.36920540709,4.613134261]]
poles = [{"re":0.378035573048,"im":-0.187730370457},{"re":0.378035573048,"im":0.187730370457}]
  by: Discrete-time LQR gain (discrete Riccati equation)  (Hewer's iteration (a discrete Lyapunov
equation per step) from the deadbeat gain)
  R = 1
  assumes: (A, B) controllable; Q symmetric positive definite; R > 0
```

In the worked example, A = [1 1; 0 1], B = [0, 1], Q = [1 0; 0 1], R = 1 go through the equation above and give K = [0.4220824404, 1.243928854], P = [[2.947122967, 2.369205407], [2.369205407, 4.613134261]], poles = [0.378035573-0.1877303705i, 0.378035573+0.1877303705i]. It applies only when (A, B) controllable; Q symmetric positive definite; R > 0: outside that it says what is wrong instead of returning a number.

LQR for a first-order system — `ctrl_scalar_lqr`

For x' = a x + b u minimising the integral of q x^2 + r u^2: the Riccati solution P, the optimal gain K = b P/r and the closed-loop pole -sqrt(a^2 + b^2 q/r).

$$2aP - \frac{b^2 P^2}{r} + q = 0, \quad K = \frac{bP}{r}$$

symbol		meaning	SI unit
`a`	in	system coefficient	—
`b`	in	input coefficient	—
`q`	in	state weight (> 0)	—

symbol		meaning	SI unit
`r`	in	input weight (> 0)	—
`P`	out	Riccati solution	—
`K`	out	optimal feedback gain	—
`pole`	out	closed-loop pole a - b K	—

Applies when: b != 0; q, r > 0.

```
$ control-systems solve ctrl_scalar_lqr a=1 b=1 q=3 r=1
P = 3
K = 3
pole = -2
  by: LQR for a first-order system  (positive root of 2 a P - b^2 P^2 / r + q = 0)
  a = 1
  b = 1
  q = 3
  r = 1
  assumes: b != 0; q, r > 0
```

In the worked example, a = 1, b = 1, q = 3, r = 1 go through the equation above and give P = 3, K = 3, pole = -2. It applies only when b != 0; q, r > 0: outside that it says what is wrong instead of returning a number.

PID tuning (9)

Closed-loop poles of a PID loop — `ctrl_pid_closed_loop`

The characteristic polynomial s D(s) + (Kd s^2 + Kp s + Ki) N(s), the closed-loop poles and stability of a plant N/D under a PID controller with unity feedback.

$$sD(s) + (K_d s^2 + K_p s + K_i)N(s) = 0$$

symbol		meaning	SI unit
`num`	in	plant numerator	—
`den`	in	plant denominator	—
`Kp`	in	proportional gain	—
`Ki`	in	integral gain (default 0) (optional)	—
`Kd`	in	derivative gain (default 0) (optional)	—
`char_poly`	out	closed-loop characteristic polynomial	—
`poles`	out	closed-loop poles	—
`max_real_part`	out	largest real part	—
`stable`	out	true when every pole is in the left half plane	—

Applies when: strictly proper plant.

```
$ control-systems solve ctrl_pid_closed_loop "num=[1]" "den=[1, 1]" Kp=3 Ki=2
char_poly = [1.0,4.0,2.0]
poles = [-3.41421356237,-0.585786437627]
max_real_part = -0.5857864376
stable = true
  by: Closed-loop poles of a PID loop  (1 + C(s) G(s) = 0, roots by the Aberth-Ehrlich iteration)
  Kp = 3
  Ki = 2
  assumes: strictly proper plant
```

In the worked example, num = [1], den = [1, 1], Kp = 3, Ki = 2 go through the equation above and give char_poly = [1, 4, 2], poles = [-3.414213562, -0.5857864376], max_real_part = -0.5857864376, stable = True. It applies only when strictly proper plant: outside that it says what is wrong instead of returning a number.

Cohen-Coon tuning of a first-order-plus-dead-time process — `ctrl_cohen_coon`

P, PI or PID settings from the Cohen-Coon formulas for K e^{-theta s}/(tau s + 1).

$$\text{PID: } K_p = \frac{\tau}{K\theta}\left(\frac{4}{3} + \frac{\theta}{4\tau}\right),\ T_i = \theta\frac{32 + 6\theta/\tau}{13 + 8\theta/\tau},\ T_d = \frac{4\theta}{11 + 2\theta/\tau}$$

symbol		meaning	SI unit
`K`	in	process gain	—
`tau`	in	time constant in seconds	—
`theta`	in	dead time in seconds	—
`controller`	in	controller type	—
`Kp`	out	proportional gain	—
`Ti`	out	integral time (0 when there is no integral action)	s
`Td`	out	derivative time	s
`Ki`	out	integral gain Kp/Ti	—
`Kd`	out	derivative gain Kp Td	—

Applies when: K, tau, theta > 0.

```
$ control-systems solve ctrl_cohen_coon K=2 tau=10 theta=2 controller=PID
Kp = 3.458333333
Ti = 4.547945205 s
Td = 0.701754386 s
Ki = 0.7604166667
Kd = 2.426900585
  by: Cohen-Coon tuning of a first-order-plus-dead-time process  (Cohen-Coon formulas (r =
theta/tau))
  K = 2
  tau = 10
  theta = 2
  controller = PID
  assumes: K, tau, theta > 0
```

In the worked example, K = 2, tau = 10, theta = 2, controller = PID go through the equation above and give Kp = 3.458333333, Ti = 4.547945205 s, Td = 0.701754386 s, Ki = 0.7604166667. It applies only when K, tau, theta > 0: outside that it says what is wrong instead of returning a number.

PI gains placing the closed-loop poles of a first-order plant — `ctrl_pi_pole_placement`

Kp = (2 zeta wn tau - 1)/K and Ki = wn^2 tau/K, so that K/(tau s + 1) under PI control with unity feedback has the characteristic polynomial s^2 + 2 zeta wn s + wn^2.

$$K_p = \frac{2\zeta\omega_n\tau - 1}{K}, \quad K_i = \frac{\omega_n^2\tau}{K}$$

symbol		meaning	SI unit
`K`	in	plant gain	—
`tau`	in	plant time constant in seconds	—
`zeta`	in	desired damping ratio	—
`wn`	in	desired natural frequency in rad/s	—
`Kp`	out	proportional gain	—
`Ki`	out	integral gain	—

Applies when: tau, zeta, wn > 0; K != 0.

```
$ control-systems solve ctrl_pi_pole_placement K=2 tau=5 zeta=0.7 wn=1
Kp = 3
Ki = 2.5
  by: PI gains placing the closed-loop poles of a first-order plant  (match tau s^2 + (1 + K Kp) s
+ K Ki to tau (s^2 + 2 zeta wn s + wn^2))
  K = 2
  tau = 5
  zeta = 0.7
  wn = 1
  assumes: tau, zeta, wn > 0; K != 0
```

In the worked example, K = 2, tau = 5, zeta = 0.7, wn = 1 go through the equation above and give Kp = 3, Ki = 2.5. It applies only when tau, zeta, wn > 0; K != 0: outside that it says what is wrong instead of returning a number.

PID: parallel gains to standard form — `ctrl_pid_parallel_to_standard`

The integral time Ti = Kp/Ki and derivative time Td = Kd/Kp of a parallel PID Kp + Ki/s + Kd s.

$$T_i = K_p/K_i, \quad T_d = K_d/K_p$$

symbol		meaning	SI unit
`Kp`	in	proportional gain (> 0)	—
`Ki`	in	integral gain (> 0)	—
`Kd`	in	derivative gain	—

symbol		meaning	SI unit
`Ti`	out	integral time	s
`Td`	out	derivative time	s

Applies when: Kp > 0; Ki > 0; Kd >= 0.

```
$ control-systems solve ctrl_pid_parallel_to_standard Kp=6 Ki=3 Kd=3
Ti = 2 s
Td = 0.5 s
  by: PID: parallel gains to standard form  (Ti = Kp/Ki, Td = Kd/Kp)
  Kp = 6
  Ki = 3
  Kd = 3
  assumes: Kp > 0; Ki > 0; Kd >= 0
```

In the worked example, Kp = 6, Ki = 3, Kd = 3 go through the equation above and give Ti = 2 s, Td = 0.5 s. It applies only when Kp > 0; Ki > 0; Kd >= 0: outside that it says what is wrong instead of returning a number.

PID: standard form to parallel gains — `ctrl_pid_standard_to_parallel`

Ki = Kp/Ti and Kd = Kp Td from the standard (ideal ISA) form Kp (1 + 1/(Ti s) + Td s).

$$K_i = K_p/T_i, \quad K_d = K_p T_d$$

symbol		meaning	SI unit
`Kp`	in	proportional gain	—
`Ti`	in	integral (reset) time in seconds	—
`Td`	in	derivative time in seconds	—
`Ki`	out	integral gain	—
`Kd`	out	derivative gain	—

Applies when: Ti > 0; Td >= 0.

```
$ control-systems solve ctrl_pid_standard_to_parallel Kp=4 Ti=2 Td=0.5
Ki = 2
Kd = 2
  by: PID: standard form to parallel gains  (Ki = Kp/Ti, Kd = Kp Td)
  Kp = 4
  Ti = 2
  Td = 0.5
  assumes: Ti > 0; Td >= 0
```

In the worked example, Kp = 4, Ti = 2, Td = 0.5 go through the equation above and give Ki = 2, Kd = 2. It applies only when Ti > 0; Td >= 0: outside that it says what is wrong instead of returning a number.

SIMC (Skogestad) PI tuning — `ctrl_simc_pi`

PI settings Kp = tau/(K (tau_c + theta)), Ti = min(tau, 4 (tau_c + theta)) for K e^{-theta s}/(tau s + 1); the default tau_c equals theta.

$$K_p = \frac{\tau}{K(\tau_c + \theta)},\ T_i = \min(\tau, 4(\tau_c + \theta))$$

symbol		meaning	SI unit
`K`	in	process gain	—
`tau`	in	time constant in seconds	—
`theta`	in	dead time in seconds	—
`tau_c`	in	desired closed-loop time constant (default theta) (optional)	—
`Kp`	out	proportional gain	—
`Ti`	out	integral time	s
`Ki`	out	integral gain	—

Applies when: K, tau, theta > 0.

```
$ control-systems solve ctrl_simc_pi K=2 tau=10 theta=1
Kp = 2.5
Ti = 8 s
Ki = 0.3125
  by: SIMC (Skogestad) PI tuning  (Skogestad's SIMC rule)
  K = 2
  tau = 10
  theta = 1
  assumes: K, tau, theta > 0
```

In the worked example, K = 2, tau = 10, theta = 1 go through the equation above and give Kp = 2.5, Ti = 8 s, Ki = 0.3125. It applies only when K, tau, theta > 0: outside that it says what is wrong instead of returning a number.

Ziegler-Nichols tuning from a plant model — `ctrl_zn_from_plant`

The ultimate gain Ku = 1/|G(j w180)| and period Pu = 2 pi/w180 of a plant model, then the Ziegler-Nichols P, PI or PID settings.

$$K_u = \frac{1}{|G(j\omega_{180})|},\quad P_u = \frac{2\pi}{\omega_{180}}$$

symbol		meaning	SI unit
`num`	in	plant numerator	—
`den`	in	plant denominator	—
`controller`	in	controller type	—
`Kp`	out	proportional gain	—
`Ti`	out	integral time (0 when there is no integral action)	s
`Td`	out	derivative time	s
`Ki`	out	integral gain Kp/Ti	—
`Kd`	out	derivative gain Kp Td	—

symbol		meaning	SI unit
`Ku`	out	ultimate gain	—
`Pu`	out	ultimate period	s

Applies when: exactly one phase crossover.

```
$ control-systems solve ctrl_zn_from_plant "num=[1]" "den=[1, 3, 2, 0]" controller=PID
Kp = 3.6
Ti = 2.221441469 s
Td = 0.5553603673 s
Ki = 1.620569369
Kd = 1.999297322
Ku = 6
Pu = 4.442882938 s
  by: Ziegler-Nichols tuning from a plant model  (phase crossover from Im(N(jw) conj D(jw)) = 0;
Ziegler-Nichols table)
  controller = PID
  assumes: exactly one phase crossover
```

In the worked example, num = [1], den = [1, 3, 2, 0], controller = PID go through the equation above and give Kp = 3.6, Ti = 2.221441469 s, Td = 0.5553603673 s, Ki = 1.620569369. It applies only when exactly one phase crossover: outside that it says what is wrong instead of returning a number.

Ziegler-Nichols tuning from the process reaction curve — `ctrl_zn_reaction`

P, PI or PID settings from the open-loop (reaction-curve) Ziegler-Nichols table for a process with gain K, dead time L and time constant T.

$$\text{PID: } K_p = \frac{1.2\,T}{K\,L},\ T_i = 2L,\ T_d = 0.5L$$

symbol		meaning	SI unit
`K`	in	process gain	—
`L`	in	apparent dead time in seconds	—
`T`	in	apparent time constant in seconds	—
`controller`	in	controller type	—
`Kp`	out	proportional gain	—
`Ti`	out	integral time (0 when there is no integral action)	s
`Td`	out	derivative time	s
`Ki`	out	integral gain Kp/Ti	—
`Kd`	out	derivative gain Kp Td	—

Applies when: K, L, T > 0.

```
$ control-systems solve ctrl_zn_reaction K=2 L=1 T=10 controller=PID
Kp = 6
Ti = 2 s
Td = 0.5 s
Ki = 3
Kd = 3
  by: Ziegler-Nichols tuning from the process reaction curve  (Ziegler-Nichols reaction-curve
table)
  K = 2
  L = 1
  T = 10
  controller = PID
  assumes: K, L, T > 0
```

In the worked example, K = 2, L = 1, T = 10, controller = PID go through the equation above and give Kp = 6, Ti = 2 s, Td = 0.5 s, Ki = 3. It applies only when K, L, T > 0: outside that it says what is wrong instead of returning a number.

Ziegler-Nichols tuning from the ultimate gain and period — `ctrl_zn_ultimate`

P, PI or PID settings from the closed-loop (ultimate-cycle) Ziegler-Nichols table: P 0.5 Ku; PI 0.45 Ku, Ti = Pu/1.2; PID 0.6 Ku, Ti = Pu/2, Td = Pu/8.

$$\text{PID: } K_p = 0.6K_u,\ T_i = P_u/2,\ T_d = P_u/8$$

symbol		meaning	SI unit
`Ku`	in	ultimate gain (gain at sustained oscillation)	—
`Pu`	in	ultimate period in seconds	—
`controller`	in	controller type	—
`Kp`	out	proportional gain	—
`Ti`	out	integral time (0 when there is no integral action)	s
`Td`	out	derivative time	s
`Ki`	out	integral gain Kp/Ti	—
`Kd`	out	derivative gain Kp Td	—

Applies when: Ku > 0; Pu > 0.

```
$ control-systems solve ctrl_zn_ultimate Ku=10 Pu=4 controller=PID
Kp = 6
Ti = 2 s
Td = 0.5 s
Ki = 3
Kd = 3
  by: Ziegler-Nichols tuning from the ultimate gain and period  (Ziegler-Nichols ultimate-cycle
table)
  Ku = 10
  Pu = 4
  controller = PID
  assumes: Ku > 0; Pu > 0
```

In the worked example, Ku = 10, Pu = 4, controller = PID go through the equation above and give Kp = 6, Ti = 2 s, Td = 0.5 s, Ki = 3. It applies only when Ku > 0; Pu > 0: outside that it says what is wrong instead of returning a number.

Root locus (5)

Root-locus angle of arrival at a complex zero — `ctrl_arrival_angle`

The angle at which the root locus arrives at the complex zero z (upper half plane): 180 + sum of angles from the poles - sum of angles from the other zeros.

$$\theta_a = 180^\circ + \sum \angle(z - p_j) - \sum_{i \neq} \angle(z - z_i)$$

symbol		meaning	SI unit
`num`	in	numerator of G(s) (exactly one complex zero pair)	—
`den`	in	denominator of G(s)	—
`zero`	out	the complex zero (positive imaginary part)	—
`arrival_deg`	out	angle of arrival in degrees, (-180, 180]	—

Applies when: exactly one complex zero pair; same-sign leading coefficients.

```
$ control-systems solve ctrl_arrival_angle "num=[1, 2, 2]" "den=[1, 0]"
zero = {"re":-1.0,"im":1.0}
arrival_deg = -135
  by: Root-locus angle of arrival at a complex zero  (angle criterion at the zero)
  assumes: exactly one complex zero pair; same-sign leading coefficients
```

In the worked example, num = [1, 2, 2], den = [1, 0] go through the equation above and give zero = -1+1i, arrival_deg = -135. It applies only when exactly one complex zero pair; same-sign leading coefficients: outside that it says what is wrong instead of returning a number.

Root-locus angle of departure from a complex pole — `ctrl_departure_angle`

The angle at which the root locus leaves the complex pole p (upper half plane): 180 + sum of angles from the zeros - sum of angles from the other poles.

$$\theta_d = 180^\circ + \sum \angle(p - z_i) - \sum_{j \neq} \angle(p - p_j)$$

symbol		meaning	SI unit
`num`	in	numerator of G(s)	—
`den`	in	denominator of G(s) (exactly one complex pole pair)	—
`pole`	out	the complex pole (positive imaginary part)	—
`departure_deg`	out	angle of departure in degrees, (-180, 180]	—

Applies when: exactly one complex pole pair; same-sign leading coefficients.

```
$ control-systems solve ctrl_departure_angle "num=[1]" "den=[1, 2, 2, 0]"
pole = {"re":-1.0,"im":1.0}
departure_deg = -45
  by: Root-locus angle of departure from a complex pole  (angle criterion at the pole)
  assumes: exactly one complex pole pair; same-sign leading coefficients
```

In the worked example, num = [1], den = [1, 2, 2, 0] go through the equation above and give pole = -1+1i, departure_deg = -45. It applies only when exactly one complex pole pair; same-sign leading coefficients: outside that it says what is wrong instead of returning a number.

Root-locus asymptotes (centroid and angles) — `ctrl_locus_asymptotes`

Number of asymptotes n - m, their real-axis intercept (sum of poles - sum of zeros)/(n - m) and their angles (2k+1) 180/(n - m) degrees.

$$\sigma_a = \frac{\sum p_i - \sum z_j}{n - m}, \quad \theta_k = \frac{(2k+1)180^\circ}{n - m}$$

symbol		meaning	SI unit
`num`	in	numerator of the open-loop G(s)	—
`den`	in	denominator of G(s)	—
`n_asymptotes`	out	number of asymptotes	—
`centroid`	out	real-axis intercept	—
`angles_deg`	out	asymptote angles in degrees	—

Applies when: more poles than zeros.

```
$ control-systems solve ctrl_locus_asymptotes "num=[1]" "den=[1, 3, 2, 0]"
n_asymptotes = 3
centroid = -1
angles_deg = [60.0,180.0,300.0]
  by: Root-locus asymptotes (centroid and angles)  (sums of poles and zeros from the coefficients)
  assumes: more poles than zeros
```

In the worked example, num = [1], den = [1, 3, 2, 0] go through the equation above and give n_asymptotes = 3, centroid = -1, angles_deg = [60, 180, 300]. It applies only when more poles than zeros: outside that it says what is wrong instead of returning a number.

Root-locus breakaway and break-in points — `ctrl_breakaway_points`

Real points where root-locus branches meet and leave (or enter) the real axis: real roots of N D' - N' D = 0 with a positive gain K = -D/N there.

$$\frac{dK}{ds} = 0 \iff ND' - N'D = 0$$

symbol		meaning	SI unit
`num`	in	numerator of G(s)	—

symbol		meaning	SI unit
`den`	in	denominator of G(s)	—
`points`	out	breakaway/break-in points, ascending	—
`gains`	out	gain K at each point	—
`count`	out	number of points	—

Applies when: proper G(s).

```
$ control-systems solve ctrl_breakaway_points "num=[1]" "den=[1, 3, 2, 0]"
points = [-0.42264973081]
gains = [0.38490017946]
count = 1
  by: Root-locus breakaway and break-in points  (dK/ds = 0 with K = -D(s)/N(s))
  assumes: proper G(s)
```

In the worked example, num = [1], den = [1, 3, 2, 0] go through the equation above and give points = [-0.4226497308], gains = [0.3849001795], count = 1. It applies only when proper G(s): outside that it says what is wrong instead of returning a number.

Root-locus gain and angle at a test point — `ctrl_locus_gain_at_point`

The gain K = 1/|G(s0)| that would place a closed-loop pole at s0 (magnitude criterion) and the angle of G(s0); s0 lies on the root locus for K > 0 when the angle is 180 degrees (angle error 0).

$$K = \frac{1}{|G(s_0)|}, \quad \angle G(s_0) = \pm 180^\circ$$

symbol		meaning	SI unit
`num`	in	numerator of G(s)	—
`den`	in	denominator of G(s)	—
`s_re`	in	real part of the test point	—
`s_im`	in	imaginary part of the test point	—
`K`	out	gain from the magnitude criterion	—
`angle_deg`	out	angle of G(s0) in degrees	—
`angle_error_deg`	out	180 - |angle|: 0 on the locus	—

Applies when: s0 neither a pole nor a zero.

```
$ control-systems solve ctrl_locus_gain_at_point "num=[1]" "den=[1, 2, 0]" s_re=-1 s_im=1
K = 2
angle_deg = 180
angle_error_deg = 0
  by: Root-locus gain and angle at a test point  (K = |D(s0)|/|N(s0)|)
  s_re = -1
  s_im = 1
  assumes: s0 neither a pole nor a zero
```

In the worked example, num = [1], den = [1, 2, 0], s_re = -1, s_im = 1 go through the equation above and give K = 2, angle_deg = 180, angle_error_deg = 0. It applies only when s0 neither a pole nor a zero: outside that it says what is wrong instead of returning a number.

Stability (9)

Continuous Lyapunov equation — `ctrl_lyapunov`

The solution P of A^T P + P A + Q = 0 for a stable A (exact), and whether P is positive definite (with Q > 0 that certifies stability).

$$A^T P + P A + Q = 0$$

symbol		meaning	SI unit
`A`	in	state matrix (stable, n x n)	—
`Q`	in	symmetric matrix (n x n)	—
`P`	out	solution P	—
`positive_definite`	out	true when P is positive definite	—

Applies when: A stable; Q symmetric.

```
$ control-systems solve ctrl_lyapunov "A=[[-1, 0], [0, -2]]" "Q=[[2, 0], [0, 4]]"
P = [[1.0,0.0],[0.0,1.0]]
positive_definite = true
  by: Continuous Lyapunov equation  (Kronecker linear system in exact fractions)
  assumes: A stable; Q symmetric
```

In the worked example, A = [-1 0; 0 -2], Q = [2 0; 0 4] go through the equation above and give P = [[1, 0], [0, 1]], positive_definite = True. It applies only when A stable; Q symmetric: outside that it says what is wrong instead of returning a number.

Discrete Lyapunov equation — `ctrl_discrete_lyapunov`

The solution P of A^T P A - P + Q = 0 for a Schur-stable A (exact), and whether P is positive definite.

$$A^T P A - P + Q = 0$$

symbol		meaning	SI unit
`A`	in	discrete state matrix (eigenvalues inside the unit circle)	—
`Q`	in	symmetric matrix (n x n)	—
`P`	out	solution P	—
`positive_definite`	out	true when P is positive definite	—

Applies when: A Schur stable; Q symmetric.

```
$ control-systems solve ctrl_discrete_lyapunov "A=[[0.5, 0], [0, 0.5]]" "Q=[[3, 0], [0, 3]]"
P = [[4.0,0.0],[0.0,4.0]]
positive_definite = true
  by: Discrete Lyapunov equation  (Kronecker linear system in exact fractions)
  assumes: A Schur stable; Q symmetric
```

In the worked example, A = [0.5 0; 0 0.5], Q = [3 0; 0 3] go through the equation above and give P = [[4, 0], [0, 4]], positive_definite = True. It applies only when A Schur stable; Q symmetric: outside that it says what is wrong instead of returning a number.

Gain and phase margins — `ctrl_stability_margins`

Gain margin 1/|L(j w_pc)| (ratio and dB) at the phase crossover and phase margin 180 + arg L(j w_gc) at the gain crossover of an open loop L(s).

$$GM = \frac{1}{|L(j\omega_{pc})|}, \quad PM = 180^\circ + \angle L(j\omega_{gc})$$

symbol		meaning	SI unit
`num`	in	numerator of the open loop L(s)	—
`den`	in	denominator of L(s)	—
`gm`	out	gain margin (ratio)	—
`gm_db`	out	gain margin in dB	—
`w_pc`	out	phase-crossover frequency	rad/s
`pm_deg`	out	phase margin in degrees	—
`w_gc`	out	gain-crossover frequency	rad/s

Applies when: exactly one gain crossover and one phase crossover.

```
$ control-systems solve ctrl_stability_margins "num=[10]" "den=[1, 3, 2, 0]"
gm = 0.6
gm_db = -4.436974992
w_pc = 1.414213562 rad/s
pm_deg = -12.99720802
w_gc = 1.802203305 rad/s
  by: Gain and phase margins  (crossovers as positive real roots of |N|^2 - |D|^2 and Im(N(jw) conj
D(jw)), Newton-polished)
  assumes: exactly one gain crossover and one phase crossover
```

In the worked example, num = [10], den = [1, 3, 2, 0] go through the equation above and give gm = 0.6, gm_db = -4.436974992, w_pc = 1.414213562 rad/s, pm_deg = -12.99720802. It applies only when exactly one gain crossover and one phase crossover: outside that it says what is wrong instead of returning a number.

Jury (Schur-Cohn) stability test for a discrete polynomial — `ctrl_jury_test`

Whether every root of a polynomial in z lies inside the unit circle (Jury/Schur-Cohn table in exact arithmetic), with the necessary-condition values P(1) and (-1)^n P(-1).

$$|a_n| < a_0,\ P(1) > 0,\ (-1)^n P(-1) > 0$$

symbol		meaning	SI unit
`coefficients`	in	polynomial coefficients in z, highest power first	—
`stable`	out	true when every root is inside the unit circle	—
`P1`	out	P(1) (must be > 0)	—
`Pm1`	out	(-1)^n P(-1) (must be > 0)	—

Applies when: the table is not singular.

```
$ control-systems solve ctrl_jury_test "coefficients=[1, -1.2, 0.35]"
stable = true
P1 = 0.15
Pm1 = 2.55
  by: Jury (Schur-Cohn) stability test for a discrete polynomial  (Schur-Cohn reduction q <- q - (a_n/a_0) q_reversed in exact fractions)
  assumes: the table is not singular
```

In the worked example, coefficients = [1, -1.2, 0.35] go through the equation above and give stable = True, P1 = 0.15, Pm1 = 2.55. It applies only when the table is not singular: outside that it says what is wrong instead of returning a number.

Nyquist criterion: encirclements of -1 — `ctrl_nyquist`

For the open loop K G(s) under unity negative feedback: the open-loop right-half-plane poles P, the closed-loop right-half-plane poles Z and the net clockwise encirclements N = Z - P of the point -1 by the Nyquist curve.

$$Z = N + P$$

symbol		meaning	SI unit
`num`	in	numerator of G(s)	—
`den`	in	denominator of G(s)	—
`K`	in	loop gain (default 1) (optional)	—
`P`	out	open-loop poles in the right half plane	—
`Z`	out	closed-loop poles in the right half plane	—
`N`	out	net clockwise encirclements of -1	—
`stable`	out	true when Z = 0	—

Applies when: no open-loop or closed-loop pole on the imaginary axis.

```
$ control-systems solve ctrl_nyquist "num=[1]" "den=[1, -1]" K=2
P = 1
Z = 0
N = -1
stable = true
  by: Nyquist criterion: encirclements of -1  (Z = N + P from the poles of G and of 1 + K G)
  K = 2
  assumes: no open-loop or closed-loop pole on the imaginary axis
```

In the worked example, num = [1], den = [1, -1], K = 2 go through the equation above and give P = 1, Z = 0, N = -1, stable = True. It applies only when no open-loop or closed-loop pole on the imaginary axis: outside that it says what is wrong instead of returning a number.

Peak sensitivity Ms and modulus margin — `ctrl_sensitivity_peak`

Ms = max |1/(1 + L(jw))| of a stable unity-feedback loop, its frequency, and the modulus (stability) margin 1/Ms: the smallest distance from the Nyquist curve to -1.

$$M_s = \max_{\omega} \frac{1}{|1 + L(j\omega)|}$$

symbol		meaning	SI unit
`num`	in	numerator of the open loop L(s)	—
`den`	in	denominator of L(s)	—
`Ms`	out	peak sensitivity	—
`Ms_db`	out	peak sensitivity in dB	—
`w_ms`	out	frequency of the peak	rad/s
`sm`	out	modulus margin 1/Ms	—

Applies when: closed loop stable; strictly proper L(s).

```
$ control-systems solve ctrl_sensitivity_peak "num=[2]" "den=[1, 3, 2, 0]"
Ms = 2.312314015
Ms_db = 7.280936228
w_ms = 0.9252900062 rad/s
sm = 0.4324672141
  by: Peak sensitivity Ms and modulus margin  (stationary points of |D(jw)|^2/|D(jw) + N(jw)|^2
(positive real roots of f' g - f g'))
  assumes: closed loop stable; strictly proper L(s)
```

In the worked example, num = [2], den = [1, 3, 2, 0] go through the equation above and give Ms = 2.312314015, Ms_db = 7.280936228, w_ms = 0.9252900062 rad/s, sm = 0.4324672141. It applies only when closed loop stable; strictly proper L(s): outside that it says what is wrong instead of returning a number.

Poles and stability of a characteristic polynomial — `ctrl_pole_stability`

The roots (poles) of a characteristic polynomial and whether the system is asymptotically stable, marginally stable or unstable.

$$\text{stable} \iff \operatorname{Re} p_i < 0 \; \forall i$$

symbol		meaning	SI unit
`den`	in	characteristic polynomial (denominator) coefficients, highest power first	—
`poles`	out	the poles	—
`max_real_part`	out	largest real part of the poles	—
`stability`	out	asymptotically stable, marginally stable or unstable	—

Applies when: degree 1 or more.

```
$ control-systems solve ctrl_pole_stability "den=[1, 6, 11, 6]"
poles = [-3.0,-2.0,-1.0]
max_real_part = -1
stability = asymptotically stable
  by: Poles and stability of a characteristic polynomial  (roots by the Aberth-Ehrlich iteration;
simple poles on the imaginary axis are marginal, repeated ones unstable)
  assumes: degree 1 or more
```

In the worked example, den = [1, 6, 11, 6] go through the equation above and give poles = [-3, -2, -1], max_real_part = -1, stability = asymptotically stable. It applies only when degree 1 or more: outside that it says what is wrong instead of returning a number.

Range of gain for closed-loop stability (Routh, j-omega crossing) — `ctrl_stable_gain_range`

The interval K_min < K < K_max of positive gains for which 1 + K G(s) = 0 has every root in the left half plane, and the frequency at which the root locus crosses the imaginary axis at K_max.

$$D(j\omega) + KN(j\omega) = 0$$

symbol		meaning	SI unit
`num`	in	numerator of G(s)	—
`den`	in	denominator of G(s)	—
`K_min`	out	lower end of the stable range (0 when stable from small gains)	—
`K_max`	out	critical gain (upper end)	—
`w_cross`	out	imaginary-axis crossing frequency at K_max (0 for a crossing at s = 0)	rad/s

Applies when: one bounded interval of stable positive gains.

```
$ control-systems solve ctrl_stable_gain_range "num=[1]" "den=[1, 3, 2, 0]"
K_min = 0
K_max = 6
w_cross = 1.414213562 rad/s
  by: Range of gain for closed-loop stability (Routh, j-omega crossing)  (critical gains from D(jw)
+ K N(jw) = 0 and D(0) + K N(0) = 0; each interval tested by an exact Routh array)
  assumes: one bounded interval of stable positive gains
```

In the worked example, num = [1], den = [1, 3, 2, 0] go through the equation above and give K_min = 0, K_max = 6, w_cross = 1.414213562 rad/s. It applies only when one bounded interval of stable positive gains: outside that it says what is wrong instead of returning a number.

Routh-Hurwitz stability test — `ctrl_routh_hurwitz`

The first column of the Routh array (exact arithmetic), the number of right-half-plane roots (its sign changes) and whether the characteristic polynomial is stable.

$$b_i = \frac{a_1 a_{0,i+1} - a_0 a_{1,i+1}}{a_1}$$

symbol		meaning	SI unit
`coefficients`	in	characteristic polynomial coefficients, highest power of s first	—
`first_column`	out	first column of the Routh array	—
`rhp_roots`	out	number of roots in the right half plane	—
`stable`	out	true when every root has a negative real part	—

Applies when: no zero in the first column (special cases are refused).

```
$ control-systems solve ctrl_routh_hurwitz "coefficients=[1, 6, 11, 6]"
first_column = [1.0,6.0,10.0,6.0]
rhp_roots = 0
stable = true
  by: Routh-Hurwitz stability test  (Routh array in exact fractions; sign changes of the first
column)
  assumes: no zero in the first column (special cases are refused)
```

In the worked example, coefficients = [1, 6, 11, 6] go through the equation above and give first_column = [1, 6, 10, 6], rhp_roots = 0, stable = True. It applies only when no zero in the first column (special cases are refused): outside that it says what is wrong instead of returning a number.

State space (14)

Closed-loop poles under state feedback u = -K x — `ctrl_state_feedback_poles`

The characteristic polynomial det(sI - (A - B K)) (exact), the closed-loop poles and stability for a state-feedback gain K.

$$\det(sI - A + BK) = 0$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector	—
`K`	in	state-feedback gain (row, n entries)	—
`char_poly`	out	closed-loop characteristic polynomial	—
`poles`	out	closed-loop poles	—

symbol		meaning	SI unit
`stable`	out	true when every pole is in the left half plane	—

Applies when: single input.

```
$ control-systems solve ctrl_state_feedback_poles "A=[[0, 1], [0, 0]]" "B=[0, 1]" "K=[4, 4]"
char_poly = [1.0,4.0,4.0]
poles = [-2.0,-2.0]
stable = true
  by: Closed-loop poles under state feedback u = -K x  (Faddeev-LeVerrier on A - B K)
  assumes: single input
```

In the worked example, A = [0 1; 0 0], B = [0, 1], K = [4, 4] go through the equation above and give char_poly = [1, 4, 4], poles = [-2, -2], stable = True. It applies only when single input: outside that it says what is wrong instead of returning a number.

Controllability Gramian — `ctrl_ctrb_gramian`

The infinite-horizon controllability Gramian Wc solving A Wc + Wc A^T + B B^T = 0 for a stable A (exact), its determinant and whether (A, B) is controllable (Wc nonsingular).

$$AW_c + W_cA^T + BB^T = 0$$

symbol		meaning	SI unit
`A`	in	state matrix (stable, n x n)	—
`B`	in	input vector	—
`Wc`	out	controllability Gramian	—
`controllable`	out	true when Wc is nonsingular	—

Applies when: A stable.

```
$ control-systems solve ctrl_ctrb_gramian "A=[[-1, 0], [0, -2]]" "B=[1, 1]"
Wc = [[0.5,0.333333333333],[0.333333333333,0.25]]
controllable = true
  by: Controllability Gramian  (Lyapunov equation in exact fractions)
  assumes: A stable
```

In the worked example, A = [-1 0; 0 -2], B = [1, 1] go through the equation above and give Wc = [[0.5, 0.3333333333], [0.3333333333, 0.25]], controllable = True. It applies only when A stable: outside that it says what is wrong instead of returning a number.

Controllability matrix and rank — `ctrl_controllability`

The controllability matrix [B, AB, ..., A^{n-1}B], its exact rank and determinant, and whether (A, B) is controllable.

$$\mathcal{C} = [B\ AB\ \cdots\ A^{n-1}B]$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector (n entries)	—
`Wc`	out	controllability matrix	—
`rank`	out	rank of the controllability matrix	—
`controllable`	out	true when the rank is n	—
`det_Wc`	out	determinant of the controllability matrix	—

Applies when: single input.

```
$ control-systems solve ctrl_controllability "A=[[0, 1], [-2, -3]]" "B=[0, 1]"
Wc = [[0.0,1.0],[1.0,-3.0]]
rank = 2
controllable = true
det_Wc = -1
  by: Controllability matrix and rank  (exact rank by elimination in fractions)
  assumes: single input
```

In the worked example, A = [0 1; -2 -3], B = [0, 1] go through the equation above and give Wc = [[0, 1], [1, -3]], rank = 2, controllable = True, det_Wc = -1. It applies only when single input: outside that it says what is wrong instead of returning a number.

Controllable canonical form of a transfer function — `ctrl_tf_to_ss`

A, B, C, D in the controllable canonical form (scipy's convention) of a proper transfer function.

$$A = \begin{bmatrix} -a_1 & \cdots & -a_n \\ 1 & & 0 \\ & \ddots & \end{bmatrix}, \; B = e_1$$

symbol		meaning	SI unit
`num`	in	numerator coefficients	—
`den`	in	denominator coefficients	—
`A`	out	state matrix	—
`B`	out	input vector	—
`C`	out	output vector	—
`D`	out	feedthrough	—

Applies when: proper G(s).

```
$ control-systems solve ctrl_tf_to_ss "num=[1]" "den=[1, 3, 2]"
A = [[-3.0,-2.0],[1.0,0.0]]
B = [1.0,0.0]
C = [0.0,1.0]
D = 0
  by: Controllable canonical form of a transfer function  (normalise den; first row of A = -a1..-
an; C from num - D den)
  assumes: proper G(s)
```

In the worked example, num = [1], den = [1, 3, 2] go through the equation above and give A = [[-3, -2], [1, 0]], B = [1, 0], C = [0, 1], D = 0. It applies only when proper G(s): outside that it says what is wrong instead of returning a number.

DC gain of a state-space model — `ctrl_ss_dc_gain`

The steady-state gain G(0) = D - C A^{-1} B of a state-space model (exact).

$$G(0) = D - CA^{-1}B$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector	—
`C`	in	output vector	—
`D`	in	feedthrough (default 0) (optional)	—
`dc_gain`	out	DC gain G(0)	—

Applies when: A nonsingular.

```
$ control-systems solve ctrl_ss_dc_gain "A=[[0, 1], [-2, -3]]" "B=[0, 1]" "C=[1, 0]"
dc_gain = 0.5
  by: DC gain of a state-space model  (solve A x = B exactly, then D - C x)
  assumes: A nonsingular
```

In the worked example, A = [0 1; -2 -3], B = [0, 1], C = [1, 0] go through the equation above and give dc_gain = 0.5. It applies only when A nonsingular: outside that it says what is wrong instead of returning a number.

Deadbeat state feedback (discrete time) — `ctrl_deadbeat_gain`

The gain K that places every eigenvalue of A - B K at z = 0, so the discrete closed loop reaches the origin in at most n steps.

$$K = [0 \cdots 1]\,\mathcal{C}^{-1}A^{n}$$

symbol		meaning	SI unit
`A`	in	discrete state matrix (n x n)	—
`B`	in	input vector	—
`K`	out	deadbeat state-feedback gain	—

Applies when: (A, B) controllable.

```
$ control-systems solve ctrl_deadbeat_gain "A=[[1, 1], [0, 1]]" "B=[0, 1]"
K = [1.0,2.0]
  by: Deadbeat state feedback (discrete time)  (Ackermann's formula with alpha(z) = z^n (exact))
  assumes: (A, B) controllable
```

In the worked example, A = [1 1; 0 1], B = [0, 1] go through the equation above and give K = [1, 2]. It applies only when (A, B) controllable: outside that it says what is wrong instead of returning a number.

Eigenvalues (poles) of a state matrix — `ctrl_ss_eigenvalues`

The characteristic polynomial det(sI - A) (exact), the eigenvalues of A and whether the system is asymptotically stable.

$$\det(sI - A) = 0$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`eigenvalues`	out	eigenvalues of A	—
`char_poly`	out	characteristic polynomial (monic)	—
`max_real_part`	out	largest real part	—
`stable`	out	true when every eigenvalue has a negative real part	—

Applies when: A square, at most 6 x 6.

```
$ control-systems solve ctrl_ss_eigenvalues "A=[[0, 1], [-2, -3]]"
eigenvalues = [-2.0,-1.0]
char_poly = [1.0,3.0,2.0]
max_real_part = -1
stable = true
  by: Eigenvalues (poles) of a state matrix  (Faddeev-LeVerrier, then polynomial roots)
  assumes: A square, at most 6 x 6
```

In the worked example, A = [0 1; -2 -3] go through the equation above and give eigenvalues = [-2, -1], char_poly = [1, 3, 2], max_real_part = -1, stable = True. It applies only when A square, at most 6 x 6: outside that it says what is wrong instead of returning a number.

Observability Gramian — `ctrl_obsv_gramian`

The infinite-horizon observability Gramian Wo solving A^T Wo + Wo A + C^T C = 0 for a stable A (exact), its determinant and whether (A, C) is observable.

$$A^T W_o + W_o A + C^T C = 0$$

symbol		meaning	SI unit
`A`	in	state matrix (stable, n x n)	—

symbol		meaning	SI unit
`C`	in	output vector	—
`Wo`	out	observability Gramian	—
`observable`	out	true when Wo is nonsingular	—

Applies when: A stable.

```
$ control-systems solve ctrl_obsv_gramian "A=[[-1, 0], [0, -2]]" "C=[1, 1]"
Wo = [[0.5,0.333333333333],[0.333333333333,0.25]]
observable = true
  by: Observability Gramian  (Lyapunov equation in exact fractions)
  assumes: A stable
```

In the worked example, A = [-1 0; 0 -2], C = [1, 1] go through the equation above and give Wo = [[0.5, 0.3333333333], [0.3333333333, 0.25]], observable = True. It applies only when A stable: outside that it says what is wrong instead of returning a number.

Observability matrix and rank — `ctrl_observability`

The observability matrix [C; CA; ...; CA^{n-1}], its exact rank and determinant, and whether (A, C) is observable.

$$\mathcal{O} = \begin{bmatrix} C \\ CA \\ \vdots \\ CA^{n-1} \end{bmatrix}$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`C`	in	output vector (n entries)	—
`Wo`	out	observability matrix	—
`rank`	out	rank of the observability matrix	—
`observable`	out	true when the rank is n	—
`det_Wo`	out	determinant of the observability matrix	—

Applies when: single output.

```
$ control-systems solve ctrl_observability "A=[[0, 1], [-2, -3]]" "C=[1, 0]"
Wo = [[1.0,0.0],[0.0,1.0]]
rank = 2
observable = true
det_Wo = 1
  by: Observability matrix and rank  (exact rank by elimination in fractions)
  assumes: single output
```

In the worked example, A = [0 1; -2 -3], C = [1, 0] go through the equation above and give Wo = [[1, 0], [0, 1]], rank = 2, observable = True, det_Wo = 1. It applies only when single output: outside that it says what is wrong instead of returning a number.

Observer (estimator) gain by pole placement — `ctrl_observer_gain`

The observer gain L that gives A - L C the desired characteristic polynomial (single output), by duality with Ackermann's formula.

$$L = \alpha(A)\,\mathcal{O}^{-1}\begin{bmatrix}0\\ \vdots \\ 1\end{bmatrix}$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`C`	in	output vector	—
`alpha`	in	desired observer characteristic polynomial (n+1 coefficients)	—
`L`	out	observer gain (column)	—

Applies when: (A, C) observable.

```
$ control-systems solve ctrl_observer_gain "A=[[0, 1], [0, 0]]" "C=[1, 0]" "alpha=[1, 10, 25]"
L = [10.0,25.0]
  by: Observer (estimator) gain by pole placement  (L^T = Ackermann(A^T, C^T, alpha))
  assumes: (A, C) observable
```

In the worked example, A = [0 1; 0 0], C = [1, 0], alpha = [1, 10, 25] go through the equation above and give L = [10, 25]. It applies only when (A, C) observable: outside that it says what is wrong instead of returning a number.

Pole placement by Ackermann's formula — `ctrl_ackermann`

The state-feedback gain K that gives A - B K the desired characteristic polynomial alpha(s) (single input), computed exactly.

$$K = [0 \quad \cdots \quad 0 \quad 1]\mathcal{C}^{-1}\alpha(A)$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector	—
`alpha`	in	desired characteristic polynomial (n+1 coefficients, highest power first)	—
`K`	out	state-feedback gain (row)	—

Applies when: (A, B) controllable.

```
$ control-systems solve ctrl_ackermann "A=[[0, 1], [0, 0]]" "B=[0, 1]" "alpha=[1, 4, 4]"
K = [4.0,4.0]
  by: Pole placement by Ackermann's formula  (K = [0 ... 0 1] Wc^{-1} alpha(A) in exact fractions)
  assumes: (A, B) controllable
```

In the worked example, A = [0 1; 0 0], B = [0, 1], alpha = [1, 4, 4] go through the equation above and give K = [4, 4]. It applies only when (A, B) controllable: outside that it says what is wrong instead of returning a number.

State response to an initial state and a constant input — `ctrl_ss_response`

x(t) = e^{At} x(0) + (integral of e^{A tau} d tau) B u for x' = A x + B u with a constant input u.

$$x(t) = e^{At}x_0 + \int_0^t e^{A\tau}d\tau\, Bu$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector	—
`x0`	in	initial state	—
`u`	in	constant input	—
`t`	in	time in seconds	—
`x`	out	state at time t	—

Applies when: |A| t <= 40; t >= 0.

```
$ control-systems solve ctrl_ss_response "A=[[0, 1], [0, 0]]" "B=[0, 1]" "x0=[0, 0]" u=2 t=3
x = [9.0,6.0]
  by: State response to an initial state and a constant input  (exponential of the augmented matrix
[[A, B u], [0, 0]] t)
  u = 2
  t = 3
  assumes: |A| t <= 40; t >= 0
```

In the worked example, A = [0 1; 0 0], B = [0, 1], x0 = [0, 0], u = 2, t = 3 go through the equation above and give x = [9, 6]. It applies only when |A| t <= 40; t >= 0: outside that it says what is wrong instead of returning a number.

State-transition matrix e^{At} — `ctrl_state_transition`

The state-transition matrix Phi(t) = e^{At} that maps x(0) to x(t) for x' = A x.

$$\Phi(t) = e^{At} = \sum_k \frac{(At)^k}{k!}$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`t`	in	time in seconds	—
`Phi`	out	state-transition matrix	—

Applies when: |A| t <= 40.

```
$ control-systems solve ctrl_state_transition "A=[[0, 1], [0, 0]]" t=2
Phi = [[1.0,2.0],[0.0,1.0]]
  by: State-transition matrix e^{At}  (scaling and squaring with a Taylor series)
  t = 2
  assumes: |A| t <= 40
```

In the worked example, A = [0 1; 0 0], t = 2 go through the equation above and give Phi = [[1, 2], [0, 1]]. It applies only when |A| t <= 40: outside that it says what is wrong instead of returning a number.

Transfer function of a state-space model — `ctrl_ss_to_tf`

G(s) = C (sI - A)^{-1} B + D of a single-input single-output state-space model, computed exactly (Faddeev-LeVerrier).

$$G(s) = C(sI - A)^{-1}B + D = \frac{C\,\mathrm{adj}(sI - A)\,B}{\det(sI - A)} + D$$

symbol		meaning	SI unit
`A`	in	state matrix (n x n)	—
`B`	in	input vector (column, n entries)	—
`C`	in	output vector (row, n entries)	—
`D`	in	feedthrough (default 0) (optional)	—
`num`	out	numerator (n+1 coefficients, highest power first)	—
`den`	out	characteristic polynomial (monic)	—

Applies when: A square, at most 6 x 6.

```
$ control-systems solve ctrl_ss_to_tf "A=[[0, 1], [-2, -3]]" "B=[0, 1]" "C=[1, 0]"
num = [0.0,0.0,1.0]
den = [1.0,3.0,2.0]
  by: Transfer function of a state-space model  (Faddeev-LeVerrier in exact fractions)
  assumes: A square, at most 6 x 6
```

In the worked example, A = [0 1; -2 -3], B = [0, 1], C = [1, 0] go through the equation above and give num = [0, 0, 1], den = [1, 3, 2]. It applies only when A square, at most 6 x 6: outside that it says what is wrong instead of returning a number.

Steady-state error (1)

System type, static error constant and steady-state error — `ctrl_error_constants`

For unity feedback around G(s): the system type N (poles at the origin), the static error constant lim s^N G(s) (Kp, Kv or Ka) and the steady-state error to a step, ramp or parabola of size A.

$$e_{ss} = \frac{A}{1 + K_p},\ \frac{A}{K_v},\ \frac{A}{K_a}$$

symbol		meaning	SI unit
`num`	in	numerator of the open-loop G(s)	—
`den`	in	denominator of G(s)	—
`input`	in	test input	—
`A`	in	input size (default 1) (optional)	—
`system_type`	out	system type N	—
`K_static`	out	static error constant of type N (Kp if 0, Kv if 1, Ka if 2)	—
`ess`	out	steady-state error	—

Applies when: closed loop stable; proper G(s); type at least the input's order.

```
$ control-systems solve ctrl_error_constants "num=[10]" "den=[1, 3, 2]" input=step
system_type = 0
K_static = 5
ess = 0.1666666667
  by: System type, static error constant and steady-state error  (ess = A/(1 + Kp) (step, type 0),
A/Kv (ramp, type 1), A/Ka (parabola, type 2), 0 for a higher type)
  input = step
  assumes: closed loop stable; proper G(s); type at least the input's order
```

In the worked example, num = [10], den = [1, 3, 2], input = step go through the equation above and give system_type = 0, K_static = 5, ess = 0.1666666667. It applies only when closed loop stable; proper G(s); type at least the input's order: outside that it says what is wrong instead of returning a number.

Time delay (1)

Pade approximation of a time delay — `ctrl_pade`

The (n, n) Pade approximation of e^{-theta s} as a rational transfer function (denominator's leading coefficient 1).

$$e^{-\theta s} \approx \frac{\sum_k c_k (-\theta s)^k}{\sum_k c_k (\theta s)^k}$$

symbol		meaning	SI unit
`theta`	in	time delay in seconds	—
`n`	in	approximation order (1 to 6)	—
`num`	out	numerator coefficients	—
`den`	out	denominator coefficients (leading 1)	—

Applies when: theta > 0; 1 <= n <= 6.

```
$ control-systems solve ctrl_pade theta=2 n=1
num = [-1.0,1.0]
den = [1.0,1.0]
  by: Pade approximation of a time delay  (Pade coefficients c_k = (2n-k)! n! / ((2n)! k! (n-k)!))
  theta = 2
  assumes: theta > 0; 1 <= n <= 6
```

In the worked example, theta = 2, n = 1 go through the equation above and give num = [-1, 1], den = [1, 1]. It applies only when theta > 0; 1 <= n <= 6: outside that it says what is wrong instead of returning a number.

Time response (17)

Damping ratio from percent overshoot — `ctrl_damping_from_overshoot`

The damping ratio zeta = -ln(OS)/sqrt(pi^2 + ln^2 OS) that gives a stated overshoot.

$$\zeta = \frac{-\ln(\%OS/100)}{\sqrt{\pi^2 + \ln^2(\%OS/100)}}$$

symbol		meaning	SI unit
`OS`	in	overshoot (write 20% or 0.2)	—
`zeta`	out	damping ratio	—
`pole_angle_deg`	out	pole angle from the negative real axis, degrees	—

Applies when: 0 < OS < 100 %.

```
$ control-systems solve ctrl_damping_from_overshoot OS=0.2
zeta = 0.4559498108
pole_angle_deg = 62.87393661
  by: Damping ratio from percent overshoot  (invert OS = exp(-zeta pi / sqrt(1 - zeta^2)))
  OS = 0.2
  assumes: 0 < OS < 100 %
```

In the worked example, OS = 0.2 go through the equation above and give zeta = 0.4559498108, pole_angle_deg = 62.87393661. It applies only when 0 < OS < 100 %: outside that it says what is wrong instead of returning a number.

Exact settling time of a second-order step response — `ctrl_true_settling_time`

The last time at which the unit step response of wn^2/(s^2 + 2 zeta wn s + wn^2) leaves the band |y - 1| = band (not the envelope estimate), and which extremum precedes it.

$$T_s = \max\{t : |y(t) - 1| = \text{band}\}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 < zeta < 1)	—
`wn`	in	natural frequency in rad/s	—

symbol		meaning	SI unit
`band`	in	settling band (default 2%) (optional)	—
`Ts`	out	exact settling time	s
`last_extremum`	out	index k of the last extremum outside the band (0 = before the first peak)	—

Applies when: 0 < zeta < 1; 0 < band < 50 %.

```
$ control-systems solve ctrl_true_settling_time zeta=0.5 wn=1
Ts = 8.076348974 s
last_extremum = 2
  by: Exact settling time of a second-order step response  (extrema at k pi/wd; the last band
crossing lies between the last extremum outside the band and the next zero of y - 1 (bisection))
  zeta = 0.5
  wn = 1
  assumes: 0 < zeta < 1; 0 < band < 50 %
```

In the worked example, zeta = 0.5, wn = 1 go through the equation above and give Ts = 8.076348974 s, last_extremum = 2. It applies only when 0 < zeta < 1; 0 < band < 50 %: outside that it says what is wrong instead of returning a number.

Final value theorem — `ctrl_final_value_theorem`

lim_{t->inf} y(t) = lim_{s->0} s Y(s) for Y(s) = num/den, after checking that s Y(s) has every pole in the open left half plane.

$$y(\infty) = \lim_{s \to 0} sY(s)$$

symbol		meaning	SI unit
`num`	in	numerator of Y(s)	—
`den`	in	denominator of Y(s)	—
`final_value`	out	final value of y(t)	—

Applies when: at most one pole at the origin; all other poles in the open left half plane.

```
$ control-systems solve ctrl_final_value_theorem "num=[10]" "den=[1, 3, 2, 0]"
final_value = 5
  by: Final value theorem  (cancel factors s, then evaluate s Y(s) at s = 0)
  assumes: at most one pole at the origin; all other poles in the open left half plane
```

In the worked example, num = [10], den = [1, 3, 2, 0] go through the equation above and give final_value = 5. It applies only when at most one pole at the origin; all other poles in the open left half plane: outside that it says what is wrong instead of returning a number.

Initial value theorem (value and slope at t = 0+) — `ctrl_initial_value_theorem`

y(0+) = lim_{s->inf} s Y(s) and y'(0+) = lim_{s->inf} s (s Y(s) - y(0+)) for a strictly proper Y(s).

$$y(0^+) = \lim_{s \to \infty} sY(s)$$

symbol		meaning	SI unit
`num`	in	numerator of Y(s)	—
`den`	in	denominator of Y(s)	—
`y0`	out	initial value y(0+)	—
`dy0`	out	initial slope y'(0+)	—

Applies when: Y(s) strictly proper.

```
$ control-systems solve ctrl_initial_value_theorem "num=[2, 3]" "den=[1, 5, 6]"
y0 = 2
dy0 = -7
  by: Initial value theorem (value and slope at t = 0+)  (long division of num by den in powers of
1/s)
  assumes: Y(s) strictly proper
```

In the worked example, num = [2, 3], den = [1, 5, 6] go through the equation above and give y0 = 2, dy0 = -7. It applies only when Y(s) strictly proper: outside that it says what is wrong instead of returning a number.

Mass-spring-damper natural frequency and damping ratio — `ctrl_mass_spring_damper`

Natural frequency sqrt(k/m), damping ratio c/(2 sqrt(k m)), damped frequency and static compliance 1/k of m x'' + c x' + k x = F.

$$\omega_n = \sqrt{k/m}, \quad \zeta = \frac{c}{2\sqrt{km}}$$

symbol		meaning	SI unit
`m`	in	mass in kg	—
`c`	in	damping coefficient in N*s/m	—
`k`	in	spring stiffness in N/m	—
`wn`	out	undamped natural frequency	rad/s
`zeta`	out	damping ratio	—
`wd`	out	damped natural frequency (0 when not underdamped)	rad/s
`dc_gain`	out	static gain x/F = 1/k in m/N	—
`damping`	out	damping class	—

Applies when: m > 0; c >= 0; k > 0.

```
$ control-systems solve ctrl_mass_spring_damper m=1 c=2 k=4
wn = 2 rad/s
zeta = 0.5
wd = 1.732050808 rad/s
dc_gain = 0.25
damping = underdamped
  by: Mass-spring-damper natural frequency and damping ratio  (G(s) = 1/(m s^2 + c s + k))
  m = 1
  c = 2
  k = 4
  assumes: m > 0; c >= 0; k > 0
```

In the worked example, m = 1, c = 2, k = 4 go through the equation above and give wn = 2 rad/s, zeta = 0.5, wd = 1.732050808 rad/s, dc_gain = 0.25. It applies only when m > 0; c >= 0; k > 0: outside that it says what is wrong instead of returning a number.

Natural frequency and damping ratio of a second-order denominator — `ctrl_second_order_params`

wn, zeta, the decay rate sigma = zeta wn, the damped frequency wd and the DC gain of K/(a2 s^2 + a1 s + a0).

$$s^2 + 2\zeta\omega_n s + \omega_n^2$$

symbol		meaning	SI unit
`den`	in	denominator [a2, a1, a0]	—
`K`	in	numerator constant (default: unit DC gain) (optional)	—
`wn`	out	natural frequency	rad/s
`zeta`	out	damping ratio	—
`sigma`	out	decay rate zeta wn (1/s)	—
`wd`	out	damped frequency (0 unless underdamped)	rad/s
`damping`	out	damping class	—
`dc_gain`	out	DC gain K/a0	—

Applies when: a0/a2 > 0; a1/a2 >= 0.

```
$ control-systems solve ctrl_second_order_params "den=[1, 4, 25]"
wn = 5 rad/s
zeta = 0.4
sigma = 2
wd = 4.582575695 rad/s
damping = underdamped
dc_gain = 1
  by: Natural frequency and damping ratio of a second-order denominator  (compare with s^2 + 2 zeta
wn s + wn^2)
  assumes: a0/a2 > 0; a1/a2 >= 0
```

In the worked example, den = [1, 4, 25] go through the equation above and give wn = 5 rad/s, zeta = 0.4, sigma = 2, wd = 4.582575695 rad/s. It applies only when a0/a2 > 0; a1/a2 >= 0: outside that it says what is wrong instead of returning a number.

Peak time of a second-order step response — `ctrl_peak_time`

Peak time Tp = pi/wd and damped frequency wd = wn sqrt(1 - zeta^2) of wn^2/(s^2 + 2 zeta wn s + wn^2).

$$T_p = \frac{\pi}{\omega_n \sqrt{1 - \zeta^2}}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 <= zeta < 1)	—
`wn`	in	natural frequency in rad/s	—
`Tp`	out	peak time	s
`wd`	out	damped frequency	rad/s

Applies when: 0 <= zeta < 1; wn > 0.

```
$ control-systems solve ctrl_peak_time zeta=0.6 wn=5
Tp = 0.7853981634 s
wd = 4 rad/s
  by: Peak time of a second-order step response  (first zero of the impulse response)
  zeta = 0.6
  wn = 5
  assumes: 0 <= zeta < 1; wn > 0
```

In the worked example, zeta = 0.6, wn = 5 go through the equation above and give Tp = 0.7853981634 s, wd = 4 rad/s. It applies only when 0 <= zeta < 1; wn > 0: outside that it says what is wrong instead of returning a number.

Percent overshoot from the damping ratio — `ctrl_percent_overshoot`

Percent overshoot 100 e^{-zeta pi/sqrt(1 - zeta^2)} of the step response of a standard second-order system, and the pole angle acos(zeta).

$$\%OS = 100\, e^{-\zeta\pi/\sqrt{1-\zeta^2}}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 <= zeta < 1)	—
`PO`	out	percent overshoot (%)	—
`Mp`	out	overshoot as a fraction of the final value	—
`pole_angle_deg`	out	angle of the poles from the negative real axis, degrees	—

Applies when: 0 <= zeta < 1.

```
$ control-systems solve ctrl_percent_overshoot zeta=0.5
PO = 16.30335348
Mp = 0.1630335348
pole_angle_deg = 60
  by: Percent overshoot from the damping ratio  (peak of the step response at t = pi/wd)
  zeta = 0.5
  assumes: 0 <= zeta < 1
```

In the worked example, zeta = 0.5 go through the equation above and give PO = 16.30335348, Mp = 0.1630335348, pole_angle_deg = 60. It applies only when 0 <= zeta < 1: outside that it says what is wrong instead of returning a number.

Proportional control of a first-order plant — `ctrl_closed_loop_first_order_p`

Closed-loop DC gain K Kp/(1 + K Kp), time constant tau/(1 + K Kp), steady-state error 1/(1 + K Kp) to a unit step and the closed-loop pole, for K/(tau s + 1) under unity feedback with gain Kp.

$$T(s) = \frac{KK_p}{\tau s + 1 + KK_p}$$

symbol		meaning	SI unit
`K`	in	plant DC gain	—
`tau`	in	plant time constant in seconds	—
`Kp`	in	proportional gain	—
`dc_gain_cl`	out	closed-loop DC gain	—
`tau_cl`	out	closed-loop time constant	s
`ess`	out	steady-state error to a unit step	—
`pole`	out	closed-loop pole (1/s)	—

Applies when: tau > 0; 1 + K Kp > 0.

```
$ control-systems solve ctrl_closed_loop_first_order_p K=2 tau=10 Kp=4.5
dc_gain_cl = 0.9
tau_cl = 1 s
ess = 0.1
pole = -1
  by: Proportional control of a first-order plant  (T(s) = K Kp/(tau s + 1 + K Kp))
  K = 2
  tau = 10
  Kp = 4.5
  assumes: tau > 0; 1 + K Kp > 0
```

In the worked example, K = 2, tau = 10, Kp = 4.5 go through the equation above and give dc_gain_cl = 0.9, tau_cl = 1 s, ess = 0.1, pole = -1. It applies only when tau > 0; 1 + K Kp > 0: outside that it says what is wrong instead of returning a number.

Rise time of an underdamped second-order system — `ctrl_rise_time_second`

The 0-100 % rise time (pi - acos zeta)/wd and the 10-90 % rise time (found exactly by bisection on the step response).

$$T_{r,0-100} = \frac{\pi - \cos^{-1}\zeta}{\omega_d}$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 < zeta < 1)	—
`wn`	in	natural frequency in rad/s	—
`Tr_0_100`	out	0-100 % rise time	s
`Tr_10_90`	out	10-90 % rise time	s
`t10`	out	time to 10 %	s
`t90`	out	time to 90 %	s

Applies when: 0 < zeta < 1; wn > 0.

```
$ control-systems solve ctrl_rise_time_second zeta=0.5 wn=1
Tr_0_100 = 2.418399152 s
Tr_10_90 = 1.637572947 s
t10 = 0.4882292958 s
t90 = 2.125802243 s
  by: Rise time of an underdamped second-order system  (closed form (0-100 %); bisection on y(t)
(10-90 %))
  zeta = 0.5
  wn = 1
  assumes: 0 < zeta < 1; wn > 0
```

In the worked example, zeta = 0.5, wn = 1 go through the equation above and give Tr_0_100 = 2.418399152 s, Tr_10_90 = 1.637572947 s, t10 = 0.4882292958 s, t90 = 2.125802243 s. It applies only when 0 < zeta < 1; wn > 0: outside that it says what is wrong instead of returning a number.

Second-order specifications from the pole location — `ctrl_second_order_from_poles`

From poles at -sigma +/- j wd: wn, zeta, peak time pi/wd, 2 % settling time 4/sigma and percent overshoot 100 e^{-sigma pi/wd}.

$$\omega_n = \sqrt{\sigma^2 + \omega_d^2}, \quad \zeta = \sigma/\omega_n, \quad \%OS = 100e^{-\sigma\pi/\omega_d}$$

symbol		meaning	SI unit
`sigma`	in	decay rate: the poles' real part is -sigma (sigma > 0)	—
`wd`	in	imaginary part of the poles (rad/s)	—
`wn`	out	natural frequency	rad/s
`zeta`	out	damping ratio	—
`Tp`	out	peak time	s
`Ts`	out	2 % settling time 4/sigma	s
`PO`	out	percent overshoot (%)	—

Applies when: sigma > 0; wd > 0.

```
$ control-systems solve ctrl_second_order_from_poles sigma=3 wd=4
wn = 5 rad/s
zeta = 0.6
Tp = 0.7853981634 s
Ts = 1.333333333 s
PO = 9.478022484
  by: Second-order specifications from the pole location  (wn = |p|, zeta = sigma/wn)
  sigma = 3
  wd = 4
  assumes: sigma > 0; wd > 0
```

In the worked example, sigma = 3, wd = 4 go through the equation above and give wn = 5 rad/s, zeta = 0.6, Tp = 0.7853981634 s, Ts = 1.333333333 s. It applies only when sigma > 0; wd > 0: outside that it says what is wrong instead of returning a number.

Settling time of a second-order system (rule and envelope) — `ctrl_settling_time`

Settling time by the rule 4/(zeta wn) (2 % band) or 3/(zeta wn) (5 %), and the time at which the decay envelope enters the band.

$$T_s \approx \frac{4}{\zeta \omega_n}\ (2\%), \qquad T_s \approx \frac{3}{\zeta \omega_n}\ (5\%)$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (0 < zeta < 1)	—
`wn`	in	natural frequency in rad/s	—
`band`	in	settling band: 2% (default) or 5% (optional)	—
`Ts`	out	settling time by the rule of thumb	s
`Ts_envelope`	out	time at which e^{-zeta wn t}/sqrt(1-zeta^2) equals the band	s
`time_constant`	out	envelope time constant 1/(zeta wn)	s

Applies when: 0 < zeta < 1; band 2 % or 5 %.

```
$ control-systems solve ctrl_settling_time zeta=0.5 wn=4
Ts = 2 s
Ts_envelope = 2.027932021 s
time_constant = 0.5 s
  by: Settling time of a second-order system (rule and envelope)  (Ts = 4/(zeta wn) or 3/(zeta wn))
  zeta = 0.5
  wn = 4
  assumes: 0 < zeta < 1; band 2 % or 5 %
```

In the worked example, zeta = 0.5, wn = 4 go through the equation above and give Ts = 2 s, Ts_envelope = 2.027932021 s, time_constant = 0.5 s. It applies only when 0 < zeta < 1; band 2 % or 5 %: outside that it says what is wrong instead of returning a number.

Step response of a first-order system — `ctrl_first_order_step`

The output y(t) = K A (1 - e^{-t/tau}) of K/(tau s + 1) at time t after a step of size A, and the fraction of the final value reached.

$$y(t) = KA\left(1 - e^{-t/\tau}\right)$$

symbol		meaning	SI unit
`K`	in	steady-state (DC) gain of the system	—
`tau`	in	time constant in seconds	—
`t`	in	time after the step in seconds	—
`A`	in	step size (default 1) (optional)	—
`y`	out	output at time t	—
`fraction`	out	fraction of the final value reached, 1 - e^{-t/tau}	—
`y_final`	out	final value K A	—

Applies when: tau > 0; t >= 0; K and A not zero.

```
$ control-systems solve ctrl_first_order_step K=2 tau=5 t=5
y = 1.264241118
fraction = 0.6321205588
y_final = 2
  by: Step response of a first-order system  (y = K A (1 - exp(-t/tau)))
  K = 2
  tau = 5
  t = 5
  assumes: tau > 0; t >= 0; K and A not zero
```

In the worked example, K = 2, tau = 5, t = 5 go through the equation above and give y = 1.264241118, fraction = 0.6321205588, y_final = 2. It applies only when tau > 0; t >= 0; K and A not zero: outside that it says what is wrong instead of returning a number.

Step response of a first-order-plus-dead-time process — `ctrl_fopdt_step`

y(t) of K e^{-theta s}/(tau s + 1) after a step of size A: 0 before the dead time, K A (1 - e^{-(t - theta)/tau}) after it.

$$y(t) = KA\left(1 - e^{-(t-\theta)/\tau}\right)u(t-\theta)$$

symbol		meaning	SI unit
`K`	in	process gain	—
`tau`	in	time constant in seconds	—
`theta`	in	dead time in seconds	—
`t`	in	time in seconds	—
`A`	in	step size (default 1) (optional)	—
`y`	out	output at time t	—

Applies when: tau > 0; theta >= 0; t >= 0.

```
$ control-systems solve ctrl_fopdt_step K=2 tau=5 theta=1 t=6
y = 1.264241118
  by: Step response of a first-order-plus-dead-time process  (delayed first-order response)
  K = 2
  tau = 5
  theta = 1
  t = 6
  assumes: tau > 0; theta >= 0; t >= 0
```

In the worked example, K = 2, tau = 5, theta = 1, t = 6 go through the equation above and give y = 1.264241118. It applies only when tau > 0; theta >= 0; t >= 0: outside that it says what is wrong instead of returning a number.

Step response of a standard second-order system — `ctrl_second_order_step`

y(t) of K wn^2/(s^2 + 2 zeta wn s + wn^2) after a unit step, for underdamped, critically damped and overdamped systems, and the remaining error K - y.

$$y(t) = 1 - e^{-\zeta\omega_n t}\left(\cos\omega_d t + \frac{\zeta}{\sqrt{1-\zeta^2}}\sin\omega_d t\right)$$

symbol		meaning	SI unit
`zeta`	in	damping ratio (>= 0)	—
`wn`	in	natural frequency in rad/s	—
`t`	in	time in seconds	—
`K`	in	DC gain (default 1) (optional)	—
`y`	out	output at time t	—
`error`	out	K - y(t)	—

Applies when: zeta >= 0; wn > 0; t >= 0.

```
$ control-systems solve ctrl_second_order_step zeta=0.5 wn=2 t=1
y = 0.8494256349
error = 0.1505743651
  by: Step response of a standard second-order system  (closed-form step response for each damping
case)
  zeta = 0.5
  wn = 2
  t = 1
  assumes: zeta >= 0; wn > 0; t >= 0
```

In the worked example, zeta = 0.5, wn = 2, t = 1 go through the equation above and give y = 0.8494256349, error = 0.1505743651. It applies only when zeta >= 0; wn > 0; t >= 0: outside that it says what is wrong instead of returning a number.

Step response of a transfer function at a given time — `ctrl_step_response`

y(t) of any proper G(s) after a step of size A, computed exactly through the state-space matrix exponential.

$$y(t) = C \int_0^t e^{A\tau} d\tau \, B \, A_u + D A_u$$

symbol		meaning	SI unit
`num`	in	numerator	—
`den`	in	denominator	—
`t`	in	time in seconds	—
`A`	in	step size (default 1) (optional)	—
`y`	out	output at time t	—

Applies when: proper G(s); t >= 0.

```
$ control-systems solve ctrl_step_response "num=[1]" "den=[1, 1]" t=1
y = 0.6321205588
  by: Step response of a transfer function at a given time  (controllable canonical form;
exponential of [[A, B], [0, 0]] t)
  t = 1
  assumes: proper G(s); t >= 0
```

In the worked example, num = [1], den = [1, 1], t = 1 go through the equation above and give y = 0.6321205588. It applies only when proper G(s); t >= 0: outside that it says what is wrong instead of returning a number.

Time and frequency specifications of a first-order system — `ctrl_first_order_specs`

Time constant, 10-90 % rise time tau ln 9, 2 % and 5 % settling times tau ln 50 and tau ln 20, bandwidth 1/tau and DC gain of K/(tau s + 1).

$$t_r = \tau \ln 9, \quad t_{s,2\%} = \tau \ln 50, \quad \omega_B = 1/\tau$$

symbol		meaning	SI unit
`K`	in	steady-state (DC) gain	—
`tau`	in	time constant in seconds	—
`time_constant`	out	time constant (63.2 % of the final value)	s
`rise_time`	out	10-90 % rise time	s
`settling_time_2`	out	2 % settling time	s
`settling_time_5`	out	5 % settling time	s
`bandwidth`	out	-3 dB bandwidth	rad/s
`dc_gain`	out	DC gain	—

Applies when: tau > 0.

```
$ control-systems solve ctrl_first_order_specs K=3 tau=2
time_constant = 2 s
rise_time = 4.394449155 s
settling_time_2 = 7.824046011 s
settling_time_5 = 5.991464547 s
bandwidth = 0.5 rad/s
dc_gain = 3
  by: Time and frequency specifications of a first-order system  (exact crossing times of 1 - exp(-
t/tau))
  K = 3
  tau = 2
  assumes: tau > 0
```

In the worked example, K = 3, tau = 2 go through the equation above and give time_constant = 2 s, rise_time = 4.394449155 s, settling_time_2 = 7.824046011 s, settling_time_5 = 5.991464547 s. It applies only when tau > 0: outside that it says what is wrong instead of returning a number.

Transfer functions (6)

Closed-loop transfer function of a feedback loop — `ctrl_feedback_connection`

G/(1 + G H) for negative feedback (or G/(1 - G H) for positive feedback): numerator N_G D_H and denominator D_G D_H +/- N_G N_H.

$$T(s) = \frac{G}{1 + GH} = \frac{N_G D_H}{D_G D_H + N_G N_H}$$

symbol		meaning	SI unit
`num_g`	in	numerator of the forward path G	—
`den_g`	in	denominator of G	—
`num_h`	in	numerator of the feedback path H (default 1) (optional)	—
`den_h`	in	denominator of H (default 1) (optional)	—
`sign`	in	feedback sign (default negative) (optional)	—
`num`	out	closed-loop numerator	—
`den`	out	closed-loop denominator	—

```
$ control-systems solve ctrl_feedback_connection "num_g=[10]" "den_g=[1, 2, 0]"
num = [10.0]
den = [1.0,2.0,10.0]
  by: Closed-loop transfer function of a feedback loop  (T = N_G D_H / (D_G D_H + N_G N_H))
```

In the worked example, num_g = [10], den_g = [1, 2, 0] go through the equation above and give num = [10], den = [1, 2, 10].

DC gain and final value of a step response — `ctrl_dc_gain`

The DC gain G(0) of a stable transfer function and the final value G(0) A of its response to a step of size A.

$$y(\infty) = A\,G(0)$$

symbol		meaning	SI unit
`num`	in	numerator coefficients, highest power of s first	—
`den`	in	denominator coefficients, highest power of s first	—
`A`	in	step size (default 1) (optional)	—
`dc_gain`	out	DC gain G(0)	—
`final_value`	out	final value of the step response	—

Applies when: proper G(s); every pole in the left half plane.

```
$ control-systems solve ctrl_dc_gain "num=[10]" "den=[1, 3, 2]"
dc_gain = 5
final_value = 5
  by: DC gain and final value of a step response  (G(0) = num(0)/den(0) after a stability check of
the poles)
  assumes: proper G(s); every pole in the left half plane
```

In the worked example, num = [10], den = [1, 3, 2] go through the equation above and give dc_gain = 5, final_value = 5. It applies only when proper G(s); every pole in the left half plane: outside that it says what is wrong instead of returning a number.

Parallel connection of two transfer functions — `ctrl_parallel_connection`

The transfer function G1 + G2 of two blocks in parallel: (N1 D2 + N2 D1)/(D1 D2).

$$G_1 + G_2 = \frac{N_1 D_2 + N_2 D_1}{D_1 D_2}$$

symbol		meaning	SI unit
`num1`	in	numerator of G1	—
`den1`	in	denominator of G1	—
`num2`	in	numerator of G2	—
`den2`	in	denominator of G2	—
`num`	out	numerator of G1 + G2	—
`den`	out	denominator of G1 + G2	—

```
$ control-systems solve ctrl_parallel_connection "num1=[1]" "den1=[1, 1]" "num2=[2]" "den2=[1, 3]"
num = [3.0,5.0]
den = [1.0,4.0,3.0]
  by: Parallel connection of two transfer functions  (N = N1 D2 + N2 D1, D = D1 D2)
```

In the worked example, num1 = [1], den1 = [1, 1], num2 = [2], den2 = [1, 3] go through the equation above and give num = [3, 5], den = [1, 4, 3].

Poles, zeros and gain of a transfer function — `ctrl_poles_zeros`

The zeros (roots of the numerator), the poles (roots of the denominator) and the zero-pole-gain constant k of G(s) = num/den.

$$G(s) = k\,\frac{\prod(s - z_i)}{\prod(s - p_j)}$$

symbol		meaning	SI unit
`num`	in	numerator coefficients, highest power of s first	—
`den`	in	denominator coefficients, highest power of s first	—
`zeros`	out	the zeros	—
`poles`	out	the poles	—
`gain`	out	gain k of the zero-pole-gain form (num[0]/den[0])	—

```
$ control-systems solve ctrl_poles_zeros "num=[1, 2]" "den=[1, 4, 3]"
zeros = [-2.0]
poles = [-3.0,-1.0]
gain = 1
  by: Poles, zeros and gain of a transfer function  (roots of both polynomials (Aberth-Ehrlich
iteration))
```

In the worked example, num = [1, 2], den = [1, 4, 3] go through the equation above and give zeros = [-2], poles = [-3, -1], gain = 1.

Series (cascade) connection of two transfer functions — `ctrl_series_connection`

The transfer function G1 G2 of two blocks in series: numerators multiplied, denominators multiplied (no cancellation).

$$G(s) = G_1(s)G_2(s) = \frac{N_1 N_2}{D_1 D_2}$$

symbol		meaning	SI unit
`num1`	in	numerator of G1	—
`den1`	in	denominator of G1	—
`num2`	in	numerator of G2	—
`den2`	in	denominator of G2	—
`num`	out	numerator of G1 G2	—
`den`	out	denominator of G1 G2	—

```
$ control-systems solve ctrl_series_connection "num1=[1]" "den1=[1, 1]" "num2=[2]" "den2=[1, 3]"
num = [2.0]
den = [1.0,4.0,3.0]
  by: Series (cascade) connection of two transfer functions  (polynomial multiplication)
```

In the worked example, num1 = [1], den1 = [1, 1], num2 = [2], den2 = [1, 3] go through the equation above and give num = [2], den = [1, 4, 3].

Value of a transfer function at a complex point — `ctrl_tf_evaluate`

G(s0) = num(s0)/den(s0) at s0 = s_re + j s_im: real and imaginary parts, magnitude and angle.

$$G(s_0) = \frac{N(s_0)}{D(s_0)}$$

symbol		meaning	SI unit
`num`	in	numerator coefficients	—
`den`	in	denominator coefficients	—
`s_re`	in	real part of s0	—
`s_im`	in	imaginary part of s0	—
`G_re`	out	real part of G(s0)	—
`G_im`	out	imaginary part of G(s0)	—
`magnitude`	out	|G(s0)|	—
`angle_deg`	out	angle of G(s0) in degrees, (-180, 180]	—

Applies when: s0 is not a pole.

```
$ control-systems solve ctrl_tf_evaluate "num=[1]" "den=[1, 1]" s_re=0 s_im=1
G_re = 0.5
G_im = -0.5
magnitude = 0.7071067812
angle_deg = -45
  by: Value of a transfer function at a complex point  (Horner evaluation in complex arithmetic)
  s_re = 0
  s_im = 1
  assumes: s0 is not a pole
```

In the worked example, num = [1], den = [1, 1], s_re = 0, s_im = 1 go through the equation above and give G_re = 0.5, G_im = -0.5, magnitude = 0.7071067812, angle_deg = -45. It applies only when s0 is not a pole: outside that it says what is wrong instead of returning a number.

Questions and reports: support@ai999x.com. AI999X — The Future Is Self-Improving.