

Nextion:

```
        //else if (TS_CMD_LOOPBACK0 <= commandType && commandType
<= TS_CMD_LOOPBACK5) //Loop back Channel 0 ~ 5 Loop back
Channel 1~5 : Reserve
        else if (TS_CMD_LOOPBACK0 == commandType) //Loop back
Channel 0 ~ 5
        {
            unsigned long tempCommand;
            tempCommand=
conv4BytesToLong(swr_buffer[commandStartIndex +
4],swr_buffer[commandStartIndex + 5],
                    swr_buffer[commandStartIndex +
6],swr_buffer[commandStartIndex + 7]);
            SendCommandUL('v',tempCommand); //Return data
            SendCommandUL('g',
commandType); //
Index Input
            //return;
        }
```

Command types:

```
#define CMD_NOW_DISP        '0' //c0
char L_nowdisp = -1;        //Sended nowdisp

#define CMD_VFO_TYPE        'v' //cv
char L_vfoActive;           //vfoActive

#define CMD_CURR_FREQ        'c' //vc
unsigned long L_vfoCurr;     //vfoA
#define CMD_CURR_MODE        'c' //cc
byte L_vfoCurr_mode;        //vfoA_mode

#define CMD_VFOA_FREQ        'a' //va
unsigned long L_vfoA;        //vfoA
#define CMD_VFOA_MODE        'a' //ca
byte L_vfoA_mode;           //vfoA_mode

#define CMD_VFOB_FREQ        'b' //vb
unsigned long L_vfoB;        //vfoB
#define CMD_VFOB_MODE        'b' //cb
byte L_vfoB_mode;           //vfoB_mode

#define CMD_IS_RIT          'r' //cr
char L_ritOn;
#define CMD_RIT_FREQ        'r' //vr
```

```

unsigned long L_ritTxFrequency; //ritTxFrequency

#define CMD_IS_TX          't' //ct
char L_inTx;

#define CMD_IS_DIALLOCK    'l' //cl
byte L_isDialLock;        //byte isDialLock

#define CMD_IS_SPLIT       's' //cs
byte L_Split;             //isTxType
#define CMD_IS_TXSTOP      'x' //cx
byte L_TXStop;            //isTxType //mjh This was assumed to
be zero by default??

#define CMD_TUNEINDEX      'n' //cn
byte L_tuneStepIndex;     //byte tuneStepIndex

#define CMD_SMETER         'p' //cs
byte L_scaledSMeter;      //scaledSMeter

#define CMD_SIDE_TONE      't' //vt
unsigned long L_sideTone; //sideTone
#define CMD_KEY_TYPE       'k' //ck
byte L_cwKeyType = -1;    //L_cwKeyType 0: straight, 1 :
iambica, 2: iambicb

#define CMD_CW_SPEED       's' //vs
unsigned int L_cwSpeed;   //cwSpeed

#define CMD_CW_DELAY       'y' //vy
byte L_cwDelayTime=-1;    //cwDelayTime

#define CMD_CW_STARTDELAY  'e' //ve
byte L_delayBeforeCWStartTime=-1; //byte delayBeforeCWStartTime

#define CMD_ATT_LEVEL      'f' //vf
byte L_attLevel;

byte L_isIFShift;         //1 = ifShift, 2 extend
#define CMD_IS_IFSHIFT     'i' //ci

int L_ifShiftValue;
#define CMD_IFSHIFT_VALUE  'i' //vi

byte L_sdrModeOn;
#define CMD_SDR_MODE       'j' //cj

```

```

#define CMD_UBITX_INFO      'm' //cm Complete Send uBITX
Information

//Once Send Data, When boot
//arTuneStep, When boot, once send
//long arTuneStep[5];
#define CMD_AR_TUNE1      '1' //v1
#define CMD_AR_TUNE2      '2' //v2
#define CMD_AR_TUNE3      '3' //v3
#define CMD_AR_TUNE4      '4' //v4
#define CMD_AR_TUNE5      '5' //v5

#define CMD_IS_CW_SHIFT_DISPLAY 'h' //ch
byte L_isShiftDisplayCWFreq; //byte isShiftDisplayCWFreq

#define CMD_CW_SHIFT_ADJUST      'h' //vh
int L_shiftDisplayAdjustVal; //int shiftDisplayAdjustVal

//0:CW Display Shift Confirm, 1 : IFshift save
#define CMD_COMM_OPTION      'o' //vo
byte L_commonOption0; //byte commonOption0

//0:Line Toggle, 1 : Always display Callsign, 2 : scroll
display, 3 : s.meter
#define CMD_DISP_OPTION1      'p' //vp
byte L_displayOption1; //byte displayOption1
#define CMD_DISP_OPTION2      'q' //vq
byte L_displayOption2; //byte displayOption2
(Reserve)

#define CMD_TEXT_LINE0      '0' //s0
#define CMD_TEXT_LINE1      '1' //s1

#define CMD_CW_TEXT      'a' //sa
#define CMD_CALLSIGN      'c' //sc
#define CMD_VERSION      'v' //sv

#define TS_CMD_MODE      1
#define TS_CMD_FREQ      2
#define TS_CMD_BAND      3
#define TS_CMD_VFO      4
#define TS_CMD_SPLIT      5
#define TS_CMD_RIT      6
#define TS_CMD_TXSTOP      7
#define TS_CMD_SDR      8
#define TS_CMD_LOCK      9 //Dial Lock

```

```

#define TS_CMD_ATT          10 //ATT
#define TS_CMD_IFS          11 //IFS Enabled
#define TS_CMD_IFSVALUE    12 //IFS VALUE
#define TS_CMD_STARTADC    13
#define TS_CMD_STOPADC     14
#define TS_CMD_SPECTRUMOPT 15 //Option for Spectrum
#define TS_CMD_SPECTRUM    16 //Get Spectrum Value
#define TS_CMD_TUNESTEP    17 //Get Spectrum Value
#define TS_CMD_WPM          18 //Set WPM
#define TS_CMD_KEYTYPE     19 //Set KeyType

#define TS_CMD_SWTRIG      21 //SW Action Trigger for WSPR and
more
#define TS_CMD_READMEM     31 //Read EEPROM
#define TS_CMD_WRITEMEM    32 //Write EEPROM
#define TS_CMD_LOOPBACK0   74 //Loopback1 (Response to
Loopback Channge)
#define TS_CMD_LOOPBACK1   75 //Loopback2 (Response to
Loopback Channge)
#define TS_CMD_LOOPBACK2   76 //Loopback3 (Response to
Loopback Channge)
#define TS_CMD_LOOPBACK3   77 //Loopback4 (Response to
Loopback Channge)
#define TS_CMD_LOOPBACK4   78 //Loopback5 (Response to
Loopback Channge)
#define TS_CMD_LOOPBACK5   79 //Loopback6 (Response to
Loopback Channge)
#define TS_CMD_FACTORYRESET 85 //Factory Reset
#define TS_CMD_UBITX_REBOOT 95 //Reboot

char nowdisp = 0;

#define SWS_HEADER_CHAR_TYPE 'c' //1Byte Protocol Prefix
#define SWS_HEADER_INT_TYPE  'v' //Numeric Protocol Prefex
#define SWS_HEADER_STR_TYPE  's' //for TEXT Line compatiabale
Character LCD Control

```