

//This code was adapted from the ChangeUID example code from the MFRC522 libraries.

```
#include <SPI.h>
#include <MFRC522.h>

#define RST_PIN    9
#define SS_PIN     10
const int buzzer = 4; //buzzer to arduino pin 4
MFRC522 mfrc522(SS_PIN, RST_PIN); // Create MFRC522 instance

MFRC522::MIFARE_Key key;

void setup() {
    // put your setup code here, to run once:
    Serial.begin(9600); // Initialize serial communications with the PC
    while (!Serial);    // Do nothing if no serial port is opened (added for
    Arduinos based on ATMEGA32U4)
    SPI.begin();        // Init SPI bus
    mfrc522.PCD_Init(); // Init MFRC522 card
    Serial.println(F("Warning: this example overwrites the UID of your UID
    changeable card, use with care!"));
}

void loop() {
    // put your main code here, to run repeatedly:

    // Look for new cards, and select one if present
    if ( ! mfrc522.PICC_IsNewCardPresent() || ! mfrc522.PICC_ReadCardSerial() ) {
        delay(1500);
        return;
    }

    // Now a card is selected. The UID and SAK is in mfrc522.uid.
    //Serial.print(F("Card UID:"));

    for (byte i = 0; i < mfrc522.uid.size; i++) {
        Serial.print(mfrc522.uid.uidByte[i] < 0x10 ? " 0" : " ");
        Serial.print(mfrc522.uid.uidByte[i], HEX);
    }

    tone(buzzer, 4000); // Send 1KHz sound signal...
    delay(100);        // ...for 1 sec
    noTone(buzzer);    // Stop sound...
    delay(100);        // ...for 1sec
    //Serial.println();
}
```