7. Monday Oct 26 - CSI's GB10, 12:30-2:00

Bring an exFAT USB labelled TTL: one Sunday-attested `ttl_gb10_*.tar`, its `.sha256`, five scripts, `monday_ops.py`, `monday.sha256`; allow several GB free. Bring printed staging/numbering sheets and paper logs. Confirm CSI's supervisor and capture route. Never change cameras, controls or network settings. Live rule B′ is DEV-fit; organizer permission remains required. Labels and paper logs stay on paper and go to the Mac.

1. 12:30-12:45 - Setup: `bash /media/$USER/TTL/start.sh` No prompts: USB and the single package are found automatically. If the mount differs, use `lsblk -o NAME,SIZE,MOUNTPOINT`, then type `bash <mount>/start.sh`. Expect checksums OK → PREFLIGHT OK → BOOTSTRAP OK → SETUP OK. Check the printed commit against Sunday's attestation. Repeating start with the same verified package resumes the visit without bootstrap: SETUP OK: resumed … (N staged, sealed yes/no). Missing/failed setup starts a new visit. A different package gives STOP; choose `bash /media/$USER/TTL/start.sh --new-visit` for an intentional new visit. Old visits are kept and exported. STOP: fix the reported checksum/mount problem before retrying. No successful preflight means no live run. Context survives a closed terminal.

2. Confirm delivery. Start staging before CSI's first save. CSI may use the same camera folder for staging and live, including one repeatedly rewritten filename. Supported sizes: 1920×1080 or 640×480. Ask CSI for supported captures; never resize, crop or re-aim.

3. 12:45-1:30 - Stage: `bash ~/ttl/stage.sh` Enter the camera folder once. At each setup: Enter after CSI saves; s skip; r retake the last setup after a new save; q done. Expect filename, size, SHA256 and `staged`/`skipped`/`retake`, ending STAGING OK. Retakes become `setup_NN_rK`; all attempts stay. Duplicate bytes or wrong sizes are REFUSED without advancing: ask for a new supported capture. STOP: preserve files and reconcile the reported problem before resuming. Record setup numbers, labels, tilt evidence and timing on paper.

4. 1:30-1:35 - Seal: `bash ~/ttl/seal.sh` Expect counts, final/earlier-attempt lists, checksum OK, then SEALED USB OK. Last attempt per setup is final. Zero captures prints WARNING and still seals. USB failure gives SEALED DISK OK; live is allowed, but export must back up the disk copy. STOP: reconcile log/files/hashes; never erase evidence. An already sealed visit refuses resealing or more staging. Reset the fixture before live.

5. 1:35-1:50 - Live: `bash ~/ttl/live.sh` Enter the camera folder (the staging camera folder is allowed) or approved RTSP/HTTP(S) URL. Enter = n (continuous camera feed); y only for stills CSI saves on request. Confirm fixture reset and cleared buffered staged frames. Expect new LIVE OUT, inspector/hash, `watching ...` for folders, then console grids. Existing files are ignored; CSI saves new live frames after `watching`. Staged/sealed copies and overlapping folders are refused. Never recopy staged captures into live. `??` means check by eye. STOP: correct the reported source/seal problem; restart into a new OUT.

6. 1:50 - Stop: Ctrl-C once. Expect frame/event summary and LIVE OK (`stop_reason: ctrl-c`). STOP: retain evidence and record the abnormal stop on paper. Log every restart/gap/intervention. CSI refuses live or there is no usable terminal: preserve captures; record staging-only, not a live demo.

7. 1:50-2:00 - Export: stop writers, restore USB, then `bash ~/ttl/export.sh`. Expect archive checksums OK → RESULTS USB OK: N visits verified; includes every retry and attempt. STOP: keep GB10 files and arrange CSI-assisted recovery. Re-verify on the Mac before removing anything. On the Mac: adjudicate paper labels without predictions, lock labels by SHA256, score each arm once (§5).

Cut optional live defects, then filming, then live duration; never labels or backups. Real camera streaming and capped 1080 performance remain unverified. Appendix A retains the long blocks for reference; these steps govern.