

USB-C Connector						
Source	Desig	Sig Name		Termination	Pin#	Comments
EGSE	A1	GND		PIU-J9	5,6,7,8,13	Ground return
EGSE	B12	GND		PIU-J9	5,6,7,8,13	Ground return
EGSE	A4	Batt+		PIU-J9	1,2,3,4	Batt+: : 2A max
EGSE	B9	Batt+		PIU-J9	1,2,3,4	Batt+: : 2A max
EGSE	A5	UART_RX		PIU-J9	9	these UART signals to to the CSKB for i/f to IHU
EGSE	B8	UART_TX		PIU-J9	10	these UART signals to to the CSKB for i/f to IHU
EGSE	A6	ENA_A		PSA-J8	4	from J8, goes to K1 p3
EGSE	B7	ENA_B		PSA-J8	10	from J8, goes to K1 p10
EGSE	A7	ENA_B		PSA-J8	10	from J8, goes to K1 p10
EGSE	B6	ENA_A		PSA-J8	4	from J8, goes to K1 p3
EGSE	A8	UART_TX		PIU-J9	10	these UART signals to to the CSKB for i/f to IHU
EGSE	B5	UART_RX		PIU-J9	9	these UART signals to to the CSKB for i/f to IHU
EGSE	A9	Batt+		PIU-J9	1,2,3,4	Batt+: : 2A max
EGSE	B4	Batt+		PIU-J9	1,2,3,4	Batt+: : 2A max
EGSE	A12	GND		PIU-J9	5,6,7,8,13	Ground return
EGSE	B1	GND		PIU-J9	5,6,7,8,13	Ground return

Notes:

- 1) EGSE to USB-C is a DB-25 to USB-C connector.
- 2) PIU -J8 and J9 are ISISpace Molex connectors. See ISIS-ICEPS2-ICD Tables 4-4 & 4-5
- 3) PSA-J8 is currently a Harwin M80 connector. This may change.

Source	Desig	Sig Name		Termination	Pin#	Comments
PSA	J8 – 8	ENAOOUT_A		PIU-J10	4	Active low. GND to activate
PSA	J8 – 9	ENAOOUT_B		PIU-J10	6	Active low. GND to activate
PSA	J8 – 3	Sep Sw A		Sep Sw A	-	Sep Switch on frame
PSA	J8 – 5	Sep Sw B		Sep Sw B	-	Sep Switch on frame