Calibration Loal Cell Amplifier for Winder

1 . Press the key until PASS appears .

2. Enter password “ 1111” using and keys , then key .

3. keep pressing the key until CALL (Cal low) appears.

4. press the key and check that the program light flashes . *
* IMPORTANT NOTE : Always ensure that the programmer indicator flashes, even though the displayed value may not need to change .

5. Check that the displayed value agrees with the low calibration weight applied to the Strain Gauge (this may be zero) .

6. If this is not correct , alter the display value by pressing the and keys.

7. Ensure that the Strain Gauge is free from disturbance and press the key to capture and calibrate the CALL value.
8. CALH (Cal High) now appear on the display.

9. Press the key and check that the program light flashes.
10. Apply the known higher value weight.
11. Check that the displayed value agrees with the high calibration weight applied to the Strain Gauge.

12. If this is not correct , alter the display value by pressing the and keys .

13. Ensure that the Strain Gauge is free from disturbance and press the key. The display will now indicate the Strain Gauge auto calibrated high value.

14. Hardware setup. SW1 mV/V : 4, 6 = ON. For 2.5 mV/V For Test one Load Cell
: 6 = ON. For 10 mV/V For Field W/Four Load Cells
15. Check All of parameters for Amplifier Load cell model number : LCA 15 .
15.1 PASS : 1111
15.2 SP1 :0
15.3 IF1 :0
15.4 SP2 :0
15.5 IF1 :0
15.6 HYS:0
15.7 OA :0
15.8 CALL :0 Calibration
15.9 CALH : 200 lb Calibration
15.10 At : 0
15.11 dA : 0
15.12 OPL :0
15.13 OPH :1000
15.14 dP : 4