


ETCH sAo SKETCH – OLED VERSION



SAO PORT (6-pin, 2x3, 0.1 inch spacing, male pins)
<https://hackaday.io/project/175182-simple-add-ons-sao>
 Adam Tech BHR-06-VUA male, polarized header
<https://www.digikey.com/en/products/detail/adam-tech/BHR-06-VUA/10414837>

OLED DISPLAY (Address 0x3C, 128 x 128 pixel, 1.5 inch, 16 shade grayscale, SSD1327 controller)
<https://learn.adafruit.com/adafruit-grayscale-1-5-128x128-oled-display>
 Optional address 0x3D selectable by moving resistor in upper left on the back of the blue OLED board.

ACCELEROMETER (Address 0x19, STM LIS3DHTR, 3-axis)
<https://learn.sparkfun.com/tutorials/lis3dh-hookup-guide/all>
 CS is high for I2C mode.
 ADC effective input range is 0.8 to 1.6 V (aka 1.2 +/- .4)
 ADC 1 and 2 used for potentiometers. ADC3 for internal temperature.
 Optional address 0x18 if R3 (SAO high) is moved to R4 position (SAO low).

OPTIONAL JP3 & JP4 CONFIG
 Solder pads 1-2 to connect accelerometer interrupt output pins to SAO GPIO 1&2.
 Solder pads 2-3 to connect analog potentiometer outputs to SAO GPIO 1&2

POTENTIOMETERS/ANALOG KNOBS (Accessed through accelerometer)
 Left pot connected to accelerometer input ADC1.
 Right pot connected to accelerometer input ADC2.

All non-polarized capacitors are X7R or X5R ceramic unless otherwise noted.

<https://hackaday.io/project/197581-etch-sao-sketch>

Concept and design by Andy Geppert © www.MachineIdeas.com

Sheet: /

File: Etch_sAo_Sketch.kicad_sch

Title: Etch sAo Sketch – OLED Version

Size: A Date: 2024-11-18

Rev: 1.1

KiCad E.D.A. 8.0.4

Id: 1/1