Type text to search here...

Home > EtherChannel Quiz

EtherChannel Quiz

Go to comments

Result of EtherChannel Quiz:

Total Questions	Full Score	Passing Rate	Your Score	Correct Answer Percentage	Elapsed
5	80	80%	80	100%	00:02:09

Congratulations!

You passed this test!

If you want to retake this quiz, please press Ctrl + F5 on Windows or press CMD + R on Mac.

Your answers are shown below:

Question 1

Refer to the exhibit.

```
Switch#show etherchannel summary
<output omitted>

Group  Port-channel  Protocol    Ports
------+-------------+---------+------
10     Po10(SU)        LACP      Gi0/0(P)   Gi0/1(P)
20     Po20(SU)        LACP      Gi0/2(P)   Gi0/3(P)
```

Which two commands were used to create port channel 10? (Choose two)

- A. interface range g0/0-1
  channel-group 10 mode on
- **B. interface range g0/0-1**
  channel-group 10 mode active
- C. interface range g0/0-1
  channel-group 10 mode auto
- **D. interface range g0/0-1**
  channel-group 10 mode passive
- E. interface range g0/0-1
  channel-group 10 mode desirable

Question 2

Refer to the exhibit. Based on the LACP neighbor status, in which mode is the SW1 port channel configured?

```
SW1# show lacp neighbor
Flags:  S - Device is sending Slow LACPDUs
        F - Device is sending Fast LACPDUs
        A - Device is in Active mode
        P - Device is in Passive mode

Channel group 31 neighbors

Partner's information:

              LaCP port                    Admin  Oper  Port    Port
Port  Flags   Priority  Dev ID         Age  key    Key   Number  State
Et1/0 SP      32768     aabb.cc40.4000  6s  0x0    0x23  0x101   0x3C
Et1/1 SP      32768     aabb.cc50.4000  6s  0x0    0x23  0x101   0x3C
```

- **A. active**
- B. mode on
- C. auto
- D. passive

Explanation

From the neighbor status, we notice the "Flags" are SP. "P" here means the neighbor is in Passive mode. In order to create an Etherchannel interface, the (local) SW1 ports should be in Active mode. Moreover, the "Port State" in the exhibit is "0x3c" (which equals to "00111100″ in binary format). Bit 3 is "1" which means the ports are synchronizing -> the ports are working so the local ports should be in Active mode.

Reference:
https://www.cisco.com/c/en/us/td/docs/switches/lan/catalyst3650/software/release/3se/consolidated_guide/comn

Question 3

Which two command sequences must you configure on a switch to establish a Layer 3 EtherChannel with an open-standard protocol? (Choose two)

- A. interface GigabitEthernet0/0/1
  channel-group 10 mode auto
- B. interface port-channel 10
  switchport
  switchport mode trunk
- **C. interface GigabitEthernet0/0/1**
  channel-group 10 mode active
- **D. interface port-channel 10**
  no switchport
  ip address 172.16.0.1 255.255.255.0
- E. interface GigabitEthernet0/0/1
  channel-group 10 mode on

Explanation

In order to configure a Layer 3 EtherChannel, we must use the "no switchport" command and set the IP address on the (logical) port-channel interface. For open-standard EtherChannel protocol we must use LACP with "passive" & "active" mode.

Question 4

Which mode must be used to configure EtherChannel between two switches without using a negotiation protocol?

- A. active
- B. auto
- C. desirable
- **D. on**

Explanation

The Static Persistence (or “on” mode) bundles the links unconditionally and no negotiation protocol is used. In this mode, neither PAgP nor LACP packets are sent or received.

Question 5

Which two statements about EtherChannel technology are true? (Choose two)

- A. EtherChannel does not allow load sharing of traffic among the physical links within the EtherChannel
- **B. EtherChannel provides increased bandwidth by bundling existing FastEthernet or Gigabit Ethernet interfaces into a single EtherChannel**
- C. STP does not block EtherChannel links
- D. You can configure multiple EtherChannel links between two switches, using up to a limit of sixteen physical ports
- **E. EtherChannel allows redundancy in case one or more links in the EtherChannel fail**

Explanation

In fact answer 'STP does not block EtherChannel links' is also correct as STP considers Etherchannel links as one physical link so this question should have three correct answers. But answer 'STP does not block EtherChannel links' is not as obvious as the other two answers so we should choose them.

Answer "You can configure multiple EtherChannel links between two switches, using up to a limit of sixteen physical ports" is not correct as "Commonly up to 16 links can be assigned to an EtherChannel, but only 8 can be active at a time".

Reference: https://www.ciscopress.com/articles/article.asp?p=2348266&seqNum=3

So it should be 8 physical ports, not 16.

Comments (15) Comments

1. anonymous1
   May 25th, 2021

   for the question that asks “which two commands were used to create port channel 10”

   it says the answers are “mode passive” and “mode active.” Is this because they’re the only commands that directly relate to LACP, and thats the type of etherchannel being used, or what? Because it doesnt make sense that those commands would be used back to back.

2. anon
   May 28th, 2021

   @anonymous1
   Remember Cisco use desirable for their auto-negotiation. In this case for PagP they use Auto/desirable.

   LACP (Which is what is being used as per the output) uses passive/active. You would use one or the other.

3. Bogdan
   July 8th, 2021

   @anynimous

   An Etherchanel is 2 or more aggregated links between 2 switches. Command ” interface range g0/0-1 channel-group 10 mode passive” is applied on one switch, while “interface range g0/0-1 channel-group 10 mode active” is applied on the other switch. Hope it helps

4. Jacob B
   February 26th, 2022

   Done

5. Jose
   October 1st, 2023

   About explanation question 5. If you create a Etherchanel and use all his bandwidth where are the redundancy? Im not agree whith: EtherChannel allows redundancy in case one or more links in the EtherChannel fail

6. zxcv lee
   January 8th, 2024

   @9tut
   Question 4 option E. EtherChannel provides increased bandwidth by bundling existing FastEthernet or Gigabit Ethernet interfaces into a single EtherChannel

   suggests we can bundle fast ethernet and gigabit ethernet ports together to form a single etherchannel, which is not allowed.

7. hunterno
   May 12th, 2024

   Why is option C in question 3 wrong ?

   C. You can configure multiple EtherChannel links between two switches, using up to a limit of sixteen physical ports

   @9tut

8. 9tut
   May 13th, 2024

   @hunterno: That answer is not correct.
   “Commonly up to 16 links can be assigned to an EtherChannel, but only 8 can be active at a time”
   Reference: https://www.ciscopress.com/articles/article.asp?p=2348266&seqNum=3
   so it should be 8 physical ports, not 16.

9. CCNP in progress
   June 19th, 2024

In question 2, it should not just limit FE and GE as simple Ethernet speed can also be use to establish etherchannel right?

@9tut

10. 9tut
June 20th, 2024

@CCNP in progress: All interfaces in each EtherChannel must be the same speed so we cannot group different types of Ethernet into one bundle.

11. Yoni
June 25th, 2024

in question 3,i dont understand why option d correct

redundancy hapen’s also when i’m not using ether channel

12. AS
November 2nd, 2024

Answer format missing carriage returns:

Which two command sequences must you configure on a switch to establish a Layer 3 EtherChannel with an open-standard protocol? (Choose two)

E. interface port-channel 10 no switchport ip address 172.16.0.1 255.255.255.0

better put:
E. interface port-channel 10
no switchport
ip address 172.16.0.1 255.255.255.0

13. 9tut
November 2nd, 2024

@AS: Thank you for your detection, we updated it!

14. Anonymous
December 13th, 2024

>C. EtherChannel provides increased bandwidth by bundling existing FastEthernet or Gigabit Ethernet interfaces into a single EtherChannel

This answer is incorrect, all links need to be the same speed – so it will degrade Gigabit interfaces to 100 mbps and with a maximum of 8 links, it will actually have less bandwidth

15. Genwin
November 10th, 2025

I think the confusion in “EtherChannel provides increased bandwidth by bundling existing FastEthernet or Gigabit Ethernet interfaces into a single EtherChannel” is the conjunction or. If it says FE AND GE into a single ether channel then that is incorrect. Since it says FE OR GE then it is correct.

Add a Comment

Name

Submit Comment

Subscribe to comments feed

IP Address & Subnetting Quiz STP & VTP Quiz

Premium Member Zone

Welcome Darène MAYISSA!

- Welcome Premium Member!
- CCNA - New Questions Part 5
- CCNA - New Questions Part 6
- CCNA - New Questions Part 7
- CCNA - New Questions Part 8
- CCNA - New Questions Part 9
- CCNA - New Questions Part 10
- CCNA - New Questions Part 11
- CCNA - New Questions Part 12
- CCNA - New Questions Part 13
- CCNA - New Questions Part 14
- CCNA - New Questions Part 15
- CCNA - New Questions Part 16
- Composite Quizzes
- === New CCNA v1.1 Lab Sims (very important) ===
- Voice VLAN Configuration Sim 2
- Voice VLAN & LLDP Sim
- Allowed, Native VLAN & LACP Sim
- Static Routing Configuration Sim 4
- IPv4 and IPv6 Connectivity Sim
- VLAN & CDP Sim 2
- IPv4 and IPv6 Assignment Sim
- VLAN CDP & LLDP Sim
- OSPF Configuration Sim 2
- OSPF Configuration Sim 3
- Trunking & LACP Sim
- VLAN Configuration Sim
- Allowed, Native VLAN & LACP Sim 2
- 802.1Q Trunking & LACP
- IPv4 and IPv6 Assignment Sim 2
- 802.1Q Trunking, Native VLAN & LACP
- Static Routing Configuration Sim 5
- Static Routing Configuration Sim 6
- PAT, NTP & DHCP Relay Sim
- OSPF DR Sim
- NACL DHCP Snooping 3
- NAT DHCP SSH Sim
- ==== Lab Sims for CCNA (although they are rather old but please learn all of them too) ====
- IP Services Sim Version 2
- OSPF Configuration Sim
- LACP Configuration Sim

- Voice VLAN Configuration Sim
- VLAN and Trunking Configuration Sim
- Named Access-list & Port Security Sim
- Named Access-list & DHCP Snooping Sim
- VLAN and CDP Sim
- IPv4 and IPv6 Deployment Sim
- Static Routing Configuration Sim 3
- VLAN & LLDP Sim
- IPv6 Static Routing Sim
- Named Access-list & DHCP Snooping Sim 2
- ISL Trunking and LACP Sim
- === Below Sims are old and retired so you do not need to learn them ===
- Static Routing Configuration Sim 2
- IP Services Sim
- Static Routing Configuration Sim

CCNA Training

- CCNA Knowledge
- CCNA Tutorials, Practice Labs & Lab Challenges
- Spine-Leaf Architecture Tutorial
- Generative AI vs Predictive AI Tutorial
- REST API Tutorial
- Network Time Protocol (NTP) Tutorial
- DHCP Snooping Tutorial
- What is SDN?
- How a router makes a forwarding decision
- Configure SSH for Remote Access on Cisco Router
- Key Security Concepts Tutorial
- Forwarding per-hop behavior (PHB) for QoS Tutorial
- Port Security Tutorial
- Puppet Tutorial
- Chef Tutorial
- Ansible Tutorial
- JSON Tutorial
- Layer 2 Threats and Security Features
- AAA TACACS+ and RADIUS Tutorial
- STP Root Port Election Tutorial
- TCP and UDP Tutorial
- WAN Tutorial
- DHCP Tutorial
- Simple Network Management Protocol SNMP Tutorial
- Syslog Tutorial
- EtherChannel Tutorial
- Hot Standby Router Protocol HSRP Tutorial
- InterVLAN Routing Tutorial
- Cisco Command Line Interface CLI
- Cisco Router Boot Sequence Tutorial
- OSI Model Tutorial
- Subnetting Tutorial – Subnetting Made Easy
- Frame Relay Tutorial
- Wireless Tutorial
- Virtual Local Area Network VLAN Tutorial
- VLAN Trunking Protocol VTP Tutorial
- IPv6 Tutorial
- Rapid Spanning Tree Protocol RSTP Tutorial
- Spanning Tree Protocol STP Tutorial

- Network Address Translation NAT Tutorial
- Access List Tutorial
- RIP Tutorial
- EIGRP Tutorial
- OSPF Tutorial
- Practice CCNA GNS3 Labs
- CCNA Lab Challenges

CCNA 200-301

- CCNA FAQs & Tips
- Basic Questions
- Topology Architecture Questions
- Cloud & Virtualization Questions
- CDP & LLDP Questions
- Switch Questions
- VLAN & Trunking Questions
- VLAN & Trunking Questions 2
- STP & VTP Questions
- EtherChannel Questions
- TCP & UDP Questions
- IP Address & Subnetting Questions
- IP Routing Questions
- IP Routing Questions 2
- OSPF Questions
- OSPF Questions 2
- EIGRP Questions
- NAT Questions
- NTP Questions
- Syslog Questions
- HSRP Questions
- Access-list Questions
- AAA Questions
- Security Questions
- Security Questions 2
- DAI Questions
- IPv6 Questions
- DNS Questions
- QoS Questions
- Port Security Questions
- Wireless Questions
- Wireless Questions 2
- SDN Questions
- DNA Center Questions
- Drag Drop Questions
- Drag Drop Questions 2
- Drag Drop Questions 3
- VPN Questions
- DHCP Questions
- Automation Questions
- Miscellaneous Questions
- Share your CCNA Experience

Network Resources

- Free Router Simulators
- CCNA Website
- ENCOR Website
- ENSDWI Website
- ENARSI Website
- DevNet Website
- CCIE R&S Website
- Security Website
- Wireless Website
- Design Website
- Data Center Website
- Service Provider Website
- Collaboration Website

Top



Copyright © 2014 - 2026 CCNA Training
Privacy Policy | Disclaimer | Contact Us