

Reference Language (//www.arduino.cc/en/Reference/HomePage) | Libraries
(//www.arduino.cc/en/Reference/Libraries) | Comparison
(//www.arduino.cc/en/Reference/Comparison) | Changes (//www.arduino.cc/en/Reference/Changes)

pinMode()

Description

Configures the specified pin to behave either as an input or an output. See the description of digital pins (//www.arduino.cc/en/Tutorial/DigitalPins) for details on the functionality of the pins.

As of Arduino 1.0.1, it is possible to enable the internal pullup resistors with the mode INPUT_PULLUP. Additionally, the INPUT mode explicitly disables the internal pullups.

Syntax

pinMode(pin, mode)

Parameters

pin: the number of the pin whose mode you wish to set

mode: INPUT (//www.arduino.cc/en/Reference/Constants), OUTPUT (//www.arduino.cc/en/Reference/Constants), or INPUT_PULLUP (//www.arduino.cc/en/Reference/Constants). (see the digital pins (//www.arduino.cc/en/Tutorial/DigitalPins) page for a more complete description of the functionality.)

Returns

None

Example

```
int ledPin = 13;                // LED connected to digital pin 13

void setup()
{
  pinMode(ledPin, OUTPUT);      // sets the digital pin as output
}

void loop()
{
  digitalWrite(ledPin, HIGH);   // sets the LED on
  delay(1000);                  // waits for a second
  digitalWrite(ledPin, LOW);    // sets the LED off
}
```

```
delay(1000);  
(https://www.arduino.cc)  
}
```

```
// waits for a second
```

[Get Code] (<https://www.arduino.cc/en/Reference/PinMode?action=sourceblock&num=1>)

Note **STORE** ([//STORE.ARDUINO.CC](https://store.arduino.cc)) **SOFTWARE** **EDUCATION** ([//WWW](https://www.arduino.cc)

The analog input pins can be used as digital pins, referred to as A0, A1, etc.

See also

- constants (<https://www.arduino.cc/en/Reference/Constants>)
- digitalWrite (<https://www.arduino.cc/en/Reference/DigitalWrite>())
- digitalRead (<https://www.arduino.cc/en/Reference/DigitalRead>())
- Tutorial: Description of the pins on an Arduino board (<https://www.arduino.cc/en/Tutorial/DigitalPins>)

Reference Home (<https://www.arduino.cc/en/Reference/HomePage>)

Corrections, suggestions, and new documentation should be posted to the Forum
(<http://arduino.cc/forum/index.php/board,23.0.html>).

The text of the Arduino reference is licensed under a Creative Commons Attribution-ShareAlike 3.0 License (<http://creativecommons.org/licenses/by-sa/3.0/>). Code samples in the reference are released into the public domain.

(<https://www.arduino.cc>).

NEWSLETTER

Enter your email to sign up for our newsletter:

[STORE \(//STORE.ARDUINO.CC\)](#) [SOFTWARE](#) [EDUCATION](#) [SUBSCRIBE](#) [/WWW](#)

Terms Of Service ([//www.arduino.cc/en/Main/TermsOfService](http://www.arduino.cc/en/Main/TermsOfService))

Privacy Policy ([//www.arduino.cc/en/Main/PrivacyPolicy](http://www.arduino.cc/en/Main/PrivacyPolicy))

Contact Us ([//www.arduino.cc/en/Main/ContactUs](http://www.arduino.cc/en/Main/ContactUs))

About Us ([//www.arduino.cc/en/Main/AboutUs](http://www.arduino.cc/en/Main/AboutUs))

Distributors ([//store.arduino.cc/distributors](http://store.arduino.cc/distributors))

Careers ([//careers.arduino.cc](http://careers.arduino.cc))

Security ([//www.arduino.cc/en/Main/Security](http://www.arduino.cc/en/Main/Security))

© 2020 Arduino ([//www.arduino.cc/en/Main/CopyrightNotice](http://www.arduino.cc/en/Main/CopyrightNotice))

(<https://www.kaggle.com/competitions/whodunnit>) (photo) / andeinar_dci) noteam)