

```
// Code for Smart Home //
```

```
// include the library code:  
#include <LiquidCrystal.h>
```

```
// initialize the library with the numbers of the interface pins  
LiquidCrystal lcd(12, 11, 5, 4, 3, 2);
```

```
//For ultrasound sensor  
int distanceThreshold = 0;  
int cm = 0;  
int inches = 0;
```

```
//for Relay Control  
int releNO = 13;  
int inputPir = 8;  
int val = 0;  
int resuldoSensorLDR;  
int sensorLDR = A0;
```

```
//For Gas sensor  
int const PINO_SGAS = A1;
```

```
long readUltrasonicDistance(int triggerPin, int echoPin)  
{  
    pinMode(triggerPin, OUTPUT); // Clear the trigger  
    digitalWrite(triggerPin, LOW);  
    delayMicroseconds(2);  
    // Sets the trigger pin to HIGH state for 10 microseconds  
    digitalWrite(triggerPin, HIGH);  
    delayMicroseconds(10);  
    digitalWrite(triggerPin, LOW);  
    pinMode(echoPin, INPUT);  
    // Reads the echo pin, and returns the sound wave travel time in microseconds  
    return pulseIn(echoPin, HIGH);  
}
```

```

void setup() {
  // set up the LCD's number of columns and rows:
  lcd.begin(16, 2);

  pinMode(releNO, OUTPUT);
  pinMode(inputPir, INPUT);
  pinMode(sensorLDR, INPUT);
  Serial.begin(9600);
}

void loop() {
  // set threshold distance to activate LEDs
  distanceThreshold = 350;
  // measure the ping time in cm
  cm = 0.01723 * readUltrasonicDistance(7, 6);
  // convert to inches by dividing by 2.54
  inches = (cm / 2.54);

  lcd.setCursor(0,0); // Sets the location at which subsequent text written to the LCD
  will be displayed
  lcd.print("D:"); // Prints string "Distance" on the LCD
  lcd.print(cm); // Prints the distance value from the sensor
  lcd.print("cm");
  delay(10);

  val = digitalRead(inputPir);
  resuldoSensorLDR = analogRead(sensorLDR);
  if(resuldoSensorLDR<600)
  {
    if(val == HIGH)
    {
      digitalWrite(releNO, HIGH);
      lcd.setCursor(0,1);
      lcd.print("L: On ");
      delay(5000);
    }
    else{

```

```

        digitalWrite(releNO, LOW);lcd.setCursor(0,1);
        lcd.print("L: Off");
        delay(300);
    }
}
else{ digitalWrite (releNO, LOW);
Serial.println(resuldoSensorLDR);
delay(500);
}

int color = analogRead(PINO_SGAS);

lcd.setCursor(8,0);
//lcd.print("");
if(color <= 85){
    lcd.print("G:Low ");
} else if(color <= 120){
    lcd.print("G:Med ");
} else if(color <= 200){
    lcd.print("G:High");
} else if(color <= 300){
    lcd.print("G:Ext ");
}

delay(250);
}

```