

# OpenSTA

## Command Line Arguments

The command line arguments for sta are shown below.

```
sta
  -help          show help and exit
  -version       show version and exit
  -no_init       do not read ~/.sta
  -no_splash     do not print the splash message
  -threads count|max use count threads
  -exit         exit after reading cmd_file
  cmd_file     source cmd_file
```

When OpenSTA starts up, commands are first read from the user initialization file `~/.sta` if it exists. If a TCL command file *cmd\_file* is specified on the command line, commands are read from the file and executed before entering an interactive TCL command interpreter. If `-exit` is specified the application exits after reading *cmd\_file*. Use the TCL exit command to exit the application. The `-threads` option specifies how many parallel threads to use. Use `-threads max` to use one thread per processor.

## Example Command Scripts

To read a design into OpenSTA use the `read_liberty` command to read Liberty library files. Next, read hierarchical structural Verilog files with the `read_verilog` command. The `link_design` command links the Verilog to the Liberty timing cells. Any number of Liberty and Verilog files can be read before linking the design.

Delays used for timing analysis are calculated using the Liberty timing models. If no parasitics are read only the pin capacitances of the timing models are used in delay calculation. Use the `read_spef` command to read parasitics from an extractor, or `read_sdf` to use delays calculated by an external delay calculator.

Timing constraints can be entered as TCL commands or read using the `read_sdc` command.

The units used by OpenSTA for all command arguments and reports are taken from the first Liberty file that is read. Use the `set_cmd_units` command to override the default units.

A sample command file that reads a library and a Verilog netlist and reports timing checks is shown below.

```
read_liberty example1_slow.lib
read_verilog example1.v
link_design top
read_sdf example1.sdf
create_clock -name clk -period 10 {clk1 clk2 clk3}
set_input_delay -clock clk 0 {in1 in2}
report_checks
```

This example can be found in `examples/sdf_delays.tcl`.

An example command script using three process corners and +/-10% min/max derating is shown below.

```

define_corners wc typ bc
read_liberty -corner wc example1_slow.lib
read_liberty -corner typ example1_typ.lib
read_liberty -corner bc example1_fast.lib
read_verilog example1.v
link_design top
set_timing_derate -early 0.9
set_timing_derate -late 1.1
create_clock -name clk -period 10 {clk1 clk2 clk3}
set_input_delay -clock clk 0 {in1 in2}
report_checks -path_delay min_max
report_checks -corner typ

```

This example can be found in `examples/spef_parasitics.tcl`. Other examples can be found in the `examples` directory.

## Power Analysis

OpenSTA also supports static power analysis with the `report_power` command. Probabalistic switching activities are propagated from the input ports to determine switching activities for internal pins.

```

read_liberty sky130hd_tt.lib
read_verilog gcd_sky130hd.v
link_design gcd
read_sdc gcd_sky130hd.sdc
read_spf gcd_sky130hd.spf
set_power_activity -input -activity 0.1
set_power_activity -input_port reset -activity 0
report_power

```

In this example the activity for all inputs is set to 0.1, and then the activity for the reset signal is set to zero because it does not switch during steady state operation.

Group	Internal Power	Switching Power	Leakage Power	Total Power (Watts)	
Sequential	3.11e-04	4.31e-05	2.96e-10	3.54e-04	43.2%
Combinational	1.74e-04	2.92e-04	6.98e-10	4.66e-04	56.8%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	4.85e-04	3.35e-04	9.94e-10	8.20e-04	100.0%
	59.2%	40.8%	0.0%		

This example can be found in `examples/power.tcl`.

Gate level simulation results can be used to get a more accurate power estimate. For example, the Icarus verilog simulator can be used to run the test bench `examples/gcd_tb.v` for the gcd design in the previous example.

```

iverilog -o gcd_tb gcd_tb.v
vvp gcd_tb

```

The test bench writes the VCD (Value Change Data) file `gcd_sky130hd.vcd` which can then be read with the `read_power_activities` command.

```
read_liberty sky130hd_tt.lib
read_verilog gcd_sky130hd.v
link_design gcd
read_sdc gcd_sky130hd.sdc
read_spef gcd_sky130hd.spef
read_power_activities -scope gcd_tb/gcd1 -vcd gcd_sky130hd.vcd
report_power
```

This example can be found in `examples/power_vcd.tcl`.

Group	Internal Power	Switching Power	Leakage Power	Total Power	(Watts)
Sequential	3.05e-04	3.84e-05	2.96e-10	3.44e-04	44.6%
Combinational	1.48e-04	2.79e-04	6.98e-10	4.27e-04	55.4%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	4.53e-04	3.18e-04	9.94e-10	7.71e-04	100.0%
	58.8%	41.2%	0.0%		

Note that in this simple example design simulation based activities does not significantly change the results.

## TCL Interpreter

Keyword arguments to commands may be abbreviated. For example,

```
report_checks -unique
```

is equivalent to the following command.

```
report_checks -unique_paths_to_endpoint
```

## Commands

---

### **all\_clocks**

The `all_clocks` command returns a list of all clocks that have been defined.

---

### **all\_inputs**

The `all_inputs` command returns a list of all input and bidirect ports of the current design.

---

### **all\_outputs**

The `all_outputs` command returns a list of all output and bidirect ports of the design.

---

<b>all_registers</b>	<code>[-clock <i>clock_names</i></code> <code>[-cells   -data_pins   -clock_pins   -async_pins</code> <code>  -output_pins]</code> <code>[-level_sensitive]</code> <code>[-edge_triggered]</code>
<code>-clock <i>clock_names</i></code>	A list of clock names. Only registers clocked by these clocks are returned.
<code>-cells</code>	Return a list of register instances.
<code>-data_pins</code>	Return the register data pins.
<code>-clock_pins</code>	Return the register clock pins.
<code>-async_pins</code>	Return the register set/clear pins.
<code>-output_pins</code>	Return the register output pins.
<code>-level_sensitive</code>	Return level-sensitive latches.
<code>-edge_triggered</code>	Return edge-triggered registers.

The `all_registers` command returns a list of register instances or register pins in the design. Options allow the list of registers to be restricted in various ways. The `-clock` keyword restricts the registers to those that are clocked by a set of clocks. The `-cells` option returns the list of registers or latches (the default). The `--data_pins`, `-clock_pins`, `-async_pins` and `-output_pins` options cause `all_registers` to return a list of register pins rather than instances.

---

<b>check_setup</b>	<code>[-verbose]</code> <code>[-unconstrained_endpoints]</code> <code>[-multiple_clock]</code> <code>[-no_clock]</code> <code>[-no_input_delay]</code> <code>[-loops]</code> <code>[-generated_clocks]</code> <code>[&gt; <i>filename</i>]</code> <code>[&gt;&gt; <i>filename</i>]</code>
<code>-verbose</code>	Show offending objects rather than just error counts.
<code>-unconstrained_endpoints</code>	Check path endpoints for timing constraints (timing check or set_output_delay).

-multiple_clock	Check register/latch clock pins for multiple clocks.
-no_clock	Check register/latch clock pins for a clock.
-no_input_delay	Check for inputs that do not have a set_input_delay command.
-loops	Check for combinational logic loops.
-generated_clocks	Check that generated clock source pins have been defined as clocks.

The check\_setup command performs sanity checks on the design. Individual checks can be performed with the keywords. If no check keywords are specified all checks are performed.

---

<b>connect_pin</b>	<i>net</i> <i>port pin</i>
<i>net</i>	A net to add connections to.
<i>port</i>	A port to connect to <i>net</i> .
<i>Pin</i>	A pin to connect to <i>net</i> .

The connect\_pin command connects a port or instance pin to a net.

---

<b>create_clock</b>	-period <i>period</i> [-name <i>clock_name</i> ] [-waveform <i>edge_list</i> ] [-add] [ <i>pin_list</i> ]
-period <i>period</i>	The clock period.
-name <i>clock_name</i>	The name of the clock.
-waveform <i>edge_list</i>	A list of edge rise and fall time.
-add	Add this clock to the clocks on <i>pin_list</i> .
<i>pin_list</i>	A list of pins driven by the clock.

The create\_clock command defines the waveform of a clock used by the design.

If no *pin\_list* is specified the clock is *virtual*. A virtual clock can be referred to by name in input arrival and departure time commands but is not attached to any pins in the design.

If no clock name is specified the name of the first pin is used as the clock name.

If a waveform is not specified the clock rises at zero and falls at half the clock period. The waveform is a list with time the clock rises as the first element and the time it falls as the second element.

If a clock is already defined on a pin the clock is redefined using the new clock parameters. If multiple clocks drive the same pin, use the -add option to prevent the existing definition from being overwritten.

The following command creates a clock with a period of 10 time units that rises at time 0 and falls at 5 time units on the pin named clk1.

```
create_clock -period 10 clk1
```

The following command creates a clock with a period of 10 time units that is high at time zero, falls at time 2 and rises at time 8. The clock drives three pins named clk1, clk2, and clk3.

```
create_clock -period 10 -waveform {8 2} -name clk {clk1 clk2 clk3}
```

---

<b>create_generated_clock</b>	<b>[ -name <i>clock_name</i> ]</b> <b>-source <i>master_pin</i></b> <b>[ -master_clock <i>master_clock</i> ]</b> <b>[ -divide_by <i>divisor</i> ]</b> <b>[ -multiply_by <i>multiplier</i> ]</b> <b>[ -duty_cycle <i>duty_cycle</i> ]</b> <b>[ -invert ]</b> <b>[ -edges <i>edge_list</i> ]</b> <b>[ -edge_shift <i>shift_list</i> ]</b> <b>[ -add ]</b> <b><i>pin_list</i></b>
<b>-name <i>clock_name</i></b>	The name of the generated clock.
<b>-source <i>master_pin</i></b>	A pin or port in the fanout of the master clock that is the source of the generated clock.
<b>-master_clock <i>master_clock</i></b>	Use -master_clock to specify which source clock to use when multiple clocks are present on <i>master_pin</i> .
<b>-divide_by <i>divisor</i></b>	Divide the master clock period by <i>divisor</i> .
<b>-multiply_by <i>multiplier</i></b>	Multiply the master clock period by <i>multiplier</i> .
<b>-duty_cycle <i>duty_cycle</i></b>	The percent of the period that the generated clock is high (between 0 and 100).
<b>-invert</b>	Invert the master clock.
<b>-edges <i>edge_list</i></b>	List of master clock edges to use in the generated clock. Edges are numbered from 1. <i>edge_list</i> must be 3 edges long.

<code>-edge_shift</code>	<code>shift_list</code>	Not supported.
<code>-add</code>		Add this clock to the existing clocks on <code>pin_list</code> .
<code>pin_list</code>		A list of pins driven by the generated clock.

The `create_generated_clock` command is used to generate a clock from an existing clock definition. It is used to model clock generation circuits such as clock dividers and phase locked loops.

The `-divide_by`, `-multiply_by` and `-edges` arguments are mutually exclusive.

The `-multiply_by` option is used to generate a higher frequency clock from the source clock. The period of the generated clock is divided by *multiplier*. The clock *multiplier* must be a positive integer. If a duty cycle is specified the generated clock rises at zero and falls at  $\text{period} * \text{duty\_cycle} / 100$ . If no duty cycle is specified the source clock edge times are divided by *multiplier*.

The `-divide_by` option is used to generate a lower frequency clock from the source clock. The clock *divisor* must be a positive integer. If the clock divisor is a power of two the source clock period is multiplied by *divisor*, the clock rise time is the same as the source clock, and the clock fall edge is one half period later. If the clock divisor is not a power of two the source clock waveform edge times are multiplied by *divisor*.

The `-edges` option forms the generated clock waveform by selecting edges from the source clock waveform.

If the `-invert` option is specified the waveform derived above is inverted.

If a clock is already defined on a pin the clock is redefined using the new clock parameters. If multiple clocks drive the same pin, use the `-add` option to prevent the existing definition from being overwritten.

In the example show below generates a clock named `gclk1` on register output pin `r1/Q` by dividing it by four.

```
create_clock -period 10 -waveform {1 8} clk1
create_generated_clock -name gclk1 -source clk1 -divide_by 4 r1/Q
```

The generated clock has a period of 40, rises at time 1 and falls at time 21.

In the example shown below the duty cycle is used to define the derived clock waveform.

```
create_generated_clock -name gclk1 -source clk1 -duty_cycle 50 \
    -multiply_by 2 r1/Q
```

The generated clock has a period of 5, rises at time .5 and falls at time 3.

In the example shown below the first, third and fifth source clock edges are used to define the derived clock waveform.

```
create_generated_clock -name gclk1 -source clk1 -edges {1 3 5} r1/Q
```

The generated clock has a period of 20, rises at time 1 and falls at time 11.

---

<b>create_voltage_area</b>	<i>[-name name]</i> <i>[-coordinate coordinates]</i> <i>[-guard_band_x guard_x]</i> <i>[-guard_band_y guard_y]</i> <i>cells</i>
----------------------------	---

This command is parsed and ignored by timing analysis.

---

<b>current_design</b>	<i>[design]</i>
-----------------------	-----------------

---

<b>current_instance</b>	<i>[instance]</i>
-------------------------	-------------------

<i>instance</i>	Not supported.
-----------------	----------------

---

<b>define_corners</b>	<i>corner1 [corner2]...</i>
-----------------------	-----------------------------

<i>corner</i>	The name of a delay calculation corner.
---------------	---

Use the `define_corners` command to define the names of multiple process/temperature/voltage corners. The `define_corners` command must follow `set_operating_conditions -analysis_type` and precede any reference to the corner names and can only appear once in a command file. There is no support for re-defining corners.

For analysis type `single`, each corner has one delay calculation result and early/late path arrivals. For analysis type `best_case/worst_case` and `on_chip_variation`, each corner has min/max delay calculation results and early/late path arrivals.

---

<b>delete_clock</b>	<i>[-all] clocks</i>
---------------------	----------------------

<i>clocks</i>	A list of clocks to remove.
---------------	-----------------------------

---

<b>delete_from_list</b>	<i>list objects</i>
-------------------------	---------------------

<i>list</i>	A list of objects.
-------------	--------------------

<i>objects</i>	A list of objects to delete from list.
----------------	--



---

**delete\_generated\_clock**    [-all] *clocks*

*clocks*                            A list of generated clocks to remove.

---

**delete\_instance**            *instance*

*instance*                        Instance to delete.

The network editing command `delete_instance` removes an instance from the design.

---

**delete\_net**                    *nets*

*nets*                            Nets to delete.

The network editing command `delete_net` removes a net from the design.

---

**disconnect\_pin**            *net*  
                              *port* | *pin* | -all

*net*                                The net to disconnect pins from.

*port*                              A port to connect to *net*.

*pin*                                A pin to connect to *net*.

-all                                Disconnect all pins from the net.

Disconnects a port or pin from a net. Parasitics connected to the pin are deleted.

---

**elapsed\_run\_time**

Returns the total clock run time in seconds as a float.

---

<b>find_timing_paths</b>	<pre> [-from <i>from_list</i>  -rise_from <i>from_list</i>  -fall_from <i>from_list</i>] [-through <i>through_list</i>  -rise_through <i>through_list</i>  -fall_through <i>through_list</i>] [-to <i>to_list</i>  -rise_to <i>to_list</i>  -fall_to <i>to_list</i>] [-unconstrained] [-path_delay min min_rise min_fall  max max_rise max_fall  min_max] [-group_count <i>path_count</i>] [-endpoint_count <i>endpoint_path_count</i>] [-unique_paths_to_endpoint] [-corner <i>corner</i>] [-slack_max <i>max_slack</i>] [-slack_min <i>min_slack</i>] [-sort_by_slack] [-path_group <i>groups</i>] </pre>
<b>-from <i>from_list</i></b>	Return paths from a list of clocks, instances, ports, register clock pins, or latch data pins.
<b>-rise_from <i>from_list</i></b>	Return paths from the rising edge of clocks, instances, ports, register clock pins, or latch data pins.
<b>-fall_from <i>from_list</i></b>	Return paths from the falling edge of clocks, instances, ports, register clock pins, or latch data pins.
<b>-through <i>through_list</i></b>	Return paths through a list of instances, pins or nets.
<b>-rise_through <i>through_list</i></b>	Return rising paths through a list of instances, pins or nets.
<b>-fall_through <i>through_list</i></b>	Return falling paths through a list of instances, pins or nets.
<b>-to <i>to_list</i></b>	Return paths to a list of clocks, instances, ports or pins.
<b>-rise_to <i>to_list</i></b>	Return rising paths to a list of clocks, instances, ports or pins.
<b>-fall_to <i>to_list</i></b>	Return falling paths to a list of clocks, instances, ports or pins.
<b>-unconstrained</b>	Return unconstrained paths.
<b>-path_delay min</b>	Return min path (hold) checks.

-path_delay min_rise	Return min path (hold) checks for rising endpoints.
-path_delay min_fall	Return min path (hold) checks for falling endpoints.
-path_delay max	Return max path (setup) checks.
-path_delay max_rise	Return max path (setup) checks for rising endpoints.
-path_delay max_fall	Return max path (setup) checks for falling endpoints.
-path_delay min_max	Return max and max path (setup and hold) checks.
-group_count <i>path_count</i>	The number of paths to return in each path group.
-endpoint_count <i>endpoint_path_count</i>	The number of paths to return for each endpoint.
-unique_paths_to_endpoint	Return multiple paths to an endpoint that traverse different pins without showing multiple paths with different rise/fall transitions.
-corner <i>corner</i>	Return paths for one process corner.
-slack_max <i>max_slack</i>	Return paths with slack less than <i>max_slack</i> .
-slack_min <i>min_slack</i>	Return paths with slack greater than <i>min_slack</i> .
-sort_by_slack	Sort paths by slack rather than slack within path groups.
-path_group <i>groups</i>	Return paths in path groups. Paths in all groups are returned if this option is not specified.

The `find_timing_paths` command returns a list of path objects for scripting. Use the `get_property` function to access properties of the paths.

---

<b>get_cells</b>	[-hierarchical] [-hsc <i>separator</i> ] [-filter <i>expr</i> ] [-regex] [-nocase] [-quiet] [-of_objects <i>objects</i> ] [ <i>patterns</i> ]
-hierarchical	Searches hierarchy levels below the current instance for matches.

<code>-hsc separator</code>	Character to use to separate hierarchical instance names in <i>patterns</i> .
<code>-filter expr</code>	A filter expression of the form <code>attribute==value</code> or <code>attribute~=value</code> where <i>attribute</i> is an attribute supported by the <code>get_property</code> command.
<code>-regexp</code>	Use regular expression matching instead of glob pattern matching.
<code>-nocase</code>	Ignore case when matching. Only valid with <code>-regexp</code> .
<code>-quiet</code>	Do not warn if no matches are found.
<code>-of_objects objects</code>	The name of a pin or net, a list of pins returned by <code>get_pins</code> , or a list of nets returned by <code>get_nets</code> . The <code>-hierarchical</code> option cannot be used with <code>-of_objects</code> .
<i>patterns</i>	A list of instance name patterns.

The `get_cells` command returns a list of all cell instances that match *patterns*.

---

<b><code>get_clocks</code></b>	<code>[-regexp]</code> <code>[-nocase]</code> <code>[-quiet]</code> <i>patterns</i>
<code>-regexp</code>	Use regular expression matching instead of glob pattern matching.
<code>-nocase</code>	Ignore case when matching. Only valid with <code>-regexp</code> .
<code>-quiet</code>	Do not warn if no matches are found.
<i>patterns</i>	A list of clock name patterns.

The `get_clocks` command returns a list of all clocks that have been defined.

---

<b>get_fanin</b>	-to <i>sink_list</i> [-flat] [-only_cells] [-startpoints_only] [-levels <i>level_count</i> ] [-pin_levels <i>pin_count</i> ] [-trace_arcs timing enabled all]
-to <i>sink_list</i>	List of pins, ports, or nets to find the fanin of. For nets, the fanin of driver pins on the nets are returned.
-flat	With -flat pins in the fanin at any hierarchy level are returned. Without -flat only pins at the same hierarchy level as the sinks are returned.
-only_cells	Return the instances connected to the pins in the fanin.
-startpoints_only	Only return pins that are startpoints.
-level <i>level_count</i>	Only return pins within <i>level_count</i> instance traversals.
-pin_levels <i>pin_count</i>	Only return pins within <i>pin_count</i> pin traversals.
-trace_arcs timing	Only trace through timing arcs that are not disabled.
-trace_arcs enabled	Only trace through timing arcs that are not disabled.
-trace_arcs all	Trace through all arcs, including disabled ones.

The `get_fanin` command returns traverses the design from *sink\_list* pins, ports or nets backwards and return the fanin pins or instances.

---

<b>get_fanout</b>	-from <i>source_list</i> [-flat] [-only_cells] [-endpoints_only] [-levels <i>level_count</i> ] [-pin_levels <i>pin_count</i> ] [-trace_arcs timing enabled all]
-from <i>source_list</i>	List of pins, ports, or nets to find the fanout of. For nets, the fanout of load pins on the nets are returned.
-flat	With -flat pins in the fanin at any hierarchy level are returned. Without -flat only pins at the same hierarchy level as the sinks are returned.
-only_cells	Return the instances connected to the pins in the fanout.

-endpoints_only	Only return pins that are endpoints.
-level <i>level_count</i>	Only return pins within <i>level_count</i> instance traversals.
-pin_levels <i>pin_count</i>	Only return pins within <i>pin_count</i> pin traversals.
-trace_arcs timing	Only trace through timing arcs that are not disabled.
-trace_arcs enabled	Only trace through timing arcs that are not disabled.
-trace_arcs all	Trace through all arcs, including disabled ones.

The `get_fanout` command returns traverses the design from *source\_list* pins, ports or nets backwards and return the fanout pins or instances.

---

<b>get_full_name</b>	<i>object</i>
<i>object</i>	A library, cell, port, instance, pin or timing arc object.

Return the name of *object*. Equivalent to `[get_property object full_name]`.

---

<b>get_lib_cells</b>	[-of_objects <i>objects</i> ] [-hsc <i>separator</i> ] [-regexp] [-nocase] [-quiet] <i>patterns</i>
-of_objects <i>objects</i>	A list of instance objects.
-hsc <i>separator</i>	Character that separates the library name and cell name in <i>patterns</i> . Defaults to '/'.  
-regexp	Use regular expression matching instead of glob pattern matching.
-nocase	Ignore case when matching. Only valid with -regexp.
-quiet	Do not warn if no matches are found.
<i>patterns</i>	A list of library cell name patterns of the form library_name/cell_name.

The `get_lib_cells` command returns a list of library cells that match *pattern*. The library name can be prepended to the cell name pattern with the *separator* character, which defaults to hierarchy\_separator.

---

<b>get_lib_pins</b>	[-hsc <i>separator</i> ] [-regexp] [-nocase] [-quiet] <i>patterns</i>
-hsc <i>separator</i>	Character that separates the library name, cell name and port name in <i>pattern</i> . Defaults to '/'.
-regexp	Use regular expression matching instead of glob pattern matching.
-nocase	Ignore case when matching. Only valid with -regexp.
-quiet	Do not warn if no matches are found.
<i>patterns</i>	A list of library port name patterns of the form library_name/cell_name/port_name.

The get\_lib\_pins command returns a list of library ports that match *pattern*. Use *separator* to separate the library and cell name patterns from the port name in *pattern*.

---

<b>get_libs</b>	[-regexp] [-nocase] [-quiet] <i>patterns</i>
-regexp	Use regular expression matching instead of glob pattern matching.
-nocase	Ignore case when matching. Only valid with -regexp.
-quiet	Do not warn if no matches are found.
<i>patterns</i>	A list of library name patterns.

The get\_libs command returns a list of clocks that match *patterns*.

---

<b>get_nets</b>	[-hierarchical] [-hsc <i>separator</i> ] [-regexp] [-nocase] [-quiet] [-of_objects <i>objects</i> ] [ <i>patterns</i> ]
-----------------	---

<b>-hierarchical</b>	Searches hierarchy levels below the current instance for matches.
<b>-hsc <i>separator</i></b>	Character that separates the library name, cell name and port name in <i>pattern</i> . Defaults to '/'.
<b>-regexp</b>	Use regular expression matching instead of glob pattern matching.
<b>-nocase</b>	Ignore case when matching. Only valid with -regexp.
<b>-quiet</b>	Do not warn if no matches are found.
<b>-of_objects <i>objects</i></b>	The name of a pin or instance, a list of pins returned by get_pins, or a list of instances returned by get_cells. The -hierarchical option cannot be used with -of_objects.
<b><i>patterns</i></b>	A list of net name patterns.

The get\_nets command returns a list of all nets that match *patterns*.

---

<b>get_name</b>	<i>object</i>
<i>object</i>	A library, cell, port, instance, pin or timing arc object.

Return the name of *object*. Equivalent to [get\_property *object* name].

---

<b>get_pins</b>	[-hierarchical] [-hsc <i>separator</i> ] [-filter <i>expr</i> ] [-regexp] [-nocase] [-quiet] [-of_objects <i>objects</i> ] [ <i>patterns</i> ]
<b>-hierarchical</b>	Searches hierarchy levels below the current instance for matches.
<b>-hsc <i>separator</i></b>	Character that separates the library name, cell name and port name in <i>pattern</i> . Defaults to '/'.
<b>-filter <i>expr</i></b>	A filter expression of the form <i>attribute</i> == <i>value</i> or <i>attribute</i> ~= <i>value</i> where <i>attribute</i> is an attribute supported by the get_property command.



<code>-nocase</code>	Ignore case when matching. Only valid with <code>-regexp</code> .
<code>-quiet</code>	Do not warn if no matches are found.
<code>-of_objects <i>objects</i></code>	The name of a net or instance, a list of nets returned by <code>get_nets</code> , or a list of instances returned by <code>get_cells</code> . The <code>-hierarchical</code> option cannot be used with <code>-of_objects</code> .
<i>patterns</i>	A list of pin name patterns.

The `get_pins` command returns a list of all instance pins that match *patterns*.

A useful idiom to find the driver pin for a net is the following.

```
get_pins -of_objects [get_net net_name] -filter direction==output
```

---

<b>get_ports</b>	<code>[-filter <i>expr</i>]</code> <code>[-regexp]</code> <code>[-nocase]</code> <code>[-quiet]</code> <code>[-of_objects <i>objects</i>]</code> <code>[<i>patterns</i>]</code>
<code>-filter <i>expr</i></code>	A filter expression of the form <code><i>attribute</i>==<i>value</i></code> or <code><i>attribute</i>~=<i>value</i></code> where <i>attribute</i> is an attribute supported by the <code>get_property</code> command.
<code>-regexp</code>	Use regular expression matching instead of glob pattern matching.
<code>-nocase</code>	Ignore case when matching. Only valid with <code>-regexp</code> .
<code>-quiet</code>	Do not warn if no matches are found.
<code>-of_objects <i>objects</i></code>	The name of net or a list of nets returned by <code>get_nets</code> .
<i>patterns</i>	A list of port name patterns.

The `get_ports` command returns a list of all top level ports that match *patterns*.

---

<b>get_property</b>	<code>[-object_type <i>object_type</i>]</code> <i>object</i> <i>property</i>
---------------------	--

<i>-object_type</i>	<i>object_type</i>	The type of <i>object</i> when it is specified as a name. cell pin net port clock library library_cell  library_pin timing_arc
<i>object</i>		An object returned by get_cells, get_pins, get_nets, get_ports, get_clocks, get_libs, get_lib_cells, get_lib_pins, or get_timing_arcs, or object name. -object_type is required if <i>object</i> is a name.
<i>property</i>		A property name.

The properties for different objects types are shown below.

cell (SDC lib\_cell)

base\_name  
filename  
full\_name  
library  
name

clock

full\_name  
is\_generated  
name  
period  
propagated  
sources

edge

delay\_max\_fall  
delay\_min\_fall  
delay\_max\_rise  
delay\_min\_rise  
full\_name  
from\_pin  
sense  
to\_pin

instance (SDC cell)

cell  
full\_name  
ref\_name  
liberty\_cell  
name

liberty\_cell (SDC lib\_cell)

area  
base\_name  
dont\_use  
filename  
full\_name  
is\_buffer  
is\_inverter  
library  
name

liberty\_port (SDC lib\_pin)

capacitance  
direction  
drive\_resistance  
drive\_resistance\_max\_fall  
drive\_resistance\_max\_rise  
drive\_resistance\_min\_fall  
drive\_resistance\_min\_rise  
full\_name  
intrinsic\_delay  
intrinsic\_delay\_max\_fall  
intrinsic\_delay\_max\_rise  
intrinsic\_delay\_min\_fall  
intrinsic\_delay\_min\_rise  
is\_register\_clock  
lib\_cell  
name

library

filename (Liberty library only)  
name  
full\_name

net

full\_name  
name

path (PathEnd)

endpoint  
endpoint\_clock  
endpoint\_clock\_pin  
slack  
startpoint  
startpoint\_clock  
points

pin

activity  
slew\_max\_fall  
slew\_max\_rise

slew\_min\_fall  
slew\_min\_rise  
clocks  
direction  
full\_name  
is\_register\_clock  
lib\_pin\_name  
name  
slack\_max  
slack\_max\_fall  
slack\_max\_rise  
slack\_min  
slack\_min\_fall  
slack\_min\_rise

#### port

activity  
slew\_max\_fall  
slew\_max\_rise  
slew\_min\_fall  
slew\_min\_rise  
direction  
full\_name  
liberty\_port  
name  
slack\_max  
slack\_max\_fall  
slack\_max\_rise  
slack\_min  
slack\_min\_fall  
slack\_min\_rise

#### point (PathRef)

arrival  
pin  
required  
slack

---

<b>get_timing_edges</b>	<code>[-from <i>from_pins</i></code> <code>[-to <i>to_pins</i></code> <code>[-of_objects <i>objects</i></code> <code>[-filter <i>expr</i></code> <code>[<i>patterns</i>]</code>
<code>-from <i>from_pin</i></code>	A list of pins.
<code>-to <i>to_pin</i></code>	A list of pins.
<code>-of_objects <i>objects</i></code>	A list of instances or library cells. The <code>-from</code> and <code>-to</code> options cannot be used with <code>-of_objects</code> .

*-filter expr*                      A filter expression of the form  
    *attribute==value*  
 or  
    *attribute~=value*  
 where *attribute* is an attribute supported by the *get\_property* command.

The *get\_timing\_edges* command returns a list of timing edges (arcs) to, from or between pins. The result can be passed to *get\_property* or *set\_disable\_timing*.

---

<b>group_path</b>	-name <i>group_name</i> [-weight <i>weight</i> ] [-critical_range <i>range</i> ] [-from <i>from_list</i>  -rise_from <i>from_list</i>  -fall_from <i>from_list</i> ] [-through <i>through_list</i> ] [-rise_through <i>through_list</i> ] [-fall_through <i>through_list</i> ] [-to <i>to_list</i>  -rise_to <i>to_list</i>  -fall_to <i>to_list</i> ]
<i>-name group_name</i>	The name of the path group.
<i>-weight weight</i>	Not supported.
<i>-critical_range range</i>	Not supported.
<i>-from from_list</i>	Group paths from a list of clocks, instances, ports, register clock pins, or latch data pins.
<i>-rise_from from_list</i>	Group paths from the rising edge of clocks, instances, ports, register clock pins, or latch data pins.
<i>-fall_from from_list</i>	Group paths from the falling edge of clocks, instances, ports, register clock pins, or latch data pins.
<i>-through through_list</i>	Group paths through a list of instances, pins or nets.
<i>-rise_through through_list</i>	Group rising paths through a list of instances, pins or nets.
<i>-fall_through through_list</i>	Group falling paths through a list of instances, pins or nets.

-to <i>to_list</i>	Group paths to a list of clocks, instances, ports or pins.
-rise_to <i>to_list</i>	Group rising paths to a list of clocks, instances, ports or pins.
-fall_to <i>to_list</i>	Group falling paths to a list of clocks, instances, ports or pins.

The group\_path command is used to group paths reported by the report\_checks command. See set\_false\_path for a description of allowed *from\_list*, *through\_list* and *to\_list* objects.

---

<b>link_design</b>	[ <i>cell_name</i> ]
--------------------	----------------------

<i>cell_name</i>	The top level module/cell name of the design hierarchy to link.
------------------	---

Link (elaborate, flatten) the the top level cell *cell\_name*. The design must be linked after reading netlist and library files. The default value of *cell\_name* is the current design.

The linker creates empty "block box" cells for instances the reference undefined cells when the variable link\_create\_black\_boxes is true. When link\_create\_black\_boxes is false an error is reported and the link fails.

The link\_design command returns 1 if the link succeeds and 0 if it fails.

---

<b>make_instance</b>	<i>inst_path</i> <i>lib_cell</i>
----------------------	-------------------------------------

<i>inst_path</i>	A hierarchical instance name.
------------------	-------------------------------

<i>lib_cell</i>	The library cell of the new instance.
-----------------	---------------------------------------

The make\_instance command makes an instance of library cell *lib\_cell*.

---

<b>make_net</b>	<i>net_name_list</i>
-----------------	----------------------

<i>net_name_list</i>	A list of net names.
----------------------	----------------------

Creates a net for each hierarchical net name.

---

<b>read_liberty</b>	[-corner <i>corner</i> ] [-min] [-max] [-no_latch_infer] <i>filename</i>
---------------------	--

<code>-corner</code>	<code>corner</code>	Use the library for process corner <i>corner</i> delay calculation.
<code>-min</code>		Use library for min delay calculation.
<code>-max</code>		Use library for max delay calculation.
<code>filename</code>		The liberty file name to read.

The `read_liberty` command reads a Liberty format library file. The first library that is read sets the units used by SDC/TCL commands and reporting. The `include_file` attribute is supported.

Cells that have a triad of timing arcs between three pins as shown below are inferred as latches:

```
cell (inferred_latch) {
  pin(D) {
    direction : input ;
    timing () {
      related_pin : "E" ;
      timing_type : setup_falling ;
    }
    timing () {
      related_pin : "E" ;
      timing_type : hold_falling ;
    }
  }
  pin(E) {
    direction : input;
  }
  pin(Q) {
    direction : output ;
    timing () {
      related_pin : "D" ;
    }
    timing () {
      related_pin : "E" ;
      timing_type : rising_edge ;
    }
  }
}
```

In this example a positive level-sensitive latch is inferred.

When the `read_liberty -no_latch_infer` flag is used latches are not inferred. If a cell has the `interface_timing true` attribute, no latches are inferred in the cell.

Files compressed with gzip are automatically uncompressed.

```
read_power_activities [-scope scope]
                     -vcd filename
```

*scope* The VCD scope of the current design to extract simulation data. Typically the test bench name and design under test instance name. Scope levels are separated with `'/'`.

`-vcd filename` The name of the VCD file to read.

The `read_power_activities` command reads a VCD (Value Change Dump) file from a Verilog simulation and extracts pin activities and duty cycles for use in power estimation. Files compressed with gzip are supported. Annotated activities are propagated to the fanout of the annotated pins.

---

**read\_sdc** `[-echo]`  
`filename`

`-echo` Print each command before evaluating it.

*filename* SDC command file.

Read SDC commands from *filename*.

The `read_sdc` command stops and reports any errors encountered while reading a file unless `sta_continue_on_error` is 1.

Files compressed with gzip are automatically uncompressed.

---

**read\_sdf** `[-corner corner]`  
`[-unesaped_dividers]`  
`filename`

`-corner corner` Process corner delays to annotate.

`-unesaped_dividers` With this option path names in the SDF do not have to escape hierarchy dividers when the path name is escaped. For example, the escaped Verilog name `"\inst1/inst2 "` can be referenced as `"inst1/inst2"`. The correct SDF name is `"inst1Vinst2"`, since the divider does not represent a change in hierarchy in this case.

*filename* The name of the SDF file to read.

Read SDF delays from a file. The min and max values in the SDF tuples are used to annotate the delays for *corner*. The typical values in the SDF tuples are ignored. If multiple corners are defined `-corner` must be specified.

Files compressed with gzip are automatically uncompressed.

INCREMENT is supported as an alias for INCREMENTAL.



The following SDF statements are not supported.

PORT  
INSTANCE wildcards

---

<b>read_spef</b>	<b>[-min]</b> <b>[-max]</b> <b>[-path path]</b> <b>[-corner <i>corner</i>]</b> <b>[-keep_capacitive_coupling]</b> <b>[-coupling_reduction_factor <i>factor</i>]</b> <b>[-reduce_to pi_elmore pi_pole_residue2]</b> <b>[-delete_after_reduce]</b> <b>[-quiet]</b> <i>filename</i>
<b>-min</b>	Annotate parasitics for min delays.
<b>-max</b>	Annotate parasitics for max delays.
<b><i>path</i></b>	Hierarchical block instance path to annotate with parasitics.
<b>-corner <i>corner</i></b>	Annotate parasitics for one process corner.
<b>-keep_capacitive_coupling</b>	Keep coupling capacitors in parasitic networks rather than converting them to grounded capacitors.
<b>-coupling_reduction_factor <i>factor</i></b>	Factor to multiply coupling capacitance by when reducing parasitic networks. The default value is 1.0.
<b>-reduce_to elmore</b>	Reduce detailed parasitics to a PI/Elmore as each net is read.
<b>-reduce_to pi_pole_residue2</b>	Reduce detailed parasitics to a PI/Pole residue model as each net is read.
<b>-delete_after_reduce</b>	Delete the detailed parasitic network after reducing it.
<b>-quiet</b>	Do not print error or warning messages.
<b>-save</b>	Save the parasitics database after reading it (OpenAccess only).
<b><i>filename</i></b>	The name of the parasitics file to read.

The read\_spef command reads a file of net parasitics in SPEF format. Use the -report\_parasitic\_annotation command to check for nets that are not annotated.

Files compressed with gzip are automatically uncompressed.

Separate parasitics can be annotated for corners and min and max paths using the `-corner`, `-min` and `-max` arguments.

With the `-reduce_to` and `-delete_after_reduce` options, parasitic networks are reduced after each net is read, substantially reducing the memory footprint required to store the parasitics.

Coupling capacitors are multiplied by the `-coupling_reduction_factor` when a parasitic network is reduced.

The following SPEF constructs are ignored.

- \*DESIGN\_FLOW (all values are ignored)
- \*S slews
- \*D driving cell
- \*I pin capacitances (library cell capacitances are used instead)
- \*Q r\_net load poles
- \*K r\_net load residues

If the SPEF file contains triplet values the first value is used.

Parasitic networks (DSPEF) can be annotated on hierarchical blocks using the `-path` argument to specify the instance path to the block. Parasitic networks in the higher level netlist are stitched together at the hierarchical pins of the blocks.

---

<b>read_verilog</b>	<i>filename</i>
---------------------	-----------------

<i>filename</i>	The name of the verilog file to read.
-----------------	---------------------------------------

The `read_verilog` command reads a gate level verilog netlist. After all verilog netlist and Liberty libraries are read the design must be linked with the `link_design` command.

Verilog 2001 module port declarations are supported. An example is shown below.

```
module top (input in1, in2, clk1, clk2, clk3,
           output out);
```

Files compressed with gzip are automatically uncompressed.

---

<b>replace_cell</b>	<i>instance_list</i> <i>replacement_cell</i>
---------------------	---

<i>instance_list</i>	A list of instances to swap the cell.
----------------------	---------------------------------------

<i>replacement_cell</i>	The replacement lib cell.
-------------------------	---------------------------

The `replace_cell` command changes the cell of an instance. The replacement cell must have the same port list (number, name, and order) as the instance's existing cell for the replacement to be successful.

---

<b>report_annotated_check</b>	[-setup] [-hold] [-recovery] [-removal] [-nochange] [-width] [-period] [-max_skew] [-max_line <i>lines</i> ] [-list_annotated] [-list_not_annotated] [-constant_arcs]
-setup	Report annotated setup checks.
-hold	Report annotated hold checks.
-recovery	Report annotated recovery checks.
-removal	Report annotated removal checks.
-nochange	Report annotated nochange checks.
-width	Report annotated width checks.
-period	Report annotated period checks.
-max_skew	Report annotated max skew checks.
-max_line <i>lines</i>	Maximum number of lines listed by the -list_annotated and -list_not_annotated options.
-list_annotated	List annotated timing arcs.
-list_not_annotated	List unannotated timing arcs.
-constant_arcs	Report separate annotation counts for arcs disabled by logic constants (set_logic_one, set_logic_zero).

The `report_annotated_check` command reports a summary of SDF timing check annotation. The `-list_annotated` and `-list_not_annotated` options can be used to list arcs that are annotated or not annotated.

---

<b>report_annotated_delay</b>	[-cell] [-net] [-from_in_ports] [-to_out_ports] [-max_lines <i>lines</i> ] [-list_annotated] [-list_not_annotated] [-constant_arcs]
-cell	Report annotated cell delays.
-net	Report annotated internal net delays.
-from_in_ports	Report annotated delays from input ports.
-to_out_ports	Report annotated delays to output ports.
-max_lines <i>lines</i>	Maximum number of lines listed by the -list_annotated and -list_not_annotated options.
-list_annotated	List annotated timing arcs.
-list_not_annotated	List unannotated timing arcs.
-constant_arcs	Report separate annotation counts for arcs disabled by logic constants (set_logic_one, set_logic_zero).

The `report_annotated_delay` command reports a summary of SDF delay annotation. Without the `-from_in_ports` and `-to_out_ports` options arcs to and from top level ports are not reported. The `-list_annotated` and `-list_not_annotated` options can be used to list arcs that are annotated or not annotated.

---

<b>report_cell</b>	[-connections] [-verbose] <i>instance_path</i> [> <i>filename</i> ] [>> <i>filename</i> ]
-connections	Report the instance pins.
-verbose	With -connections also report all pins connected to each instance pin net.
<i>instance_path</i>	Hierarchical path to the instance.

The `report_cell` command is an alias for `report_instance`.

---

<b>report_checks</b>	<pre> [-from <i>from_list</i>  -rise_from <i>from_list</i>  -fall_from <i>from_list</i>] [-through <i>through_list</i>  -rise_through <i>through_list</i>  -fall_through <i>through_list</i>] [-to <i>to_list</i>  -rise_to <i>to_list</i>  -fall_to <i>to_list</i>] [-unconstrained] [-path_delay min min_rise min_fall                  max max_rise max_fall                  min_max] [-group_count <i>path_count</i>] [-endpoint_count <i>endpoint_path_count</i>] [-unique_paths_to_endpoint] [-corner <i>corner</i>] [-slack_max <i>max_slack</i>] [-slack_min <i>min_slack</i>] [-sort_by_slack] [-path_group <i>groups</i>] [-format end full short summary                  full_clock full_clock_expanded] [-fields <i>fields</i>] [-digits <i>digits</i>] [-no_line_split] [&gt; <i>filename</i>] [&gt;&gt; <i>filename</i>] </pre>
<b>-from <i>from_list</i></b>	Report paths from a list of clocks, instances, ports, register clock pins, or latch data pins.
<b>-rise_from <i>from_list</i></b>	Report paths from the rising edge of clocks, instances, ports, register clock pins, or latch data pins.
<b>-fall_from <i>from_list</i></b>	Report paths from the falling edge of clocks, instances, ports, register clock pins, or latch data pins.
<b>-through <i>through_list</i></b>	Report paths through a list of instances, pins or nets.
<b>-rise_through <i>through_list</i></b>	Report rising paths through a list of instances, pins or nets.
<b>-fall_through <i>through_list</i></b>	Report falling paths through a list of instances, pins or nets.

-to <i>to_list</i>	Report paths to a list of clocks, instances, ports or pins.
-rise_to <i>to_list</i>	Report rising paths to a list of clocks, instances, ports or pins.
-fall_to <i>to_list</i>	Report falling paths to a list of clocks, instances, ports or pins.
-unconstrained	Report unconstrained paths. By default unconstrained paths are not reported.
-path_delay min	Report min path (hold) checks.
-path_delay min_rise	Report min path (hold) checks for rising endpoints.
-path_delay min_fall	Report min path (hold) checks for falling endpoints.
-path_delay max	Report max path (setup) checks.
-path_delay max_rise	Report max path (setup) checks for rising endpoints.
-path_delay max_fall	Report max path (setup) checks for falling endpoints.
-path_delay min_max	Report max and max path (setup and hold) checks.
-group_count <i>path_count</i>	The number of paths to report in each path group. The default is 1.
-endpoint_count <i>endpoint_path_count</i>	The number of paths to report for each endpoint. The default is 1.
-unique_paths_to_endpoint	When multiple paths to and endpoint are specified with -endpoint_count many of the paths may differ only in the rise/fall edges of the pins in the paths. With this option only the worst path through the set of pins is reported.
-corner <i>corner</i>	Report paths for one process corner. The default is to report paths for all process corners.
-slack_max <i>max_slack</i>	Only report paths with less slack than <i>max_slack</i> .
-slack_min <i>min_slack</i>	Only report paths with more slack than <i>min_slack</i> .
-sort_by_slack	Sort paths by slack rather than slack grouped by path group.
-path_group <i>groups</i>	List of path groups to report. The default is to report all path groups.
-format end	Report path ends in one line with delay, required time and slack.
-format full	Report path start and end points and the path. This is the default path type.

-format full_clock	Report path start and end points, the path, and the source and target clock paths.
-format full_clock_expanded	Report path start and end points, the path, and the source and target clock paths. If the clock is generated and propagated, the path from the clock source pin is also reported.
-format short	Report only path start and end points.
-format summary	Report only path ends with delay.
-fields <i>fields</i>	List of capacitance slew input_pins nets fanout
-digits <i>digits</i>	The number of digits after the decimal point to report. The default value is the variable sta_report_default_digits.
-no_line_splits	Do not split long lines into multiple lines.

The report\_checks command reports paths in the design. Paths are reported in groups by capture clock, unlocked path delays, gated clocks and unconstrained.

See set\_false\_path for a description of allowed *from\_list*, *through\_list* and *to\_list* objects.

---

<b>report_check_types</b>	[-violators] [-verbose] [-format slack_only end] [-max_delay] [-min_delay] [-recovery] [-removal] [-clock_gating_setup] [-clock_gating_hold] [-max_slew] [-min_slew] [-min_pulse_width] [-min_period] [-digits <i>digits</i> ] [-no_split_lines] [> <i>filename</i> ] [>> <i>filename</i> ]
---------------------------	---

-violators	Report all violated timing and design rule constraints.
-verbose	Use a verbose output format.

-format slack_only	Report the minimum slack for each timing check.
-format end	Report the endpoint for each check.
-max_delay	Report setup and max delay path delay constraints.
-min_delay	Report hold and min delay path delay constraints.
-recovery	Report asynchronous recovery checks.
-removal	Report asynchronous removal checks.
-clock_gating_setup	Report gated clock enable setup checks.
-clock_gating_hold	Report gated clock hold setup checks.
-max_slew	Report max transition design rule checks.
-max_skew	Report max skew design rule checks.
-min_pulse_width	Report min pulse width design rule checks.
-min_period	Report min period design rule checks.
-min_slew	Report min slew design rule checks.
-digits <i>digits</i>	The number of digits after the decimal point to report. The default value is the variable <code>sta_report_default_digits</code> .
-no_split_lines	Do not split long lines into multiple lines.

The `report_check_types` command reports the slack for each type of timing and design rule constraint. The keyword options allow a subset of the constraint types to be reported.

---

**report\_clock\_min\_period** [-clocks *clocks*]  
 [-include\_port\_paths]

-clocks <i>clocks</i>	The clocks to report.
-include_port_paths	Include paths from input port and to output ports.

Report the minimum period and maximum frequency for *clocks*. If the `-clocks` argument is not specified all clocks are reported. The minimum period is determined by examining the smallest slack paths between registers the rising edges of the clock or between falling edges of the clock. Paths between different clocks,



different clock edges of the same clock, level sensitive latches, or paths constrained by `set_multicycle_path`, `set_max_path` are not considered.

---

**report\_clock\_properties** [*clock\_names*]

---

<i>clock_names</i>	List of clock names to report.
--------------------	--------------------------------

The `report_clock_properties` command reports the period and rise/fall edge times for each clock that has been defined.

---

<b>report_clock_skew</b>	<code>[-setup  -hold]</code> <code>[-clock <i>clocks</i>]</code> <code>[-digits <i>digits</i>]</code>
--------------------------	---

<code>-setup</code>	Report skew for setup checks.
---------------------	-------------------------------

<code>-hold</code>	Report skew for hold checks.
--------------------	------------------------------

<code>-clock <i>clocks</i></code>	The target clocks to report.
-----------------------------------	------------------------------

<code>-digits <i>digits</i></code>	The number of digits to report for delays.
------------------------------------	--

Report the maximum difference in clock arrival between every source and target register that has a path between the source and target registers.

---

<b>report_dcalc</b>	<code>[-from <i>from_pin</i>]</code> <code>[-to <i>to_pin</i>]</code> <code>[-corner <i>corner</i>]</code> <code>[-min]</code> <code>[-max]</code> <code>[-digits <i>digits</i>]</code> <code>[&gt; <i>filename</i>]</code> <code>[&gt;&gt; <i>filename</i>]</code>
---------------------	--

<code>-from <i>from_pin</i></code>	Report delay calculations for timing arcs from instance input pin <i>from_pin</i> .
------------------------------------	---

<code>-to <i>to_pin</i></code>	Report delay calculations for timing arcs to instance output pin <i>to_pin</i> .
--------------------------------	--

<code>-corner <i>corner</i></code>	Report paths for process <i>corner</i> . The <code>-corner</code> keyword is required if more than one process corner is defined.
------------------------------------	---

<code>-min</code>	Report delay calculation for min delays.
-------------------	--

<code>-max</code>	Report delay calculation for max delays.
-------------------	--

`-digits digits`                      The number of digits after the decimal point to report. The default is `sta_report_default_digits`.

The `report_dcalc` command shows how the delays between instance pins are calculated. It is useful for debugging problems with delay calculation.

---

## **report\_disabled\_edges**

The `report_disabled_edges` command reports disabled timing arcs along with the reason they are disabled. Each disabled timing arc is reported as the instance name along with the from and to ports of the arc. The disable reason is shown next. Arcs that are disabled with `set_disable_timing` are reported with `constraint` as the reason. Arcs that are disabled by constants are reported with `constant` as the reason along with the constant instance pin and value. Arcs that are disabled to break combinational feedback loops are reported with `loop` as the reason.

```
> report_disabled_edges
u1 A B constant B=0
```

---

<b>report_instance</b>	<code>[-connections]</code> <code>[-verbose]</code> <code><i>instance_path</i></code> <code>[&gt; <i>filename</i>]</code> <code>[&gt;&gt; <i>filename</i>]</code>
<code>-connections</code>	Report the pins connected to the net.
<code>-verbose</code>	Report the connections of each pin.
<code><i>instance_path</i></code>	Hierarchical path to a instance.

---

<b>report_lib_cell</b>	<code><i>cell_name</i></code> <code>[&gt; <i>filename</i>]</code> <code>[&gt;&gt; <i>filename</i>]</code>
<code><i>cell_name</i></code>	The name of a library cell.

Describe the liberty library cell `cell_name`.

---

<b>report_net</b>	[-connections] [-verbose] [-digits <i>digits</i> ] <i>net_path</i> [> <i>filename</i> ] [>> <i>filename</i> ]
-connections	Report the net pins.
-verbose	With -connections also report all pins connected to each instance pin net.
-digits <i>digits</i>	The number of digits after the decimal point to report. The default value is the variable <code>sta_report_default_digits</code> .
<i>net_path</i>	Hierarchical path to a net.

---

**report\_parasitic\_annotation** [-report\_unannotated]  
 [> *filename*]  
 [>> *filename*]

-report\_unannotated      Report unannotated and partially annotated nets.

Report SPEF parasitic annotation completeness.

---

<b>report_power</b>	[-instances <i>instances</i> ] [-digits <i>digits</i> ] [> <i>filename</i> ] [>> <i>filename</i> ]
-instances <i>instances</i>	Report the power for each instance of <i>instances</i> . If the instance is hierarchical the total power for the instances inside the hierarchical instance is reported.
-digits <i>digits</i>	The number of digits after the decimal point to report. The default value is the variable <code>sta_report_default_digits</code> .

The `report_power` command uses static power analysis based on propagated or annotated pin activities in the circuit using Liberty power models. The internal, switching, leakage and total power are reported. Design power is reported separately for combinational, sequential, macro and pad groups. Power values are reported in watts.

The `read_power_activities` command can be used to read activities from a file based on simulation. If no simulation activities are available, the `set_power_activity` command should be used to set the activity of

input ports or pins in the design. The default input activity and duty for inputs are 0.1 and 0.5 respectively. The activities are propagated from annotated input ports or pins through gates and used in the power calculations.

Group	Internal Power	Switching Power	Leakage Power	Total Power	
Sequential	3.29e-06	3.41e-08	2.37e-07	3.56e-06	92.4%
Combinational	1.86e-07	3.31e-08	7.51e-08	2.94e-07	7.6%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	3.48e-06 90.2%	6.72e-08 1.7%	3.12e-07 8.1%	3.86e-06	100.0%

---

**report\_pulse\_width\_checks** [-verbose]

[-digits *digits*]  
 [-no\_line\_splits]  
 [*pins*]  
 [> *filename*]  
 [>> *filename*]

-verbose                      Use a verbose output format.

-digits *digits*              The number of digits after the decimal point to report. The default value is the variable `sta_report_default_digits`.

-no\_line\_splits

*pins*                         List of pins or ports to report.

The `report_pulse_width_checks` command reports min pulse width checks for pins in the clock network. If *pins* is not specified all clock network pins are reported.

---

**report\_units**

Report the units used for command arguments and reporting.

```
report_units
time 1ns
capacitance 1pF
resistance 1kohm
voltage 1v
current 1A
power 1pW
distance 1um
```

---

<b>report_worst_slack</b>	[-min] [-max] [-digits <i>digits</i> ]
-max	Report the worst max/setup slack.
-min	Report the worst min/hold slack.
-digits <i>digits</i>	The number of digits after the decimal point to report. The default value is the variable <code>sta_report_default_digits</code> .

---

<b>set_assigned_check</b>	-setup -hold -recovery -removal [-rise] [-fall] [-corner <i>corner</i> ] [-min] [-max] [-from <i>from_pins</i> ] [-to <i>to_pins</i> ] [-clock rise fall] [-cond sdf_cond] [-worst] <i>margin</i>
-setup	Annotate setup timing checks.
-hold	Annotate hold timing checks.
-recovery	Annotate recovery timing checks.
-removal	Annotate removal timing checks.
-rise	Annotate rising delays.
-fall	Annotate falling delays.
-corner <i>corner</i>	The name of a process corner. The <code>-corner</code> keyword is required if more than one process corner is defined.
-min	Annotate the minimum value of the process corner.
-max	Annotate the maximum value of the process corner.

<code>-from <i>from_pins</i></code>	A list of pins for the clock.
<code>-to <i>to_pins</i></code>	A list of pins for the data.
<code>-clock rise fall</code>	The timing check clock pin transition.
<code><i>margin</i></code>	The timing check margin.

The `set_assigned_check` command is used to annotate the timing checks between two pins on an instance. The annotated delay overrides the calculated delay. This command is a interactive way to back-annotate delays like an SDF file.

---

<b><code>set_assigned_delay</code></b>	<code>-cell -net</code> <code>[-rise]</code> <code>[-fall]</code> <code>[-corner <i>corner</i>]</code> <code>[-min]</code> <code>[-max]</code> <code>[-from <i>from_pins</i>]</code> <code>[-to <i>to_pins</i>]</code> <code><i>delay</i></code>
<code>-cell</code>	Annotate the delays between two pins on an instance.
<code>-net</code>	Annotate the delays between two pins on a net.
<code>-rise</code>	Annotate the rising delays.
<code>-fall</code>	Annotate the falling delays.
<code>-corner <i>corner</i></code>	The name of a process corner. The <code>-corner</code> keyword is required if more than one process corner is defined.
<code>-min</code>	Annotate the minimum delays.
<code>-max</code>	Annotate the maximum delays.
<code>-from <i>from_pins</i></code>	A list of pins.
<code>-to <i>to_pins</i></code>	A list of pins.
<code><i>delay</i></code>	The delay between <i>from_pins</i> and <i>to_pins</i> .

The `set_assigned_delay` command is used to annotate the delays between two pins on an instance or net. The annotated delay overrides the calculated delay. This command is a interactive way to back-annotate delays like an SDF file.

Use the `-corner` keyword to specify a process corner. The `-corner` keyword is required if more than one process corner is defined.

---

<b>set_assigned_transition</b>	<code>[-rise]</code> <code>[-fall]</code> <code>[-corner <i>corner</i>]</code> <code>[-min]</code> <code>[-max]</code> <i>slew</i> <i>pin_list</i>
<code>-rise</code>	Annotate the rising transition.
<code>-fall</code>	Annotate the falling transition.
<code>-corner <i>corner</i></code>	Annotate delays for process <i>corner</i> .
<code>-min</code>	Annotate the minimum transition time.
<code>-max</code>	Annotate the maximum transition time.
<i>slew</i>	The pin transition time.
<i>pin_list</i>	A list of pins.

The `set_assigned_transition` command is used to annotate the transition time (slew) of a pin. The annotated transition time overrides the calculated transition time.

---

<b>set_case_analysis</b>	<code>0 1 zero one rise rising fall falling</code> <i>port_or_pin_list</i>
<i>port_or_pin_list</i>	A list of ports or pins.

The `set_case_analysis` command sets the signal on a port or pin to a constant logic value. No paths are propagated from constant pins. Constant values set with the `set_case_analysis` command are propagated through downstream gates.

---

<b>set_clock_gating_check</b>	<b>[ -setup <i>setup_time</i></b> <b>[ -hold <i>hold_time</i></b> <b>[ -rise</b> <b>[ -fall</b> <b>[ -high</b> <b>[ -low</b> <b>[ <i>objects</i></b>
-------------------------------	--

<b>-setup <i>setup_time</i></b>	Clock enable setup margin.
---------------------------------	----------------------------

<b>-hold <i>hold_time</i></b>	Clock enable hold margin.
-------------------------------	---------------------------

<b>-rise</b>	The setup/hold margin is for the rising edge of the clock enable.
--------------	---

<b>-fall</b>	The setup/hold margin is for the falling edge of the clock enable.
--------------	--

<b>-high</b>	The gating clock is active high (pin and instance objects only).
--------------	--

<b>-low</b>	The gating clock is active low (pin and instance objects only).
-------------	---

<b><i>objects</i></b>	A list of clocks, instances, pins or ports.
-----------------------	---

The `set_clock_gating_check` command is used to add setup or hold timing checks for data signals used to gate clocks.

If no objects are specified the setup/hold margin is global and applies to all clock gating circuits in the design. If neither of the `-rise` and `-fall` options are used the setup/hold margin applies to the rising and falling edges of the clock gating signal.

Normally the library cell function is used to determine the active state of the clock. The clock is active high for AND/NAND functions and active low for OR/NOR functions. The `-high` and `-low` options are used to specify the active state of the clock for other cells, such as a MUX.

If multiple `set_clock_gating_check` commands apply to a clock gating instance the priority of the commands is shown below (highest to lowest priority).

```
clock enable pin
instance
clock pin
clock
global
```

---

<b>set_clock_groups</b>	<b>[ -name <i>name</i></b> <b>[ -logically_exclusive</b> <b>[ -physically_exclusive</b> <b>[ -asynchronous</b> <b>[ -allow_paths</b> <b>-group <i>clocks</i></b>
-------------------------	---



-name <i>name</i>	The clock group name.
-logically_exclusive	The clocks in different groups do not interact logically but can be physically present on the same chip. Paths between clock groups are considered for noise analysis.
-physically_exclusive	The clocks in different groups cannot be present at the same time on a chip. Paths between clock groups are not considered for noise analysis.
-asynchronous	The clock groups are asynchronous. Paths between clock groups are considered for noise analysis.
-allow_paths	
<i>clocks</i>	A list of clocks in the group.

The `set_clock_groups` command is used to define groups of clocks that interact with each other. Clocks in different groups do not interact and paths between them are not reported. Use a `-group` argument for each clock group.

<b>set_clock_latency</b>	[-source] [-clock <i>clock</i> ] [-rise] [-fall] [-min] [-max] <i>delay</i> <i>objects</i>
-source	The latency is at the clock source.
-clock <i>clock</i>	If multiple clocks are defined at a pin this use this option to specify the latency for a specific clock.
-rise	The latency is for the rising edge of the clock.
-fall	The latency is for the falling edge of the clock.
-min	<i>delay</i> is the minimum latency.
-max	<i>delay</i> is the maximum latency.
<i>delay</i>	Clock source or insertion delay.

*objects*                                      A list of clocks, pins or ports.

The `set_clock_latency` command describes expected delays of the clock tree when analyzing a design using ideal clocks. Use the `-source` option to specify latency at the clock source, also known as insertion delay. Source latency is delay in the clock tree that is external to the design or a clock tree internal to an instance that implements a complex logic function.

---

<b>set_clock_transition</b>	<code>[-rise]</code> <code>[-fall]</code> <code>[-min]</code> <code>[-max]</code> <i>transition</i> <i>clocks</i>
<code>-rise</code>	Set the transition time for the rising edge of the clock.
<code>-fall</code>	Set the transition time for the falling edge of the clock.
<code>-min</code>	Set the min transition time.
<code>-max</code>	Set the min transition time.
<i>transition</i>	Clock transition time (slew).
<i>clocks</i>	A list of clocks.

The `set_clock_transition` command describes expected transition times of the clock tree when analyzing a design using ideal clocks.

---

<b>set_clock_uncertainty</b>	<code>[-from -rise_from -fall_from <i>from_clock</i>]</code> <code>[-to -rise_to -fall_to <i>to_clock</i>]</code> <code>[-rise]</code> <code>[-fall]</code> <code>[-setup]</code> <code>[-hold]</code> <i>uncertainty</i> <i>[objects]</i>
<code>-from <i>from_clock</i></code>	Inter-clock uncertainty source clock.
<code>-to <i>to_clock</i></code>	Inter-clock uncertainty target clock.
<code>-rise</code>	Inter-clock target clock rise edge, alternative to <code>-rise_to</code> . Inter-clock target clock rise edge, alternative to <code>-rise_to</code> .

<code>-fall</code>	Inter-clock target clock rise edge, alternative to <code>-fall_to</code> .
<code>-setup</code>	<i>uncertainty</i> is for setup checks.
<code>-hold</code>	<i>uncertainty</i> is for hold checks.
<i>uncertainty</i>	Clock uncertainty.
<i>objects</i>	A list of clocks, ports or pins.

The `set_clock_uncertainty` command specifies the uncertainty or jitter in a clock. The uncertainty for a clock can be specified on its source pin or port, or the clock itself.

```
set_clock_uncertainty .1 [get_clock clk1]
```

Inter-clock uncertainty between the source and target clocks of timing checks is specified with the `-from| -rise_from| -fall_from` and `-to| -rise_to| -fall_to` arguments .

```
set_clock_uncertainty -from [get_clock clk1] -to [get_clocks clk2] .1
```

The following commands are equivalent.

```
set_clock_uncertainty -from [get_clock clk1] -rise_to [get_clocks clk2] .1
set_clock_uncertainty -from [get_clock clk1] -to [get_clocks clk2] -rise .1
```

---

<b>set_cmd_units</b>	<code>[-capacitance <i>cap_unit</i></code> <code>[-resistance <i>res_unit</i></code> <code>[-time <i>time_unit</i></code> <code>[-voltage <i>voltage_unit</i></code> <code>[-current <i>current_unit</i></code> <code>[-power <i>power_unit</i></code> <code>[-distance <i>distance_unit</i></code>
<code>-capacitance <i>cap_unit</i></code>	The capacitance scale factor followed by 'f' .
<code>-resistance <i>res_unit</i></code>	The resistance scale factor followed by 'ohm' .
<code>-time <i>time_unit</i></code>	The time scale factor followed by 's'.
<code>-voltage <i>voltage_unit</i></code>	The voltage scale factor followed by 'v' .
<code>-current <i>current_unit</i></code>	The current scale factor followed by 'A' .
<code>-power <i>power_unit</i></code>	The power scale factor followed by 'w' .

-distance *distance\_unit* The distance scale factor followed by 'm'.

The `set_cmd_units` command is used to change the units used by the STA command interpreter when parsing commands and reporting results. The default units are the units specified in the first Liberty library file that is read.

Units are specified as a scale factor followed by a unit name. The scale factors are as follows.

```
M 1E+6
k 1E+3
m 1E-3
u 1E-6
n 1E-9
p 1E-12
f 1E-15
```

An example of the `set_units` command is shown below.

```
set_cmd_units -time ns -capacitance pF -current mA -voltage V
              -resistance kOhm -distance um
```

---

<b>set_data_check</b>	<code>[-from -rise_from -fall_from <i>from_pin</i>]</code> <code>[-to -rise_to -fall_to <i>to_pin</i>]</code> <code>[-setup]</code> <code>[-hold]</code> <code>[-clock <i>clock</i>]</code> <i>margin</i>
-----------------------	--

-from <i>from_pin</i>	A pin used as the timing check reference.
-----------------------	---

-to <i>to_pin</i>	A pin that the setup/hold check is applied to.
-------------------	--

-setup	Add a setup timing check.
--------	---------------------------

-hold	Add a hold timing check.
-------	--------------------------

-clock <i>clock</i>	The setup/hold check clock.
---------------------	-----------------------------

<i>margin</i>	The setup or hold time margin.
---------------	--------------------------------

The `set_data_check` command is used to add a setup or hold timing check between two pins.

---

**set\_disable\_inferred\_clock\_gating** *objects*

<i>objects</i>	A list of clock gating instances, clock gating pins, or clock enable pins.
----------------	--

The `set_disable_inferred_clock_gating` command disables clock gating checks on a clock gating instance, clock gating pin, or clock gating enable pin.

```
set_disable_timing    [-from from_port]  
                      [-to to_port]  
                      objects
```

-from *from\_port*

```
-to to_port
```

<i>objects</i>	A list of instances, ports, pins, cells, cell/port, or library/cell/port.
----------------	---

The `set_disable_timing` command is used to disable paths through pins in the design. There are many different forms of the command depending on the objects specified in *objects*.

All timing paths though an instance are disabled when *objects* contains an instance. Timing checks in the instance are *not* disabled.

```
set_disable_timing u2
```

The `-from` and `-to` options can be used to restrict the disabled path to those from, to or between specific pins on the instance.

```
set_disable_timing -from A u2
set_disable_timing -to Z u2
set_disable_timing -from A -to Z u2
```

A list of top level ports or instance pins can also be disabled.

```
set_disable_timing u2/Z
set_disable_timing in1
```

Timing paths through all instances of a library cell in the design can be disabled by naming the cell using a hierarchy separator between the library and cell name. Paths from or to a cell port can be disabled with the -from and -to options or a port name after library and cell names.

```
set_disable_timing liberty1/snl_bufx2
set_disable_timing -from A liberty1/snl_bufx
set_disable_timing -to Z liberty1/snl_bufx
set_disable_timing liberty1/snl_bufx2/A
```

---

<b>set_drive</b>	[-rise] [-fall] [-max] [-min] <i>resistance</i> <i>ports</i>
-rise	Set the drive rise resistance.
-fall	Set the drive fall resistance.
-max	Set the maximum resistance.
-min	Set the minimum resistance.
<i>resistance</i>	The external drive resistance.
<i>ports</i>	A list of ports.

The set\_drive command describes the resistance of an input port external driver.

---

<b>set_driving_cell</b>	[-lib_cell <i>cell_name</i> ] [-library <i>library</i> ] [-rise] [-fall] [-min] [-max] [-pin <i>pin</i> ] [-from_pin <i>from_pin</i> ] [-input_transition_rise <i>trans_rise</i> ] [-input_transition_fall <i>trans_fall</i> ] <i>ports</i>
-lib_cell <i>cell_name</i>	The driving cell.
-library <i>library</i>	The driving cell library.
-rise	Set the driving cell for a risingn edge.
-fall	Set the driving cell for a falling edge.
-max	Set the driving cell for max delays.
-min	Set the driving cell for min delays.

<code>-pin <i>pin</i></code>	The output port of the driving cell.
<code>-from_pin <i>from_pin</i></code>	Use timing arcs from <i>from_pin</i> to the output pin.
<code>-input_transition_rise <i>trans_rise</i></code>	The transition time for a rising input at <i>from_pin</i> .
<code>-input_transition_fall <i>trans_fall</i></code>	The transition time for a falling input at <i>from_pin</i> .
<code><i>ports</i></code>	A list of ports.

The `set_driving_cell` command describes an input port external driver.

---

<b><code>set_false_path</code></b>	<code>[-setup]</code> <code>[-hold]</code> <code>[-rise]</code> <code>[-fall]</code> <code>[-from <i>from_list</i>]</code> <code>[-rise_from <i>from_list</i>]</code> <code>[-fall_from <i>from_list</i>]</code> <code>[-through <i>through_list</i>]</code> <code>[-rise_through <i>through_list</i>]</code> <code>[-fall_through <i>through_list</i>]</code> <code>[-to <i>to_list</i>]</code> <code>[-rise_to <i>to_list</i>]</code> <code>[-fall_to <i>to_list</i>]</code> <code>[-reset_path]</code>
<code>-setup</code>	Apply to setup checks.
<code>-hold</code>	Apply to hold checks.
<code>-rise</code>	Apply to rising path edges.
<code>-fall</code>	Apply to falling path edges.
<code>-reset_path</code>	Remove any matching <code>set_false_path</code> , <code>set_multicycle_path</code> , <code>set_max_delay</code> , <code>set_min_delay</code> exceptions first.
<code>-from <i>from_list</i></code>	A list of clocks, instances, ports or pins.
<code>-through <i>through_list</i></code>	A list of instances, pins or nets.

**-to** *to\_list*                      A list of clocks, instances, ports or pins.

The `set_false_path` command disables timing along a path from, through and to a group of design objects.

Objects in *from\_list* can be clocks, register/latch instances, or register/latch clock pins. The `-rise_from` and `-fall_from` keywords restrict the false paths to a specific clock edge.

Objects in *through\_list* can be nets, instances, instance pins, or hierarchical pins,. The `-rise_through` and `-fall_through` keywords restrict the false paths to a specific path edge that traverses through the object.

Objects in *to\_list* can be clocks, register/latch instances, or register/latch clock pins. The `-rise_to` and `-fall_to` keywords restrict the false paths to a specific transition at the path end.

---

**set\_fanout\_load**                      *fanout*  
   *port\_list*

This command is ignored.

---

**set\_hierarchy\_separator** *separator*

*separator*                              Character used to separate hierarchical names.

Set the character used to separate names in a hierarchical instance, net or pin name. This separator is used by the command interpreter to read arguments and print results. The default separator is `'/'`.

---

**set\_ideal\_latency**                      [-rise] [-fall] [-min] [-max] *delay objects*

The `set_ideal_latency` command is parsed but ignored.

---

**set\_ideal\_network**                      [-no\_propagation] *objects*

The `set_ideal_network` command is parsed but ignored.

---

**set\_ideal\_transition**                      [-rise] [-fall] [-min] [-max] *transition\_time objects*

The `set_ideal_transition` command is parsed but ignored.



---

<b>set_input_delay</b>	[-rise] [-fall] [-max] [-min] [-clock <i>clock</i> ] [-clock_fall] [-reference_pin <i>ref_pin</i> ] [-source_latency_included] [-network_latency_included] [-add_delay] <i>delay</i> <i>port_pin_list</i>
-rise	Set the arrival time for the rising edge of the input.
-fall	Set the arrival time for the falling edge of the input.
-max	Set the maximum arrival time.
-min	Set the minimum arrival time.
-clock <i>clock</i>	The arrival time is from <i>clock</i> .
-clock_fall	The arrival time is from the falling edge of <i>clock</i> .
-reference_pin <i>ref_pin</i>	The arrival time is with respect to the clock that arrives at <i>ref_pin</i> .
-source_latency_included	Do not add the clock source latency (insertion delay) to the delay value.
-network_latency_included	Do not add the clock latency to the delay value when the clock is ideal.
-add_delay	Add this arrival to any existing arrivals.
<i>delay</i>	The arrival time after <i>clock</i> .
<i>pin_port_list</i>	A list of pins or ports.

The set\_input\_delay command is used to specify the arrival time of an input signal.

The following command sets the min, max, rise and fall times on the in1 input port 1.0 time units after the rising edge of clk1.

```
set_input_delay -clock clk1 1.0 [get_ports in1]
```

Use multiple commands with the `-add_delay` option to specify separate arrival times for min, max, rise and fall times or multiple clocks. For example, the following specifies separate arrival times with respect to clocks `clk1` and `clk2`.

```
set_input_delay -clock clk1 1.0 [get_ports in1]
set_input_delay -add_delay -clock clk2 2.0 [get_ports in1]
```

The `-reference_pin` option is used to specify an arrival time with respect to the arrival on a pin in the clock network. For propagated clocks, the input arrival time is relative to the clock arrival time at the reference pin (the clock source latency and network latency from the clock source to the reference pin). For ideal clocks, input arrival time is relative to the reference pin clock source latency. With the `-clock_fall` flag the arrival time is relative to the falling transition at the reference pin. If no clocks arrive at the reference pin the `set_input_delay` command is ignored. If no `-clock` is specified the arrival time is with respect to all clocks that arrive at the reference pin. The `-source_latency_included` and `-network_latency_included` options cannot be used with `-reference_pin`.

Paths from inputs that do not have an arrival time defined by `set_input_delay` are not reported. Set the `sta_input_port_default_clock` variable to 1 to report paths from inputs without a `set_input_delay`.

---

<b>set_input_transition</b>	[-rise] [-fall] [-max] [-min] <i>transition</i> <i>port_list</i>
-rise	Set the rising edge transition.
-fall	Set the falling edge transition.
-max	Set the minimum transition time.
-min	Set the maximum transition time.
<i>transition</i>	The transition time (slew).
<i>port_list</i>	A list of ports.

The `set_input_transition` command is used to specify the transition time (slew) of an input signal.

---

**set\_level\_shifter\_strategy** [-rule *rule\_type*]

This command is parsed and ignored by timing analysis.

---

**set\_level\_shifter\_threshold** [-voltage *voltage*]

This command is parsed and ignored by timing analysis.

---

<b>set_load</b>	<b>[ -rise]</b> <b>[ -fall]</b> <b>[ -max]</b> <b>[ -min]</b> <b>[ -subtract_pin_load]</b> <b>[ -pin_load]</b> <b>[ -wire_load]</b> <i>capacitance</i> <i>objects</i>
<b>-rise</b>	Set the rising capacitance.
<b>-fall</b>	Set the falling capacitance.
<b>-max</b>	Set the max capacitance.
<b>-min</b>	Set the min capacitance.
<b>-subtract_pin_load</b>	Subtract the capacitance of all instance pins connected to the net from <i>wire-capacitance</i> .
<b>-pin_load</b>	<i>capcitanace</i> is external instance pin capacitance (ports only).
<b>-wire_load</b>	<i>capcitanace</i> is external wire capacitance (ports only).
<i>capacitance</i>	The capacitance, in library capacitance units.
<i>objects</i>	A list of nets or ports.

The set\_load command annotates capacitance on a net or port.

Ports can have external wire or pin capacitance that is annotated separately with the -pin\_load and -wire\_load options. Without the -pin\_load and -wire\_load options pin capacitance is annotated. External capacitances are used by delay calculator to find output driver delays and transition times.

Net wire capacitance can also be annotated with the set\_load command. If the -subtract\_pin\_load option is specified the capacitance of all instance pins connected to the net is subtracted from *capacitance*. set\_load command annotates capacitance has precedence over RC SPEF parasitics.

---

<b>set_logic_dc</b>	<i>port_list</i>
<i>port_pin_list</i>	List of ports or pins.

Set a port or pin to a constant unknown logic value. No paths are propagated from constant pins.

---

<b>set_logic_one</b>	<i>port_list</i>
----------------------	------------------

<i>port_pin_list</i>	List of ports or pins.
----------------------	------------------------

Set a port or pin to a constant logic one value. No paths are propagated from constant pins. Constant values set with the set\_logic\_one command are **not** propagated through downstream gates.

---

<b>set_logic_zero</b>	<i>port_list</i>
-----------------------	------------------

<i>port_pin_list</i>	List of ports or pins.
----------------------	------------------------

Set a port or pin to a constant logic zero value. No paths are propagated from constant pins. Constant values set with the set\_logic\_zero command are **not** propagated through downstream gates.

---

<b>set_max_area</b>	<i>area</i>
---------------------	-------------

<i>area</i>	
-------------	--

The set\_max\_area command is ignored during timing but is included in SDC files that are written.

---

<b>set_max_capacitance</b>	<i>capacitance</i> <i>objects</i>
----------------------------	--------------------------------------

<i>capacitance</i>	
--------------------	--

<i>objects</i>	List of ports or cells.
----------------	-------------------------

The set\_max\_capacitance command is ignored during timing but is included in SDC files that are written.

---

<b>set_max_delay</b>	[-rise] [-fall] [-from <i>from_list</i> ] [-rise_from <i>from_list</i> ] [-fall_from <i>from_list</i> ] [-through <i>through_list</i> ] [-rise_through <i>through_list</i> ] [-fall_through <i>through_list</i> ] [-to <i>to_list</i> ] [-rise_to <i>to_list</i> ] [-fall_to <i>to_list</i> ] [-reset_path] [-ignore_clock_latency] <i>delay</i>
-rise	Set max delay for rising paths.
-fall	Set max delay for falling paths.
-from <i>from_list</i>	A list of clocks, instances, ports or pins.
-through <i>through_list</i>	A list of instances, pins or nets.
-to <i>to_list</i>	A list of clocks, instances, ports or pins.
-ignore_clock_latency	Ignore clock latency at the source and target registers.
-reset_path	Remove any matching set_false_path, set_multicycle_path, set_max_delay, set_min_delay exceptions first.
<i>delay</i>	The maximum delay.

The set\_max\_delay command constrains the maximum delay through combinational logic paths. See set\_false\_path for a description of allowed *from\_list*, *through\_list* and *to\_list* objects. If the *to\_list* ends at a timing check the setup/hold time is included in the path delay.

When the -ignore\_clock\_latency option is used clock latency at the source and destination of the path delay is ignored. The constraint is reported in the default path group (\*\*default\*\*) rather than the clock path group when the path ends at a timing check.

---

**set\_max\_dynamic\_power**    *power* [*unit*]

The set\_max\_dynamic\_power command is ignored.

---

<b>set_max_fanout</b>	<i>fanout</i> <i>objects</i>
-----------------------	---------------------------------

*fanout*

*objects*                      List of ports or cells.

The set\_max\_fanout command is ignored during timing but is included in SDC files that are written.

---

<b>set_max_leakage_power</b>	<i>power</i> [ <i>unit</i> ]
------------------------------	------------------------------

The set\_max\_leakage\_power command is ignored.

---

<b>set_max_time_borrow</b>	<i>delay</i> <i>objects</i>
----------------------------	--------------------------------

*delay*                      The maximum time the latches can borrow.

*objects*                      List of clocks, instances or pins.

The set\_max\_time\_borrow command specifies the maximum amount of time that latches can borrow. Time borrowing is the time that a data input to a transparent latch arrives after the latch opens.

---

<b>set_max_transition</b>	[-data_path] [-clock_path] [-rise] [-fall] <i>transition</i> <i>objects</i>
---------------------------	--

-data\_path                      Set the max slew for data paths.

-clock\_path                      Set the max slew for clock paths.

-rise                              Set the max slew for rising paths.

-fall                               Set the max slew for falling paths.

*transition*                      The maximum slew/transition time.

*objects*                      List of clocks, ports or designs.

The `set_max_transition` command specifies the maximum transition time (slew) design rule checked by the `report_constraint -max_transition` command.

If specified for a design, the default maximum transition is set for the design.

If specified for a clock, the maximum transition is applied to all pins in the clock domain. The `-clock_path` option restricts the maximum transition to clocks in clock paths. The `-data_path` option restricts the maximum transition to clocks data paths. The `-clock_path`, `-data_path`, `-rise` and `-fall` options only apply to clock objects.

---

<b>set_min_capacitance</b>	<i>capacitance</i> <i>objects</i>
<i>capacitance</i>	Minimum capacitance.
<i>objects</i>	List of ports or cells.

The `set_min_capacitance` command is ignored during timing but is included in SDC files that are written.

---

<b>set_min_delay</b>	<code>[-rise]</code> <code>[-fall]</code> <code>[-from from_list]</code> <code>[-rise_from from_list]</code> <code>[-fall_from from_list]</code> <code>[-through through_list]</code> <code>[-rise_through through_list]</code> <code>[-fall_through through_list]</code> <code>[-to to_list]</code> <code>[-rise_to to_list]</code> <code>[-fall_to to_list]</code> <code>[-ignore_clock_latency]</code> <code>[-reset_path]</code> <i>delay</i>
<code>-rise</code>	Set min delay for rising paths.
<code>-fall</code>	Set min delay for falling paths.
<code>-from from_list</code>	A list of clocks, instances, ports or pins.
<code>-through through_list</code>	A list of instances, pins or nets.
<code>-to to_list</code>	A list of clocks, instances, ports or pins.
<code>-ignore_clock_latency</code>	Ignore clock latency at the source and target registers.

-reset_path	Remove any matching set_false_path, set_multicycle_path, set_max_delay, set_min_delay exceptions first.
delay	The minimum delay.

The set\_min\_delay command constrains the minimum delay through combinational logic. See set\_false\_path for a description of allowed *from\_list*, *through\_list* and *to\_list* objects. If the *to\_list* ends at a timing check the setup/hold time is included in the path delay.

When the -ignore\_clock\_latency option is used clock latency at the source and destination of the path delay is ignored. The constraint is reported in the default path group (\*\*default\*\*) rather than the clock path group when the path ends at a timing check.

---

set_min_pulse_width	[-high] [-low] <i>min_width</i> <i>objects</i>
-high	Set the minimum high pulse width.
-low	Set the minimum low pulse width.
<i>min_width</i>	
<i>objects</i>	List of pins, instances or clocks.

If -low and -high are not specified the minimum width applies to both high and low pulses.



---

<b>set_multicycle_path</b>	[-setup] [-hold] [-rise] [-fall] [-start] [-end] [-from <i>from_list</i> ] [-rise_from <i>from_list</i> ] [-fall_from <i>from_list</i> ] [-through <i>through_list</i> ] [-rise_through <i>through_list</i> ] [-fall_through <i>through_list</i> ] [-to <i>to_list</i> ] [-rise_to <i>to_list</i> ] [-fall_to <i>to_list</i> ] [-reset_path] <i>path_multiplier</i>
-setup	Set cycle count for setup checks.
-hold	Set cycle count for hold checks.
-rise	Set cycle count for rising path edges.
-fall	Set cycle count for falling path edges.
-start	Multiply the source clock period by <i>period_multiplier</i> .
-end	Multiply the target clock period by <i>period_multiplier</i> .
-from <i>from_list</i>	A list of clocks, instances, ports or pins.
-through <i>through_list</i>	A list of instances, pins or nets.
-to <i>to_list</i>	A list of clocks, instances, ports or pins.
-reset_path	Remove any matching set_false_path, set_multicycle_path, set_max_delay, set_min_delay exceptions first.
<i>path_multiplier</i>	The number of clock periods to add to the path required time.

Normally the path between two registers or latches is assumed to take one clock cycle. The set\_multicycle\_path command overrides this assumption and allows multiple clock cycles for a timing check. See set\_false\_path for a description of allowed *from\_list*, *through\_list* and *to\_list* objects.

---

<b>set_operating_conditions</b>	[-analysis_type single bc_wc on_chip_variation] [-library <i>lib</i> ] [ <i>condition</i> ] [-min <i>min_condition</i> ] [-max <i>max_condition</i> ] [-min_library <i>min_lib</i> ] [-max_library <i>max_lib</i> ]
-analysis_type single	Use one operating condition for min and max paths.
-analysis_type bc_wc	Best case, worst case analysis. Setup checks use <i>max_condition</i> for clock and data paths. Hold checks use the <i>min_condition</i> for clock and data paths.
-analysis_type on_chip_variation	The min and max operating conditions represent variations on the chip that can occur simultaneously. Setup checks use <i>max_condition</i> for data paths and <i>min_condition</i> for clock paths. Hold checks use <i>min_condition</i> for data paths and <i>max_condition</i> for clock paths. This is the default analysis type.
-library <i>lib</i>	The name of the library that contains <i>condition</i> .
<i>condition</i>	The operating condition for analysis type single.
-min <i>min_condition</i>	The operating condition to use for min paths and hold checks.
-max <i>max_condition</i>	The operating condition to use for max paths and setup checks.
-min_library <i>min_lib</i>	The name of the library that contains <i>min_condition</i> .
-max_library <i>max_lib</i>	The name of the library that contains <i>max_condition</i> .

The set\_operating\_conditions command is used to specify the type of analysis performed and the operating conditions used to derate library data.

---

<b>set_output_delay</b>	[-rise] [-fall] [-max] [-min] [-clock <i>clock</i> ] [-clock_fall] [-reference_pin <i>ref_pin</i> ] [-source_latency_included] [-network_latency_included] [-add_delay] <i>delay</i> <i>port_pin_list</i>
-------------------------	--

<code>-rise</code>	Set the output delay for the rising edge of the input.
<code>-fall</code>	Set the output delay for the falling edge of the input.
<code>-max</code>	Set the maximum output delay.
<code>-min</code>	Set the minimum output delay.
<code>-clock <i>clock</i></code>	The external check is to <i>clock</i> . The default clock edge is rising.
<code>-clock_fall</code>	The external check is to the falling edge of <i>clock</i> .
<code>-reference_pin <i>ref_pin</i></code>	The external check is clocked by the clock that arrives at <i>ref_pin</i> .
<code>-add_delay</code>	Add this output delay to any existing output delays.
<i>delay</i>	The external delay to the check clocked by <i>clock</i> .
<i>pin_port_list</i>	A list of pins or ports.

The `set_output_delay` command is used to specify the external delay to a setup/hold check on an output port or internal pin that is clocked by *clock*. Unless the `-add_delay` option is specified any existing output delays are replaced.

The `-reference_pin` option is used to specify a timing check with respect to the arrival on a pin in the clock network. For propagated clocks, the timing check is relative to the clock arrival time at the reference pin (the clock source latency and network latency from the clock source to the reference pin). For ideal clocks, the timing check is relative to the reference pin clock source latency. With the `-clock_fall` flag the timing check is relative to the falling edge of the reference pin. If no clocks arrive at the reference pin the `set_output_delay` command is ignored. If no `-clock` is specified the timing check is with respect to all clocks that arrive at the reference pin. The `-source_latency_included` and `-network_latency_included` options cannot be used with `-reference_pin`.

---

<b><code>set_port_fanout_number</code></b>	<code>[-min]</code> <code>[-max]</code> <i>fanout</i> <i>ports</i>
<code>-min</code>	Set the min fanout.
<code>-max</code>	Set the max fanout.
<i>fanout</i>	The external fanout of the ports.
<i>port_list</i>	A list of ports.

Set the external fanout for *ports*.

---

<b>set_power_activity</b>	<code>[-global]</code> <code>[-input]</code> <code>[-input_ports <i>ports</i>]</code> <code>[-pins <i>pins</i>]</code> <code>[-activity <i>activity</i>]</code> <code>[-duty <i>duty</i>]</code>
<code>-global</code>	Set the activity/duty for all non-clock pins.
<code>-input</code>	Set the default input port activity/duty.
<code>-input_ports <i>input_ports</i></code>	Set the input port activity/duty.
<code>-pins <i>pins</i></code>	Set the pin activity/duty.
<code>-activity <i>activity</i></code>	The activity, or number of transitions per clock cycle.
<code>-duty <i>duty</i></code>	The duty, or probability the signal is high. Defaults to 0.5.

The `set_power_activity` command is used to set the activity and duty used for power analysis globally or for input ports or pins in the design.

The default input activity and duty for inputs are 0.1 and 0.5 respectively, which is equivalent to the following command:

```
set_power_activity -input -activity 0.1 -duty 0.5
```

---

<b>set_propagated_clock</b>	<i>objects</i>
<i>objects</i>	A list of clocks, ports or pins.

The `set_propagated_clock` command changes a clock tree from an ideal network that has no delay one that uses calculated or back-annotated gate and interconnect delays. When *objects* is a port or pin, clock delays downstream of the object are used.

---

<b>set_pvt</b>	<code>[-min]</code> <code>[-max]</code> <code>[-process <i>process</i>]</code> <code>[-voltage <i>voltage</i>]</code> <code>[-temperature <i>temperature</i>]</code> <i>instances</i>
----------------	--

<code>-min</code>	Set the PVT values for max delays.
-------------------	------------------------------------

<code>-max</code>	Set the PVT values for min delays.
-------------------	------------------------------------

<code>-process <i>process</i></code>	A process value (float).
--------------------------------------	--------------------------

<code>-voltage <i>voltage</i></code>	A voltage value (float).
--------------------------------------	--------------------------

<code>-temperature <i>temperature</i></code>	A temperature value (float).
--	------------------------------

<i>instances</i>	A list instances.
------------------	-------------------

The `set_pvt` command sets the process, voltage and temperature values used during delay calculation for a specific instance in the design.

---

<b>set_sense</b>	<code>[-type clock data]</code> <code>[-positive]</code> <code>[-negative]</code> <code>[-pulse <i>pulse_type</i>]</code> <code>[-stop_propagation]</code> <code>[-clock <i>clocks</i>]</code> <i>pins</i>
------------------	--

---

<code>-type clock</code>	Set the sense for clock paths.
--------------------------	--------------------------------

<code>-type data</code>	Set the sense for data paths (not supported).
-------------------------	---

<code>-positive</code>	The clock sense is positive unate.
------------------------	------------------------------------

---

<code>-negative</code>	The clock sense is negative unate.
------------------------	------------------------------------

---

<b>-pulse</b> <i>pulse_type</i>	rise_triggered_high_pulse rise_triggered_low_pulse fall_triggered_high_pulse fall_triggered_low_pulse Not supported.
<b>-stop_propagation</b>	Stop propagating <i>clocks</i> at <i>pins</i> .

---

<i>clocks</i>	A list of clocks to apply the sense.
<i>pins</i>	A list of pins.

---

The `set_sense` command is used to modify the propagation of a clock signal. The clock sense is set with the `-positive` and `-negative` flags. Use the `-stop_propagation` flag to stop the clock from propagating beyond a pin. The `-positive`, `-negative`, `-stop_propagation`, and `-pulse` options are mutually exclusive. If the `-clock` option is not used the command applies to all clocks that traverse *pins*. The `-pulse` option is currently not supported.

---

<b>set_timing_derate</b>	[-rise] [-fall] [-early] [-late] [-clock] [-data] [-net_delay] [-cell_delay] [-cell_check] <i>derate</i> <i>[objects]</i>
<b>-rise</b>	Set the derating for rising delays.
<b>-fall</b>	Set the derating for falling delays.
<b>-early</b>	Derate early (min) paths.
<b>-late</b>	Derate late (max) paths.
<b>-clock</b>	Derate paths in the clock network.
<b>-data</b>	Derate data paths.
<b>-net_delay</b>	Derate net (interconnect) delays.

---

<code>-cell_delay</code>	Derate cell delays.
<code>-cell_check</code>	Derate cell timing check margins.
<code>derate</code>	The derating factor to apply to delays.
<code>objects</code>	A list of instances, library cells, or nets.

The `set_timing_derate` command is used to derate delay calculation results used by the STA. If the `-early` and `-late` flags are omitted the both min and max paths are derated. If the `-clock` and `-data` flags are not used the derating both clock and data paths are derated.

Use the `unset_timing_derate` command to remove all derating factors.

---

<b><code>set_resistance</code></b>	<code>[-max]</code> <code>[-min]</code> <i>resistance</i> <i>nets</i>
<code>-min</code>	The resistance for minimum path delay calculation.
<code>-max</code>	The resistance for maximum path delay calculation.
<i>resistance</i>	The net resistance.
<i>nets</i>	A list of nets.

---

<b><code>set_units</code></b>	<code>[-capacitance <i>cap_unit</i>]</code> <code>[-resistance <i>res_unit</i>]</code> <code>[-time <i>time_unit</i>]</code> <code>[-voltage <i>voltage_unit</i>]</code> <code>[-current <i>current_unit</i>]</code> <code>[-power <i>power_unit</i>]</code> <code>[-distance <i>distance_unit</i>]</code>
<code>-capacitance <i>cap_unit</i></code>	The capacitance scale factor followed by 'f'.
<code>-resistance <i>res_unit</i></code>	The resistance scale factor followed by 'ohm'.
<code>-time <i>time_unit</i></code>	The time scale factor followed by 's'.

-*voltage voltage\_unit*     The voltage scale factor followed by 'v' .

-*current current\_unit*     The current scale factor followed by 'A' .

-*power power\_unit*         The power scale factor followed by 'w' .

The set\_units command is used to **check** the units used by the STA command interpreter when parsing commands and reporting results. If the current units differ from the set\_unit value a warning is printed. Use the set\_cmd\_units command to change the command units.

Units are specified as a scale factor followed by a unit name. The scale factors are as follows.

```
M 1E+6
k 1E+3
m 1E-3
u 1E-6
n 1E-9
p 1E-12
f 1E-15
```

An example of the set\_units command is shown below.

```
set_units -time ns -capacitance pF -current mA -voltage V -resistance kOhm
```

---

**set\_wire\_load\_min\_block\_size** *size*

The set\_wire\_load\_min\_block\_size command is not supported.

---

**set\_wire\_load\_mode**            top|enclosed|segmented

top

enclosed

segmented

The set\_wire\_load\_mode command is ignored during timing but is included in SDC files that are written.

---

**set\_wire\_load\_model**        -name *model\_name*  
                               [-library *library*]  
                               [-max]  
                               [-min]  
                               [*objects*]



<b>-name</b> <i>model_name</i>	The name of a wire load model.
<b>-library</b> <i>library</i>	Library to look for <i>model_name</i> .
<b>-max</b>	The wire load model is for maximum path delays.
<b>-min</b>	The wire load model is for minimum path delays.
<i>objects</i>	Not supported.

---

**set\_wire\_load\_selection\_group** [-library *library*]  
 [-max]  
 [-min]  
*group\_name*  
 [*objects*]

<i>library</i>	Library to look for <i>group_name</i> .
<b>-max</b>	The wire load selection is for maximum path delays.
<b>-min</b>	The wire load selection is for minimum path delays.
<i>group_name</i>	A wire load selection group name.
<i>objects</i>	Not supported.

The set\_wire\_load\_selection\_group command is parsed but not supported.

---

**source** [-echo]  
 [-verbose]  
*filename*  
 [> *log\_filename*]  
 [>> *log\_filename*]

<b>-echo</b>	Print each command before evaluating it.
<b>-verbose</b>	Print each command before evaluating it as well as the result it returns.
<i>filename</i>	The name of the file containing commands to read.
> <i>log_filename</i>	Redirect command output to <i>log_filename</i> .

>> *log\_filename*                      Redirect command output and append *log\_filename*.

Read STA/SDC/Tcl commands from *filename*.

The source command stops and reports any errors encountered while reading a file unless *sta\_continue\_on\_error* is 1.

---

**unset\_case\_analysis**            *port\_or\_pin\_list*

*port\_or\_pin\_list*                      A list of ports or pins.

The *unset\_case\_analysis* command removes the constant values defined by the *set\_case\_analysis* command.

---

**unset\_clock\_latency**            [-source]  
                                  *objects*

---

-source                                Specifies source clock latency (clock insertion delay).

*objects*                                A list of clocks, pins or ports.

The *unset\_clock\_latency* command removes the clock latency set with the *set\_clock\_latency* command.

---

**unset\_clock\_transition**        *clocks*

*clocks*                                A list of clocks.

The *unset\_clock\_transition* command removes the clock transition set with the *set\_clock\_transition* command.

---

**unset\_clock\_uncertainty** [-from|-rise\_from|-fall\_from *from\_clock*]  
                              [-to|-rise\_to|-fall\_to *to\_clock*]  
                              [-rise]  
                              [-fall]  
                              [-setup]  
                              [-hold]  
                              [*objects*]

-from *from\_clock*

-to *to\_clock*

<code>-rise</code>	The uncertainty is for the rising edge of the clock.
<code>-fall</code>	The uncertainty is for the falling edge of the clock.
<code>-setup</code>	<i>uncertainty</i> is the setup check uncertainty.
<code>-hold</code>	<i>uncertainty</i> is the hold uncertainty.
<i>uncertainty</i>	Clock uncertainty.
<i>objects</i>	A list of clocks, ports or pins.

The `unset_clock_uncertainty` command removes clock uncertainty defined with the `set_clock_uncertainty` command.

---

<b><code>unset_data_check</code></b>	<code>[-from -rise_from -fall_from <i>from_object</i>]</code> <code>[-to -rise_to -fall_to <i>to_object</i>]</code> <code>[-setup]</code> <code>[-hold]</code> <code>[-clock <i>clock</i>]</code>
<code>-from <i>from_object</i></code>	A pin used as the timing check reference.
<code>-to <i>to_object</i></code>	A pin that the setup/hold check is applied to.
<code>-setup</code>	Add a setup timing check.
<code>-hold</code>	Add a hold timing check.
<i>clock</i>	The setup/hold check clock.

The `unset_clock_transition` command removes a setup or hold check defined by the `set_data_check` command.

---

### **`unset_disable_inferred_clock_gating` *objects***

<i>objects</i>	A list of clock gating instances, clock gating pins, or clock enable pins.
----------------	--

The `unset_disable_inferred_clock_gating` command removes a previous `set_disable_inferred_clock_gating` command.

---

<b>unset_disable_timing</b>	[-from <i>from_port</i> ] [-to <i>to_port</i> ] <i>objects</i>
-----------------------------	--

*from\_port*

*to\_port*

*objects*                      A list of instances, ports, pins, cells or [library/]cell/port.

The unset\_disable\_timing command is used to remove the effect of previous set\_disable\_timing commands.

---

<b>unset_input_delay</b>	[-rise] [-fall] [-max] [-min] [-clock <i>clock</i> ] [-clock_fall] <i>port_pin_list</i>
--------------------------	---

-rise                      Unset the arrival time for the rising edge of the input.

-fall                      Unset the arrival time for the falling edge of the input.

-max                      Unset the minimum arrival time.

-min                      Unset the maximum arrival time.

*clock*                      Unset the arrival time from *clock*.

-clock\_fall              Unset the arrival time from the falling edge of *clock*

*pin\_port\_list*            A list of pins or ports.

The unset\_input\_delay command removes a previously defined set\_input\_delay.

---

<b>unset_output_delay</b>	[-rise] [-fall] [-max] [-min] [-clock <i>clock</i> ] [-clock_fall] <i>port_pin_list</i>
-rise	This is the arrival time for the rising edge of the input.
-fall	This is the arrival time for the falling edge of the input.
-max	This is the minimum arrival time.
-min	This is the maximum arrival time.
<i>clock</i>	The arrival time is from this clock.
-clock_fall	The arrival time is from the falling edge of <i>clock</i>
<i>pin_port_list</i>	A list of pins or ports.

The unset\_output\_delay command a previously defined set\_output\_delay.

---

<b>unset_path_exceptions</b>	[-setup] [-hold] [-rise] [-fall] [-from -rise_from -fall_from <i>from</i> ] [-through -rise_through -fall_through <i>through</i> ] [-to -rise_to -fall_to <i>to</i> ]
-setup	Unset path exceptions for setup checks.
-hold	Unset path exceptions for hold checks.
-rise	Unset path exceptions for rising path edges.
-fall	Unset path exceptions for falling path edges.
-from <i>from</i>	A list of clocks, instances, ports or pins.

-through <i>through</i>	A list of instances, pins or nets.
-to <i>to</i>	A list of clocks, instances, ports or pins.

The unset\_path\_exceptions command removes any matching set\_false\_path, set\_multicycle\_path, set\_max\_delay, and set\_min\_delay exceptions.

---

### **unset\_propagated\_clock** *objects*

<i>objects</i>	A list of clocks, ports or pins.
----------------	----------------------------------

Remove a previous set\_propagated\_clock command.

---

### **unset\_timing\_derate**

Remove all derating factors set with the set\_timing\_derate command.

---

### **user\_run\_time**

Returns the total user cpu run time in seconds as a float.

---

### **with\_output\_to\_variable** *var* { *commands* }

<i>var</i>	The name of a variable to save the output of <i>commands</i> to.
------------	--

<i>commands</i>	TCL commands that the output will be redirected from.
-----------------	---

The with\_output\_to\_variable command redirects the output of TCL commands to a variable.

---

<b>write_path_spice</b>	-path_args <i>path_args</i> -spice_directory <i>spice_directory</i> -lib_subckt_file <i>lib_subckts_file</i> -model_file <i>model_file</i> -power <i>power</i> -ground <i>ground</i>
<i>path_args</i>	-from -through -to arguments as in report_checks.
<i>spice_directory</i>	Spice output directory.
<i>lib_subckts_file</i>	Cell transistor level subckts.

<i>model_file</i>	Transistor model definitions .included by <i>spice_file</i> .
<i>power</i>	Voltage supply name in <i>voltage_map</i> of the default liberty library.
<i>ground</i>	Ground supply name in <i>voltage_map</i> of the default liberty library.

The `write_path_spice` command writes a spice netlist for timing paths. Use *path\_args* to specify -from/-through/-to as arguments to the `find_timing_paths` command. For each path, a spice netlist and the subckts referenced by the path are written in *spice\_directory*. The spice netlist is written in `path_<id>.sp` and subckt file is `path_<id>.subckt`.

The spice netlists used by the path are written to *subckt\_file*, which *spice\_file* .includes. The device models used by the spice subckt netlists in *model\_file* are also .included in *spice\_file*. Power and ground names are specified with the -power and -ground arguments. The spice netlist includes a piecewise linear voltage source at the input and .measure statement for each gate delay and pin slew.

Example command:

```
write_path_spice -path_args {-from "in0" -to "out1" -unconstrained} \
  -spice_directory $result_dir \
  -lib_subckt_file "write_spice1.subckt" \
  -model_file "write_spice1.models" \
  -power VDD -ground VSS
```

---

<b>write_sdc</b>	[-digits <i>digits</i> ] [-gzip] [-no_timestamp] <i>filename</i>
<i>digits</i>	The number of digits after the decimal point to report. The default is 4.
-gzip	Compress the SDC with gzip.
-no_timestamp	Do not include a time and date in the SDC file.
<i>filename</i>	The name of the file to write the constraints to.

Write the constraints for the design in SDC format to *filename*.

---

<b>write_sdf</b>	[-corner <i>corner</i> ] [-divider / .] [-include_typ] [-digits <i>digits</i> ] [-gzip] [-no_timestamp] [-no_version] <i>filename</i>
<i>corner</i>	Write delays for <i>corner</i> .
-divider	Divider to use between hierarchy levels in pin and instance names.
-include_typ	Include a 'typ' value in the SDF triple that is the average of min and max delays to satisfy some Verilog simulators that require three values in the delay triples.
-digits <i>digits</i>	The number of digits after the decimal point to report. The default is 4.
-gzip	Compress the SDF using gzip.
-no_timestamp	Do not write a DATE statement.
-no_version	Do not write a VERSION statement.
<i>filename</i>	The SDF filename to write.

Write the delay calculation delays for the design in SDF format to *filename*. The SDF TIMESCALE is same as the *time\_unit* in the first liberty file read.

---

<b>write_timing_model</b>	[-library_name <i>lib_name</i> ] [-cell_name <i>cell_name</i> ] [-corner <i>corner</i> ] <i>filename</i>
-library_name <i>lib_name</i>	The name to use for the liberty library. Defaults to <i>cell_name</i> .
-cell_name <i>cell_name</i>	The name to use for the liberty cell. Defaults to the top level module name.
-corner <i>corner</i>	The process corner to use for extracting the model.
<i>filename</i>	Filename for the liberty timing model.

The `write_timing_model` command constructs a liberty timing model for the current design and writes it to *filename*. *cell\_name* defaults to the cell name of the top level block in the design.



The SDC used to extract the block should include the clock definitions. If the block contains a clock network `set_propagated_clock` should be used so the clock delays are included in the timing model. The following SDC commands are ignored when bulding the timing model.

```
set_input_delay
set_output_delay
set_load
set_timing_derate
```

Using `set_input_transition` with the slew from the block context will be used will improve the match between the timing model and the block netlist. Paths defined on clocks that are defined on internal pins are ignored because the model has no way to include the clock definition.

The resulting timing model can be used in a hierarchical timing flow as a replacement for the block to speed up timing analysis. This hierarchical timing methodology does not handle timing exceptions that originate or terminate inside the block. The timing model includes:

```
combinational paths between inputs and outputs
setup and hold timing constraints on inputs
clock to output timing paths
```

Resistance of long wires on inputs and outputs of the block cannot be modeled in Liberty. To reduce inaccuracies from wire resistance in technologies with resistive wires place buffers on inputs and ouputs.

The extracted timing model setup/hold checks are scalar (no input slew dependence). Delay timing arcs are load dependent but do not include input slew dependency.

---

<b>write_verilog</b>	<code>[-sort]</code> <code>[-include_pwr_gnd]</code> <code>[-remove_cells lib_cells]</code> <i>filename</i>
<code>-sort</code>	Sort the instances in the netlist.
<code>-include_pwr_gnd</code>	Incluce power and ground pins on instances.
<code>-remove_cells lib_cells</code>	Liberty cells to remove from the verilog netlist. Use <code>get_lib_cells</code> , a list of cells names, or a cell name with wildcards.
<i>filename</i>	Filename for the liberty library.

The `write_verilog` command writes a verilog netlist to *filename*. Use `-sort` to sort the instances so the results are reproducible across operating systems. Use `-remove_cells` to remove instances of *lib\_cells* from the netlist.

## Variables

---

<b>hierarchy_separator</b>	Any character.
----------------------------	----------------

The `hierarchy_separator` separates instance names in a hierarchical instance, net, or pin name. The default value is `'/'`.

---

<b>link_make_black_boxes</b>	0 1
------------------------------	-----

When `link_make_black_boxes` is 1 the `link_design` command will make empty “black box” cells for instances that reference undefined cells. The default value is 1.

---

<b>sta_bidirect_net_paths_enabled</b>	0 1
---------------------------------------	-----

When set to 0, paths from bidirectional (inout) ports back through nets are disabled. When set to 1, paths from bidirectional paths from the net back into the instance are enabled. The default value is 0.

---

<b>sta_continue_on_error</b>	0 1
------------------------------	-----

The source and read\_sdc commands stop and report any errors encountered while reading a file unless `sta_continue_on_error` is 1. The default value is 0.

---

<b>sta_crpr_mode</b>	same_pin same_transition
----------------------	--------------------------

When the data and clock paths of a timing check overlap (see `sta_crpr_enabled`), pessimism is removed independent of whether of the path rise/fall transitions. When `sta_crpr_mode` is `same_transition`, the pessimism is only removed if the path rise/fall transitions are the same. The default value is `same_pin`.

---

<b>sta_cond_default_arcs_enabled</b>	0 1
--------------------------------------	-----

When set to 0, default timing arcs with no condition (Liberty timing arcs with no “when” expression) are disabled if there are other conditional timing arcs between the same pins. The default value is 1.

---

<b>sta_crpr_enabled</b>	0 1
-------------------------	-----

During min/max timing analysis for on\_chip\_variation the data and clock paths may overlap. For a setup check the maximum path delays are used for the data and the minimum path delays are used for the clock. Because the gates cannot simultaneously have minimum and maximum delays the timing check slack is pessimistic. This pessimism is known as Common Reconvergent Pessimism Removal, or “CRPR”. Enabling CRPR slows down the analysis. The default value is 1.

---

<b>sta_dynamic_loop_breaking</b>	0 1
----------------------------------	-----

When `sta_dynamic_loop_breaking` is 0, combinational logic loops are disabled by disabling a timing arc that closes the loop. When `sta_dynamic_loop_breaking` is 1, all paths around the loop are reported. The default value is 0.

---

<b>sta_gated_clock_checks_enabled</b>	0 1
---------------------------------------	-----

When `sta_gated_clock_checks_enabled` is 1, clock gating setup and hold timing checks are checked. The default value is 1.

---

<b><code>sta_input_port_default_clock</code></b>	<b><code>0 1</code></b>
--	-------------------------

When `sta_input_port_default_clock` is 1 a default input arrival is added for input ports that do not have an arrival time specified with the `set_input_delay` command. The default value is 0.

---

<b><code>sta_internal_bidirect_instance_paths_enabled</code></b>	<b><code>0 1</code></b>
--	-------------------------

When set to 0, paths from bidirectional (inout) ports back into the instance are disabled. When set to 1, paths from bidirectional ports back into the instance are enabled. The default value is 0.

---

<b><code>sta_pocv_enabled</code></b>	<b><code>0 1</code></b>
--------------------------------------	-------------------------

Enable parametric on chip variation using statistical timing analysis. The default value is 0.

---

<b><code>sta_propagate_all_clocks</code></b>	<b><code>0 1</code></b>
--	-------------------------

All clocks defined after `sta_propagate_all_clocks` is set to 1 are propagated. If it is set before any clocks are defined it has the same effect as

```
set_propagated_clock [all_clocks]
```

after all clocks have been defined. The default value is 0.

---

<b><code>sta_propagate_gated_clock_enable</code></b>	<b><code>0 1</code></b>
--	-------------------------

When set to 1, paths of gated clock enables are propagated through the clock gating instances. If the gated clock controls sequential elements setting `sta_propagate_gated_clock_enable` to 0 prevents spurious paths from the clock enable. The default value is 1.

---

<b><code>sta_recovery_removal_checks_enabled</code></b>	<b><code>0 1</code></b>
---	-------------------------

When `sta_recovery_removal_checks_enabled` is 0, recovery and removal timing checks are disabled. The default value is 1.

---

<b><code>sta_report_default_digits</code></b>	<b><code>integer</code></b>
---	-----------------------------

The number of digits to print after a decimal point. The default value is 2.

---

<b>sta_preset_clear_arcs_enabled</b>	0 1
--------------------------------------	-----

When set to 1, paths through asynchronous preset and clear timing arcs are searched. The default value is 0.

Version 2.4.0, Jan 18, 2023

Copyright (c) 2023, Parallax Software, Inc.

This program is free software: you can redistribute it and/or modify it under the terms of the GNU General Public License as published by the Free Software Foundation, either version 3 of the License, or (at your option) any later version.

This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU General Public License for more details.

You should have received a copy of the GNU General Public License along with this program. If not, see <https://www.gnu.org/licenses/>.