



CODEC driver



CODEC driver

The CODEC driver registers a `struct snd_soc_component_driver` . Before v4.17, it was `struct snd_soc_codec_driver` . Also registers a `struct snd_soc_dai_driver`

linux

```
int snd_soc_register_component(struct device *dev,  
                             const struct snd_soc_component_driver *component_driver,  
                             struct snd_soc_dai_driver *dai_drv, int num_dai); int  
devm_snd_soc_register_component(struct device *dev,  
                               const struct snd_soc_component_driver *component_driver,  
                               struct snd_soc_dai_driver *dai_drv, int num_dai);
```



```
struct snd_soc_component_driver {  
    const char *name;  
  
    /* Default control and setup, added after probe() is run */  
    const struct snd_kcontrol_new *controls;  
    unsigned int num_controls;  
    const struct snd_soc_dapm_widget *dapm_widgets;  
    unsigned int num_dapm_widgets;  
    const struct snd_soc_dapm_route *dapm_routes;  
    unsigned int num_dapm_routes;  
  
    int (*probe)(struct snd_soc_component *component);  
    void (*remove)(struct snd_soc_component *component);  
    int (*suspend)(struct snd_soc_component *component);  
    int (*resume)(struct snd_soc_component *component);  
};
```



snd_soc_component_driver

```
[ ... ]
```



- ▶ `struct snd_kcontrol_new *controls` is an array of controls (volume, mixing, muxing, switches) available on the CODEC.
- ▶ `struct snd_soc_dapm_widget *dapm_widgets` is an array of power management controls so ASoC can power down the routes that are not currently used.
- ▶ `struct snd_soc_dapm_route *dapm_routes` is an array describing those routes.



```
/* component wide operations */
int (*set_sysclk)(struct snd_soc_component *component,
                  int clk_id, int source, unsigned int freq, int
dir);

int (*set_pll)(struct snd_soc_component *component, int pll_id,
               int source, unsigned int freq_in, unsigned int
freq_out);
[ ... ]
int (*hw_params)(struct snd_soc_component *component,
                 struct snd_pcm_substream *substream,
                 struct snd_pcm_hw_params *params);
[ ... ]
}
```



- ▶ `set_sysclk` allows setting the input clock of the component.
- ▶ `set_pll` allows setting the PLLs, this is mostly useful when the component is the clock producer.
- ▶ `hw_params` is a callback called on PCM stream setup. When called, all the parameters of the stream are known so it is possible to configure the component to handle the stream correctly.
- ▶ Those are mostly not used, the DAI specific callbacks are used instead.



```
/*
 * Digital Audio Interface Driver.
 *
 * Describes the Digital Audio Interface in terms of its ALSA, DAI and AC97
 * operations and capabilities. Codec and platform drivers will register
this
 * structure for every DAI they have.
 *
 * This structure covers the clocking, formatting and ALSA operations for
each
 * interface.
 */
struct snd_soc_dai_driver {
    /* DAI description */
    const char *name;
```



```
[...]  
  
/* ops */  
const struct snd_soc_dai_ops *ops;  
const struct snd_soc_cdai_ops *cops;  
  
/* DAI capabilities */  
struct snd_soc_pcm_stream capture;  
struct snd_soc_pcm_stream playback;  
[...]  
};
```




linux

```
/* SoC PCM stream information */
struct snd_soc_pcm_stream {
    const char *stream_name;
    u64 formats;
    unsigned int rates;
    unsigned int rate_min;
    unsigned int rate_max;
    unsigned int channels_min;
    unsigned int channels_max;
    unsigned int sig_bits;
};

/* SNDRV_PCM_FMTBIT_* */
/* SNDRV_PCM_RATE_* */
/* min rate */
/* max rate */
/* min channels */
/* max channels */
/* number of bits of content */
```



PCM5102






```
static struct snd_soc_dai_driver pcm5102a_dai = {
    .name = "pcm5102a-hifi",
    .playback = {
        .channels_min = 2,
        .channels_max = 2,
        .rates = SNDRV_PCM_RATE_8000_384000,
        .formats = SNDRV_PCM_FMTBIT_S16_LE |
                   SNDRV_PCM_FMTBIT_S24_LE |
                   SNDRV_PCM_FMTBIT_S32_LE
    },
};

static struct snd_soc_component_driver soc_component_dev_pcm5102a = {
    .idle_bias_on = 1,
    .use_pmdown_time = 1,
```



```
        .endianness          = 1,  
};  
  
static int pcm5102a_probe(struct platform_device *pdev)  
{  
    return devm_snd_soc_register_component(&pdev->dev,  
&soc_component_dev_pcm5102a,  
                                           &pcm5102a_dai, 1);  
}
```





```
#define PCM3008_RATES (SNDRV_PCM_RATE_32000 | SNDRV_PCM_RATE_44100  
|  
                        SNDRV_PCM_RATE_48000)  
  
static struct snd_soc_dai_driver pcm3008_dai = {  
    .name = "pcm3008-hifi",  
    .playback = {  
        .stream_name = "PCM3008 Playback",  
        .channels_min = 1,  
        .channels_max = 2,  
        .rates = PCM3008_RATES,  
        .formats = SNDRV_PCM_FMTBIT_S16_LE,  
    },  
    .capture = {  
        .stream_name = "PCM3008 Capture",
```



```
        .channels_min = 1,  
        .channels_max = 2,  
        .rates = PCM3008_RATES,  
        .formats = SNDRV_PCM_FMTBIT_S16_LE,  
    },  
};
```



```
static const struct snd_soc_component_driver soc_component_dev_pcm3008 = {
    .dapm_widgets          = pcm3008_dapm_widgets,
    .num_dapm_widgets      = ARRAY_SIZE(pcm3008_dapm_widgets),
    .dapm_routes           = pcm3008_dapm_routes,
    .num_dapm_routes       = ARRAY_SIZE(pcm3008_dapm_routes),
    .idle_bias_on          = 1,
    .use_pmdown_time       = 1,
    .endianness            = 1,
};

static int pcm3008_codec_probe(struct platform_device *pdev)
{
    [...]

    return devm_snd_soc_register_component(&pdev->dev,
```



```
}  
    &soc_component_dev_pcm3008, &pcm3008_dai, 1);
```



```
static const struct snd_soc_dapm_widget pcm3008_dapm_widgets[] = {
    SND_SOC_DAPM_INPUT("VINL"), SND_SOC_DAPM_INPUT("VINR"),

    SND_SOC_DAPM_DAC_E("DAC", NULL, SND_SOC_NOPM, 0, 0, pcm3008_dac_ev,
        SND_SOC_DAPM_PRE_PMU | SND_SOC_DAPM_POST_PMD),
    SND_SOC_DAPM_ADC_E("ADC", NULL, SND_SOC_NOPM, 0, 0, pcm3008_adc_ev,
        SND_SOC_DAPM_PRE_PMU | SND_SOC_DAPM_POST_PMD),

    SND_SOC_DAPM_OUTPUT("VOUTL"), SND_SOC_DAPM_OUTPUT("VOUTR"),
};

static const struct snd_soc_dapm_route pcm3008_dapm_routes[] = {
    { "PCM3008 Capture", NULL, "ADC" },
    { "ADC", NULL, "VINL" },
    { "ADC", NULL, "VINR" },
}
```



```
{ "DAC", NULL, "PCM3008 Playback" },  
{ "VOUTL", NULL, "DAC" },  
{ "VOUTR", NULL, "DAC" },  
};
```