

Document Title	Specification of SPI Handler/Driver
Document Owner	AUTOSAR
Document Responsibility	AUTOSAR
Document Identification No	38

Document Status	published
Part of AUTOSAR Standard	Classic Platform
Part of Standard Release	R23-11

Document Change History			
Date	Release	Changed by	Change Description
2023-11-23	R23-11	AUTOSAR Release Management	<ul style="list-style-type: none"> SWS_Spi_00389 moved to mandatory interfaces Editorial changes
2022-11-24	R22-11	AUTOSAR Release Management	<ul style="list-style-type: none"> Reworked or rephrased requirements: SWS_Spi_NA_00999, SWS_Spi_00126, SWS_Spi_00151, ECUC_Spi_00220, SWS_Spi_00377, SWS_Spi_00389, SWS_Spi_00150, ECUC_Spi_00214 Editorial changes

Document Change History			
Date	Release	Changed by	Change Description
2021-11-25	R21-11	AUTOSAR Release Management	<ul style="list-style-type: none"> Chapter 10 diagrams updated New configuration parameter: ECUC_Spi_00249 Reworked or rephrased requirements: SWS_Spi_00128, SWS_Spi_00382, SWS_Spi_00360, SWS_Spi_00170, SWS_Spi_00150, SWS_Spi_00185, SWS_Spi_00328, SWS_Spi_00329, SWS_Spi_00154, ECUC_Spi_00208, ECUC_Spi_00214, ECUC_Spi_00202, ECUC_Spi_00204, ECUC_Spi_00205, ECUC_Spi_00234, ECUC_Spi_00242, ECUC_Spi_00197, ECUC_Spi_00198, ECUC_Spi_00199, ECUC_Spi_00236 Removed requirements: SWS_Spi_00108, SWS_Spi_00155, SWS_Spi_00152, SWS_Spi_00271, SWS_Spi_00008, SWS_Spi_00009, SWS_Spi_00010, SWS_Spi_00063, SWS_Spi_00064, SWS_Spi_00344 Editorial changes, errors descriptions updated, SpiDataWidth up to 64bits
2020-11-30	R20-11	AUTOSAR Release Management	<ul style="list-style-type: none"> Error sections refactored New configuration parameters: SWS_Spi_00247, SWS_Spi_00248 Removed requirements: SWS_Spi_00008, SWS_Spi_00009, SWS_Spi_00010, SWS_Spi_00063 and SWS_Spi_00064 Chapter 8.2: enumeration types have the values specified
2019-11-28	R19-11	AUTOSAR Release Management	<ul style="list-style-type: none"> SWS_Spi_00082 removed Changed Document Status from Final to published
2018-10-31	4.4.0	AUTOSAR Release Management	<ul style="list-style-type: none"> Editorial changes

Document Change History			
Date	Release	Changed by	Change Description
2017-12-08	4.3.1	AUTOSAR Release Management	<ul style="list-style-type: none"> SPI_E_SEQ_IN_PROCESS and SPI_E_SEQ_PENDING are migrated to runtime errors The notion of prearranged bus is removed to simplify the use Modified or removed requirements: SWS_Spi_00135, SWS_Spi_00324, SWS_Spi_00039 Restored requirement: SWS_Spi_00035
2016-11-30	4.3.0	AUTOSAR Release Management	<ul style="list-style-type: none"> Requirements removed: SWS_Spi_00339, SWS_Spi_00191, SWS_Spi_00367, SWS_Spi_00239, SWS_Spi_00056, SWS_Spi_00076, SWS_Spi_00148 Requirements updated: SWS_Spi_00999, SWS_Spi_00092 Improvement of the traceability with SRS BSW General requirements Editorial changes
2015-07-31	4.2.2	AUTOSAR Release Management	<ul style="list-style-type: none"> Cleanup of requirements chapter Debugging support marked as obsolete Editorial changes
2014-10-31	4.2.1	AUTOSAR Release Management	<ul style="list-style-type: none"> Added SWS_Spi_00383, SWS_Spi_00384, SWS_Spi_00385, SWS_Spi_00386 and ECUC_Spi_00243 New configuration parameter SpiUser-CallbackHeaderFile SPI hardware error is applicable for sync and async transmits Editorial changes
2014-03-31	4.1.3	AUTOSAR Release Management	<ul style="list-style-type: none"> Description for Spi_AsyncTransmit and Spi_SyncTransmit development errors for already ongoing transmission Clarification of Spi Channel width and data access type relation

Document Change History			
Date	Release	Changed by	Change Description
2013-10-31	4.1.2	AUTOSAR Release Management	<ul style="list-style-type: none">• ECUC_Spi_00242 (added)• ECUC_Spi_00240 (added)• SWS_Spi_00189 (modified)• Editorial changes• Removed chapter(s) on change documentation
2013-03-15	4.1.1	AUTOSAR Administration	<ul style="list-style-type: none">• Added chapter 7.6 and 7.7, table from chapter 7.4 moved to chapter 7.7• SWS_Spi_00129 removed, SWS_Spi_00128 reformulated• ECUC_Spi_00180, ECUC_Spi_00204 Lengh is in data elements instead of bytes• MemMap header file rename• Added Subchapter 3.x due to SWS General Rollout

Document Change History			
Date	Release	Changed by	Change Description
2011-12-22	4.0.3	AUTOSAR Administration	<ul style="list-style-type: none"> • Rephrased: requirement SWS_Spi_00002, SWS_Spi_00046, SWS_Spi_00129, SWS_Spi_00233, SWS_Spi_00163, SPI 171, SWS_Spi_00172, SWS_Spi_00289 and SWS_Spi_00290, block 2 in chapter 7.2.2 • Removed: requirement SPI083; SPI132, SPI284 and SPI107 removed from statement • Corrected: Dem_EventStatusType in SWS_Spi_00191, Spi_SyncTransmit Syn/Async changed to Synchronous, SPI_E_PARAM_POINTER in SWS_Spi_00371, • Reference to MCU in SWS_Spi_00244 and SWS_Spi_00342 • Added: requirement SWS_Spi_00140, chapter 10 - SpiCsSelection, SWS_Spi_00194 - SPI_JOB_QUEUED state introduced, SWS_Spi_00195 with error table update • Modified: SWS_Spi_00114 and SWS_Spi_00135, chapter 10 - SpiEnableCs
2010-09-30	3.1.5	AUTOSAR Administration	<ul style="list-style-type: none"> • Added SWS_Spi_00369, SWS_Spi_00371, SWS_Spi_00370 • Removed SPI190, SPI094 • Updated configuration: base on min-max value for defined parameter; SpiHwUnit belongs to SpiExternalDevice Container; updated SpiTimeClk2Cs

Document Change History			
Date	Release	Changed by	Change Description
2010-02-02	3.1.4	AUTOSAR Administration	<ul style="list-style-type: none">• Splitting and refinement of several requirements• Removal of redundant requirements• Introduction of new IDs to allow implementation of debugging concept• Inserted UML diagram in chapter 9• Updating of Chapter 10 with the inclusion of 2 new container and the definition of the Chip Select configuration• Legal disclaimer revised
2008-08-13	3.1.1	AUTOSAR Administration	<ul style="list-style-type: none">• Legal disclaimer revised
2007-12-21	3.0.1	AUTOSAR Administration	<ul style="list-style-type: none">• Updated Chapter 10 with the inclusion of CS configuration• Document meta information extended• Small layout adaptations made
2007-01-24	2.1.15	AUTOSAR Administration	<ul style="list-style-type: none">• Configuration Specification updating• General rephrasing for clarification• Syntax error• Legal disclaimer revised• Release Notes added• “Advice for users” revised• “Revision Information” added
2006-05-16	2.0	AUTOSAR Administration	<ul style="list-style-type: none">• Document structure adapted to common Release 2.0 SWS Template.• Major changes in chapter 10• Structure of document changed partly• Other changes see chapter 13
2005-05-31	1.0	AUTOSAR Administration	<ul style="list-style-type: none">• Initial Release

Disclaimer

This work (specification and/or software implementation) and the material contained in it, as released by AUTOSAR, is for the purpose of information only. AUTOSAR and the companies that have contributed to it shall not be liable for any use of the work.

The material contained in this work is protected by copyright and other types of intellectual property rights. The commercial exploitation of the material contained in this work requires a license to such intellectual property rights.

This work may be utilized or reproduced without any modification, in any form or by any means, for informational purposes only. For any other purpose, no part of the work may be utilized or reproduced, in any form or by any means, without permission in writing from the publisher.

The work has been developed for automotive applications only. It has neither been developed, nor tested for non-automotive applications.

The word AUTOSAR and the AUTOSAR logo are registered trademarks.

Table of Contents

1	Introduction and functional overview	11
2	Acronyms and abbreviations.....	12
3	Related documentation	13
3.1	Input documents.....	13
3.2	Related standards and norms	13
3.3	Related specification	14
4	Constraints and assumptions.....	14
4.1	Limitations	14
4.2	Applicability to car domains.....	14
5	Dependencies to other modules	15
6	Requirements traceability	16
7	Functional specification.....	19
7.1	Overall view of functionalities and features	19
7.2	General behaviour.....	20
7.2.1	Common configurable feature: Allowed Channel Buffers	23
7.2.2	LEVEL 0, Simple Synchronous behaviour	25
7.2.3	LEVEL 1, Basic Asynchronous behavior	26
7.2.4	Asynchronous configurable feature: Interruptible Sequences	28
7.2.5	LEVEL 2, Enhanced behaviour.....	30
7.3	Scheduling Advices	31
7.4	Error classification	31
7.4.1	Development Errors	31
7.4.2	Runtime Errors	32
7.4.3	Transient faults.....	32
7.4.4	Production Errors	32
7.4.5	Extended Production Errors.....	32
8	API specification.....	34
8.1	Imported types.....	34
8.2	Type definitions	34
8.2.1	Spi_ConfigType.....	34
8.2.2	Spi_StatusType.....	34
8.2.3	Spi_JobResultType.....	35
8.2.4	Spi_SeqResultType	36
8.2.5	Spi_DataBufferType.....	37
8.2.6	Spi_NumberOfDataType.....	38
8.2.7	Spi_ChannelType	38
8.2.8	Spi_JobType	39
8.2.9	Spi_SequenceType.....	39
8.2.10	Spi_HWUnitType.....	39
8.2.11	Spi_AsyncModeType	40
8.3	Function definitions	41
8.3.1	Spi_Init	41

8.3.2	Spi_DeInit.....	42
8.3.3	Spi_WriteIB	43
8.3.4	Spi_AsyncTransmit	45
8.3.5	Spi_ReadIB	48
8.3.6	Spi_SetupEB.....	49
8.3.7	Spi_GetStatus	52
8.3.8	Spi_GetJobResult	52
8.3.9	Spi_GetSequenceResult.....	53
8.3.10	Spi_GetVersionInfo	54
8.3.11	Spi_SyncTransmit	55
8.3.12	Spi_GetHWUnitStatus	57
8.3.13	Spi_Cancel.....	58
8.3.14	Spi_SetAsyncMode.....	59
8.4	Callback notifications.....	60
8.5	Scheduled functions.....	60
8.5.1	Spi_MainFunction_Handling.....	60
8.6	Expected Interfaces.....	61
8.6.1	Mandatory Interfaces	61
8.6.2	Optional Interfaces	61
8.6.3	Configurable interfaces	62
8.7	Error detection	64
8.7.1	API parameter checking.....	64
8.7.2	SPI state checking	65
8.7.3	SPI runtime checking	66
9	Sequence diagrams	67
9.1	Initialization	67
9.2	Modes transitions	67
9.3	Write/AsyncTransmit/Read (IB).....	68
9.3.1	One Channel, one Job then one Sequence	68
9.3.2	Many Channels, one Job then one Sequence	70
9.3.3	Many Channels, many Jobs and one Sequence.....	71
9.3.4	Many Channels, many Jobs and many Sequences	73
9.4	Setup/AsyncTransmit (EB)	74
9.4.1	Variable Number of Data / Constant Number of Data	74
9.4.2	One Channel, one Job then one Sequence	75
9.4.3	Many Channels, one Job then one Sequence	77
9.4.4	Many Channels, many Jobs and one Sequence.....	78
9.4.5	Many Channels, many Jobs and many Sequences	80
9.5	Mixed Jobs Transmission.....	82
9.6	LEVEL 0 SyncTransmit diagrams	82
9.6.1	Write/SyncTransmit/Read (IB): Many Channels, many Jobs and one Sequence	82
9.6.2	Setup/SyncTransmit (EB): Many Channels, many Jobs and one Sequence	83
10	Configuration specification.....	85
10.1	How to read this chapter	85
10.2	Containers and configuration parameters	85
10.2.1	Spi 85	

10.2.2 SpiDemEventParameterRefs.....	86
10.2.3 SpiGeneral	87
10.2.4 SpiSequence.....	94
10.2.5 SpiChannel.....	97
10.2.6 SpiChannelList.....	101
10.2.7 SpiJob	103
10.2.8 SpiExternalDevice.....	106
10.2.9 SpiDriver	115
10.2.10 SpiPublishedInformation.....	118
10.3 Published information	119
10.4 Configuration concept.....	119
11 Not applicable requirements	121
12 Appendix	122

1 Introduction and functional overview

The SPI Handler/Driver provides services for reading from and writing to devices connected via SPI busses. It provides access to SPI communication to several users (e.g. EEPROM, Watchdog, I/O ASICs). It also provides the required mechanism to configure the onchip SPI peripheral.

This specification describes the API for a monolithic SPI Handler/Driver. This software module includes handling and driving functionalities. Main objectives of this monolithic SPI Handler/Driver are to take the best of each microcontroller features and to allow implementation optimization depending on static configuration to fit as much as possible to ECU needs.

Hence, this specification defines selectable levels of functionalities and configurable features to allow the design of a high scalable module that exploits the peculiarities of the microcontroller.

To configure the SPI Handler/Driver these steps shall be followed:

- SPI Handler/Driver Level of Functionality shall be selected and optional features configured.
- SPI Channels shall be defined according to data usage, and they could be buffered inside the SPI Handler/Driver (IB) or provided by the user (EB).
- SPI Jobs shall be defined according to HW properties (CS), and they will contain a list of channels using those properties.
- As a final step, Sequences of Jobs shall be defined, in order to transmit data in a sorted way (priority sorted).

The SPI Handler/Driver can transmit data frames in asynchronous or synchronous way according to the API function called and the level of functionality selected.

The specification covers the Handler/Driver functionality combined in one single module. One is the SPI handling part that handles multiple access to busses that could be located in the ECU Abstraction layer. The other part is the SPI driver that accesses the microcontroller hardware directly that could be located in the Microcontroller Abstraction layer.

2 Acronyms and abbreviations

Acronyms and abbreviations which have a local scope and therefore are not contained in the AUTOSAR glossary must appear in a local glossary.

Acronym:	Description:
DET	Default Error Tracer – module to which errors are reported.
DEM	Diagnostic Event Manager – module to which production relevant errors are reported.
SPI	Serial Peripheral Interface. It is exactly defined hereafter in this document.
CS	Chip Select
MISO	Master Input Slave Output
MOSI	Master Output Slave Input

Abbreviation:	Description:
EB	Externally buffered channels. Buffers containing data to transfer are outside the SPI Handler/Driver.
IB	Internally buffered channels. Buffers containing data to transfer are inside the SPI Handler/Driver.
ID	Identification Number of an element (Channel, Job, Sequence).

Definition:	Description:
Channel	A Channel is a software exchange medium for data that are defined with the same criteria: Config. Parameters, Number of Data elements with same size and data pointers (Source & Destination) or location.
Job	A Job is composed of one or several Channels with the same Chip Select (one chip select = one external device). A Job is considered atomic and therefore cannot be interrupted by another Job. A Job has an assigned priority. Depending on the configuration, the CS may be kept asserted for the whole job (so for all the Channels) or released for each data frame at SPI bus level.
Sequence	A Sequence is a number of consecutive Jobs to transmit but it can be rescheduled between Jobs using a priority mechanism. A Sequence transmission is interruptible (by another Sequence transmission) or not depending on a static configuration.
Data frame	A data frame is the physical frame of bits on the SPI bus in relation with SpiDataWidth.

3 Related documentation

3.1 Input documents

- [1] Layered Software Architecture
AUTOSAR_CP_EXP_LayeredSoftwareArchitecture.pdf
- [2] General Requirements on SPAL
AUTOSAR_CP_SRS_SPALGeneral.pdf
- [3] General Requirements on Basic Software Modules
AUTOSAR_CP_SRS_BSWGeneral.pdf
- [4] Specification of Default Error Tracer
AUTOSAR_CP_SWS_DefaultErrorTracer.pdf
- [5] Specification of ECU Configuration
AUTOSAR_CP_TPS_ECUConfiguration.pdf
- [6] Requirements on SPI Handler/Driver
AUTOSAR_CP_SRS_SPIHandlerDriver.pdf
- [7] Specification of Diagnostic Event Manager
AUTOSAR_CP_SWS_DiagnosticEventManager.pdf
- [8] Glossary
AUTOSAR_FO_TR_Glossary.pdf
- [9] Specification of MCU Driver
AUTOSAR_CP_SWS_MCUDriver .pdf
- [10] Specification of PORT Driver
AUTOSAR_CP_SWS_PORTDriver
- [11] Basic Software Module Description Template,
AUTOSAR_CP_TPS_BSWModuleDescriptionTemplate.pdf
- [12] List of Basic Software Modules
AUTOSAR_CP_TR_BSWModuleList
- [13] Specification of Standard Types,
AUTOSAR_CP_SWS_StandardTypes.pdf
- [14] General Specification of Basic Software Modules
AUTOSAR_CP_SWS_BSWGeneral.pdf

3.2 Related standards and norms

Not related.

3.3 Related specification

AUTOSAR provides a General Specification on Basic Software modules [14] (SWS BSW General), which is also valid for SPI Handler Driver.

Thus, the specification SWS BSW General shall be considered as additional and required specification for SPI Handler Driver.

4 Constraints and assumptions

4.1 Limitations

[SWS_Spi_00040] 「The SPI Handler/Driver handles only the Master mode.」()

[SWS_Spi_00050] 「The SPI Handler/Driver only supports full-duplex mode.」()

4.2 Applicability to car domains

No restrictions.

5 Dependencies to other modules

[SWS_Spi_00244] 「The SPI Handler/Driver module does not take care of setting the registers which configure the clock, prescaler(s) and PLL in its init function. This has to be done by the MCU module [9].」()

Note: SPI peripherals may depend on the system clock, prescaler(s) and PLL. Thus, any change of the system clock (e.g. PLL on / PLL off / clock dividers) may also affect the clock settings of the SPI hardware.

[SWS_Spi_00342] 「Depending on microcontrollers, the SPI peripheral could share registers with other peripherals. In this typical case, the SPI Handler/Driver has a relationship with MCU module [9] for initialising and de-initialising those registers.」()

[SWS_Spi_00343] 「If Chip Selects are done using microcontroller pins the SPI Handler/Driver has a relationship with PORT module [10]. In this case, this specification assumes that these microcontroller pins are directly accessed by the SPI Handler/Driver module without using APIs of DIO module. Anyhow, the SPI depends on ECU hardware design and for that reason it may depend on other modules.」()

6 Requirements traceability

Requirement	Description	Satisfied by
SRS_BSW_00101	The Basic Software Module shall be able to initialize variables and hardware in a separate initialization function	SWS_Spi_00013, SWS_Spi_00015
SRS_BSW_00323	All AUTOSAR Basic Software Modules shall check passed API parameters for validity	SWS_Spi_00031, SWS_Spi_00032, SWS_Spi_00060
SRS_BSW_00327	Error values naming convention	SWS_Spi_00004
SRS_BSW_00335	Status values naming convention	SWS_Spi_00019, SWS_Spi_00061, SWS_Spi_00062, SWS_Spi_00373
SRS_BSW_00336	Basic SW module shall be able to shutdown	SWS_Spi_00021, SWS_Spi_00022
SRS_BSW_00337	Classification of development errors	SWS_Spi_00004
SRS_BSW_00359	All AUTOSAR Basic Software Modules callback functions shall avoid return types other than void if possible	SWS_Spi_00048
SRS_BSW_00360	AUTOSAR Basic Software Modules callback functions are allowed to have parameters	SWS_Spi_00048
SRS_BSW_00369	All AUTOSAR Basic Software Modules shall not return specific development error codes via the API	SWS_Spi_00048
SRS_BSW_00385	List possible error notifications	SWS_Spi_00004
SRS_BSW_00405	BSW Modules shall support multiple configuration sets	SWS_Spi_00013
SRS_BSW_00406	A static status variable denoting if a BSW module is initialized shall be initialized with value 0 before any APIs of the BSW module is called	SWS_Spi_00015, SWS_Spi_00046, SWS_Spi_00373
SRS_SPAL_00157	All drivers and handlers of the AUTOSAR Basic Software shall implement notification mechanisms of drivers and handlers	SWS_Spi_00026, SWS_Spi_00038, SWS_Spi_00042, SWS_Spi_00057, SWS_Spi_00071, SWS_Spi_00073, SWS_Spi_00075, SWS_Spi_00324
SRS_SPAL_12056	All driver modules shall allow the static configuration of notification mechanism	SWS_Spi_00044, SWS_Spi_00054
SRS_SPAL_12057	All driver modules shall implement an interface for initialization	SWS_Spi_00013, SWS_Spi_00015
SRS_SPAL_12064	All driver modules shall raise an error if the change of the operation mode leads to degradation of running operations	SWS_Spi_00021, SWS_Spi_00025
SRS_SPAL_12075	All drivers with random streaming capabilities shall use application buffers	SWS_Spi_00053

SRS_SPAL_12125	All driver modules shall only initialize the configured resources	SWS_Spi_00013
SRS_SPAL_12163	All driver modules shall implement an interface for de-initialization	SWS_Spi_00021, SWS_Spi_00022
SRS_Spi_12025	The SPI Handler/Driver shall allow the static configuration of all software and hardware properties related to SPI	SWS_Spi_00052, SWS_Spi_00053
SRS_Spi_12032	For an SPI channel assigned to an SPI HW Unit the chip select mode "normal" shall be available	SWS_Spi_00066
SRS_Spi_12033	For an SPI channel assigned to an SPI HW Unit the chip select mode "hold" shall be available	SWS_Spi_00066
SRS_Spi_12037	The SPI Handler/Driver shall allow a priority controlled allocation of the HW SPI unit	SWS_Spi_00014, SWS_Spi_00059, SWS_Spi_00124, SWS_Spi_00127
SRS_Spi_12093	The SPI Handler/Driver shall be able to handle multiple busses of communication	SWS_Spi_00034, SWS_Spi_00041, SWS_Spi_00135
SRS_Spi_12094	The SPI Handler/Driver shall handle the chip select	SWS_Spi_00066
SRS_Spi_12099	The SPI Handler/Driver shall provide an asynchronous read functionality	SWS_Spi_00016, SWS_Spi_00020, SWS_Spi_00162, SWS_Spi_00163
SRS_Spi_12101	The SPI Handler/Driver shall provide an asynchronous write functionality	SWS_Spi_00018, SWS_Spi_00020, SWS_Spi_00162, SWS_Spi_00163
SRS_Spi_12103	The SPI Handler/Driver shall provide an asynchronous read-write functionality	SWS_Spi_00020, SWS_Spi_00053, SWS_Spi_00058, SWS_Spi_00067, SWS_Spi_00162, SWS_Spi_00163
SRS_Spi_12104	The SPI Handler/Driver shall provide a synchronous functionality which returns any transfer status	SWS_Spi_00025, SWS_Spi_00026, SWS_Spi_00324
SRS_Spi_12108	The SPI Handler/Driver shall call the statically configured notification function	SWS_Spi_00057, SWS_Spi_00118, SWS_Spi_00119, SWS_Spi_00120
SRS_Spi_12150	The SPI Handler/Driver shall allow the static configuration of all software and hardware properties related to asynchronous SPI aspects	SWS_Spi_00093
SRS_Spi_12152	The SPI Handler/Driver shall provide a synchronous read functionality	SWS_Spi_00016, SWS_Spi_00134
SRS_Spi_12153	The SPI Handler/Driver shall provide a synchronous write functionality	SWS_Spi_00018, SWS_Spi_00134
SRS_Spi_12154	The SPI Handler/Driver shall provide a synchronous write-read functionality	SWS_Spi_00134
SRS_Spi_12170	The SPI Handler/Driver shall not provide the ability to prevent a channel data overwrite	SWS_Spi_00042, SWS_Spi_00084
SRS_Spi_12179	The SPI Handler/Driver shall allow linking consecutive SPI channels by static configuration	SWS_Spi_00003, SWS_Spi_00065


SRS_Spi_12180	The SPI Driver shall access the SPI bus only for the channel	SWS_Spi_00003, SWS_Spi_00065
SRS_Spi_12181	If an SPI access request for a linked channel is performed, the SPI Handler/Driver shall use this SPI channel and all the linked channels	SWS_Spi_00055, SWS_Spi_00065
SRS_Spi_12198	The SPI Handler/Driver shall provide the functionality of transferring one short data sequence with variable data content	SWS_Spi_00053, SWS_Spi_00077
SRS_Spi_12199	The SPI Handler/Driver shall provide the functionality of transferring any data to any devices in one transfer sequence	SWS_Spi_00003, SWS_Spi_00065
SRS_Spi_12200	Reading large data sequences from one slave device using dummy send data shall be possible	SWS_Spi_00003, SWS_Spi_00035, SWS_Spi_00053, SWS_Spi_00065, SWS_Spi_00077
SRS_Spi_12201	Reading large data sequences from multiple slave devices using dummy send data shall be possible	SWS_Spi_00003, SWS_Spi_00035, SWS_Spi_00065, SWS_Spi_00077
SRS_Spi_12202	The SPI Handler/Driver shall support data streams to a HW device with variable number of data	SWS_Spi_00053, SWS_Spi_00078
SRS_Spi_12253	The SPI Handler/Driver shall provide the functionality of transferring one short data sequence with constant data content	SWS_Spi_00052, SWS_Spi_00078
SRS_Spi_12256	The SPI Handler/Driver shall support all controller peripherals	SWS_Spi_00034
SRS_Spi_12257	The SPI Handler/Driver shall support the communication to daisy chained HW devices	SWS_Spi_00034, SWS_Spi_00065, SWS_Spi_00066
SRS_Spi_12258	Data shall be accessible from each device individually	SWS_Spi_00003, SWS_Spi_00065
SRS_Spi_12260	Different priorities of sequences shall be supported	SWS_Spi_00002, SWS_Spi_00014, SWS_Spi_00059, SWS_Spi_00093
SRS_Spi_12261	Reading large data sequences from one slave device using variable send data shall be possible	SWS_Spi_00003, SWS_Spi_00053, SWS_Spi_00065
SRS_Spi_12262	Reading large data sequences from multiple slave devices using variable send data shall be possible	SWS_Spi_00003, SWS_Spi_00053, SWS_Spi_00065, SWS_Spi_00078
SRS_Spi_13400	The SPI Handler/Driver shall have a scalable functionality to fit the needs of the ECU	SWS_Spi_00110
SRS_Spi_13401	The SPI Handler/Driver functionalities shall be statically configurable	SWS_Spi_00109, SWS_Spi_00111, SWS_Spi_00121, SWS_Spi_00122, SWS_Spi_00125

7 Functional specification

The SPI (Serial Peripheral Interface) has a 4-wire synchronous serial interface. Data communication is enabled with a Chip select wire (CS). Data is transmitted with a 3-wire interface consisting of wires for serial data output (MOSI), serial data input (MISO) and serial clock (CLOCK).

7.1 Overall view of functionalities and features

This specification is based on previous specification experiences and also based on predominant identified use cases. The intention of this section is to summarize how the scalability of this monolithic SPI Handler/Driver allows getting a simple software module that fits simple needs up to a smart software module that fits enhanced needs.



This document specifies the following 3 Levels of Scalable Functionality for the SPI Handler/Driver:

- **LEVEL 0, Simple Synchronous SPI Handler/Driver:** the communication is based on synchronous handling (using polling mechanism) and with a FIFO policy to handle multiple accesses. Buffer usage is configurable to optimize and/or to take advantage of HW capabilities.

- **LEVEL 1, Basic Asynchronous SPI Handler/Driver:** the communication is based on asynchronous behavior (using either interrupts or polling mechanism selectable during execution time) and with a Priority policy to handle multiple accesses. Buffer usage is configurable as for "Simple Synchronous" level.
- **LEVEL 2, Enhanced (Synchronous/Asynchronous) SPI Handler/Driver:** the communication is based on asynchronous behavior (using either interrupts or polling mechanism selectable during execution time), or synchronous handling, and with a Priority policy to handle multiple accesses. Buffer usage is configurable as for other levels.

Even if notification functions are specified for jobs and/or sequences used in synchronous transmission, these are not called in case of LEVEL0.

[SWS_Spi_00109] 「The SPI Handler/Driver's level of scalable functionality shall always be statically configurable, i.e. configured at pre-compile time to allow the best source code optimisation.」(SRS_Spi_13401)

[SWS_Spi_00110] 「The `SpiLevelDelivered` parameter shall be configured with one of the 3 authorized values according to the described levels (0, 1 or 2) to allow the selection of the SPI Handler/Driver's level of scalable functionality.」(SRS_Spi_13400)

To improve the scalability, each level has optional features which are configurable (ON / OFF) or selectable. These are described in detail in the dedicated chapters.

7.2 General behaviour

This chapter, on the one hand, introduces common behavior and configuration for all levels. On the other, it specifies the behavior of each level and also the allowed optional features.

[SWS_Spi_00041] 「The SPI Handler/Driver interface configuration shall be based on Channels, Jobs and Sequences as defined in this document (see chapter 2).」(SRS_Spi_12093)

[SWS_Spi_00034] 「The SPI Handler/Driver shall support one or more Channels, Jobs and Sequences to drive all kind of SPI compatible HW devices.」(SRS_Spi_12093, SRS_Spi_12256, SRS_Spi_12257)

[SWS_Spi_00255] 「Data transmissions shall be done according to Channels, Jobs and Sequences configuration parameters.」()

[SWS_Spi_00066] 「The Chip Select (CS) is attached to the Job definition.」(SRS_Spi_12094, SRS_Spi_12257, SRS_Spi_12032, SRS_Spi_12033)

[SWS_Spi_00263] 「Chip Select shall be handled during Job transmission and shall be released at the end of it. This Chip Select handling shall be done according to the Job configuration parameters.」()

[SWS_Spi_00370] 「It shall be possible to define if the Chip Select handling is managed autonomously by the HW peripheral, without explicit chip select control by the driver, or the SPI driver shall drive the chip select lines explicitly as DIO (see [ECUC_Spi_00212](#)).」()

It is up to the implementation to decide whether the behavior of the chip select configured into SpiCsBehavior is applicable when SpiCsSelection = CS_VIA_GPIO.

Example of CS handling: Set the CS active at the beginning of Job transmission; maintain it until the end of transmission of all Channels belonging to this Job afterwards set the CS inactive.

A Channel is defined one time but it could belong to several Jobs according to the user needs and this software specification.

[SWS_Spi_00065] 「A Job shall contain at least one Channel.」(SRS_Spi_12257, SRS_Spi_12179, SRS_Spi_12258, SRS_Spi_12180, SRS_Spi_12181, SRS_Spi_12199, SRS_Spi_12200, SRS_Spi_12261, SRS_Spi_12201, SRS_Spi_12262)

[SWS_Spi_00368] 「Each Channel shall have an associated index which is used for specifying the order of the Channel within the Job.」()


[SWS_Spi_00262] 「If a Job contains more than one Channel, all Channels contained have the same Job properties during transmission and shall be linked together statically.」()

A Job is defined one time but it could belong to several Sequences according to the user needs and this software specification.

[SWS_Spi_00003] 「A Sequence shall contain at least one Job.」(SRS_Spi_12179, SRS_Spi_12258, SRS_Spi_12180, SRS_Spi_12199, SRS_Spi_12200, SRS_Spi_12261, SRS_Spi_12201, SRS_Spi_12262)

[SWS_Spi_00236] 「If it contains more than one, all Jobs contained have the same Sequence properties during transmission and shall be linked together statically.」()

A Channel used for a transmission should have its parameters configured but it is allowed to pass Null pointers as source and destination pointers to generate a dummy transmission (See also [\[SWS_Spi_00028\]](#) & [\[SWS_Spi_00030\]](#)).



Note: the figure above corresponds to a configuration with SpiCsBehavior=CS_KEEP_ASSERTED.

Channel data may differ from the hardware handled and user (client application) given. On the client side the data is handled in 8, 16 or 32bits mode base on SpiDataWidth (see chapter 8.2.5). On the microcontroller side, the hardware may handle between 1 and 32bits or may handle a fixed value (8 or 16bits) and this width is configurable for each Channel (see SpiDataWidth)..

[SWS_Spi_00149] 「The SPI Handler/Driver shall take care of the differences between the frame width of channel (SpiDataWidth) and data access data type (given by SWS_Spi_00437).」()

[SWS_Spi_00289] 「If data width (SpiDataWidth) are exactly same (8 or 16 or 32 bits), the SPI Handler/Driver can send and receive data without any bit changes straightforward.」()

[SWS_Spi_00290] 「If data access casting type is superior to data width (for example SpiDataWidth = 12bits, data access is 16 bits), the data transmitted through the SPI Handler/Driver shall send the lower part, ignore the upper part. Receive the lower part, extend with zero.」()

This ensures that the user always gets the same interface.

[SWS_Spi_00437] 「Data buffers are accessed as uint8, uint16 or uint32 according to SpiDataWidth independently to Spi_DataBufferType.

The data access will use following casting:

uint8 for SpiDataWidth < 9

uint16 for 9 ≤ SpiDataWidth < 17

uint32 for 17 ≤ SpiDataWidth」()

7.2.1 Common configurable feature: Allowed Channel Buffers

In order to allow taking advantages of all microcontroller capabilities but also to allow sending/receiving of data to/from a dedicated memory location, all levels have an optional feature with respect to the location of Channel Buffers.

Hence, two main kinds of channel buffering can be used by configuration:

- Internally buffered Channels (IB): The buffer to transmit/receive data is provided by the Handler/Driver.
- Externally buffered Channels (EB): The buffer to transmit/receive is provided by the user (statically and/or dynamically).

Both channel buffering methods may be used depending on the 3 use cases described below:

- Usage 0: the SPI Handler/Driver manages only Internal Buffers.
- Usage 1: the SPI Handler/Driver manages only External Buffers.
- Usage 2: the SPI Handler/Driver manages both buffers types.

[SWS_Spi_00111] 「The SpiChannelBuffersAllowed parameter shall be configured with one of the 3 authorized values (0, 1 or 2) according to the described usage.」(SRS_Spi_13401)

[SWS_Spi_00279] 「The SpiChannelBuffersAllowed parameter shall be configured to select which Channel Buffers the SPI Handler/Driver manages.」()

7.2.1.1 Behaviour of IB channels

The intention of Internal Buffer channels is to take advantage of microcontrollers including this feature by hardware. Otherwise, this feature should be simulated by software.

[SWS_Spi_00052] 「For the IB Channels, the Handler/Driver shall provide the buffering but it is not able to take care of the consistency of the data in the buffer during transmission. The size of the Channel buffer is fixed.」(SRS_Spi_12025, SRS_Spi_12253)

[SWS_Spi_00049] 「The channel data received shall be stored in 1 entry deep internal buffers by channel. The SPI Handler/Driver shall not take care of the overwriting of these “receive” buffers by another transmission on the same channel.」()

[SWS_Spi_00051] 「The channel data to be transmitted shall be copied in 1 entry deep internal buffers by channel.」()

[SWS_Spi_00257] 「The SPI Handler/Driver is not able to prevent the overwriting of these “transmit” buffers by users during transmissions.」()

[SWS_Spi_00438] 「The Handler/Driver shall provide separate buffer for receive and transmit to ensure that transmitted data are not overwritten by the receive data.」()

7.2.1.2 Behaviour of EB channels

The intention of External Buffer channels is to reuse existing buffers that are located outside. That means the SPI Handler/Driver does not monitor them.

[SWS_Spi_00053] 「For EB Channels the application shall provide the buffering and shall take care of the consistency of the data in the buffer during transmission.」(SRS_SPAL_12075, SRS_Spi_12025, SRS_Spi_12198, SRS_Spi_12200, SRS_Spi_12261, SRS_Spi_12262, SRS_Spi_12202, SRS_Spi_12103)

[SWS_Spi_00112] 「The size of the Channel buffer is either fixed or variable. A maximum size for the Channel buffer shall be defined by the configuration.」()

[SWS_Spi_00280] 「The buffer provided by the application for the SPI Handler Driver may have a different size.」()

7.2.1.3 Buffering channel usage

The following table provides information about the Channel characteristics:

IB Channels	
It provides...	<ul style="list-style-type: none"> • A more abstracted concept (buffering mechanisms are hidden) • Actual and future optimal implementation taken profit of HW buffer facilities (Given size of 256 bytes covers nowadays requirements).
Suggested use ...	<ul style="list-style-type: none"> • Daisy-chain implementation. • Small data transfer devices (up to 10 Bytes).
EB Channels	
It provides...	<ul style="list-style-type: none"> • Efficient mechanism to support large stream communication. • Send constant data out of ROM tables and spare RAM size. • Send various data tables each for a different device (highly complex ASICS with several integrated peripheral devices, also mixed signal types, could exceed IB HW buffer size)
Suggested use ...	<ul style="list-style-type: none"> • Large streams communication. • EEPROM communication. • Control of complex HW Chips .

Note:

For each channel, the user configures the number of IB buffers (at least 1) if IB is selected for the current channel, or the maximum of data for EB buffers if EB is selected for the current channel.

7.2.2 LEVEL 0, Simple Synchronous behaviour

The intention of this functionality level is to provide a Handler/Driver with a reduced set of services to handle only simple synchronous transmissions. This is often the case for ECU including simple SPI networks but also for ECU using high speed external devices.

A simple synchronous transmission means that the function calling the transmission service is blocked during the ongoing transmission until the transmission is finished.

[SWS_Spi_00160] 「The LEVEL 0 SPI Handler/Driver shall offer a synchronous transfer service for SPI busses.」()

[SWS_Spi_00161] 「 For an SPI Handler/Driver operating in LEVEL 0, when there is no on going Sequence transmission, the SPI Handler/Driver shall be in the idle state SPI_IDLE.」()

[SWS_Spi_00294] 「This monolithic SPI Handler/Driver is able to handle one to n SPI buses according to the microcontroller used.」()

Then SPI buses are assigned to Jobs and not to Sequences. Consequently, Jobs, on different SPI buses, could belong to the same Sequence. Therefore:

[SWS_Spi_00114] 「The LEVEL 0 SPI Handler/Driver shall accept concurrent Spi_SyncTransmit(), if the sequences to be transmitted use different bus and parameter SPI_SUPPORT_CONCURRENT_SYNC_TRANSMIT is enabled. This feature shall be disabled per default. That means during a Sequence on-going transmission, all requests to transmit another Sequence shall be rejected.」()

[SWS_Spi_00115] 「The LEVEL 0 SPI Handler/Driver behaviour shall include the common feature: Allowed Channel Buffers, which is selected.」()

[SWS_Spi_00084] 「If different Jobs (and consequently also Sequences) have common Channels, the SPI Handler/Driver' environment shall ensure that read and/or write functions are not called during transmission.」(SRS_Spi_12170)

[SWS_Spi_00384]「 When a hardware error is detected, the SPI Handler/Driver shall stop the current sequence, report an error to the DEM as configured and set the state of the Job to SPI_JOB_FAILED and the state of the Sequence to SPI_SEQ_FAILED.」()

Read and write functions can not guarantee the data integrity while Channel data is being transmitted.

7.2.3 LEVEL 1, Basic Asynchronous behavior

The intention of this functionality level is to provide a Handler/Driver with a reduced set of services to handle asynchronous transmissions only. This is often the case for ECU with functions related to SPI networks having different priorities but also for ECU using low speed external devices.

An asynchronous transmission means that the user calling the transmission service is not blocked when the transmission is on-going. Furthermore, the user can be notified at the end of transmission.

Usually, depending on software design, asynchronous end transmission may be detected by polling or interrupt mechanisms. This level of functionality proposes both mechanisms that are selectable during execution time.

[SWS_Spi_00156] 「Both the polling mechanism and interrupt mechanism modes for SPI busses shall be selectable during execution time (see [\[SWS_Spi_00188\]](#)).」()

[SWS_Spi_00162] 「The LEVEL 1 SPI Handler/Driver shall offer an asynchronous transfer service for SPI buses. An asynchronous transmission means that the user calling the transmission service is not blocked when the transmission is on going.」(SRS_Spi_12099, SRS_Spi_12101, SRS_Spi_12103)

[SWS_Spi_00295] 「The LEVEL 1 SPI Handler/Driver shall offer an asynchronous transfer service for SPI buses. Furthermore, the user can be notified at the end of transmission.」()

[SWS_Spi_00163] 「For an SPI Handler/Driver operating in LEVEL 1, when there is no on-going Sequence transmission, the SPI Handler/Driver shall be in the idle state (SPI_IDLE).」(SRS_Spi_12099, SRS_Spi_12101, SRS_Spi_12103)

This Handler/Driver will be used by several software modules which may be independent from each other and also may belong to different layers. Therefore, priorities will be assigned to Jobs in order to figure out specific cases of multiple accesses. These cases usually occur within real time systems based on asynchronous mechanisms.

[SWS_Spi_00002] 「Jobs have priorities assigned. Jobs linked in a Sequence shall have same or de-creasing priorities. That means the first Job shall have the equal priority or the highest priority of all Jobs within the Sequence.」(SRS_Spi_12260)

[SWS_Spi_00093] 「Priority order of jobs shall be from the lower to the higher value defined, higher value higher priority (from 0, the lower to 3, the higher, limited to 4 priority levels).」(SRS_Spi_12260, SRS_Spi_12150)

With reference to Jobs priorities, this Handler/Driver needs rules to make a decision in these specific cases of multiple accesses.

[SWS_Spi_00059] 「The SPI Handler/Driver scheduling method shall schedule Jobs in order to send the highest priority Job first.」(SRS_Spi_12260, SRS_Spi_12037)

This monolithic SPI Handler/Driver is able to handle one to n SPI busses according to the microcontroller used. But SPI busses are assigned to Jobs and not to Sequences. Consequently, Jobs on different SPI buses could belong to the same Sequence. Therefore:

[SWS_Spi_00116] 「The LEVEL 1 SPI Handler/Driver may allow transmitting more than one Sequence at the same time. That means during a Sequence transmission, all requests to transmit another Sequence shall be evaluated in order to accept to start a new sequence or to reject it accordingly to the lead Job.」()

[SWS_Spi_00117] 「The LEVEL 1 SPI Handler/Driver behaviour shall include the common feature: Allowed Channel Buffers, which is selected, and the configured asynchronous feature: Interruptible Sequence (see next chapter).」()

[SWS_Spi_00267] 「When a hardware error is detected, the SPI Handler/Driver shall stop the current Sequence, report an error to the DEM as configured and set the state of the Job to SPI_JOB_FAILED and the state of the Sequence to SPI_SEQ_FAILED.」()

[SWS_Spi_00118] 「If Jobs are configured with a specific end notification function, the SPI Handler/Driver shall call this notification function at the end of the Job transmission.」(SRS_Spi_12108)

[SWS_Spi_00281] 「If Sequences are configured with a specific end notification function, the SPI Handler/Driver shall call this notification function at the end of the Sequence transmission.」()

[SWS_Spi_00119] 「When a valid notification function pointer is configured (see [\[SWS_Spi_00071\]](#)), the SPI Handler/Driver shall call this notification function at the end of a Job transmission regardless of the result of the Job transmission being either SPI_JOB_FAILED or SPI_JOB_OK (rational: avoid deadlocks or endless loops).」(SRS_Spi_12108)

[SWS_Spi_00120] 「When a valid notification function pointer is configured (see [\[SWS_Spi_00073\]](#)), the SPI Handler/Driver shall call this notification function at the end of a Sequence transmission regardless of the result of the Sequence transmission being either SPI_SEQ_FAILED, SPI_SEQ_OK or SPI_SEQ_CANCELLED (rational: avoid deadlocks or endless loops).」(SRS_Spi_12108)

7.2.4 Asynchronous configurable feature: Interruptible Sequences

In order to allow taking advantages of asynchronous transmission mechanism, level 1 and level 2 of this SPI Handler/Driver have an optional feature with respect to suspending the transmission of Sequences.

Hence two main kinds of sequences can be used by configuration:

- Non-Interruptible Sequences, every Sequence transmission started is not suspended by the Handler/Driver until the end of transmission.
- Mixed Sequences, according to its configuration, a Sequence transmission started may be suspended by the Handler/Driver between two of their consecutive Jobs.

[SWS_Spi_00121] 「The SPI Handler/Driver's environment shall configure the `SpiInterruptibleSeqAllowed` parameter (ON / OFF) in order to select which kind of Sequences the SPI Handler/Driver manages.」(SRS_Spi_13401)

7.2.4.1 Behavior of Non-Interruptible Sequences

The intention of the Non-Interruptible Sequences feature is to provide a simple software module based on a basic asynchronous mechanism, if only non blocking transmissions should be used.

[SWS_Spi_00122] 「Interruptible Sequences are not allowed within levels 1 and 2 of the SPI/Handler/Driver when the `SpiInterruptibleSeqAllowed` parameter is switched off (i.e. configured with value "OFF").」(SRS_Spi_13401)

[SWS_Spi_00123] 「When the SPI Handler/Driver is configured not allowing interruptible Sequences, all Sequences declared are considered as Non-Interruptible Sequences¹.」()

[SWS_Spi_00282] 「When the SPI Handler/Driver is configured not allowing interruptible Sequences their dedicated parameter `SpiInterruptibleSequence` can be omitted or the FALSE value should be used as default.」()

[SWS_Spi_00124] 「According to [\[SWS_Spi_00116\]](#) and [\[SWS_Spi_00122\]](#) requirements, the SPI Handler/Driver is not allowed to suspend a Sequence transmission already started in favour of another Sequence.」(SRS_Spi_12037)

7.2.4.2 Behavior of Mixed Sequences

The intention of the Mixed Sequences feature is to provide a software module with specific asynchronous mechanisms, if, for instance, very long Sequences that could or should be suspended by others with higher priority are used.

¹ The intention of this requirement is not to enforce any implementation solution in comparison with another one. But, it is only to ensure that anyhow, all Sequences will be considered as Non Interruptible Sequences.

[SWS_Spi_00125] ⌈Interruptible Sequences are allowed within levels 1 and 2 of SPI Handler/Driver when the `SpiInterruptibleSeqAllowed` parameter is switched on (i.e. configured with value “ON”).⌋(SRS_Spi_13401)

[SWS_Spi_00126] ⌈When the SPI Handler/Driver is configured allowing interruptible Sequences, all Sequences declared shall have their dedicated parameter `SpiInterruptibleSequence` (see ECUC_Spi_00106) to identify whether the Sequence can be suspended during transmission.⌋()

[SWS_Spi_00014] ⌈In case of a Sequence configured as Interruptible Sequence and according to [\[SWS_Spi_00125\]](#) requirement, the SPI Handler/Driver is allowed to suspend an already started Sequence transmission in favour of another Sequence with a higher priority Job (see [SWS_Spi_00002](#) & [SWS_Spi_00093](#)). That means, at the end of a Job transmission (that belongs to the interruptible sequence) with another Sequence transmit request pending, the SPI Handler/Driver shall perform a re-scheduling in order to elect the next Job to transmit.⌋(SRS_Spi_12260, SRS_Spi_12037)

[SWS_Spi_00127] ⌈In case of a Sequence configured as Non-Interruptible Sequence and according to requirement [\[SWS_Spi_00125\]](#), the SPI Handler/Driver is not allowed to suspend this already started Sequence transmission in favour of another Sequence.⌋(SRS_Spi_12037)

[SWS_Spi_00080] ⌈When using Interruptible Sequences, the caller must be aware that if the multiple Sequences access the same Channels, the data for these Channels may be overwritten by the highest priority Job accessing each Channel.⌋()

7.2.5 LEVEL 2, Enhanced behaviour

The intention of this functionality level is to provide a Handler/Driver with a complete set of services to handle synchronous and asynchronous transmissions. This could be the case for ECU with a lot of functions related to SPI networks having different priorities but also for ECU using external devices with different speeds. Usually, depending on software design, asynchronous end transmission may be detected by polling or interrupt mechanisms. This level of functionality proposes both mechanisms that are selectable during execution time.

The requirements from LEVEL 0 apply to synchronous behaviour.
The requirements from LEVEL 1 apply to asynchronous behaviour.

[SWS_Spi_00128] ⌈The LEVEL 2 SPI Handler/Driver shall offer both an asynchronous transfer service and a synchronous transfer service for SPI buses. ⌋()

[SWS_Spi_00283] 「In LEVEL 2 if there is no on going Sequence transmission, the SPI Handler/Driver shall be in idle state (SPI_IDLE).」()

7.3 Scheduling Advices

For asynchronous levels, LEVEL 1 and LEVEL 2, the SPI Handler/Driver can call end notification functions at the end of a Job and/or Sequence transmission (see [\[SWS_Spi_00118\]](#)). In a second time, in case of interruptible Sequences (that could be suspended), if another Sequence transmit request is pending, a rescheduling is also done by the SPI Handler/Driver in order to elect the next Job to transmit (see [\[SWS_Spi_00014\]](#)).

[SWS_Spi_00088] 「For asynchronous levels, LEVEL 1 and LEVEL 2, the SPI Handler/Driver can call end notification functions at the end of a Job.」()

[SWS_Spi_00268] 「For asynchronous levels, LEVEL 1 and LEVEL 2, the SPI Handler/Driver can call end notification functions at the end of a Sequence transmission.」()

[SWS_Spi_00269] 「For asynchronous levels, LEVEL 1 and LEVEL 2 in case of interruptible Sequences, if another Sequence transmit request is pending, a rescheduling is also done by the SPI Handler/Driver in order to elect the next Job to transmit.」()

[SWS_Spi_00270] 「In case call end notification function and rescheduling are fully done by software, the order between these shall be first scheduling and then the call of end notification function executed.」()

7.4 Error classification

The section 7.2 "Error Handling" of the document "General Specification of Basic Software Modules" describes the error handling of the Basic Software in detail. Above all, it constitutes a classification scheme consisting of five error types which may occur in BSW modules.

Based on this foundation, the following section specifies particular errors arranged in the respective subsections below.

7.4.1 Development Errors

[SWS_Spi_91001]

<i>Type of error</i>	<i>Related error code</i>	<i>Error value</i>
----------------------	---------------------------	--------------------

API service called with wrong channel	SPI_E_PARAM_CHANNEL	0x0A
API service called with wrong job	SPI_E_PARAM_JOB	0x0B
API service called with wrong sequence	SPI_E_PARAM_SEQ	0x0C
API service called with wrong length for EB	SPI_E_PARAM_LENGTH	0x0D
API service called with wrong hardware unit	SPI_E_PARAM_UNIT	0x0E
APIs called with an unexpected value for the pointer	SPI_E_PARAM_POINTER	0x10
API service used without module initialization	SPI_E_UNINIT	0x1A
API SPI_Init service called while the SPI driver has been already initialized	SPI_E_ALREADY_INITIALIZED	0x4A

()

7.4.2 Runtime Errors

[SWS_Spi_91002]

Type of error	Related error code	Error value
API Spi_AsyncTransmit service called in a wrong order	SPI_E_SEQ_PENDING	0x2A
API Spi_SyncTransmit service called at wrong time	SPI_E_SEQ_IN_PROCESS	0x3A

()

7.4.3 Transient faults

There are no transient faults.

7.4.4 Production Errors

There are no production errors.

7.4.5 Extended Production Errors

[SWS_Spi_00383]

Error Name:	SPI_E_HARDWARE_ERROR	
Short Description:	An hardware error occurred during asynchronous or synchronous SPI transmit	
Long Description:	This Extended Production Error shall be issued when any error bit inside the SPI hardware transmit status register is raised	
Detection Criteria:	Fail	The SPI transmit status register information shall be reported to DEM as Dem_SetEventStatus (SPI_E_HARDWARE_ERROR, DEM_EVENT_STATUS_FAILED) when any error bit inside the SPI transmit status register is set.

		(SWS_Spi_00385)
	Pass	The SPI transmit status register information shall be reported to DEM as Dem_SetEventStatus (SPI_E_HARDWARE_ERROR, DEM_EVENT_STATUS_PASSED) when no error bit inside the SPI transmit status register is set. (SWS_Spi_00386)
Secondary Parameters:	N/A	
Time Required:	N/A	
Monitor Frequency	continuous	

」()

[SWS_Spi_00385]「 When any error bit inside the SPI transmit status register is set, the SPI transmit status register information shall be reported to DEM as Dem_SetEventStatus (SPI_E_HARDWARE_ERROR, DEM_EVENT_STATUS_FAILED)」()

[SWS_Spi_00386]「 When no error bit inside the SPI transmit status register is set, the SPI transmit status register information shall be reported to DEM as Dem_SetEventStatus (SPI_E_HARDWARE_ERROR, DEM_EVENT_STATUS_PASSED)」()

8 API specification

8.1 Imported types

In this chapter all types included from the following modules are listed:

[SWS_Spi_91003]

Module	Header File	Imported Type
Dem	Rte_Dem_Type.h	Dem_EventIdType
	Rte_Dem_Type.h	Dem_EventStatusType
Std	Std_Types.h	Std_ReturnType
	Std_Types.h	Std_VersionInfoType

]()

8.2 Type definitions

8.2.1 Spi_ConfigType

[SWS_Spi_00372]

Name	Spi_ConfigType		
Kind	Structure		
Elements	Implementation Specific		
	Type	--	
	Comment	The contents of the initialization data structure are SPI specific.	
Description	This type of the external data structure shall contain the initialization data for the SPI Handler/Driver.		
Available via	Spi.h		

]()

8.2.2 Spi_StatusType

[SWS_Spi_00373]

Name	Spi_StatusType		
Kind	Enumeration		
Range	SPI_UNINIT	0x00	The SPI Handler/Driver is not initialized or not usable.
	SPI_IDLE	0x01	The SPI Handler/Driver is not currently transmitting any Job.

	SPI_BUSY	0x02	The SPI Handler/Driver is performing a SPI Job (transmit).
Description	This type defines a range of specific status for SPI Handler/Driver.		
Available via	Spi.h		

](SRS_BSW_00406, SRS_BSW_00335)

[SWS_Spi_00061] 「The type Spi_StatusType defines a range of specific status for SPI Handler/Driver. It informs about the SPI Handler/Driver status or specified SPI Hardware microcontroller peripheral.」(SRS_BSW_00335)

[SWS_Spi_00259] 「The type Spi_StatusType can be obtained calling the API service Spi_GetStatus.」()

[SWS_Spi_00260] 「The type Spi_StatusType can be obtained calling the API service Spi_GetHWUnitStatus.」()

[SWS_Spi_00011] 「After reset, the type Spi_StatusType shall have the default value SPI_UNINIT.」()

[SWS_Spi_00345] 「API service Spi_GetStatus shall return SPI_UNINIT when the SPI Handler/Driver is not initialized or not usable.」()

[SWS_Spi_00346] 「API service Spi_GetStatus shall return SPI_IDLE when The SPI Handler/Driver is not currently transmitting any Job.」()

[SWS_Spi_00347] 「API service Spi_GetStatus shall return SPI_BUSY when The SPI Handler/Driver is performing a SPI Job transmit.」()

[SWS_Spi_00348] 「Spi_GetHWUnitStatus function shall return SPI_IDLE when The SPI Hardware microcontroller peripheral is not currently transmitting any Job,」()

[SWS_Spi_00349] 「Spi_GetHWUnitStatus function shall return SPI_BUSYwhen The SPI Hardware microcontroller peripheral is performing a SPI Job transmit.」()

8.2.3 Spi_JobResultType

[SWS_Spi_00374]「

Name	Spi_JobResultType		
Kind	Enumeration		
Range	SPI_JOB_OK	0x00	The last transmission of the Job has been finished

			successfully.
	SPI_JOB_PENDING	0x01	The SPI Handler/Driver is performing a SPI Job. The meaning of this status is equal to SPI_BUSY.
	SPI_JOB_FAILED	0x02	The last transmission of the Job has failed.
	SPI_JOB_QUEUED	0x03	An asynchronous transmit Job has been accepted, while actual transmission for this Job has not started yet.
Description	This type defines a range of specific Jobs status for SPI Handler/Driver.		
Available via	Spi.h		

]()

[SWS_Spi_00062] 「The type Spi_JobResultType defines a range of specific Jobs status for SPI Handler/Driver.」(SRS_BSW_00335)

[SWS_Spi_00261] 「The type Spi_JobResultType it informs about a SPI Handler/Driver Job status and can be obtained calling the API service Spi_GetJobResult with the Job ID.」()

[SWS_Spi_00012] 「After reset, the type Spi_JobResultType shall have the default value SPI_JOB_OK.」()

[SWS_Spi_00350] 「The function Spi_GetJobResult shall return SPI_JOB_OK when the last transmission of the Job has been finished successfully.」()

8.2.4 Spi_SeqResultType

[SWS_Spi_00375]

Name	Spi_SeqResultType		
Kind	Enumeration		
Range	SPI_SEQ_OK	0x00	The last transmission of the Sequence has been finished successfully.
	SPI_SEQ_PENDING	0x01	The SPI Handler/Driver is performing a SPI Sequence. The meaning of this status is equal to SPI_BUSY.
	SPI_SEQ_FAILED	0x02	The last transmission of the Sequence has failed.
	SPI_SEQ_CANCELED	0x03	The last transmission of the Sequence has been canceled by user.
Description	This type defines a range of specific Sequences status for SPI Handler/Driver.		

Available via	Spi.h
----------------------	-------

]()

[SWS_Spi_00351] 「The type Spi_SeqResultType defines a range of specific Sequences status for SPI Handler/Driver and can be obtained calling the API service Spi_GetSequenceResult, it shall be provided for external use.」()

[SWS_Spi_00019] 「The type Spi_SeqResultType defines the range of specific Sequences status for SPI Handler/Driver.」(SRS_BSW_00335)

[SWS_Spi_00251] 「The type Spi_SeqResultType defines about SPI Handler/Driver Sequence status and can be obtained calling the API service Spi_GetSequenceResult with the Sequence ID.」()

[SWS_Spi_00017] 「After reset, the type Spi_SeqResultType shall have the default value SPI_SEQ_OK.」()

[SWS_Spi_00352] 「Spi_GetSequenceResult function shall return SPI_SEQ_OK when the last transmission of the Sequence has been finished successfully.」()

[SWS_Spi_00353] 「Spi_GetSequenceResult function shall return SPI_SEQ_PENDING when the SPI Handler/Driver is performing a SPI Sequence. The meaning of this status is equal to SPI_BUSY.」()

[SWS_Spi_00354] 「Spi_GetSequenceResult function shall return SPI_SEQ_FAILED when the last transmission of the Sequence has failed.」()

8.2.5 Spi_DataBufferType

[SWS_Spi_00376]

Name	Spi_DataBufferType
Kind	Type
Derived from	uint8
Description	Type of application data buffer elements.
Available via	Spi.h

]()

[SWS_Spi_00355] 「Spi_DataBufferType defines the type of application data buffer elements. Type is uint8. Access to the data is selected dynamically as is described in [SWS_SPI_00437](#). The data buffer has to be aligned to 32 bits. It shall be provided for external use.」()

[SWS_Spi_00164] 「The type Spi_DataBufferType refers to application data buffer elements.」()

8.2.6 Spi_NumberOfDataType

[SWS_Spi_00377]「

Name	Spi_NumberOfDataType
Kind	Type
Derived from	uint16
Description	Type for defining the number of data elements to send and / or receive by Channel
Available via	Spi.h

」()

[SWS_Spi_00165] 「The type Spi_NumberOfDataType is used for defining the number of data elements of the type specified in [SWS_SPI_00437](#) to send and / or receive by Channel.」()

8.2.7 Spi_ChannelType

[SWS_Spi_00378]「

Name	Spi_ChannelType
Kind	Type
Derived from	uint8
Description	Specifies the identification (ID) for a Channel.
Available via	Spi.h

」()

[SWS_Spi_00356] 「The type Spi_ChannelType specifies the identification (ID) for a Channel.」()

[SWS_Spi_00166] 「The type Spi_ChannelType is used for specifying the identification (ID) for a Channel.」()

8.2.8 Spi_JobType

[SWS_Spi_00379]

Name	Spi_JobType
Kind	Type
Derived from	uint16
Description	Specifies the identification (ID) for a Job.
Available via	Spi.h

]()

[SWS_Spi_00357] 「The type Spi_JobType specifies the identification (ID) for a Job.」()

[SWS_Spi_00167] 「The type Spi_JobType is used for specifying the identification (ID) for a Job.」()

8.2.9 Spi_SequenceType

[SWS_Spi_00380]

Name	Spi_SequenceType
Kind	Type
Derived from	uint8
Description	Specifies the identification (ID) for a sequence of jobs.
Available via	Spi.h

]()

[SWS_Spi_00358] 「The type Spi_SequenceType specifies the identification (ID) for a sequence of jobs.」()

[SWS_Spi_00168] 「The type Spi_SequenceType is used for specifying the identification (ID) for a sequence of jobs.」()

8.2.10 Spi_HWUnitType

[SWS_Spi_00381]

Name	Spi_HWUnitType
Kind	Type

Derived from	uint8
Description	Specifies the identification (ID) for a SPI Hardware microcontroller peripheral (unit).
Available via	Spi.h

]()

[SWS_Spi_00359] 「The type `Spi_HWUnitType` specifies the identification (ID) for a SPI Hardware microcontroller peripheral (unit).」()

[SWS_Spi_00169] 「The type `Spi_HWUnitType` is used for specifying the identification (ID) for a SPI Hardware microcontroller peripheral (unit).」()

8.2.11 Spi_AsyncModeType

[SWS_Spi_00382]「

Name	Spi_AsyncModeType		
Kind	Enumeration		
Range	SPI_POLLING_MODE	0x00	The asynchronous mechanism is ensured by polling, so interrupts related to SPI busses handled asynchronously are disabled.
	SPI_INTERRUPT_MODE	0x01	The asynchronous mechanism is ensured by interrupt, so interrupts related to SPI busses handled asynchronously are enabled.
Description	Specifies the asynchronous mechanism mode for SPI busses handled asynchronously.		
Available via	Spi.h		

]()

[SWS_Spi_00360] 「The asynchronous mechanism is selected by the API `Spi_SetAsyncMode`.」()

[SWS_Spi_00170] 「The type `Spi_AsyncModeType` is used for specifying the asynchronous mechanism mode for SPI busses handled asynchronously.」()

[SWS_Spi_00150] 「The type `Spi_AsyncModeType` is made available or not depending on the pre-compile time parameter: `SpiLevelDelivered`. This is only relevant for LEVEL 1 and LEVEL 2.」()

[SWS_Spi_00361] 「If API Spi_SetAsyncMode function is called by the parameter value SPI_POLLING_MODE then asynchronous mechanism is ensured by polling. So interrupts related to SPI buses handled asynchronously are disabled.」()

[SWS_Spi_00362] 「If API Spi_SetAsyncMode function is called by the parameter value SPI_INTERRUPT_MODE asynchronous mechanism is ensured by interrupt, so interrupts related to SPI buses handled asynchronously are enabled.」()

8.3 Function definitions

8.3.1 Spi_Init

[SWS_Spi_00175]

Service Name	Spi_Init	
Syntax	<pre>void Spi_Init (const Spi_ConfigType* ConfigPtr)</pre>	
Service ID [hex]	0x00	
Sync/Async	Synchronous	
Reentrancy	Non Reentrant	
Parameters (in)	ConfigPtr	Pointer to configuration set
Parameters (inout)	None	
Parameters (out)	None	
Return value	None	
Description	Service for SPI initialization.	
Available via	Spi.h	

」()

[SWS_Spi_00298] 「The operation Spi_Init is Non Re-entrant.」()

[SWS_Spi_00299] 「The function Spi_Init provides the service for SPI initialization.」()

[SWS_Spi_00013] 「The function Spi_Init shall initialize all SPI relevant registers with the values of the structure referenced by the parameter Config-

Ptr.](SRS_BSW_00405, SRS_BSW_00101, SRS_SPAL_12057,
SRS_SPAL_12125)

[SWS_Spi_00015] 「After the module initialization using the function `Spi_Init`, the SPI Handler/Driver shall set its state to `SPI_IDLE`, the Sequences result to `SPI_SEQ_OK` and the jobs result to `SPI_JOB_OK`.」(SRS_BSW_00406, SRS_BSW_00101, SRS_SPAL_12057)

[SWS_Spi_00151] [For LEVEL 2 (see chapter 7.2.5), the function `Spi_Init` shall set the SPI Handler/Driver asynchronous mechanism mode to `SPI_POLLING_MODE` by default. Interrupts related to SPI busses shall be disabled.]()

A re-initialization of a SPI Handler/Driver by executing the `Spi_Init()` function requires a de-initialization before by executing a `Spi_DeInit()`.

Parameters of the function `Spi_Init` shall be checked as it is explained in section API parameter checking

8.3.2 Spi_DeInit

[SWS_Spi_00176]

Service Name	Spi_DeInit	
Syntax	<pre>Std_ReturnType Spi_DeInit (void)</pre>	
Service ID [hex]	0x01	
Sync/Async	Synchronous	
Reentrancy	Non Reentrant	
Parameters (in)	None	
Parameters (inout)	None	
Parameters (out)	None	
Return value	Std_Return-Type	E_OK: de-initialisation command has been accepted E_NOT_OK: de-initialisation command has not been accepted
Description	Service for SPI de-initialization.	
Available via	Spi.h	

]()

[SWS_Spi_00300] 「The operation Std_ReturnType Spi_DeInit() is Non Re-entrant.」()

[SWS_Spi_00301] 「When the API Spi_DeInit has been accepted the return value of this function shall be E_OK.」()

[SWS_Spi_00302] 「When the API Spi_DeInit has not been accepted the return value of this function shall be E_NOT_OK.」()

[SWS_Spi_00303] 「The function Spi_DeInit provides the service for SPI de-initialization.」()

[SWS_Spi_00021] 「The function Spi_DeInit shall de-initialize SPI Handler/Driver.」(SRS_BSW_00336, SRS_SPAL_12163, SRS_SPAL_12064)

[SWS_Spi_00252] 「In case of the SPI Handler/Driver state is not SPI_BUSY, the deinitialization function shall put all already initialized microcontroller SPI peripherals into the same state such as Power On Reset.」()

[SWS_Spi_00253] 「The function call Spi_DeInit shall be rejected if the status of SPI Handler/Driver is SPI_BUSY.」()

[SWS_Spi_00022] 「After the module de-initialization using the function Spi_DeInit, the SPI Handler/Driver shall set its state to SPI_UNINIT.」(SRS_BSW_00336, SRS_SPAL_12163)

The SPI Handler/Driver shall have been initialized before the function Spi_DeInit is called, otherwise see [\[SWS_Spi_00046\]](#).

8.3.3 Spi_WriteIB

[SWS_Spi_00177]「

Service Name	Spi_WriteIB
Syntax	Std_ReturnType Spi_WriteIB (Spi_ChannelType Channel, const Spi_DataBufferType* DataBufferPtr)
Service ID	0x02

[hex]		
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Channel	Channel ID.
	DataBuffer Ptr	Pointer to source data buffer. If this pointer is null, it is assumed that the data to be transmitted is not relevant and the default transmit value of this channel will be used instead.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Std_-Return-Type	E_OK: write command has been accepted E_NOT_OK: write command has not been accepted
Description	Service for writing one or more data to an IB SPI Handler/Driver Channel specified by parameter.	
Available via	Spi.h	

]()

[SWS_Spi_00304] 「The operation Spi_WriteIB is Re-entrant.」()

[SWS_Spi_00305] 「When the API Spi_WriteIB command has been accepted the function returns the value E_OK.」()

[SWS_Spi_00306] 「When the API Spi_WriteIB command has not been accepted the function returns the value E_NOT_OK.」()

[SWS_Spi_00307] 「The function Spi_WriteIB provides the service for writing one or more data to an IB SPI Handler/Driver Channel by the respective parameter.」()

[SWS_Spi_00018] 「The function Spi_WriteIB shall write one or more data to an IB SPI Handler/Driver Channel specified by the respective parameter.」(SRS_Spi_12101, SRS_Spi_12153)

[SWS_Spi_00024] 「The function Spi_WriteIB shall take over the given parameters, and save the pointed data to the internal buffer defined with the function Spi_Init.」()

[SWS_Spi_00023] 「If the given parameter “DataBufferPtr” is null, the function Spi_WriteIB shall assume that the data to be transmitted is not relevant and the default transmit value of the given channel shall be used instead.」()

[SWS_Spi_00137] 「The function Spi_WriteIB shall be pre-compile time configurable by the parameter SpiChannelBuffersAllowed. This function is only relevant for Channels with IB.」()

Parameters of the function Spi_WriteIB shall be checked as it is explained in section [API parameter checking](#).

The SPI Handler/Driver shall have been initialized before the function Spi_WriteIB is called, otherwise see [\[SWS_Spi_00046\]](#).

8.3.4 Spi_AsyncTransmit

[SWS_Spi_00178]

Service Name	Spi_AsyncTransmit	
Syntax	Std_ReturnType Spi_AsyncTransmit (Spi_SequenceType Sequence)	
Service ID [hex]	0x03	
Sync/Async	Asynchronous	
Reentrancy	Reentrant	
Parameters (in)	Sequence	Sequence ID.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Std_Return-Type	E_OK: Transmission command has been accepted E_NOT_OK: Transmission command has not been accepted
Description	Service to transmit data on the SPI bus.	
Available via	Spi.h	

」()

[SWS_Spi_00308] 「The operation Std_ReturnType Spi_AsyncTransmit(Spi_SequenceType Sequence) is Re-entrant.」()

[SWS_Spi_00309] 「When the API `Spi_AsyncTransmit` command has been accepted the function shall return the value `E_OK`.」()

[SWS_Spi_00310] 「When the API `Spi_AsyncTransmit` command has not been accepted the function shall return the value `E_NOT_OK`.」()

[SWS_Spi_00311] 「The function `Spi_AsyncTransmit` provides service to transmit data on the SPI bus.」()

[SWS_Spi_00020] 「The function `Spi_AsyncTransmit` shall take over the given parameter, initiate a transmission, set the SPI Handler/Driver status to `SPI_BUSY`, set the sequence result to `SPI_SEQ_PENDING` and return. 」(`SRS_Spi_12099`, `SRS_Spi_12101`, `SRS_Spi_12103`)

[SWS_Spi_00194] 「When the function `Spi_AsyncTransmit` is called, shall take over the given parameter and set the Job status to `SPI_JOB_QUEUED`, which can be obtained by calling the API service `Spi_GetJobResult`.」()

[SWS_Spi_00157] 「When the function `Spi_AsyncTransmit` is called, the SPI Handler/Driver shall handle the Job results. Result shall be `SPI_JOB_PENDING` when the transmission of Jobs is started.」()

[SWS_Spi_00292] 「When the function `Spi_AsyncTransmit` is called, the SPI Handler/Driver shall handle the Job results. Result shall be `SPI_JOB_OK` when the transmission of Jobs is success.」()

[SWS_Spi_00293] 「When the function `Spi_AsyncTransmit` is called, the SPI Handler/Driver shall handle the Job results. Result shall be `SPI_JOB_FAILED` when the transmission of Jobs is failed.」()

[SWS_Spi_00081] 「When the function `Spi_AsyncTransmit` is called and the requested Sequence is already in state `SPI_SEQ_PENDING`, the SPI Handler/Driver shall not take in account this new request and this function shall return with value `E_NOT_OK`, in this case.」()

[SWS_Spi_00266] 「When the function `Spi_AsyncTransmit` is called and the requested Sequence is already in state `SPI_SEQ_PENDING` the SPI Handler/Driver shall report the `SPI_E_SEQ_PENDING` error according to `[SWS_BSW_00042]` and `[SWS_BSW_00045]`.」()

[SWS_Spi_00086] 「When the function `Spi_AsyncTransmit` is called and the requested Sequence shares Jobs with another sequence that is in the state `SPI_SEQ_PENDING`, the SPI Handler/Driver shall not take into account this new request and this function shall return the value `E_NOT_OK`. In this case and according to [\[SWS_BSW_00042\]](#) and [\[SWS_BSW_00045\]](#), the SPI Handler/Driver shall report the `SPI_E_SEQ_PENDING` error.」()

[SWS_Spi_00035] 「When the function `Spi_AsyncTransmit` is used with EB and the source data pointer has been provided as `NULL` using the `Spi_SetupEB` method, the default transmit data configured for each channel shall be transmitted. (See also [\[SWS_SPI_00028\]](#))」([SRS_Spi_12200](#), [SRS_Spi_12201](#))

[SWS_Spi_00036] 「When the function `Spi_AsyncTransmit` is used with EB and the destination data pointer has been provided as `NULL` using the `Spi_SetupEB` method, the SPI Handler/Driver shall ignore receiving data (See also [\[SWS_Spi_00030\]](#))」()

[SWS_Spi_00055] 「When the function `Spi_AsyncTransmit` is used for a Sequence with linked Jobs, the function shall transmit from the first Job up to the last Job in the sequence.」([SRS_Spi_12181](#))

[SWS_Spi_00057] 「At the end of a sequence transmission initiated by the function `Spi_AsyncTransmit` and if configured, the SPI Handler/Driver shall invoke the sequence notification call-back function after the last Job end notification if this one is also configured.」([SRS_SPAL_00157](#), [SRS_Spi_12108](#))

[SWS_Spi_00133] 「The function `Spi_AsyncTransmit` is pre-compile time selectable by the configuration parameter `SpiLevelDelivered`. This function is only relevant for LEVEL 1 and LEVEL 2.」()

[SWS_Spi_00173] 「The SPI Handler/Driver's environment shall call the function `Spi_AsyncTransmit` after a function call of `Spi_SetupEB` for EB Channels or a function call of `Spi_WriteIB` for IB Channels but before the function call `Spi_ReadIB`.」()

Parameters of the function `Spi_AsyncTransmit` shall be checked as explained in section [API parameter checking](#)

The SPI Handler/Driver shall have been initialized before the function `Spi_AsyncTransmit` is called otherwise see [\[SWS_Spi_00046\]](#).

8.3.5 Spi_ReadIB

[SWS_Spi_00179]

Service Name	Spi_ReadIB	
Syntax	<pre>Std_ReturnType Spi_ReadIB (Spi_ChannelType Channel, Spi_DataBufferType* DataBufferPointer)</pre>	
Service ID [hex]	0x04	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Channel	Channel ID.
Parameters (inout)	None	
Parameters (out)	DataBufferPointer	Pointer to destination data buffer in RAM
Return value	Std_ReturnType	E_OK: read command has been accepted E_NOT_OK: read command has not been accepted
Description	Service for reading synchronously one or more data from an IB SPI Handler/Driver Channel specified by parameter.	
Available via	Spi.h	

⌋()

[SWS_Spi_00312] 「The operation Spi_ReadIB is Re-entrant.」()

[SWS_Spi_00313] 「The function Spi_ReadIB return values E_OK: read command has been accepted.」()

[SWS_Spi_00314] 「The function Spi_ReadIB return values E_NOT_OK: read command has not been accepted.」()

[SWS_Spi_00315] 「The function Spi_ReadIB provides the service for reading synchronously one or more data from an IB SPI Handler/Driver Channel specified by parameter.」()

[SWS_Spi_00016] 「The function `Spi_ReadIB` shall read synchronously one or more data from an IB SPI Handler/Driver Channel specified by the respective parameter.」(SRS_Spi_12099, SRS_Spi_12152)

[SWS_Spi_00027] 「The SPI Handler/Driver's environment shall call the function `Spi_ReadIB` after a Transmit method call to have relevant data within IB Channel.」()

[SWS_Spi_00138] 「The function `Spi_ReadIB` is pre-compile time configurable by the parameter `SpiChannelBuffersAllowed`. This function is only relevant for Channels with IB.」()

Parameters of the function `Spi_ReadIB` shall be checked as it is explained in section [API parameter checking](#).

The SPI Handler/Driver shall have been initialized before the function `Spi_ReadIB` is called otherwise see [\[SWS_Spi_00046\]](#).

8.3.6 Spi_SetupEB

[SWS_Spi_00180]

Service Name	Spi_SetupEB	
Syntax	<pre>Std_ReturnType Spi_SetupEB (Spi_ChannelType Channel, const Spi_DataBufferType* SrcDataBufferPtr, Spi_DataBufferType* DesDataBufferPtr, Spi_NumberOfDataType Length)</pre>	
Service ID [hex]	0x05	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Channel	Channel ID.
	SrcData BufferPtr	Pointer to source data buffer.
	Length	Length (number of data elements) of the data to be transmitted from SrcDataBufferPtr and/or received from DesDataBufferPtr Min.: 1 Max.: Max of data specified at configuration for this channel
Parameters (inout)	DesData BufferPtr	Pointer to destination data buffer in RAM.
Parameters (out)	None	

Return value	Std_-Return-Type	E_OK: Setup command has been accepted E_NOT_OK: Setup command has not been accepted
Description	Service to setup the buffers and the length of data for the EB SPI Handler/Driver Channel specified.	
Available via	Spi.h	

]()

[SWS_Spi_00316] 「The operation Spi_SetupEB is Re-entrant.」()

[SWS_Spi_00317] 「Return values of the function Spi_SetupEB are E_OK: Setup command has been accepted and E_NOT_OK: Setup command has not been accepted.」()

[SWS_Spi_00318] 「The function Spi_SetupEB provides the service to setup the buffers and the length of data for the EB SPI Handler/Driver Channel specified.」()

[SWS_Spi_00058] 「The function Spi_SetupEB shall set up the buffers and the length of data for the specific EB SPI Handler/Driver Channel.」(SRS_Spi_12103)

[SWS_Spi_00067] 「The function Spi_SetupEB shall update the buffer pointers and length attributes of the specified Channel with the provided values.」(SRS_Spi_12103)

As these attributes are persistent, they will be used for all succeeding calls to a Transmit method (for the specified Channel).

[SWS_Spi_00028] 「When the SPI Handler/Driver's environment is calling the function Spi_SetupEB with the parameter SrcDataBufferPtr being a Null pointer, the function shall transmit the default transmit value configured for the channel after a Transmit method is requested. (See also [\[SWS_Spi_00035\]](#))」()

[SWS_Spi_00030] 「When the function Spi_SetupEB is called with the parameter DesDataBufferPtr being a Null pointer, the SPI Handler/Driver shall ignore the received data after a Transmit method is requested.(See also [\[SWS_Spi_00036\]](#))」()

[SWS_Spi_00037] 「The SPI Handler/Driver's environment shall call the Spi_SetupEB function once for each Channel with EB declared before the SPI Handler/Driver's environment calls a Transmit method on them.」()

[SWS_Spi_00139] 「The function `Spi_SetupEB` is pre-compile time configurable by the parameter `SpiChannelBuffersAllowed`. This function is only relevant for Channels with EB.」()

Parameters of the function `Spi_SetupEB` shall be checked as it is explained in section API parameter checking.

The SPI Handler/Driver shall have been initialized before the function `Spi_SetupEB` is called otherwise see [\[SWS_Spi_00046\]](#).

8.3.7 Spi_GetStatus

[SWS_Spi_00181]

Service Name	Spi_GetStatus	
Syntax	<pre>Spi_StatusType Spi_GetStatus (void)</pre>	
Service ID [hex]	0x06	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	None	
Parameters (inout)	None	
Parameters (out)	None	
Return value	Spi_StatusType	Spi_StatusType
Description	Service returns the SPI Handler/Driver software module status.	
Available via	Spi.h	

⌋()

[SWS_Spi_00319] 「The operation `Spi_GetStatus` is Re-entrant.⌋()

[SWS_Spi_00320] 「The function `Spi_GetStatus` returns the SPI Handler/Driver software module status.⌋()

[SWS_Spi_00025] 「The function `Spi_GetStatus` shall return the SPI Handler/Driver software module status.⌋(SRS_SPAL_12064, SRS_Spi_12104)

8.3.8 Spi_GetJobResult

[SWS_Spi_00182]

Service Name	Spi_GetJobResult	
Syntax	<pre>Spi_JobResultType Spi_GetJobResult (Spi_JobType Job)</pre>	

Service ID [hex]	0x07	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Job	Job ID. An invalid job ID will return an undefined result.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Spi_JobResultType	Spi_JobResultType
Description	This service returns the last transmission result of the specified Job.	
Available via	Spi.h	

]()

[SWS_Spi_00321] 「The operation `Spi_GetJobResult` is Re-entrant.」()

[SWS_Spi_00322] 「The function `Spi_GetJobResult` service returns the last transmission result of the specified Job.」()

[SWS_Spi_00026] 「The function `Spi_GetJobResult` shall return the last transmission result of the specified Job. 」(`SRS_SPAL_00157`, `SRS_Spi_12104`)

[SWS_Spi_00038] 「The SPI Handler/Driver's environment shall call the function `Spi_GetJobResult` to inquire whether the Job transmission has succeeded (`SPI_JOB_OK`) or failed (`SPI_JOB_FAILED`).」(`SRS_SPAL_00157`)

NOTE: Every new transmit job that has been accepted by the SPI Handler/Driver overwrites the previous job result with `SPI_JOB_QUEUED` or `SPI_JOB_PENDING`.

Parameters of the function `Spi_GetJobResult` shall be checked as it is explained in section [API parameter checking](#).

If SPI Handler/Driver has not been initialized before the function `Spi_GetJobResult` is called, the return value is undefined.

8.3.9 Spi_GetSequenceResult

[SWS_Spi_00183]「

Service Name	<code>Spi_GetSequenceResult</code>
Syntax	<code>Spi_SeqResultType Spi_GetSequenceResult (</code>

	Spi_SequenceType Sequence)	
Service ID [hex]	0x08	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Sequence	Sequence ID. An invalid sequence ID will return an undefined result.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Spi_SeqResult-Type	Spi_SeqResultType
Description	This service returns the last transmission result of the specified Sequence.	
Available via	Spi.h	

()

[SWS_Spi_00323] 「The operation Spi_GetSequenceResult is Re-entrant.」()

[SWS_Spi_00324] 「The function Spi_GetSequenceResult shall return the last transmission result of the specified Sequence.」(SRS_SPAL_00157, SRS_Spi_12104)

[SWS_Spi_00042] 「The SPI Handler/Driver's environment shall call the function Spi_GetSequenceResult to inquire whether the full Sequence transmission has succeeded (SPI_SEQ_OK) or failed (SPI_SEQ_FAILED).」(SRS_SPAL_00157, SRS_Spi_12170)

Note:

- Every new transmit sequence that has been accepted by the SPI Handler/Driver overwrites the previous sequence result with SPI_SEQ_PENDING.
- If the SPI Handler/Driver has not been initialized before the function Spi_GetSequenceResult is called, the return value is undefined.

Parameters of the function Spi_GetSequenceResult shall be checked as it is explained in section [API parameter checking](#).

8.3.10 Spi_GetVersionInfo

[SWS_Spi_00184]「

Service Name	Spi_GetVersionInfo	
Syntax	<pre>void Spi_GetVersionInfo (Std_VersionInfoType* versioninfo)</pre>	
Service ID [hex]	0x09	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	None	
Parameters (inout)	None	
Parameters (out)	versioninfo	Pointer to where to store the version information of this module.
Return value	None	
Description	This service returns the version information of this module.	
Available via	Spi.h	

]()

[SWS_Spi_00371] 「If Det is enabled, the parameter versioninfo shall be checked for being NULL. The error SPI_E_PARAM_POINTER shall be reported in case the value is a NULL pointer.」()

8.3.11 Spi_SyncTransmit

[SWS_Spi_00185]

Service Name	Spi_SyncTransmit	
Syntax	<pre>Std_ReturnType Spi_SyncTransmit (Spi_SequenceType Sequence)</pre>	
Service ID [hex]	0x0a	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	Sequence	Sequence ID.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Std_ReturnType	E_OK: Transmission has been successful E_NOT_OK: Transmission failed
Description	Service to transmit data on the SPI bus	

Available via	Spi.h
---------------	-------

]()

[SWS_Spi_00327] 「The operation Spi_SyncTransmit is Re-entrant.」()

[SWS_Spi_00328] 「The function Spi_SyncTransmit returns E_OK if the transmission request has been successful.」()

[SWS_Spi_00329] 「The function Spi_SyncTransmit returns E_NOT_OK if the transmission request failed.」()

[SWS_Spi_00330] 「The function Spi_SyncTransmit provides the service to transmit data on the SPI bus.」()

[SWS_Spi_00134] 「When the function Spi_SyncTransmit is called, shall take over the given parameter and set the SPI Handler/Driver status to SPI_BUSY can be obtained calling the API service SPI_GetStatus.」(SRS_Spi_12152, SRS_Spi_12153, SRS_Spi_12154)

[SWS_Spi_00285] 「When the function Spi_SyncTransmit is called, shall take over the given parameter and set the Sequence status to SPI_SEQ_PENDING can be obtained calling the API service Spi_GetSequenceResult.」()

[SWS_Spi_00286] 「When the function Spi_SyncTransmit is called, shall take over the given parameter and set the Job status to SPI_JOB_PENDING can be obtained calling the API service Spi_GetJobResult.」()

[SWS_Spi_00135] 「When the function Spi_SyncTransmit is called while a sequence is on transmission and SPI_SUPPORT_CONCURRENT_SYNC_TRANSMIT is disabled or another sequence is on transmission on same bus, the SPI Handler/Driver shall not take into account this new transmission request and the function shall return the value E_NOT_OK (see [\[SWS_Spi_00114\]](#)). In this case, the SPI Handler/Driver shall report the SPI_E_SEQ_IN_PROCESS error according to [\[SWS_BSW_00042\]](#) and [\[SWS_BSW_00045\]](#).」(SRS_Spi_12093)

[SWS_Spi_00136] 「The function Spi_SyncTransmit is pre-compile time selectable by the configuration parameter SpiLevelDelivered. This function is only relevant for LEVEL 0 and LEVEL 2.」()

Parameters of the function `Spi_SyncTransmit` shall be checked as it is explained in section [API parameter checking](#)

8.3.12 Spi_GetHWUnitStatus

[SWS_Spi_00186]

Service Name	Spi_GetHWUnitStatus	
Syntax	<pre>Spi_StatusType Spi_GetHWUnitStatus (Spi_HWUnitType HWUnit)</pre>	
Service ID [hex]	0x0b	
Sync/Async	Synchronous	
Reentrancy	Reentrant	
Parameters (in)	HWUnit	SPI Hardware microcontroller peripheral (unit) ID.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Spi_StatusType	Spi_StatusType
Description	This service returns the status of the specified SPI Hardware microcontroller peripheral.	
Available via	Spi.h	

⌋()

[SWS_Spi_00331] 「The operation `Spi_GetHWUnitStatus` is Re-entrant.⌋()

[SWS_Spi_00332] 「The function `Spi_GetHWUnitStatus` service returns the status of the specified SPI Hardware microcontroller peripheral.⌋()

[SWS_Spi_00141] 「The function `Spi_GetHWUnitStatus` shall return the status of the specified SPI Hardware microcontroller peripheral.⌋()

[SWS_Spi_00287] 「The SPI Handler/Driver's environment shall call this function to inquire whether the specified SPI Hardware microcontroller peripheral is `SPI_IDLE` or `SPI_BUSY`.⌋()

[SWS_Spi_00142] 「The function `Spi_GetHWUnitStatus` is pre-compile time configurable On / Off by the configuration parameter `SpiHwStatusApi`.⌋()

Parameters of the function `Spi_GetHWUnitStatus` shall be checked as it is explained in section [API parameter checking](#).

If SPI Handler/Driver has not been initialized before the function `Spi_GetHWUnitStatus` is called, the return value is undefined.

8.3.13 Spi_Cancel

[SWS_Spi_00187]

Service Name	Spi_Cancel	
Syntax	<pre>void Spi_Cancel (Spi_SequenceType Sequence)</pre>	
Service ID [hex]	0x0c	
Sync/Async	Asynchronous	
Reentrancy	Reentrant	
Parameters (in)	Sequence	Sequence ID.
Parameters (inout)	None	
Parameters (out)	None	
Return value	None	
Description	Service cancels the specified on-going sequence transmission.	
Available via	Spi.h	

]()

[SWS_Spi_00333] 「The operation Spi_Cancel is Re-entrant.」()

[SWS_Spi_00334] 「The function Spi_Cancel service cancels the specified on-going sequence transmission.」()

[SWS_Spi_00144] 「The function `Spi_Cancel` shall cancel the specified on-going sequence transmission without cancelling any Job transmission and set the sequence result to `SPI_SEQ_CANCELLED`.」()

With other words, the `Spi_Cancel` function stops a Sequence transmission after a (possible) on transmission Job ended and before a (potential) next Job transmission starts.

[SWS_Spi_00145] 「When the sequence is cancelled by the function `Spi_Cancel` and if configured, the SPI Handler/Driver shall call the sequence notification call-back function instead of starting a potential next job belonging to it.」()

[SWS_Spi_00146] 「The function `Spi_Cancel` is pre-compile time configurable On / Off by the configuration parameter `SpiCancelApi.()`

The SPI Handler/Driver is not responsible on external devices damages or undefined state due to cancelling a sequence transmission. It is up to the SPI Handler/Driver's environment to be aware to what it is doing!

8.3.14 Spi_SetAsyncMode

[SWS_Spi_00188]

Service Name	Spi_SetAsyncMode	
Syntax	<pre>Std_ReturnType Spi_SetAsyncMode (Spi_AsyncModeType Mode)</pre>	
Service ID [hex]	0x0d	
Sync/Async	Synchronous	
Reentrancy	Non Reentrant	
Parameters (in)	Mode	New mode required.
Parameters (inout)	None	
Parameters (out)	None	
Return value	Std_ReturnType	E_OK: Setting command has been done E_NOT_OK: setting command has not been accepted
Description	Service to set the asynchronous mechanism mode for SPI busses handled asynchronously.	
Available via	Spi.h	

」()

[SWS_Spi_00335] 「The operation `Spi_SetAsyncMode` is Non Re-entrant.」()

[SWS_Spi_00336] 「Return value of the function `Spi_SetAsyncMode` is E_OK: Setting command has been done.」()

[SWS_Spi_00337] 「Return value of the function `Spi_SetAsyncMode` is `E_NOT_OK`: setting command has not been accepted.」()

[SWS_Spi_00338] 「The function `Spi_SetAsyncMode` service to set the asynchronous mechanism mode for SPI buses handled asynchronously.」()

[SWS_Spi_00171] 「If the function `Spi_SetAsyncMode` is called while the SPI Handler/Driver status is `SPI_BUSY` and an asynchronous transmission is in progress, the SPI Handler/Driver shall not change the `AsyncModeType` and keep the mode type as it is. The function shall return the value `E_NOT_OK`.」()

[SWS_Spi_00172] 「If `Spi_SetAsyncMode` is called while a synchronous transmission is in progress, the SPI Handler/Driver shall set the `AsyncModeType` according to parameter 'Mode', even if the SPI Handler/Driver status is `SPI_BUSY`. The function shall return the value `E_OK`.」()

[SWS_Spi_00154] 「The function `Spi_SetAsyncMode` is pre-compile time selectable by the configuration parameter `SpiLevelDelivered`. This function is only relevant for LEVEL 1 and 2.」()

8.4 Callback notifications

This chapter lists all functions provided by the SPI module to lower layer modules.

The SPI Handler/Driver module belongs to the lowest layer of AUTOSAR Software Architecture hence this module specification has not identified any callback functions.

8.5 Scheduled functions

This chapter lists all functions provided by the SPI Handler/Driver and called directly by the Basic Software Module Scheduler.

The SPI Handler/Driver module requires a scheduled function for the management of the asynchronous mode managed with polling (see [SWS_Spi_00361](#)). The specified functions below exemplify how to implement them if they are needed.

8.5.1 Spi_MainFunction_Handling

[SWS_Spi_00189]

Service Name	<code>Spi_MainFunction_Handling</code>
---------------------	--

Syntax	<pre>void Spi_MainFunction_Handling (void)</pre>
Service ID [hex]	0x10
Description	--
Available via	SchM_Spi.h

l()

This function shall poll the SPI interrupts linked to HW Units allocated to the transmission of SPI sequences to enable the evolution of transmission state machine.

8.6 Expected Interfaces

This chapter lists all functions that the SPI Handler/Driver requires from other modules.

8.6.1 Mandatory Interfaces

The SPI Handler/Driver module requires some interfaces to fulfill its core functionality.

[SWS_Spi_00389]

API Function	Header File	Description
Det_Report- RuntimeError	Det.h	Service to report runtime errors. If a callout has been configured then this callout shall be called.

l()

8.6.2 Optional Interfaces

This chapter defines all interfaces which are required to fulfill an optional functionality of SPI Handler/Driver module.

[SWS_Spi_00339]

API Function	Header File	Description
Dem_Set- EventStatus	Dem.h	Called by SW-Cs or BSW modules to report monitor status information to the Dem. BSW modules calling Dem_SetEventStatus can safely ignore the return value. This API will be available only if ((Dem/DemConfigSet/DemEventParameter/DemEventReportingType) == STANDARD_REPORTING)
Det_- ReportError	Det.h	Service to report development errors.

]()

8.6.3 Configurable interfaces

In this chapter all interfaces are listed where the target function could be configured. The target function is usually a call-back function. The name of these interfaces is not fixed because they are configurable.

[SWS_Spi_00075] 「The SPI Handler/Driver shall use the callback routines `Spi_JobEndNotification` to inform other software modules about certain states or state changes.」(SRS_SPAL_00157)

[SWS_Spi_00264] 「The SPI Handler/Driver shall use the callback routines `Spi_SeqEndNotification` to inform other software modules about certain states or state changes.」()

[SWS_Spi_00265] 「For implement the call back function other modules are required to provide the routines in the expected manner.」()

[SWS_Spi_00044] 「The SPI Handler/Driver's implementer must implement the callback notifications `Spi_JobEndNotification` and `Spi_SeqEndNotification` as function pointers defined within the initialization data structure (`Spi_ConfigType`).」(SRS_SPAL_12056)

[SWS_Spi_00048] 「The callback notifications `Spi_JobEndNotification` and `Spi_SeqEndNotification` shall have no parameters and no return value.」(SRS_BSW_00359, SRS_BSW_00360, SRS_BSW_00369)

[SWS_Spi_00054] 「If a callback notification is configured as null pointer, no callback shall be executed.」(SRS_SPAL_12056)

[SWS_Spi_00085] 「It is allowed to use the following API calls within the SPI callback notifications:

- `Spi_ReadIB`
- `Spi_WriteIB`
- `Spi_SetupEB`
- `Spi_GetJobResult`
- `Spi_GetSequenceResult`
- `Spi_GetHWUnitStatus`
- `Spi_Cancel`

All other SPI Handler/Driver API calls are not allowed.」()

8.6.3.1 Spi_JobEndNotification

[SWS_Spi_00192]

Service Name	(*Spi_JobEndNotification)
Syntax	<pre>void (*Spi_JobEndNotification) (void)</pre>
Sync/Async	Synchronous
Reentrancy	Reentrant
Parameters (in)	None
Parameters (inout)	None
Parameters (out)	None
Return value	None
Description	Callback routine provided by the user for each Job to notify the caller that a job has been finished.
Available via	Spi_Externals.h

]()

[SWS_Spi_00340] 「The operation SpiJobEndNotification is Re-entrant.」()

[SWS_Spi_00071] 「If the `SpiJobEndNotification` is configured (i.e. not a null pointer), the SPI Handler/Driver shall call the configured callback notification at the end of a Job transmission.」(SRS_SPAL_00157)

Note: This routine might be called on interrupt level, depending on the calling function.

8.6.3.2 Spi_SeqEndNotification

[SWS_Spi_00193]

Service Name	(*Spi_SeqEndNotification)
Syntax	<pre>void (*Spi_SeqEndNotification) (void)</pre>
Sync/Async	Synchronous

Reentrancy	Reentrant
Parameters (in)	None
Parameters (inout)	None
Parameters (out)	None
Return value	None
Description	Callback routine provided by the user for each Sequence to notify the caller that a sequence has been finished.
Available via	Spi_Externals.h

]()

[SWS_Spi_00341] 「The operation SpiSeqEndNotification is Re-entrant.」()

[SWS_Spi_00073] 「If the SpiSeqEndNotification is configured (i.e. not a null pointer), the SPI Handler/Driver shall call the configured callback notification at the end of a Sequence transmission.」(SRS_SPAL_00157)

Note: This routine might be called on interrupt level, depending on the calling function.

8.7 Error detection

8.7.1 API parameter checking

[SWS_Spi_00004] 「SPI Handler/driver shall be able to detect the error SPI_E_PARAM_CHANNEL when API service called with wrong parameter.」(SRS_BSW_00327, SRS_BSW_00337, SRS_BSW_00385)

[SWS_Spi_00237] 「SPI Handler/driver shall be able to detect the error SPI_E_PARAM_JOB when API service called with wrong parameter.」()

[SWS_Spi_00238] 「SPI Handler/driver shall be able to detect the error SPI_E_PARAM_SEQ when API service called with wrong parameter.」()

[SWS_Spi_00240] 「SPI Handler/driver shall be able to detect the error SPI_E_PARAM_LENGTH when API service called with wrong parameter.」()

[SWS_Spi_00241] 「SPI Handler/driver shall be able to detect the error SPI_E_PARAM_UNIT when API service called with wrong parameter.」()

[SWS_Spi_00031] 「The API parameter `Channel` shall have a value within the defined channels in the initialization data structure, and the correct type of channel (IB or EB) has to be used with services. Related error value: SPI_E_PARAM_CHANNEL. Otherwise, the service is not done and the return value shall be E_NOT_OK.」(SRS_BSW_00323)

[SWS_Spi_00032] 「The API parameters `Sequence` and `Job` shall have values within the specified range of values. Related errors values: SPI_E_PARAM_SEQ or SPI_E_PARAM_JOB.」(SRS_BSW_00323)

[SWS_Spi_00060] 「The API parameter `Length` of data shall have a value within the specified buffer maximum value. Related error value: SPI_E_PARAM_LENGTH.」(SRS_BSW_00323)

[SWS_Spi_00258] 「If the API parameter `Length` related service is not done and the return value shall be E_NOT_OK.」()

[SWS_Spi_00143] 「The API parameter `HWUnit` shall have a value within the specified range of values. Related error value: SPI_E_PARAM_UNIT.」()

[SWS_Spi_00288] 「If `HWUnit` related service is not done and the return value shall be SPI_UNINIT.」()

[SWS_Spi_00235] 「If not applicable, the SPI Handler/Driver module's environment shall pass a NULL pointer to the function `Spi_Init`.」()

8.7.2 SPI state checking

[SWS_Spi_00242] 「SPI Handler/driver shall be able to detect the error SPI_E_UNINIT when API service used without module initialization.」()

[SWS_Spi_00046] 「If development error detection for the SPI module is enabled and the SPI Handler/Driver's environment calls any API function before initialization,

an error should be reported to the DET with the error value `SPI_E_UNINIT` according to the configuration.」(SRS_BSW_00406)

[SWS_Spi_00246] 「SPI Handler/driver shall be able to detect the error `SPI_E_ALREADY_INITIALIZED` when API `SPI_Init` service called while the SPI driver has already been initialized time.」()

[SWS_Spi_00233] 「

If development error detection for the SPI module is enabled, the calling of the routine `SPI_Init()` while the SPI driver is already initialized will cause a development error `SPI_E_ALREADY_INITIALIZED` and the desired functionality shall be left without any action.」()

8.7.3 SPI runtime checking

[SWS_Spi_00243] 「SPI Handler/driver shall be able to detect the error `SPI_E_SEQ_PENDING` when services called in a wrong sequence.」()

[SWS_Spi_00245] 「SPI Handler/driver shall be able to detect the error `SPI_E_SEQ_IN_PROCESS` when synchronous transmission service called at wrong time.」()


[SWS_Spi_00195] 「SPI Handler/driver shall be able to detect the error `SPI_E_HARDWARE_ERROR` when an hardware error occur during asynchronous or synchronous transmit. Please see also SWS_Spi_00267 and SWS_Spi_00384.」()

[SWS_Spi_00254] 「If the Sequence and Job related service is not done and, depending on services, either the return value shall be `E_NOT_OK` or a failed result (`SPI_JOB_FAILED` or `SPI_SEQ_FAILED`).」()

[SWS_Spi_00256] 「The SPI Handler/Driver shall not process the invoked function but, depending on the invoked function, shall either return the value `E_NOT_OK` or a failed result (`SPI_JOB_FAILED` or `SPI_SEQ_FAILED`).」()


9 Sequence diagrams

9.1 Initialization



9.2 Modes transitions

The following sequence diagram shows an example of an Init / Delnit calls for a running mode transition.




9.3 Write/AsyncTransmit/Read (IB)

9.3.1 One Channel, one Job then one Sequence

The following sequence diagram shows an example of Spi_WriteIB / Spi_AsyncTransmit / Spi_ReadIB calls for a Sequence transmission with only one Job composed of only one Channel. Write or Read step could be skipped when Job is just reading or writing respectively.

Example: Channel ID 2 belongs to Job ID 1 which belongs to Sequence ID 0

Sequence	Job	Channel
ID0	ID1	ID2




9.3.2 Many Channels, one Job then one Sequence

The following sequence diagram shows an example of Spi_WriteIB / Spi_AsyncTransmit / Spi_ReadIB calls for a Sequence transmission with only one Job composed of many Channels. Write or Read steps could be skipped when Job is just reading or writing respectively.

Example: Channels ID 2 & 3 belong to Job ID 1 which belongs to Sequence ID 0

Sequence	Job	Channel
ID0	ID1	ID2
		ID3




9.3.3 Many Channels, many Jobs and one Sequence

The following sequence diagram shows an example of Spi_WriteIB / Spi_AsyncTransmit / Spi_ReadIB calls for a Sequence transmission of linked Jobs. Write or Read steps could be skipped when Jobs are just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (higher priority), Channels ID 4 to 10 belong to Job ID 2 (Lower priority) which has not an end notification function. These Jobs belong to the same Sequence ID 0

Sequence	Job		Channel
	Name	Priority	
ID0	ID1	High	ID0...ID3
	ID2	Low	ID4...ID10




9.3.4 Many Channels, many Jobs and many Sequences

The following sequence diagram shows an example of Spi_WriteIB / Spi_AsyncTransmit / Spi_ReadIB calls for Sequences transmission. Write or Read steps could be skipped when Jobs are just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (high priority 2), Channels ID 4 to 10 belong to Job ID 2 (Low priority 1) which has not an end notification function. These Jobs belong to the same Sequence ID 0 which is configured as interruptible. Channels ID 11 to 13 belong to Job ID 0 (higher priority 3) which belongs to Sequence ID 1 which is configured as not interruptible.

Sequence		Job		Channel
Name	Interruptible	Name	Priority	
ID0	Yes	ID1	2	ID0...ID3
		ID2	1	ID4...ID10
ID1	No	ID0	3	ID11...ID13



9.4 Setup/AsyncTransmit (EB)

9.4.1 Variable Number of Data / Constant Number of Data

[SWS_Spi_00077] 「To transmit a variable number of data, it is mandatory to call the `Spi_SetupEB` function to store new parameters within SPI Handler/Driver before each `Spi_AsyncTransmit` function call.」(SRS_Spi_12198, SRS_Spi_12200, SRS_Spi_12201)


[SWS_Spi_00078] 「To transmit a constant number of data, it is only mandatory to call the `Spi_SetupEB` function to store parameters within SPI Handler/Driver before the first `Spi_AsyncTransmit` function call.」(SRS_Spi_12253, SRS_Spi_12262, SRS_Spi_12202)

9.4.2 One Channel, one Job then one Sequence

The following sequence diagram shows an example of `Spi_SetupEB` / `Spi_AsyncTransmit` calls for a Sequence transmission with only one Job composed of only one Channel. Write or Read accesses are “User Dependant” and could be skipped when Job is just reading or writing respectively.

Example: Channel ID 2 belongs to Job ID 1 which belongs to Sequence ID 0

<i>Sequence</i>	<i>Job</i>	<i>Channel</i>
ID0	ID1	ID2




9.4.3 Many Channels, one Job then one Sequence

The following sequence diagram shows an example of `Spi_SetupEB` / `Spi_AsyncTransmit` calls for a Sequence transmission with only one Job composed of many Channels. Write or Read accesses are “User Dependant” and could be skipped when Job is just reading or writing respectively.

Example: Channels ID 2 & 3 belong to Job ID 1 which belongs to Sequence ID 0

Sequence	Job	Channel
ID0	ID1	ID2
		ID3




9.4.4 Many Channels, many Jobs and one Sequence

The following sequence diagram shows an example of `Spi_SetupEB` / `Spi_AsyncTransmit` calls for a Sequence transmission of linked Jobs. Write or Read accesses are “User Dependant” and could be skipped when Job is just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (higher priority), Channels ID 4 to 10 belong to Job ID 2 (Lower priority) which has not an end notification function. These Jobs belong to the same Sequence ID 0

Sequence	Job	Channel
ID0	ID1	ID0...ID3
	ID2	ID4...ID10




9.4.5 Many Channels, many Jobs and many Sequences

The following sequence diagram shows an example of `Spi_SetupEB` / `Spi_AsyncTransmit` calls for Sequences transmission. Write or Read accesses are “User Dependant” and could be skipped when Job is just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (high priority 2), Channels ID 4 to 10 belong to Job ID 2 (Low priority 1) which has not an end notification function. These Jobs belong to the same Sequence ID 0 which is configured as interruptible. Channels ID 11 to 13 belong to Job ID 0 (higher priority 3) which belongs to Sequence ID 1 which is configured as not interruptible.

Sequence		Job		Channel
Name	Interruptible	Name	Priority	
ID0	Yes	ID1	2	ID0...ID3
		ID2	1	ID4...ID10
ID1	No	ID0	3	ID11...ID13



9.5 Mixed Jobs Transmission

All kind of mixed Jobs transmission is possible according to the Channels configuration and the priority requirement inside Sequences.

The user knows which Channels are in use. Then, according to the types of these Channels, the appropriate methods shall be called.


9.6 LEVEL 0 SyncTransmit diagrams

9.6.1 Write/SyncTransmit/Read (IB): Many Channels, many Jobs and one Sequence

The following sequence diagram shows an example of Spi_WriteIB / Spi_SyncTransmit / Spi_ReadIB calls for a Sequence transmission of linked Jobs. Write or Read steps could be skipped when Jobs are just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (higher priority), Channels ID 4 to 10 belong to Job ID 2 (Lower priority). These Jobs belong to the same Sequence ID 0

Sequence	Job		Channel
	Name	Priority	
ID0	ID1	High	ID0...ID3
	ID2	Low	ID4...ID10




9.6.2 Setup/SyncTransmit (EB): Many Channels, many Jobs and one Sequence

The following sequence diagram shows an example of `Spi_SetupEB` / `Spi_SyncTransmit` calls for a Sequence transmission of linked Jobs. Write or Read accesses are “User Dependant” and could be skipped when Job is just reading or writing respectively.

Example: Channels ID 0 to 3 belong to Job ID 1 (higher priority), Channels ID 4 to 10 belong to Job ID 2 (Lower priority). These Jobs belong to the same Sequence ID 0

Sequence	Job	Channel
ID0	ID1	ID0...ID3
	ID2	ID4...ID10



10 Configuration specification

10.1 How to read this chapter

For details refer to the chapter 10.1 “Introduction to configuration specification” in *SWS_BSWGeneral*.

10.2 Containers and configuration parameters

The following chapters summarize all configuration parameters. The detailed meanings of the parameters are described in Chapter 7 and Chapter 8. Further hardware / implementation specific parameters can be added if necessary.

[SWS_Spi_00390] [The SPI module shall reject configurations with partition mappings which are not supported by the implementation.]()

10.2.1 Spi

SWS Item	[ECUC_Spi_00103]
Module Name	Spi
Description	Configuration of the Spi (Serial Peripheral Interface) module.
Post-Build Variant Support	true
Supported Config Variants	VARIANT-LINK-TIME, VARIANT-POST-BUILD, VARIANT-PRE-COMPILE

Included Containers		
Container Name	Multiplicity	Scope / Dependency
SpiDem-Event-Parameter-Refs	0..1	Container for the references to DemEventParameter elements which shall be invoked using the API Dem_SetEventStatus in case the corresponding error occurs. The EventId is taken from the referenced DemEventParameter's DemEventId symbolic value. The standardized errors are provided in this container and can be extended by vendor-specific error references.
SpiDriver	1	This container contains the configuration parameters and sub containers of the AUTOSAR Spi module.
SpiGeneral	1	General configuration settings for SPI-Handler
SpiPublished-Information	1	Container holding all SPI specific published information parameters

10.2.2 SpiDemEventParameterRefs

SWS Item	[ECUC_Spi_00240]
Container Name	SpiDemEventParameterRefs
Parent Container	Spi
Description	Container for the references to DemEventParameter elements which shall be invoked using the API Dem_SetEventStatus in case the corresponding error occurs. The EventId is taken from the referenced DemEventParameter's DemEventId symbolic value. The standardized errors are provided in this container and can be extended by vendor-specific error references.
Configuration Parameters	

SWS Item	[ECUC_Spi_00241]		
Parameter Name	SPI_E_HARDWARE_ERROR		
Parent Container	SpiDemEventParameterRefs		
Description	Reference to configured DEM event to report "Hardware failure". If the reference is not configured the error shall not be reported.		
Multiplicity	0..1		
Type	Symbolic name reference to DemEventParameter		
Post-Build Variant Multiplicity	false		
Post-Build Variant Value	false		
Multiplicity Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

No Included Containers

10.2.3 SpiGeneral

SWS Item	[ECUC_Spi_00225]
Container Name	SpiGeneral
Parent Container	Spi
Description	General configuration settings for SPI-Handler
Configuration Parameters	

SWS Item	[ECUC_Spi_00226]		
Parameter Name	SpiCancelApi		
Parent Container	SpiGeneral		
Description	Switches the Spi_Cancel function ON or OFF.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00227]		
Parameter Name	SpiChannelBuffersAllowed		
Parent Container	SpiGeneral		
Description	Selects the SPI Handler/Driver Channel Buffers usage allowed and delivered. IB = 0; EB = 1; IB/EB = 2;		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	0 .. 2		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	

	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00228]		
Parameter Name	SpiDevErrorDetect		
Parent Container	SpiGeneral		
Description	Switches the development error detection and notification on or off. <ul style="list-style-type: none"> true: detection and notification is enabled. false: detection and notification is disabled. 		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	false		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00229]		
Parameter Name	SpiHwStatusApi		
Parent Container	SpiGeneral		
Description	Switches the Spi_GetHWUnitStatus function ON or OFF.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00230]		
Parameter Name	SpiInterruptibleSeqAllowed		
Parent Container	SpiGeneral		
Description	Switches the Interruptible Sequences handling functionality ON or OFF.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local dependency: This parameter depends on SPI_LEVEL_DELIVERED value. It is only used for SPI_LEVEL_DELIVERED configured to 1 or 2.		

SWS Item	[ECUC_Spi_00231]		
Parameter Name	SpiLevelDelivered		
Parent Container	SpiGeneral		
Description	Selects the SPI Handler/Driver level of scalable functionality that is available and delivered.		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	0 .. 2		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00242]		
Parameter Name	SpiMainFunctionPeriod		

Parent Container	SpiGeneral		
Description	This parameter defines the cycle time of the function Spi_MainFunction_Handling in seconds. The parameter is not used by the driver it self, but it is used by upper layer.		
Multiplicity	0..1		
Type	EcucFloatParamDef		
Range]0 .. INF[
Default value	0.01		
Post-Build Variant Multiplicity	false		
Post-Build Variant Value	false		
Multiplicity Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00237]		
Parameter Name	SpiSupportConcurrentSyncTransmit		
Parent Container	SpiGeneral		
Description	Specifies whether concurrent Spi_SyncTransmit() calls for different sequences shall be configurable.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	


Scope / Dependency	scope: local
---------------------------	--------------

SWS Item	[ECUC_Spi_00232]		
Parameter Name	SpiVersionInfoApi		
Parent Container	SpiGeneral		
Description	Switches the Spi_GetVersionInfo function ON or OFF.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	false		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00244]		
Parameter Name	SpiEcucPartitionRef		
Parent Container	SpiGeneral		
Description	Maps the SPI driver to zero or multiple ECUC partitions to make the driver API available in the according partition.		
Multiplicity	0..*		
Type	Reference to EcucPartition		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: ECU		

SWS Item	[ECUC_Spi_00245]		
Parameter Name	SpiKernelEcucPartitionRef		
Parent Container	SpiGeneral		
Description	Maps the SPI kernel to zero or one ECUC partitions to assign the driver kernel to a certain core. The ECUC partition referenced is a subset of the ECUC partitions where the SPI driver is mapped to.		
Multiplicity	0..1		
Type	Reference to EcucPartition		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: ECU		

No Included Containers



[SWS_Spi_CONSTR_00001] [The ECUC partitions referenced by SpiKernelEcucPartitionRef shall be a subset of the ECUC partitions referenced by SpiEcucPartitionRef.]()

[SWS_Spi_CONSTR_00003] [If SpiEcucPartitionRef references one or more ECUC partitions, SpiKernelEcucPartitionRef shall have a multiplicity of one and reference one of these ECUC partitions as well.]()

10.2.4 SpiSequence

SWS Item	[ECUC_Spi_00106]
Container Name	SpiSequence
Parent Container	SpiDriver
Description	All data needed to configure one SPI-sequence
Configuration Parameters	

SWS Item	[ECUC_Spi_00222]		
Parameter Name	SpiInterruptibleSequence		
Parent Container	SpiSequence		
Description	This parameter allows or not this Sequence to be suspended by another one.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local dependency: This SPI_INTERRUPTIBLE_SEQ_ALLOWED parameter as to be configured as ON.		

SWS Item	[ECUC_Spi_00223]
Parameter Name	SpiSeqEndNotification
Parent Container	SpiSequence
Description	This parameter is a reference to a notification function.


Multiplicity	0..1		
Type	EcucFunctionNameDef		
Default value	--		
Regular Expression	--		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00224]		
Parameter Name	SpiSequenceId		
Parent Container	SpiSequence		
Description	SPI Sequence ID, used as parameter in SPI API functions.		
Multiplicity	1		
Type	EcucIntegerParamDef (Symbolic Name generated for this parameter)		
Range	0 .. 255		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: ECU		

SWS Item	[ECUC_Spi_00221]		
Parameter Name	SpiJobAssignment		
Parent Container	SpiSequence		

Description	A sequence references several jobs, which are executed during a communication sequence		
Multiplicity	1..*		
Type	Reference to SpiJob		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

No Included Containers



10.2.5 SpiChannel

SWS Item	[ECUC_Spi_00104]
Container Name	SpiChannel
Parent Container	SpiDriver
Description	All data needed to configure one SPI-channel
Configuration Parameters	

SWS Item	[ECUC_Spi_00200]		
Parameter Name	SpiChannelId		
Parent Container	SpiChannel		
Description	SPI Channel ID, used as parameter in SPI API functions.		
Multiplicity	1		
Type	EcucIntegerParamDef (Symbolic Name generated for this parameter)		
Range	0 .. 255		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00201]		
Parameter Name	SpiChannelType		
Parent Container	SpiChannel		
Description	Buffer usage with EB/IB channel.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	EB	External Buffer	
	IB	Internal Buffer	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME

	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local dependency: SPI_CHANNEL_BUFFERS_ALLOWED		

SWS Item	[ECUC_Spi_00202]		
Parameter Name	SpiDataWidth		
Parent Container	SpiChannel		
Description	This parameter is the width of a transmitted data unit.		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	1 .. 64		
Default value	32		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00203]		
Parameter Name	SpiDefaultData		
Parent Container	SpiChannel		
Description	The default data to be transmitted when (for internal buffer or external buffer) the pointer passed to Spi_WriteIB (for internal buffer) or to Spi_SetupEB (for external buffer) is NULL.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		
Range	0 .. 4294967295		
Default value	--		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME

Class	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		


SWS Item	[ECUC_Spi_00204]		
Parameter Name	SpiEbMaxLength		
Parent Container	SpiChannel		
Description	This parameter contains the maximum size (number of data elements) of data buffers in case of EB Channels and only.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		
Range	1 .. 1048576		
Default value	1024		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local dependency: The SPI_CHANNEL_TYPE parameter has to be configured as EB for this Channel. The SPI_CHANNEL_BUFFERS_ALLOWED parameter has to be configured as 1 or 2.		

SWS Item	[ECUC_Spi_00205]		
Parameter Name	SpiIbNBuffers		
Parent Container	SpiChannel		
Description	This parameter contains the maximum number of data buffers in case of IB Channels and only.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		

Range	1 .. 65535		
Default value	1		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local dependency: The SPI_CHANNEL_TYPE parameter has to be configured as IB for this Channel. The SPI_CHANNEL_BUFFERS_ALLOWED parameter has to be configured as 0 or 2.		

SWS Item	[ECUC_Spi_00206]		
Parameter Name	SpiTransferStart		
Parent Container	SpiChannel		
Description	This parameter defines the first starting bit for transmission.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	LSB	Transmission starts with the Least Significant Bit first	
	MSB	Transmission starts with the Most Significant Bit first	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

No Included Containers



10.2.6 SpiChannelList


SWS Item	[ECUC_Spi_00233]
Container Name	SpiChannelList
Parent Container	SpiJob

Description	References to SPI channels and their order within the Job.
Configuration Parameters	

SWS Item	[ECUC_Spi_00234]		
Parameter Name	SpiChannelIndex		
Parent Container	SpiChannelList		
Description	This parameter specifies the order of Channels within the Job.		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	0 .. 65535		
Default value	0		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00215]		
Parameter Name	SpiChannelAssignment		
Parent Container	SpiChannelList		
Description	A job reference to a SPI channel.		
Multiplicity	1		
Type	Reference to SpiChannel		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

No Included Containers



10.2.7 SpiJob

SWS Item	[ECUC_Spi_00105]
Container Name	SpiJob
Parent Container	SpiDriver
Description	All data needed to configure one SPI-Job, amongst others the connection between the internal SPI unit and the special settings for an external device is done.
Configuration Parameters	

SWS Item	[ECUC_Spi_00218]
Parameter Name	SpiJobEndNotification
Parent Container	SpiJob
Description	This parameter is a reference to a notification function.
Multiplicity	0..1
Type	EcucFunctionNameDef
Default value	--
Regular Expression	--
Post-Build Variant Multiplicity	true
Post-Build Variant Value	true

Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		


SWS Item	[ECUC_Spi_00219]		
Parameter Name	SpiJobId		
Parent Container	SpiJob		
Description	SPI Job ID, used as parameter in SPI API functions.		
Multiplicity	1		
Type	EcucIntegerParamDef (Symbolic Name generated for this parameter)		
Range	0 .. 65535		
Default value	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00220]		
Parameter Name	SpiJobPriority		
Parent Container	SpiJob		
Description	Priority: 0, lowest, 3, highest (see SWS_Spi_00093)		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	0 .. 3		
Default value	--		
Post-Build Variant Value	true		

Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00216]		
Parameter Name	SpiDeviceAssignment		
Parent Container	SpiJob		
Description	Reference to the external device used by this job		
Multiplicity	1		
Type	Reference to SpiExternalDevice		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

Included Containers		
Container Name	Multiplicity	Scope / Dependency
SpiChannelList	1..*	References to SPI channels and their order within the Job.



10.2.8 SpiExternalDevice

SWS Item	[ECUC_Spi_00207]
Container Name	SpiExternalDevice
Parent Container	SpiDriver
Description	The communication settings of an external device. Closely linked to SpiJob.
Configuration Parameters	

SWS Item	[ECUC_Spi_00208]	
Parameter Name	SpiBaudrate	
Parent Container	SpiExternalDevice	
Description	This parameter is the communication baudrate - This parameter allows using a range of values, from the point of view of configuration tools, from Hz up to MHz.	
Multiplicity	1	
Type	EcucFloatParamDef	
Range]0 .. INF[
Default value	1000000	

Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00249]		
Parameter Name	SpiCsBehavior		
Parent Container	SpiExternalDevice		
Description	This parameter is used to define the chip select behavior. Either the CS is toggled for each data frame (bit frame on the SPI bus in relation with SpiData Width) inside the channel(s) composing the job or the CS is kept asserted for the whole job.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	CS_KEEP_ASSERTED	The chip select is kept asserted for the whole job	
	CS_TOGGLE	The chip select is released after each data frame completion	
Default value	CS_KEEP_ASSERTED		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00209]		
Parameter Name	SpiCsIdentifier		
Parent Container	SpiExternalDevice		
Description	This parameter is the symbolic name to identify the Chip Select (CS) allocated to this Job.		
Multiplicity	1		

Type	EcucStringParamDef (Symbolic Name generated for this parameter)		
Default value	--		
Regular Expression	--		
Post-Build Variant Value	false		
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00210]		
Parameter Name	SpiCsPolarity		
Parent Container	SpiExternalDevice		
Description	This parameter defines the active polarity of Chip Select.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	HIGH	--	
	LOW	--	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00239]		
Parameter Name	SpiCsSelection		
Parent Container	SpiExternalDevice		
Description	When the Chip select handling is enabled (see SpiEnableCs), then this parameter specifies if the chip select is handled automatically by Peripheral HW engine or via general purpose IO by Spi driver.		
Multiplicity	0..1		
Type	EcucEnumerationParamDef		
Range	CS_VIA_GPIO	chip select handled via gpio by Spi	

		driver.
	CS_VIA_PERIPHERAL_ENGINE	chip select is handled automatically by Peripheral HW engine.
Default value	CS_VIA_PERIPHERAL_ENGINE	
Post-Build Variant Multiplicity	true	
Post-Build Variant Value	true	
Multiplicity Configuration Class	Pre-compile time	X VARIANT-PRE-COMPILE
	Link time	X VARIANT-LINK-TIME
	Post-build time	X VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X VARIANT-PRE-COMPILE
	Link time	X VARIANT-LINK-TIME
	Post-build time	X VARIANT-POST-BUILD
Scope / Dependency	scope: local dependency: SpiEnableCs	

SWS Item	[ECUC_Spi_00211]		
Parameter Name	SpiDataShiftEdge		
Parent Container	SpiExternalDevice		
Description	This parameter defines the SPI data shift edge.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	LEADING	--	
	TRAILING	--	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00212]
Parameter Name	SpiEnableCs

Parent Container	SpiExternalDevice		
Description	This parameter enables or not the Chip Select handling functions. If this parameter is enabled then parameter SpiCsSelection further details the type of chip selection.		
Multiplicity	1		
Type	EcucBooleanParamDef		
Default value	--		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00217]		
Parameter Name	SpiHwUnit		
Parent Container	SpiExternalDevice		
Description	This parameter is the symbolic name to identify the HW SPI Hardware microcontroller peripheral allocated to this Job.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	CSIB0	--	
	CSIB1	--	
	CSIB2	--	
	CSIB3	--	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00213]
-----------------	------------------

Parameter Name	SpiShiftClockIdleLevel		
Parent Container	SpiExternalDevice		
Description	This parameter defines the SPI shift clock idle level.		
Multiplicity	1		
Type	EcucEnumerationParamDef		
Range	HIGH	--	
	LOW	--	
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00214]		
Parameter Name	SpiTimeClk2Cs		
Parent Container	SpiExternalDevice		
Description	Timing between clock and chip select assertion (in seconds) - This parameter allows to use a range of values from 10 ns up to 0.01 seconds. The real configuration-value used in software BSW-SPI is calculated out of this by the generator-tools.		
Multiplicity	1		
Type	EcucFloatParamDef		
Range	[1E-8 .. 0.01]		
Default value	1E-6		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		


SWS Item	[ECUC_Spi_00247]		
Parameter Name	SpiTimeCs2Clk		

Parent Container	SpiExternalDevice		
Description	Timing between chip select assertion and clock (in seconds) - This parameter allows to use a range of values from 10ns up to 0.01 seconds. The real configuration-value used in software BSW-SPI is calculated out of this by the generator-tools.		
Multiplicity	1		
Type	EcucFloatParamDef		
Range	[1E-8 .. 0.01]		
Default value	1E-6		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00248]		
Parameter Name	SpiTimeCs2Cs		
Parent Container	SpiExternalDevice		
Description	Timing between the negation of the chip select at the end of frame and the assertion of the chip select at the beginning of the next frame (in seconds) - This parameter allows to use a range of values from 10ns up to 0.01 seconds. The real configuration-value used in software BSW-SPI is calculated out of this by the generator-tools.		
Multiplicity	1		
Type	EcucFloatParamDef		
Range	[1E-8 .. 0.01]		
Default value	1E-6		
Post-Build Variant Value	true		
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope /	scope: local		

Dependency			
SWS Item	[ECUC_Spi_00246]		
Parameter Name	SpiDeviceEcucPartitionRef		
Parent Container	SpiExternalDevice		
Description	Maps an SPI external device to zero or multiple ECUC partitions to limit the access to this external device. The ECUC partitions referenced are a subset of the ECUC partitions where the SPI driver is mapped to.		
Multiplicity	0..*		
Type	Reference to EcucPartition		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Value Configuration Class	Pre-compile time	X	All Variants
	Link time	--	
	Post-build time	--	
Scope / Dependency	scope: ECU		

No Included Containers



[SWS_Spi_CONSTR_00002] [The ECUC partitions referenced by SpiDeviceEcucPartitionRef shall be a subset of the ECUC partitions referenced by SpiEcucPartitionRef.]()

[SWS_Spi_CONSTR_00004] [If SpiEcucPartitionRef references one or more ECUC partitions, SpiDeviceEcucPartitionRef shall have a multiplicity of greater than zero and reference one or several of these ECUC partitions as well.]()

10.2.9 SpiDriver

SWS Item	[ECUC_Spi_00091]
Container Name	SpiDriver
Parent Container	Spi
Description	This container contains the configuration parameters and sub containers of the AUTOSAR Spi module.
Configuration Parameters	

SWS Item	[ECUC_Spi_00197]		
Parameter Name	SpiMaxChannel		
Parent Container	SpiDriver		
Description	This parameter contains the number of Channels configured. It will be gathered by tools during the configuration stage.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		
Range	0 .. 65535		
Default value	0		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME


	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00198]		
Parameter Name	SpiMaxJob		
Parent Container	SpiDriver		
Description	Total number of Jobs configured.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		
Range	0 .. 65535		
Default value	0		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		
Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

SWS Item	[ECUC_Spi_00199]		
Parameter Name	SpiMaxSequence		
Parent Container	SpiDriver		
Description	Total number of Sequences configured.		
Multiplicity	0..1		
Type	EcucIntegerParamDef		
Range	0 .. 65535		
Default value	0		
Post-Build Variant Multiplicity	true		
Post-Build Variant Value	true		

Multiplicity Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Value Configuration Class	Pre-compile time	X	VARIANT-PRE-COMPILE
	Link time	X	VARIANT-LINK-TIME
	Post-build time	X	VARIANT-POST-BUILD
Scope / Dependency	scope: local		

Included Containers		
Container Name	Multiplicity	Scope / Dependency
SpiChannel	1..*	All data needed to configure one SPI-channel
SpiExternal-Device	1..*	The communication settings of an external device. Closely linked to Spi Job.
SpiJob	1..*	All data needed to configure one SPI-Job, amongst others the connection between the internal SPI unit and the special settings for an external device is done.
SpiSequence	1..*	All data needed to configure one SPI-sequence



10.2.10 SpiPublishedInformation

SWS Item	[ECUC_Spi_00235]
Container Name	SpiPublishedInformation
Parent Container	Spi
Description	Container holding all SPI specific published information parameters
Configuration Parameters	

SWS Item	[ECUC_Spi_00236]		
Parameter Name	SpiMaxHwUnit		
Parent Container	SpiPublishedInformation		
Description	Number of different SPI hardware microcontroller peripherals (units/busses) available and handled by this SPI Handler/Driver module.		
Multiplicity	1		
Type	EcucIntegerParamDef		
Range	0 .. 65535		
Default value	0		
Post-Build Variant Value	false		
Value Configuration Class	Published Information	X	All Variants
Scope / Dependency	scope: local		

No Included Containers

10.3 Published information


For details refer to the chapter 10.3 “Published Information” in *SWS_BSWGeneral*

10.4 Configuration concept

There is a relationship between the SPI Handler/Driver module and the modules that use it. This relationship is resolved during the configuration stage and the result of it influences the proper API and behaviour between those modules.

The user needs to provide to the SPI Handler/Driver part of the configuration to adapt it to its necessities. The SPI Handler/Driver shall take this configuration and provide the needed tools to the user.

The picture shows the information flow during the configuration of the SPI Handler/Driver. It is shown only for one user, using an External EEPROM Driver as example, but this situation is common to all users of the SPI Handler/Driver. To highlight the situation where more users are affected, several overlapping documents are drawn.



The steps on the diagrams are:

1. The user (External EEPROM Driver) of SPI Handler/Driver edits a XML configuration file. This XML configuration file is the same used by the user to generate its own configuration.
2. For each ECU, a XML HW configuration document contains information which should be used in order to configure some parameters.
3. The "SPI generation tool". The Generation tool (here is reflected only the part that generates code to SPI usage) shall generate the handles to export and the instance of the configuration sets. In this step the software integrator will provide missing information.
4. SPI instance configuration file. As a result of the generation all the symbolic handlers needed by the user are included in the configuration header file of the SPI Handler/Driver.
5. User gets the symbolic name of handlers. User imports the handle generated to make use of them as requested by its XML configuration file.


11 Not applicable requirements

[SWS_Spi_NA_00999] 「 These requirements are not applicable to this specification.

」 (SRS_BSW_00301, SRS_BSW_00302, SRS_BSW_00306, SRS_BSW_00307, SRS_BSW_00308, SRS_BSW_00309, SRS_BSW_00312, SRS_BSW_00325, SRS_BSW_00328, SRS_BSW_00330, SRS_BSW_00331, SRS_BSW_00334, SRS_BSW_00341, SRS_BSW_00342, SRS_BSW_00343, SRS_BSW_00347, SRS_BSW_00375, SRS_BSW_00399, SRS_BSW_00400, SRS_BSW_00401, SRS_BSW_00413, SRS_BSW_00416, SRS_BSW_00417, SRS_BSW_00422, SRS_BSW_00423, SRS_BSW_00424, SRS_BSW_00426, SRS_BSW_00427, SRS_BSW_00428, SRS_BSW_00429, SRS_BSW_00432, SRS_BSW_00433, SRS_BSW_00005, SRS_BSW_00006, SRS_BSW_00009, SRS_BSW_00010, SRS_BSW_00161, SRS_BSW_00164, SRS_BSW_00168, SRS_BSW_00170, SRS_BSW_00172, SRS_SPAL_12267, SRS_SPAL_12068, SRS_SPAL_12069, SRS_SPAL_12063, SRS_SPAL_12129, SRS_SPAL_12067, SRS_SPAL_12077, SRS_SPAL_12078, SRS_SPAL_12092, SRS_SPAL_12265)

12 Appendix

The table shown on the next page is just an example to help future users (and/or developers) that have to configure software modules to use the SPI Handler/Driver. This table is independent of the `Spi_ConfigType` structure but contains all elements and aggregations like Channels, Jobs and Sequences.



External EEPROM Write/Read Configuration for SPI Handler/Driver								
Sequences			Jobs			Channels		
Symbolic Name	ID	Attributes	Symbolic Name	ID	Attributes	Symbolic Name	ID	Attributes
EEP_WRITE_SEQ	0	2 (Number of Jobs), {EEP_CMD_JOB, EEP_DATA_JOB} (List of Jobs), Not Interruptible, EEP_vidEndOfWriteSeq	EEP_CMD_JOB	0	SPI_BUS_0, CS_EEPROM, CS_ON, CS_LOW, CLK_2MHz, 1 (time in μ s), Polarity 180, Falling Edge, 3, EEP_vidEndOfStartWrJob, 1 (Number of Channels) {EEP_CMD_CH} (List of Channels)	EEP_CMD_CH	0	EB, 8 bits, 1 data to TxD, MSB First, Default value is 0x00
EEP_READ_SEQ	1	1 (Number of Jobs), {EEP_DATA_JOB} (List of Jobs), Not Interruptible, EEP_vidEndOfReadSeq	EEP_DATA_JOB	1	SPI_BUS_0, CS_EEPROM, CS_ON, CS_LOW, CLK_2MHz, 1 (time in μ s), Polarity 180, Falling Edge, 2, NULL, 3 (Number of Channels) {EEP_CMD_CH, EEP_ADR_CH, EEP_DATA_CH} (List of Channels)	EEP_ADR_CH	1	EB, 16 bits, 1 data to TxD, MSB First, Default value is 0x0000
						EEP_DATA_CH	2	EB, 8 bits, 32 data to TxD, MSB First, Default value is 0x00