



**Department of Electronics and
Electrical Communications Engineering
Faculty of Engineering
Cairo University**



Final Report

Mobile Communications

EDGE: Enhanced Data Rates for GSM Evolution

ELC4017

4th Year

2nd Semester – Academic Year 2025 / 2026

Submitted to

Prof. Hebat-Allah M. Mourad

Presented by

Name	Section	ID	Contribution
Ibrahim Ramadan Ibrahim Hassan	1	9220009	Cell Coverage
Ahmed Khalaf Mohamed Ali	1	9220036	Interference Management
Hassan Osama Hassan Mohamed	2	9202478	Services & Specifications
Hussein Abd El-Aal Ali Abd El-Aal	2	9161160	Radio Interface & Channels
Khaled Mohamed Ramadan Ali	2	9221589	Architecture & Components
Mohamed Khaled Mohamed Shata	3	9203230	

Contents

List of Equations	2
List of Abbreviations	2
1 Introduction	5
2 Network Architecture and Components	6
2.1 The Mobile Station (MS)	6
2.2 Base Station Subsystem (BSS / GERAN)	7
2.3 The Core Network (NSS & GPRS Core)	7
2.4 Architectural Significance of the PCU and Dual Domain Split	8
3 Services & Specifications	8
3.1 High-Speed Mobile Internet and Services	8
3.2 Modulation Scheme	9
3.3 Modulation and Coding Schemes (MCS) & Data Rates	10
3.4 Spectral Efficiency	11
4 Cell Coverage	12
4.1 Introduction	12
4.2 Factors Affecting Coverage	12
4.2.1 Frequency Band	12
4.2.2 Transmit Power and Receiver Sensitivity	12
4.2.3 Terrain and Environment	12
4.3 Propagation Models and Link Budget	12
4.3.1 Free Space and Empirical Path Loss Models	13
4.3.2 Okumura-Hata Model	13
4.3.3 COST-231 Extension	13
4.3.4 Link Budget: The Core Planning Tool	13
4.4 Coverage Enhancement Techniques	14
5 Interference Management	14
5.1 Introduction	14
5.2 Causes of Interference	14
5.3 Measurement of Interference	15
5.4 Mitigation Techniques	15
5.5 Limitations of Interference Mitigation	16
6 Radio Interface & Channel Structure	16
6.1 TDMA Frame Structure and Burst Types	17
6.2 Logical and Packet Channels	17
6.3 Network Interfaces	18
7 Conclusion	21
References	22

List of Figures

1	TheDual Domain Architecture of the EDGE Network [2].	6
2	Comparison of peak theoretical data rates across GSM-family technologies [3, 6].	9
3	8PSK constellation diagram showing eight equally spaced phase states [4, 3].	9
4	Per-time-slot data rate across the MCS ladder [4, 3].	11
5	Modulation efficiency comparison between GMSK and 8PSK [4, 3].	11
6	Link Adaptation Thresholds based on C/I Ratio [3].	16
7	Detailed Packet Core and Control Interfaces [8].	19

List of Tables

2	Hardware and Software Upgrade Requirements from GSM to EDGE [3]. . . .	7
3	Modulation and Coding Schemes (MCS-1 to MCS-9) [4, 3].	10
4	Logical Packet Channels in the Radio Interface [3].	18
5	Critical Standardized Interfaces in the Architecture [3].	20

List of Equations

1	Free-Space Path Loss (FSPL)	13
2	Empirical Power-Law Path Loss	13
3	Okumura-Hata Urban Path Loss Model	13
4	COST-231 Extension to Hata Model	13
5	Received Power Link Budget Equation	13
6	Maximum Allowed Path Loss (MAPL)	13
7	Carrier-to-Interference Ratio (C/I)	15
8	Error Vector Magnitude (EVM)	15

List of Abbreviations

Abbreviation	Meaning
8PSK	8-Phase Shift Keying
AAC	Advanced Audio Coding
ACI	Adjacent Channel Interference
ARQ	Automatic Repeat Request
BER	Bit Error Rate
BIC	Blind Interference Cancellation
BLER	Block Error Rate
BSC	Base Station Controller

Abbreviation	Meaning
BSS	Base Station Subsystem
BTS	Base Transceiver Station
C/I	Carrier-to-Interference Ratio
CCI	Co-Channel Interference
COST	European Cooperation in Science and Technology
CS	Circuit Switched
CSD	Circuit-Switched Data
DARP	Downlink Advanced Receiver Performance
dB	Decibel
dB _i	Decibel over isotropic
dB _m	Decibel-milliwatts
DIR	Dominant to rest of Interference Ratio
EDGE	Enhanced Data rates for GSM Evolution
EGPRS	Enhanced General Packet Radio Service
ERP	Enterprise Resource Planning
EVM	Error Vector Magnitude
FFR	Fractional Frequency Reuse
FH	Frequency Hopping
FSPL	Free-Space Path Loss
GERAN	GSM EDGE Radio Access Network
GGSN	Gateway GPRS Support Node
GMSK	Gaussian Minimum Shift Keying
GPRS	General Packet Radio Service
GPS	Global Positioning System
GSM	Global System for Mobile Communications
HLR	Home Location Register
HSCSD	High-Speed Circuit-Switched Data
HSPA	High Speed Packet Access
IR	Incremental Redundancy
ISI	Intersymbol Interference
JD	Joint Detection
kbps	Kilobits per second
LA	Link Adaptation
LBS	Location-Based Services
MAC	Medium Access Control
MAPL	Maximum Allowed Path Loss
MCS	Modulation and Coding Scheme
ME	Mobile Equipment
MHz	Megahertz
MLSE	Maximum Likelihood Sequence Estimation

Abbreviation	Meaning
MMS	Multimedia Messaging Service
MP3	MPEG-1 Audio Layer III
MS	Mobile Station
MSC	Mobile Switching Center
NSS	Network and Switching Subsystem
PACCH	Packet Associated Control Channel
PCU	Packet Control Unit
PDTCH	Packet Data Traffic Channel
PRACH	Packet Random Access Channel
PS	Packet Switched
PTCCH	Packet Timing Advance Control Channel
QCIF	Quarter Common Intermediate Format
RLC	Radio Link Control
SAIC	Single Antenna Interference Cancellation
SGSN	Serving GPRS Support Node
SIM	Subscriber Identity Module
SNR	Signal-to-Noise Ratio
TDMA	Time Division Multiple Access
TSC	Training Sequence Code
UMTS	Universal Mobile Telecommunications System
VLR	Visitor Location Register
VPN	Virtual Private Network

Abstract

This report provides a comprehensive architectural and operational analysis of Enhanced Data rates for GSM Evolution (EDGE). Widely recognized as a 2.75G technology, EDGE was developed to bridge the gap between legacy 2G GSM/GPRS networks and 3G capabilities without requiring massive infrastructural overhauls. This paper begins by exploring the evolution from GSM, detailing the "Dual Domain" network architecture and the critical hardware upgrades required at the Base Station Subsystem. It then comprehensively analyzes the supported data services, including high-speed internet and MMS. The underlying physical-layer specifications—specifically 8-Phase Shift Keying (8PSK) modulation and adaptive Modulation and Coding Schemes (MCS)—are examined to demonstrate how the system achieves theoretical peak data rates of up to 384 kbps. Furthermore, the report presents rigorous radio coverage planning methods, including Okumura-Hata propagation models and link budget formulations. Dominant interference sources (CCI, ACI, and ISI) are characterized, and physical-layer mitigation techniques (Link Adaptation and SAIC) are evaluated. Finally, the report breaks down the fundamental Radio Interface, detailing the TDMA frame structure, burst types, and standardized network interfaces that allow the seamless decoupling of circuit-switched voice and packet-switched data.

1 Introduction

The evolution of mobile communications from the 2nd Generation (2G) to the 3rd Generation (3G) was not an instantaneous leap, but rather a calculated series of infrastructural upgrades. The Global System for Mobile Communications (GSM) was initially designed as a strictly circuit-switched (CS) network optimized exclusively for voice traffic. The subsequent introduction of General Packet Radio Service (GPRS), often dubbed 2.5G, added packet-switched (PS) capabilities, allowing for basic internet access. However, as data demand surged, telecom operators faced a critical economic challenge: they needed 3G-like data speeds but were hesitant to invest billions of dollars to immediately deploy entirely new Wideband CDMA (WCDMA/UMTS) core networks [1].

To resolve this, the 3GPP standardized **Enhanced Data rates for GSM Evolution (EDGE)**, universally classified as a 2.75G technology. While the EDGE standard technically encompasses both EDGE Circuit Switched Data (ECSD) and Enhanced GPRS (EGPRS), the packet-switched EGPRS became the dominant global standard and serves as the primary focus of this report.

The overarching motivation behind EDGE was to drastically increase the bit rates of the existing GSM/GPRS networks by focusing the upgrades entirely on the air interface rather than the core network [1, 2]. The most significant technological leap was the replacement of standard GSM's Gaussian Minimum Shift Keying (GMSK) with a higher-order modulation scheme known as **8-Phase Shift Keying (8PSK)**. While GMSK transmits 1 bit per symbol, 8PSK transmits 3 bits per symbol. By implementing 8PSK, EDGE effectively tripled the gross data rate of the system while miraculously retaining the exact same 200 kHz channel spacing and TDMA frame structure used by legacy GSM [2]. This allowed operators to deliver high-speed, 3G-like services to users through a simple software and transceiver upgrade at the base station, making EDGE one of the most cost-effective evolutionary steps in telecommunications history.

2 Network Architecture and Components

Unlike modern Long-Term Evolution (LTE) networks, which utilize a flat, all-IP architecture, the EDGE network is strictly a "**Dual Domain**" architecture. It is essentially a hybrid system built by bolting a packet-switched data network on top of a legacy circuit-switched voice network. When a user makes a standard phone call, the traffic is routed through the Circuit-Switched (CS) domain. When a user browses the internet, the traffic is routed through the Packet-Switched (PS) domain [3].




Figure 1: The Dual Domain Architecture of the EDGE Network [2].

As illustrated in Figure 1, the EDGE network architecture is divided into three major functional subsystems: the Mobile Station, the Base Station Subsystem, and the Core Network [3]. The core philosophy of EDGE was to maximize the reuse of existing GSM/GPRS nodes.

2.1 The Mobile Station (MS)

The Mobile Station is the user's physical device. In EDGE, the MS consists of two parts: the Mobile Equipment (the actual phone hardware) and the Subscriber Identity Module (SIM), which handles authentication. A critical architectural concept introduced in GPRS and expanded in EDGE is **Multislot Classes**. Because EDGE utilizes Time Division Multiple Access (TDMA), the 200 kHz frequency channel is divided into 8 timeslots. An EDGE Mobile Station is categorized by a "class" that dictates how many of those 8 timeslots it can process simultaneously for downloading and uploading [3]. Higher multislot classes allow the MS to aggregate more timeslots, directly increasing the user's throughput. Naturally, an EDGE-capable MS requires a more advanced RF transceiver to demodulate the 8PSK signals [2].

2.2 Base Station Subsystem (BSS / GERAN)

The Base Station Subsystem (also referred to as GERAN - GSM/EDGE Radio Access Network) handles all radio-related functions. In EDGE, the radio access is split into three highly distinct pieces of hardware [3]:

- **Base Transceiver Station (BTS):** The physical antennas and radio transceivers. To upgrade a 2G network to EDGE, the BTS hardware required a new transceiver (TRX) board capable of generating and decoding the complex 8PSK modulation waveforms.
- **Base Station Controller (BSC):** The intelligent "brain" that controls multiple BTS towers. It handles radio channel allocation, frequency administration, and handovers between BTS cells. For EDGE, the BSC typically only required a software upgrade to handle the new coding schemes and link adaptation algorithms.
- **Packet Control Unit (PCU):** The PCU was the most critical architectural addition required for EDGE data services. Situated at or near the BSC, the PCU acts as a traffic router. It inspects incoming traffic from the BTS and physically separates it: voice traffic is sent to the circuit-switched core, while packet data is stripped out and routed to the packet-switched internet core [3].

Table 2: Hardware and Software Upgrade Requirements from GSM to EDGE [3].

Network Node	Required Upgrade for EDGE Deployment
Mobile Station	New hardware required to support 8PSK modulation, advanced equalizers, and higher multislot classes.
BTS	Hardware upgrade required (new EDGE-capable TRX boards) to transmit and receive 8PSK.
BSC	Software upgrade only to support EDGE Link Adaptation and Incremental Redundancy protocols.
PCU	Software upgrade to handle higher bandwidth and EDGE-specific RLC/MAC protocols.
SGSN / GGSN	No physical hardware changes; purely reuses existing GPRS infrastructure (software dimensioning only).

Table 2 perfectly encapsulates the economic brilliance of the EDGE architecture. As detailed in the table, the heavy hardware modifications were strictly confined to the extreme edges of the network (the Mobile Station and the BTS antennas). As data moves deeper into the network toward the BSC and the Core, the upgrades become purely software-based, allowing telecom operators to protect their massive infrastructure investments [3].

2.3 The Core Network (NSS & GPRS Core)

Once the PCU separates the traffic, it enters the core network. The legacy voice traffic enters the Network and Switching Subsystem (NSS), which contains the Mobile Switching Center (MSC). The EDGE data traffic, however, enters the specialized GPRS Core Network, which consists of two primary nodes [3]:

- **Serving GPRS Support Node (SGSN):** The SGSN is the mobility management and routing hub for data. It tracks the geographic location of the EDGE mobile station, performs authentication, and handles the routing of data packets to and from the correct BSC.
- **Gateway GPRS Support Node (GGSN):** The GGSN acts as the gateway/firewall between the mobile operator's internal network and external packet data networks (like the global Internet or corporate intranets). It allocates IP addresses to the mobile stations and handles the final routing of data to the outside world [3].

Finally, both the CS and PS domains share the **Home Location Register (HLR)**, a centralized database that stores permanent subscriber information, service profiles, and billing statuses.

2.4 Architectural Significance of the PCU and Dual Domain Split

The introduction of the PCU and the dual-domain architecture in GPRS/EDGE had profound implications for the future of mobile networks [3]:

1. **Decoupling of Voice and Data:** By splitting the traffic at the BSC/PCU level, EDGE ensured that bursty, high-volume internet traffic did not overwhelm the highly sensitive, delay-intolerant MSC voice switches.
2. **Legacy Preservation:** Operators could leave their expensive NSS voice infrastructure completely untouched while independently scaling the capacity of their SGSN/GGSN packet nodes—a generational throughput gain at minimal infrastructure cost [3].
3. **Persistent IP anchoring at the GGSN:** The SGSN/GGSN split (session control / IP anchor) directly prefigures the S-GW and P-GW architecture of LTE-Advanced, demonstrating a clear design continuity across cellular generations [3].
4. **OSS continuity:** Software-only Operations and Maintenance Center (OMC) updates preserved all operational workflows with no structural changes to network management [3].

3 Services & Specifications

EDGE improves network performance through a tightly coupled set of technical enhancements to the GSM/GPRS physical and link layers, enabling a broad portfolio of data services [4]. As a transitional technology, it substantially improves mobile communication capabilities compared to earlier systems [3, 5].

3.1 High-Speed Mobile Internet and Services

EDGE enables significantly faster mobile internet access than its predecessor, GPRS. Whereas GPRS typically delivers 40–60 kbps under field conditions, EDGE achieves up to 384 kbps under optimal radio conditions and sustains 120–200 kbps in typical deployments [3, 6]. This

improvement allows users to browse modern websites, download email attachments, and access online services at speeds that approach those of early fixed-line broadband connections [5].




Figure 2: Comparison of peak theoretical data rates across GSM-family technologies [3, 6].

As shown in Figure 2, EDGE achieves an approximately seven-fold improvement over standard GPRS [3, 6]. Beyond basic browsing, it provides the bandwidth necessary for Multimedia Messaging Service (MMS), VPN tunnels, and access to enterprise middleware platforms [3, 5].

3.2 Modulation Scheme

The most fundamental departure from GPRS is the introduction of **8-Phase Shift Keying (8PSK)** modulation as an alternative to the Gaussian Minimum Shift Keying (GMSK) used in GSM and GPRS [4, 3].




Figure 3: 8PSK constellation diagram showing eight equally spaced phase states [4, 3].

As depicted in Figure 3, unlike GMSK which encodes 1 bit per symbol, 8PSK encodes 3 bits per symbol by exploiting eight distinct phase states separated by 45, tripling the raw symbol capacity of each 200 kHz GSM carrier [5]. Because 8PSK is not a constant-envelope

modulation, terminals require linear power amplifiers, which historically increased device cost compared to GMSK-only handsets [3].

3.3 Modulation and Coding Schemes (MCS) & Data Rates

The standard defines nine Modulation and Coding Schemes (MCS-1 through MCS-9), partitioned into three families based on underlying modulation [4, 3]:

- **MCS-1 to MCS-4** use GMSK modulation with progressively lower code rates, providing high redundancy for poor radio conditions.
- **MCS-5 and MCS-6** also use GMSK but with reduced coding overhead, serving as transitional schemes.
- **MCS-7 to MCS-9** employ 8PSK modulation with minimal redundancy, optimised for high signal quality environments.

Table 3: Modulation and Coding Schemes (MCS-1 to MCS-9) [4, 3].

MCS	Modulation	Code Rate	Rate per Slot (kbps)	Family
MCS-1	GMSK	0.53	8.8	C
MCS-2	GMSK	0.66	11.2	B
MCS-3	GMSK	0.80	14.8	A
MCS-4	GMSK	1.00	17.6	C
MCS-5	GMSK	0.37	22.4	B
MCS-6	GMSK	0.49	29.6	A
MCS-7	8PSK	0.76	44.8	B
MCS-8	8PSK	0.92	54.4	A
MCS-9	8PSK	1.00	59.2	A

Code rate $\approx$ information bits / coded bits per block.

Table 3 details the coding rates and per-slot throughput for all nine schemes. The Link Adaptation (LA) mechanism dynamically selects and adjusts the active MCS based on the measured Block Error Rate (BLER) [3].




Figure 4: Per-time-slot data rate across the MCS ladder [4, 3].

As mapped in Figure 4, the per-time-slot data rate dramatically shifts when the system transitions from GMSK to 8PSK modulation at MCS-7. By allocating multiple time slots simultaneously (up to eight), a Mobile Station can theoretically achieve 384 kbps, offering a robust transitional speed tier before full UMTS deployment [3, 6].

3.4 Spectral Efficiency

Spectral efficiency quantifies the data throughput achievable per unit of radio-frequency bandwidth [3].




Figure 5: Modulation efficiency comparison between GMSK and 8PSK [4, 3].

As illustrated in Figure 5, replacing GMSK with 8PSK triples the raw modulation efficiency of each 200 kHz GSM channel. While 8PSK is more sensitive to channel impairments, it consistently delivers greater average spectral efficiency than GPRS, enabling operators to serve more simultaneous data users on the same carrier without requiring additional frequency spectrum allocation [6].

4 Cell Coverage

4.1 Introduction

Cell coverage refers to the ability of a wireless network to provide an acceptable received signal level to users within a geographic area. Coverage is more challenging than in traditional GSM because higher data-rate services require better signal quality. As data rates increase, stronger signal conditions and higher Signal-to-Noise Ratio (SNR) become necessary. High-speed services generally achieve smaller effective coverage areas compared to conventional voice services. Adaptive transmission techniques are used to maintain reliable communication under varying radio conditions [3].

4.2 Factors Affecting Coverage

4.2.1 Frequency Band

The operating frequency strongly affects coverage performance. GSM/EDGE commonly operates at 850, 900, 1800, and 1900 MHz. Lower frequencies such as 900 MHz provide better propagation characteristics, lower path loss, and larger cell coverage because signals can diffract more effectively around obstacles. In contrast, 1800/1900 MHz bands experience higher path loss, which reduces the maximum cell radius and requires more careful link budget planning [3].

4.2.2 Transmit Power and Receiver Sensitivity

Coverage also depends on transmitter power and receiver sensitivity. Higher transmit power increases signal reach, while better receiver sensitivity allows communication at lower signal levels. High data-rate services generally require stronger received signal conditions; as a result, they achieve smaller coverage areas compared to lower-speed services [3].

4.2.3 Terrain and Environment

The propagation environment has a major impact on coverage. Three main propagation effects are considered:

- **Path Loss:** Signal strength decreases with distance, especially in dense urban environments.
- **Shadow Fading:** Large buildings and terrain obstacles block signals and create variations in received power.
- **Multipath Fading:** Multiple reflected signal paths cause rapid signal fluctuations, especially in urban areas.

Rural environments usually allow larger cell radii due to fewer obstacles, while dense urban environments experience higher attenuation and therefore require smaller cells [3].

4.3 Propagation Models and Link Budget

Propagation models are essential tools used to predict the cell coverage area and the received signal strength. These models allow network engineers to estimate the path loss between the base station and the mobile user [3].

4.3.1 Free Space and Empirical Path Loss Models

The foundation of coverage prediction is path loss modelling. The **Free-Space Path Loss** (FSPL) under line-of-sight conditions is:

$$L = 32.44 + 20 \log_{10}(f) + 20 \log_{10}(d) \quad (1)$$

Where f is frequency (MHz) and d is distance (km).

In realistic terrestrial environments, path loss follows the empirical power law:

$$L = 10\gamma \log_{10}(d) + k \quad (2)$$

Where γ is the path loss slope (typically 3–5) and k is an environment-dependent constant [3].

4.3.2 Okumura-Hata Model

The Okumura-Hata model is the primary empirical propagation model referenced for macro-cellular outdoor environments. The general form for urban environments is:

$$L = 69.55 + 26.16 \log_{10}(f_c) - 13.82 \log_{10}(h_b) - a(h_m) + [44.9 - 6.55 \log_{10}(h_b)] \log_{10}(d) \quad (3)$$

Where f_c is carrier frequency (MHz), h_b is base station height (m), h_m is mobile antenna height (m), and $a(h_m)$ is a correction factor for mobile antenna height.

4.3.3 COST-231 Extension

For 1800 MHz and 1900 MHz deployments in dense urban environments, the COST-231 extension to the Hata model is applied. It adds a metropolitan correction factor C_m (0 dB for medium cities, 3 dB for metropolitan centres):

$$L = 46.3 + 33.9 \log_{10}(f_c) - 13.82 \log_{10}(h_b) - a(h_m) + [44.9 - 6.55 \log_{10}(h_b)] \log_{10}(d) + C_m \quad (4)$$

4.3.4 Link Budget: The Core Planning Tool

The radio link power budget is the fundamental engineering tool for determining the maximum cell range — the maximum allowed propagation path loss — for each service. The received power is determined by:

$$P_{received} = P_{tx} + G_{tx} + G_{rx} - L_{pathloss} - L_{margins} \quad (5)$$

Rearranging to find the Maximum Allowed Path Loss (MAPL):

$$MAPL = P_{tx} + G_{tx} + G_{rx} - L_{tx_cable} - L_{rx_cable} - P_{rx_sensitivity} - M_{interference} - M_{fading} \quad (6)$$

Where:

- P_{tx} : Transmitter output power (e.g., 43 dBm for BTS downlink).
- G_{tx}/G_{rx} : Antenna gains.
- $P_{rx_sensitivity}$: Minimum acceptable received power level.
- $M_{interference}$: Interference degradation margin.
- M_{fading} : Slow fading margin (e.g., approximately 7.3 dB for 95% location probability).

4.4 Coverage Enhancement Techniques

To maintain high-quality service and reliable data rates, sectorization (dividing a cell into multiple directional sectors, typically three of 120°) is used to increase antenna gain and reduce interference from neighboring cells. Furthermore, Microcells are deployed in dense urban environments with low transmit power and a small cell radius (50 to 500 meters) to significantly improve indoor and hotspot coverage [3].

5 Interference Management

5.1 Introduction

Interference represents the introduction of unwanted electromagnetic signals that distort the desired carrier frequency reception [3]. High data rates are achieved by introducing 8PSK modulation. Unlike GMSK, which uses constant-envelope modulation relying purely on phase transitions, 8PSK encodes information in both phase and amplitude. Because 8PSK maps three bits per symbol, its constellation points have a significantly smaller Euclidean distance between them. Consequently, even minor phase rotations or additive interference can easily shift the received symbol across the decision boundary in the I/Q plane, causing decoding errors. This fundamental physical vulnerability explains the substantially higher Carrier-to-Interference (C/I) requirements compared to legacy GSM [7].

5.2 Causes of Interference

Interference in a cellular network is categorized into three main types [3, 4]:

- **Co-Channel Interference (CCI):** Due to the necessity of Frequency Reuse, cellular networks must reuse the same limited frequency spectrum across different geographic cells. CCI occurs when a mobile station (MS) or base transceiver station (BTS) receives signals from another cell operating on the exact same carrier frequency. This is a dominant limiting factor in dense deployments.
- **Adjacent Channel Interference (ACI):** ACI occurs when power from an adjacent frequency band leaks into the desired channel. This is strictly a hardware and filtering phenomenon caused by imperfect spectral shaping or non-linear power amplification causing spectral regrowth.

- **Intersymbol Interference (ISI):** ISI is a form of self-interference. It occurs due to multipath fading, where the transmitted signal reflects off terrain and buildings. This causes multiple copies of the signal to arrive at the receiver at slightly different times (delay spread). If the delay spread exceeds the guard interval, it forces consecutive 8PSK symbols to smear into one another.

5.3 Measurement of Interference

Interference is rigorously quantified at the physical layer using specific Key Performance Indicators (KPIs). The primary metric is the Carrier-to-Interference Ratio (C/I), which evaluates the ratio of the desired carrier signal power ($P_{carrier}$) to the total interference power ($P_{interference}$) originating from all surrounding sources:

$$C/I \text{ (dB)} = 10 \log_{10} \left(\frac{P_{carrier}}{\sum P_{interference}} \right) \quad (7)$$

While GMSK requires a C/I of approximately 9 dB, decoding the highest Modulation and Coding Scheme (MCS-9) strictly requires a C/I exceeding 30 dB to maintain a Block Error Rate (BLER) below 10% [3]. Error Vector Magnitude (EVM) is another critical metric specifically for 8PSK. It measures the scalar distance between the ideal theoretical position of a constellation point and the actual received point post-interference [7]:

$$EVM = \sqrt{\frac{\frac{1}{N} \sum_{i=1}^N |S_{ideal,i} - S_{actual,i}|^2}{P_{avg}}} \quad (8)$$

5.4 Mitigation Techniques

The standard employs several advanced techniques to avoid or decrease the effects of interference:

Combating CCI, ACI, and ISI: Fractional Frequency Reuse (FFR) and Baseband Frequency Hopping (FH) decrease interference via statistical averaging [3]. At the receiver level, Single Antenna Interference Cancellation (SAIC) mitigates CCI utilizing either Joint Detection (JD) or Blind Interference Cancellation (BIC) techniques. To decrease ISI, the receiver utilizes a Maximum Likelihood Sequence Estimation (MLSE) Equalizer based on the Viterbi algorithm, referencing the 26-bit training sequence to reverse the multipath smearing effect [3].

Link Adaptation (LA) and Incremental Redundancy (IR): When interference cannot be physically eliminated, the network relies on Link Adaptation combined with Incremental Redundancy.




Figure 6: Link Adaptation Thresholds based on C/I Ratio [3].

As illustrated in Figure 6, Link Adaptation dynamically traces the optimal upper envelope of the throughput curves. As the C/I ratio deteriorates (moving left on the x-axis), the system steps down from 8PSK schemes like MCS-9 to highly robust GMSK schemes like MCS-1, sacrificing peak throughput to maintain a non-zero data rate and ensure link stability [3]. Furthermore, the IR mechanism improves the reception of retransmissions by soft-combining the information from the original failed transmission with the new retransmitted block [3].

5.5 Limitations of Interference Mitigation

While the aforementioned techniques significantly improve performance, they are bounded by several fundamental physical and architectural limitations [3, 7]:

- **SAIC Dependencies and Constraints:** The interference suppression capability of an SAIC receiver is strictly bounded by the Dominant to rest of Interference Ratio (DIR). The algorithms excel when a single dominant interferer is present, but their effectiveness drops substantially in low DIR scenarios.
- **Equalizer Complexity:** The computational complexity of the MLSE Viterbi equalizer increases exponentially, and its memory is typically limited to handle delay spreads up to approximately $16 \mu s$. Multipath delay spreads beyond this limit fundamentally break the 8PSK link [7].
- **Throughput Trade-offs:** Mitigation strategies inherently trade performance for stability. Link Adaptation preserves the connection at the cost of drastically lowering user throughput.

6 Radio Interface & Channel Structure

The radio interface is the critical boundary where packet data transitions into physical electromagnetic waveforms. Because the network was designed as an evolutionary upgrade

to GSM, its radio interface strictly adheres to the legacy GSM structural parameters, ensuring full backward compatibility [3]. The system utilizes a combination of Time Division Multiple Access (TDMA) and Frequency Division Multiple Access (FDMA). The available frequency spectrum is divided into 200 kHz carriers (FDMA), and each carrier is further subdivided into 8 distinct timeslots (TDMA), forming a single TDMA frame.

6.1 TDMA Frame Structure and Burst Types

A fundamental unit of transmission is the "burst," which corresponds to the data transmitted during a single timeslot (approximately 0.577 ms). The standard defines five distinct types of bursts to handle different synchronization and data payloads [3, 4]:

- **Normal Burst:** The primary burst used to carry traffic (user data) and control signaling. It contains a 26-bit Training Sequence Code (TSC) in the middle to allow the receiver's equalizer to estimate the channel impulse response.
- **Frequency Correction Burst:** Used for frequency synchronization of the mobile station. It consists entirely of zero-bits, which generates an unmodulated pure sine wave.
- **Synchronization Burst:** Contains a long, 64-bit training sequence to provide precise timing synchronization to the mobile station.
- **Dummy Burst:** Transmitted by the BTS when there is no data to send, ensuring that the carrier maintains a constant power profile for MS measurements.
- **Access Burst:** Transmitted by the MS on the Random Access Channel (RACH) when requesting initial access. It features a significantly extended guard period to account for unknown propagation delays before timing advance is applied.

6.2 Logical and Packet Channels

To efficiently multiplex packet-switched internet traffic over the TDMA frame structure, GPRS and EDGE introduced a 52-multiframe structure (unlike the 26-multiframe used for CS voice). Within this multiframe, data is logically organized into specific Packet Channels [3]:

Table 4: Logical Packet Channels in the Radio Interface [3].

Logical Channel	Direction	Primary Function
PDTCH	Bi-Dir	Packet Data Traffic Channel: Dedicated temporarily to a single MS for transmitting user payload (web data, emails).
PACCH	Bi-Dir	Packet Associated Control Channel: Carries signaling related to a specific MS, such as resource assignment and acknowledgment (ACK/NACK) messages.
PTCCH	Bi-Dir	Packet Timing Advance Control Channel: Continuously estimates and updates the timing advance required to prevent burst overlap due to propagation delays.
PRACH	Uplink	Packet Random Access Channel: Used by the MS to initiate a packet transfer session.

As summarized in Table 4, the RLC/MAC (Radio Link Control / Medium Access Control) layer dynamically maps these logical packet channels onto the physical timeslots. The MAC layer manages the Automatic Repeat Request (ARQ) protocols, operating in either acknowledged mode (for reliable data) or unacknowledged mode (for real-time streaming) [3].

6.3 Network Interfaces

To ensure seamless interoperability between equipment manufactured by different vendors, the 3GPP rigidly standardized the interfaces that connect the network components. Understanding these interfaces is critical to understanding how data traverses the hybrid network [2].




Figure 7: Detailed Packet Core and Control Interfaces [8].

As illustrated in Figure 7 (which highlights the critical radio and serving nodes), the architecture relies on specific connection points to route data through the system. The physical air interface (the radio waves bridging the MS and BTS) constitutes the **Um** interface. Deeper in the network, each interface employs a specific protocol stack designed for either physical transmission robustness or high-speed packet routing [3].

Table 5: Critical Standardized Interfaces in the Architecture [3].

Interface	Connecting Nodes	Functional Description
Um	MS ↔ BTS	The physical air interface. This is where the 8PSK modulation and specific radio link control (RLC) occur.
Abis	BTS ↔ BSC	The terrestrial link transporting both voice frames and packet data to the controller.
A	BSC ↔ MSC	The circuit-switched interface. Carries purely voice and SMS traffic to the core network.
Gb	PCU ↔ SGSN	The packet-switched interface. Utilizes Frame Relay or IP protocols to route internet data away from the voice switches.
Gn	SGSN ↔ GGSN	The IP-based backbone interface of the GPRS core, utilizing the GPRS Tunneling Protocol (GTP).

As summarized in Table 5, the complete set of interfaces includes the deep-core Gn link connecting the SGSN to the GGSN. The most critical fork in the architecture occurs directly after the Abis interface. Once the data reaches the BSC, the Packet Control Unit (PCU) analyzes it. If it is voice traffic, it is routed over the **A interface** to the MSC. If it is packet data, it is routed over the **Gb interface** to the SGSN. This physical routing split is the defining operational characteristic of the network architecture [3].

7 Conclusion

The development and deployment of EDGE represented a masterful engineering compromise between the technical demand for high-speed packet data and the economic reality of existing 2G infrastructure. By restricting major hardware changes to the radio access edges—specifically the Mobile Station and the BTS transceivers—and introducing the Packet Control Unit (PCU) to cleanly separate voice and data traffic, the system achieved a generational leap in performance without requiring a new core network.

Through the implementation of 8-Phase Shift Keying (8PSK) and nine dynamic Modulation and Coding Schemes (MCS), the technology successfully tripled the spectral efficiency of standard GSM channels, pushing theoretical peak rates to 384 kbps. Coverage planning utilized robust link budgets and Okumura-Hata path loss modeling to sustain these data rates. While 8PSK proved highly sensitive to Co-Channel Interference (CCI) and Intersymbol Interference (ISI), the rigorous application of Link Adaptation, Incremental Redundancy, and advanced equalisation (MLSE/SAIC) allowed the network to maintain robust service continuity even under adverse radio conditions.

By retaining the exact legacy TDMA frame structure and defining standardized packet logical channels and interfaces, the dual-domain architecture and IP-anchoring principles established by EDGE laid the direct foundational groundwork for all subsequent mobile broadband technologies, seamlessly paving the evolutionary path toward UMTS, HSPA, and LTE-Advanced.

References

- [1] T. S. Rappaport, *Wireless Communications: Principles and Practice*, 2nd ed. Upper Saddle River, NJ, USA: Prentice Hall, 2002, ch. 2, pp. 54–58. [Online]. Available: <https://telkom2013.wordpress.com/wp-content/uploads/2014/02/wireless-comm-princip-n-practice-theodoresrappaport.pdf>
- [2] A. Furuskär, S. Mazur, F. Muller, and H. Olofsson, “EDGE: Enhanced Data Rates for GSM and TDMA/136 Evolution,” *IEEE Personal Communications*, vol. 6, no. 3, pp. 56–66, Jun. 1999. [Online]. Available: <https://courses.cs.washington.edu/courses/cse590y/02sp/furaskar.pdf>
- [3] T. Halonen, J. Romero, and J. Melero, *GSM, GPRS and EDGE Performance: Evolution Towards 3G/UMTS*, 2nd ed. Chichester, UK: John Wiley & Sons, 2003.
- [4] 3GPP TS 45.005, “Radio transmission and reception,” 3rd Generation Partnership Project (3GPP), Release 99.
- [5] M. Sauter, *Beyond 3G – Bringing Networks, Terminals and the Web Together: LTE, WiMAX, IMS, 4G Devices and the Mobile Web 2.0*. Chichester, UK: John Wiley & Sons, 2010.
- [6] M. R. Bhalla and A. V. Bhalla, “Generations of mobile wireless technology: A survey,” *International Journal of Computer Applications*, vol. 5, no. 4, pp. 26–32, Aug. 2010.
- [7] C. Albuquerque, “Radio Link Performance of Third Generation (3G) Technologies For Wireless Networks,” Master’s thesis, Virginia Tech, VTechWorks, 2002.
- [8] McGraw-Hill Education, “Chapter 5: GPRS and EDGE.” [Online]. Available: <https://pro-s3.mhem2.magento.prod.mheducation.com/downloads/05-ch05.pdf>