

# Access Control Event Types

The access control events are classified as four major types, i.e., alarm events (0x1), exception events (0x2), operation events (0x3), additional information (0x4) and other events (0x5). Each major type corresponds to multiple minor types, see details below.

## Alarm Events (0x1)

| Value | Description                               |
|-------|-------------------------------------------|
| 0x1   | Alarm Input                               |
| 0x2   | Alarm Output                              |
| 0x3   | Motion Detection Alarm Starts             |
| 0x4   | Motion Detection Alarm Stops              |
| 0x5   | Tampering Alarm Starts                    |
| 0x6   | Tampering Alarm Stops                     |
| 0x7   | VCA Alarm Starts                          |
| 0x8   | VCA Alarm Stops                           |
| 0xb   | Network Alarm Starts                      |
| 0xc   | Network Alarm Stops                       |
| 0xd   | Restore Network Alarm                     |
| 0x400 | Zone Short Circuit Attempts Alarm         |
| 0x401 | Zone Disconnected Alarm                   |
| 0x402 | Zone Exception Alarm                      |
| 0x403 | Zone Restored                             |
| 0x404 | Zone Tampering Alarm                      |
| 0x405 | Zone Tampering Restored                   |
| 0x406 | Card Reader Tampering Alarm               |
| 0x407 | Card Reader Tampering Restored            |
| 0x408 | Alarm Input Alarm Triggered               |
| 0x409 | Alarm Input Restored                      |
| 0x40a | Duress Alarm                              |
| 0x40b | No Memory Alarm for Offline Events        |
| 0x40c | Maximum Failed Card Authentications Alarm |
| 0x40d | SD Card Full Alarm                        |

| Value | Description                                        |
|-------|----------------------------------------------------|
| 0x40e | Capture Linkage Alarm                              |
| 0x40f | Secure Door Control Unit Tampering Alarm           |
| 0x410 | Secure Door Control Unit Tampering Restored        |
| 0x411 | POS Starts                                         |
| 0x412 | POS Stops                                          |
| 0x413 | Low Face Picture Quality                           |
| 0x414 | Low Fingerprint Picture Quality                    |
| 0x415 | Fire Input Short Circuit Attempts Alarm            |
| 0x416 | Fire Input Open Circuit Attempts Alarm             |
| 0x417 | Fire Input Restored                                |
| 0x418 | Fire Button Triggered                              |
| 0x419 | Fire Button Resumed                                |
| 0x41a | Maintenance Button Triggered                       |
| 0x41b | Maintenance Button Resumed                         |
| 0x41c | Panic Button Triggered                             |
| 0x41d | Panic Button Resumed                               |
| 0x41e | Distributed Elevator Controller Tampering Alarm    |
| 0x41f | Distributed Elevator Controller Tampering Restored |
| 0x420 | People Density Overload Alarm Starts               |
| 0x421 | People Density Overload Alarm Stops                |
| 0x422 | Lane Controller Tampering Alarm                    |
| 0x423 | Lane Controller Tampering Alarm Restored           |
| 0x424 | Lane Controller Fire Input Alarm                   |
| 0x425 | Lane Controller Fire Input Alarm Restored          |
| 0x426 | Heart Rate Exception Alarm Starts                  |
| 0x427 | Heart Rate Exception Alarm Stops                   |
| 0x428 | Blood Oxygen Exception Alarm Starts                |
| 0x429 | Blood Oxygen Exception Alarm Stops                 |
| 0x42a | Systolic Blood Pressure Exception Alarm Starts     |
| 0x42b | Systolic Blood Pressure Exception Alarm Stops      |
| 0x42c | Diastolic Blood Pressure Exception Alarm Starts    |
| 0x42d | Diastolic Blood Pressure Exception Alarm Stops     |
| 0x42e | Absence Detection Starts                           |
| 0x42f | Absence Detection Stops                            |

| Value          | Description                                                   |
|----------------|---------------------------------------------------------------|
| 0x430          | Standing Detection Starts                                     |
| 0x431          | Standing Detection Stops                                      |
| 0x434          | People Counting Change Starts                                 |
| 0x435          | People Counting Change Stops                                  |
| 0x438          | People Running Starts                                         |
| 0x439          | People Running Stops                                          |
| 0x43a          | Violent Motion Detection Starts                               |
| 0x43b          | Violent Motion Detection Stops                                |
| 0x43c          | People Falling Down Detection Starts                          |
| 0x43d          | People Falling Down Detection Stops                           |
| 0x43e          | People Overstay Detection Starts                              |
| 0x43f          | People Overstay Detection Stops                               |
| 0x440          | No Paper in Printer Alarm                                     |
| 0x441          | Failed Attempts of Opening Door via Password Exceeded Limit   |
| 0x442          | No Memory Alarm for Valid Offline Events                      |
| 0x900 to 0x93f | Access Control: Custom Alarm Event 1 to Custom Alarm Event 64 |
| 0x950          | Smart Lock Duress Alarm (Fingerprint)                         |
| 0x951          | Smart Lock Duress Alarm (Password)                            |
| 0x952          | Smart Lock Broken Alarm                                       |
| 0x953          | Smart Lock Locked Alarm                                       |
| 0x954          | Smart Lock Low Voltage Alarm                                  |
| 0x955          | Smart Lock Blocklist Alarm                                    |
| 0x956          | Smart Lock Device Offline Alarm                               |
| 0x957          | Smart Lock Unlatched Alarm                                    |
| 0x958          | Smart Lock User Not In Alarm                                  |
| 0x959          | Magnetic Contact Detector Alarm                               |
| 0x95a          | Infrared Detector Alarm                                       |
| 0x95b          | Fingerprint Locked Alarm                                      |
| 0x95c          | Password Locked Alarm                                         |
| 0x95d          | Smart Door Lock Duress Alarm                                  |
| 0x95e          | Access Module Fire Input Short Circuit Alarm                  |
| 0x95f          | Restore Access Module Fire Input                              |
| 0x960          | Network Loop Alarm                                            |
| 0x961          | Restore Network Loop Alarm                                    |

## Exception Events (0x2)

| Value | Description                                        |
|-------|----------------------------------------------------|
| 0x21  | Video Signal Loss                                  |
| 0x22  | Illegal Access                                     |
| 0x23  | HDD Full                                           |
| 0x24  | HDD Error                                          |
| 0x25  | MODEM Offline                                      |
| 0x26  | IP Address Conflict                                |
| 0x27  | Network Disconnected                               |
| 0x28  | Recording Error                                    |
| 0x29  | Network Camera Connection Error                    |
| 0x2a  | Video Input Exception                              |
| 0x2b  | Network Camera IP Address Conflicted               |
| 0x2e  | Video Standard Mismatch                            |
| 0x31  | Video Management System: Fan Status Exception      |
| 0x32  | Video Management System: Fan Status Recovered      |
| 0x33  | Video Management System: 6476 Reboot Exception     |
| 0x34  | Video Management System: dm6467 Exception (Buzzer) |
| 0x35  | Network Exception                                  |
| 0x36  | Memory Status Exception                            |
| 0x37  | File Status Exception                              |
| 0x3a  | RS485 Connection Exception                         |
| 0x3b  | RS485 Connection Restored                          |
| 0x400 | Power on                                           |
| 0x401 | Power off                                          |
| 0x402 | Watchdog Reset                                     |
| 0x403 | Low Battery Voltage                                |
| 0x404 | Battery Voltage Restored                           |
| 0x405 | AC Power Disconnected                              |
| 0x406 | AC Power Restored                                  |
| 0x407 | Network Restored                                   |
| 0x408 | Flash Reading and Writing Exception                |
| 0x409 | Card Reader Offline                                |
| 0x40a | Card Reader Online                                 |
| 0x40b | Indicator Turns off                                |
| 0x40c | Indicator Resumed                                  |

| Value | Description                                                      |
|-------|------------------------------------------------------------------|
| 0x40d | Lane Controller Offline                                          |
| 0x40e | Lane Controller Online                                           |
| 0x40f | Secure Door Control Unit Offline                                 |
| 0x410 | Secure Door Control Unit Online                                  |
| 0x411 | Low Battery Voltage (Only for Face Recognition Terminal)         |
| 0x412 | Battery Voltage Recovered (Only for Face Recognition Terminal)   |
| 0x413 | Network of Distributed Access Controller Disconnected            |
| 0x414 | Network of Distributed Access Controller Restored                |
| 0x415 | RS485 Loop of Main Access Controller Disconnected                |
| 0x416 | RS485 Loop of Main Access Controller Connected                   |
| 0x417 | Distributed Access Controller Offline                            |
| 0x418 | Distributed Access Controller Online                             |
| 0x419 | Downstream RS485 Loop of Distributed Access Control Disconnected |
| 0x41a | Downstream RS485 Loop of Distributed Access Control Connected    |
| 0x41b | Distributed Elevator Controller Online                           |
| 0x41c | Distributed Elevator Controller Offline                          |
| 0x41d | ID Card Reader Disconnected                                      |
| 0x41e | ID Card Reader Connected                                         |
| 0x41f | Fingerprint Module Disconnected                                  |
| 0x420 | Fingerprint Module Connected                                     |
| 0x421 | Camera Disconnected                                              |
| 0x422 | Camera Connected                                                 |
| 0x423 | COM Port Disconnected                                            |
| 0x424 | COM Port Connected                                               |
| 0x425 | Device Unauthorized                                              |
| 0x426 | Face Recognition Terminal Online                                 |
| 0x427 | Face Recognition Terminal Offline                                |
| 0x428 | Local Login Lock                                                 |

| Value | Description                                          |
|-------|------------------------------------------------------|
| 0x429 | Local Login Unlock                                   |
| 0x42a | Communication with Anti-passing Back Server Failed   |
| 0x42b | Communication with Anti-passing Back Server Restored |
| 0x42c | Motor or Sensor Exception                            |
| 0x42d | CAN Bus Exception                                    |
| 0x42e | CAN Bus Exception Restored                           |
| 0x42f | Too High Pedestal Temperature                        |
| 0x430 | Active Infrared Intrusion Detector Exception         |
| 0x431 | Active Infrared Intrusion Detector Restored          |
| 0x432 | Communication with Light Board Failed                |
| 0x433 | Communication with Light Board Restored              |
| 0x434 | Communication with IR Adaptor Failed                 |
| 0x435 | Communication with IR Adaptor Restored               |
| 0x436 | Printer Online                                       |
| 0x437 | Printer Offline                                      |
| 0x438 | 4G Module Online                                     |
| 0x439 | 4G Module Offline                                    |
| 0x43a | DSP Starting Failed                                  |
| 0x43b | Smart Rule Not Supported                             |
| 0x43c | Auxiliary Board Disconnected                         |
| 0x43d | Auxiliary Board Connected                            |
| 0x43e | Secure ID Card Unit Exception                        |
| 0x43f | Secure ID Card Unit Restored                         |
| 0x440 | Fingerprint Collection Peripheral Exception          |
| 0x441 | Fingerprint Collection Peripheral Restored           |
| 0x442 | Repetitive Attack                                    |
| 0x443 | TLS Communication Exception                          |
| 0x444 | Smart Disk Offline                                   |
| 0x445 | Smart Disk Online                                    |
| 0x446 | Lock Refund                                          |
| 0x447 | Coding Disk Online                                   |
| 0x448 | Coding Disk Offline                                  |

| Value          | Description                                                                                                                                              |
|----------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|
| 0x449          | Keypad Offline                                                                                                                                           |
| 0x44a          | Keypad Online                                                                                                                                            |
| 0x44b          | 5G Module Online                                                                                                                                         |
| 0x44c          | 5G Module Offline                                                                                                                                        |
| 0x44d          | Extension Module (Modules Externally Accessed via USB and Supporting Hot Swapping: E.g., ID Card Reader, Fingerprint Sensor, Bluetooth, QR Code) Online  |
| 0x44e          | Extension Module (Modules Externally Accessed via USB and Supporting Hot Swapping: E.g., ID Card Reader, Fingerprint Sensor, Bluetooth, QR Code) Offline |
| 0x44f          | Disconnect from Multi-Door Interlocking Server                                                                                                           |
| 0x450          | Restore Communication with Multi-Door Interlocking Server                                                                                                |
| 0x451          | QR Code Reader Offline                                                                                                                                   |
| 0x452          | QR Code Reader Online                                                                                                                                    |
| 0x453          | Lock Health Information Exception                                                                                                                        |
| 0x454          | Unlock Health Information Exception                                                                                                                      |
| 0x455          | Optional Board Offline                                                                                                                                   |
| 0x456          | Restore Optional Board Offline                                                                                                                           |
| 0x457          | Lock Offline                                                                                                                                             |
| 0x458          | Restore Lock Offline                                                                                                                                     |
| 0x459          | Doorbell Offline                                                                                                                                         |
| 0x45a          | Restore Doorbell Offline                                                                                                                                 |
| 0x45b          | Exit Button Offline                                                                                                                                      |
| 0x45c          | Restore Exit Button Offline                                                                                                                              |
| 0x45d          | Lock Low Battery                                                                                                                                         |
| 0x45e          | Lock Low Battery Restored                                                                                                                                |
| 0x45f          | Lock Battery to Be Depleted                                                                                                                              |
| 0x460          | Card Reader Low Battery                                                                                                                                  |
| 0x461          | Card Reader Low Battery Restored                                                                                                                         |
| 0x462          | Exit Button Low Battery                                                                                                                                  |
| 0x463          | Exit Button Low Battery Restored                                                                                                                         |
| 0x464          | Unlocking Stops Unexpectedly                                                                                                                             |
| 0x465          | Locking Stops Unexpectedly                                                                                                                               |
| 0x466          | Relay Offline                                                                                                                                            |
| 0x467          | Restore Relay Offline                                                                                                                                    |
| 0x468          | Relay Low Battery                                                                                                                                        |
| 0x469          | Relay Low Battery Restored                                                                                                                               |
| 0x46a          | Lock Extremely Low Battery                                                                                                                               |
| 0x900 to 0x93f | Access Control: Custom Exception Event 1 to Custom Exception Event 64                                                                                    |

| Value | Description                                                           |
|-------|-----------------------------------------------------------------------|
| 0x950 | Switch to Wired Network                                               |
| 0x951 | Switch to Wireless Network                                            |
| 0x952 | Restore Smart Lock Offline                                            |
| 0x953 | USB Camera Online                                                     |
| 0x954 | USB Camera Offline                                                    |
| 0x955 | Communication Exception Occurred During Distributed Controller Backup |
| 0x956 | Social Security Card Reader Online                                    |
| 0x957 | Social Security Card Reader Offline                                   |
| 0x958 | Turnstile Infrared Component Exception                                |
| 0x959 | Turnstile Infrared Running Exception                                  |
| 0x95a | Turnstile Infrared Detection Exception                                |
| 0x95b | No Calibration Target in Turnstile Infrared Detection                 |
| 0x95c | Incorrect Calibration Distance from Turnstile Infrared Target         |
| 0x95d | Channel Width Not Applied to Turnstile Infrared Detector              |
| 0x95e | Lock Control Board Online                                             |
| 0x95f | Lock Control Board Offline                                            |

### Operation Events (0x3)

| Value | Description                      |
|-------|----------------------------------|
| 0x41  | Startup                          |
| 0x42  | Shutdown                         |
| 0x43  | Shutdown Exception               |
| 0x44  | Local: Device Restart            |
| 0x50  | Local Login                      |
| 0x51  | Local Logout                     |
| 0x52  | Local: Configuration             |
| 0x53  | Local: Playback/Download by File |
| 0x54  | Local: Playback/Download by Time |
| 0x55  | Local: Start Recording           |
| 0x56  | Local: Stop Recording            |
| 0x59  | Local: Edit Time                 |
| 0x5a  | Local Upgrade                    |
| 0x5b  | Local: Back Up Recording File(s) |
| 0x5c  | Local: Initialize HDD            |
| 0x5d  | Local: Export Configuration File |
| 0x5e  | Local: Import Configuration File |

| Value | Description                                 |
|-------|---------------------------------------------|
| 0x5f  | Local: Back Up Files                        |
| 0x60  | Local: Lock Recording Files                 |
| 0x61  | Local: Unlock Recording Files               |
| 0x62  | Local: Manually Clear and Trigger Alarms    |
| 0x66  | Local: Start Backup                         |
| 0x67  | Local: Stop Backup                          |
| 0x68  | Local: Start Time of Backup                 |
| 0x69  | Local: End Time of Backup                   |
| 0x6d  | Local: Restore Admin's Default Password     |
| 0x70  | Remote Login                                |
| 0x71  | Remote Logout                               |
| 0x72  | Remote: Start Recording                     |
| 0x73  | Remote: Stop Recording                      |
| 0x74  | Start Transparent Transmission              |
| 0x75  | Stop Transparent Transmission               |
| 0x76  | Remote: Get Parameters                      |
| 0x77  | Remote: Configure Parameters                |
| 0x78  | Remote: Get Status                          |
| 0x79  | Remote Arming                               |
| 0x7a  | Remote Disarming                            |
| 0x7b  | Remote Reboot                               |
| 0x7c  | Start Two-Way Audio                         |
| 0x7d  | Stop Two-Way Audio                          |
| 0x7e  | Remote Upgrade                              |
| 0x7f  | Remote: Playback/Download by File           |
| 0x80  | Remote: Playback/Download by Time           |
| 0x83  | Remote: Shutdown                            |
| 0x84  | Remote: Lock File                           |
| 0x85  | Remote: Unlock File                         |
| 0x86  | Remote Operation: Export Configuration File |
| 0x87  | Remote Operation: Import Configuration File |
| 0x88  | Remote: Export Recording Files              |
| 0x89  | Remote: Manually Clear and Trigger Alarms   |
| 0x8a  | Remote: Add Network Camera                  |
| 0x8b  | Remote: Delete Network Camera               |
| 0x8c  | Remote: Set Network Camera                  |

| Value | Description                                     |
|-------|-------------------------------------------------|
| 0x9a  | Remote: Delete Exceptional HDD                  |
| 0x9b  | Remote: Load HDD                                |
| 0x9c  | Remote: Uninstall HDD                           |
| 0x9d  | Local: Lock                                     |
| 0x9e  | Local: Unlock                                   |
| 0xd6  | Remote Operation: Enable Alarm Output Manually  |
| 0xd7  | Remote Operation: Disable Alarm Output Manually |
| 0x137 | Remote: Lock Login                              |
| 0x138 | Remote: Unlock Login                            |
| 0x200 | Other Operations                                |
| 0x400 | Door Remotely Open                              |
| 0x401 | Door Remotely Closed                            |
| 0x402 | Remain Open Remotely                            |
| 0x403 | Remain Closed Remotely                          |
| 0x404 | Remote: Manual Time Sync                        |
| 0x405 | Network Time Protocol Synchronization           |
| 0x406 | Remote Operation: Clear All Card No.            |
| 0x407 | Remote Operation: Restore Defaults              |
| 0x408 | Zone Arming                                     |
| 0x409 | Zone Disarming                                  |
| 0x40a | Local Operation: Restore Defaults               |
| 0x40b | Remote Operation: Capture                       |
| 0x40c | Edit Network Parameters                         |
| 0x40d | Edit GPRS Parameters                            |
| 0x40e | Edit Control Center Parameters                  |
| 0x40f | Enter Dismiss Code                              |
| 0x410 | Auto Renumber                                   |
| 0x411 | Auto Supplement Number                          |
| 0x412 | Import Configuration File                       |
| 0x413 | Export Configuration File                       |

| Value | Description                              |
|-------|------------------------------------------|
| 0x414 | Import Card Permission Parameters        |
| 0x415 | Export Card Permission Parameters        |
| 0x416 | Upgrade Device via USB Flash Drive       |
| 0x417 | Visitor Calling Elevator                 |
| 0x418 | Resident Calling Elevator                |
| 0x419 | Remotely Arming                          |
| 0x41a | Remotely Disarming                       |
| 0x41b | Operation Failed: Keyfob Not Pairing     |
| 0x41c | Keyfob Operation: Close Door             |
| 0x41d | Keyfob Operation: Open Door              |
| 0x41e | Keyfob Operation: Remain Door Open       |
| 0x41f | M1 Card Encryption Verification Enabled  |
| 0x420 | M1 Card Encryption Verification Disabled |
| 0x421 | Opening Door with NFC Card Enabled       |
| 0x422 | Opening Door with NFC Card Disabled      |
| 0x423 | Export Offline Collected Data            |
| 0x42d | Establish SSH Connection                 |
| 0x42e | Disconnect SSH Connection                |
| 0x42f | Local: Import Person Data                |
| 0x430 | Local: Export Person Data                |
| 0x431 | Create Certificate                       |
| 0x432 | Upload Certificate                       |
| 0x433 | Delete Certificate                       |
| 0x434 | Consumption Armed                        |
| 0x435 | Consumption Disarmed                     |
| 0x436 | Change QR Code Secret Key                |
| 0x437 | Remote: Upgrade Lock                     |
| 0x438 | Remote: Upgrade Card Reader              |
| 0x439 | Remote: Upgrade Exit Button              |
| 0x43a | Remote: Upgrade Doorbell                 |
| 0x43b | AP Mode Switch                           |
| 0x43c | Enable Registration Mode                 |
| 0x43d | Card Reader Added                        |
| 0x43e | Lock Added                               |

| Value       | Description                                                           |
|-------------|-----------------------------------------------------------------------|
| 0x43f       | Doorbell Added                                                        |
| 0x440       | Exit Button Added                                                     |
| 0x441       | Delete Card Reader (Unbound from Security Control Panel)              |
| 0x442       | Delete Door Lock (Unbound from Security Control Panel)                |
| 0x443       | Delete Doorbell (Unbound from Security Control Panel)                 |
| 0x444       | Delete Exit Button (Unbound from Security Control Panel)              |
| 0x445       | Enable Card Swiping on Card Reader                                    |
| 0x446       | Disable Swiping Card on Card Reader                                   |
| 0x447       | Enable Card Reader Button                                             |
| 0x448       | Disable Card Reader Button                                            |
| 0x449       | Enable Card Reader Proximity Sensor                                   |
| 0x44a       | Disable Card Reader Proximity Sensor                                  |
| 0x44b       | Enable Card Reader Buzzer                                             |
| 0x44c       | Disable Card Reader Buzzer                                            |
| 0x44d       | Enable Card Reader Bluetooth                                          |
| 0x44e       | Disable Card Reader Bluetooth                                         |
| 0x44f       | Remote: Upgrade Relay                                                 |
| 0x450       | Relay Added                                                           |
| 0x451       | Delete Relay                                                          |
| 0x900-0x93f | Access Control: Custom Operation Event 1 to Custom Operation Event 64 |
| 0x940       | Live Broadcast                                                        |
| 0x941       | Scheduled Broadcast                                                   |
| 0x942       | Local: Import Cuisine Data                                            |
| 0x943       | Local: Export Cuisine Data                                            |
| 0x950       | Set Wi-Fi Parameters                                                  |
| 0x951       | Log In to Cloud Service                                               |
| 0x952       | Log Out from Cloud Service                                            |
| 0x953       | Add Smart Lock                                                        |
| 0x954       | Delete Smart Lock                                                     |
| 0x955       | Get Smart Lock Status                                                 |
| 0x956       | Apply Temporary Password of Smart Lock                                |
| 0x957       | Set Smart Lock Mute Parameters                                        |
| 0x958       | Set Smart Lock Late-Return Notifications                              |
| 0x959       | Link Smart Lock with Network Camera                                   |
| 0x95a       | Unlink Smart Lock with Network Camera                                 |
| 0x95b       | Link Smart Lock with Detector                                         |
| 0x95c       | Unlink Smart Lock with Detector                                       |
| 0x95d       | Enable Smart Lock Message Notification                                |
| 0x95e       | Disable Smart Lock Message Notification                               |
| 0x95f       | Set Smart Lock Heartbeat                                              |

| Value  | Description                                      |
|--------|--------------------------------------------------|
| 0x960  | Reboot Smart Lock                                |
| 0x961  | Clear Users of Smart Lock                        |
| 0x962  | Format Smart Lock                                |
| 0x963  | Change Smart Lock Fingerprint                    |
| 0x964  | Change Smart Lock Password                       |
| 0x965  | Change Smart Lock Card Information               |
| 0x966  | Change Smart Lock User Information               |
| 0x967  | Change Smart Lock System Information             |
| 0x968  | Add User to Smart Lock                           |
| 0x969  | Delete User from Smart Lock                      |
| 0x96a  | Change Username of Smart Lock's Custom User      |
| 0x96b  | Change Smart Lock Keyfob Information             |
| 0x96c  | Add Fingerprint to Smart Lock                    |
| 0x96d  | Delete Fingerprint from Smart Lock               |
| 0x96e  | Add Password to Smart Lock                       |
| 0x96f  | Delete Password from Smart Lock                  |
| 0x970  | Add Card to Smart Lock                           |
| 0x971  | Delete Card from Smart Lock                      |
| 0x972  | Change Smart Lock Network Status                 |
| 0x973  | Clear Smart Lock Network Data                    |
| 0x974  | Clear Smart Lock Hosts                           |
| 0x975  | Clear Smart Lock Guests                          |
| 0x976  | Clear Keyfob User Information                    |
| 0x977  | Clear Normal Users' Fingerprints on Smart Lock   |
| 0x978  | Clear All Cards on Smart Lock                    |
| 0x979  | Clear All Smart Lock Passwords                   |
| 0x97a  | Enable Device Hotspot                            |
| 0x97b  | Disable Device Hotspot                           |
| 0x97c  | Authorize Panic Management Card to Normal Card   |
| 0x97d  | Change Channel Mode                              |
| 0x97e  | Doorbell Event (Triggered by Lock Operation)     |
| 0x97f  | Access Module Restarts                           |
| 0x980  | Restore Access Module Parameters                 |
| 0x981  | Local: Restore Default Parameters of AP Password |
| 0xf0   | Local: Activate Device                           |
| 0xf1   | Remote: Activate Device                          |
| 0xf2   | Local: Restore Default Settings                  |
| 0xf3   | Remote: Restore Default Settings                 |
| 0x2600 | Local: Reset Admin Login Password                |
| 0x2601 | Remote: Reset Admin Login Password               |

## Additional Information (0x4)

| Value | Description                                |
|-------|--------------------------------------------|
| 0xa1  | HDD information                            |
| 0xaa  | System Running Status Information          |
| 0xbd  | Global Error Information                   |
| 0xbe  | Buffer Status Log                          |
| 0xbf  | HDD Error Detailed Information             |
| 0xc0  | Cloud Storage Data Expired                 |
| 0xc1  | Platform Information                       |
| 0xc2  | Dial-Up Status                             |
| 0xc3  | Unlocking Log                              |
| 0xc4  | Zone Alarm                                 |
| 0xc5  | Call Log                                   |
| 0xc6  | Accessory Board Information                |
| 0xc9  | Smart Board Status                         |
| 0xcb  | Auto Time Sync                             |
| 0xcc  | Cloud Service Running Status               |
| 0xd8  | Formatting HDD Starts                      |
| 0xd9  | Formatting HDD Stops                       |
| 0x400 | Enable Live Facial Detection               |
| 0x401 | Disable Live Facial Detection              |
| 0x402 | Clear Collected Data                       |
| 0x403 | Delete Collected Data                      |
| 0x404 | Export Collected Data                      |
| 0x405 | Set Card Length                            |
| 0x406 | Initializing Database Failed               |
| 0x407 | Upgrade Database Patch                     |
| 0x408 | Insert Psam Card                           |
| 0x409 | Pull out Psam Card                         |
| 0x40a | Hardware Restarts Unexpectedly (hardFault) |
| 0x40b | Psam Card Overcurrent Protection           |
| 0x40c | Stack Overflow                             |
| 0x40d | Configure Parameters                       |
| 0x40e | Clear All Users                            |
| 0x40f | Clear All Cards                            |
| 0x410 | Clear All Fingerprints by Card Reader      |
| 0x411 | Clear All Fingerprints by Card No.         |
| 0x412 | Clear All Fingerprints by Employee ID      |
| 0x413 | Delete a Fingerprint                       |
| 0x414 | Clear All Weekly Permission Schedules      |
| 0x415 | Set Weekly Permission Schedule             |

|       |                                              |
|-------|----------------------------------------------|
| 0x416 | Set Holiday Permission Schedule              |
| 0x417 | Clear All Holiday Permission Schedules       |
| 0x418 | Set Holiday Group Permission Schedule        |
| 0x419 | Clear All Holiday Group Permission Schedules |
| 0x41a | Clear All Permission Schedules               |
| 0x41b | Set Permission Schedule                      |
| 0x41c | Add Card                                     |
| 0x41d | Edit Card                                    |
| 0x41e | Add Fingerprint by Card No.                  |
| 0x41f | Add Fingerprint by Employee ID               |
| 0x420 | Edit Fingerprint by card No.                 |
| 0x421 | Edit Fingerprint by Employee ID              |
| 0x422 | Import User List (Collected Offline)         |
| 0x423 | USB Login                                    |
| 0x424 | USB Logout                                   |
| 0x425 | ISAPI and HTTP Login                         |
| 0x426 | ISAPI and HTTP Logout                        |
| 0x427 | ISAPI and HTTPS Login                        |
| 0x428 | ISAPI and HTTPS Logout                       |
| 0x429 | ISUP Online                                  |
| 0x42a | ISUP Offline                                 |
| 0x42b | Fingerprint Card Issuing Records             |
| 0x42c | Face Picture Card Issuing Records            |
| 0x42d | Add Iris                                     |
| 0x42e | Edit Iris                                    |
| 0x42f | Delete Users' Irises (By Employee ID)        |
| 0x430 | Delete All Irises                            |
| 0x431 | Edit Iris Parameters                         |
| 0x432 | Add Person Information                       |
| 0x433 | Edit Person Information                      |
| 0x434 | Delete Person Information (by Employee ID)   |
| 0x435 | Delete Card by Card No. or Employee ID       |
| 0x436 | Delete All Cards                             |
| 0x437 | SIM Card Inserted                            |
| 0x438 | SIM Card Unplugged                           |
| 0x439 | Enable Fingerprint Recognition               |
| 0x43a | Disable Fingerprint Recognition              |
| 0x43b | Enable Face Capture                          |
| 0x43c | Disable Face Capture                         |
| 0x43d | Reset Online Card Reader                     |
| 0x43e | Clear Registered Iris Pictures               |
| 0x43f | Add Voiceprint                               |

|       |                                               |
|-------|-----------------------------------------------|
| 0x440 | Edit Voiceprint                               |
| 0x441 | Delete Voiceprint                             |
| 0x442 | Delete All Voiceprints                        |
| 0x443 | Face Picture Data Library Upgrade Log Records |

## Other Events (0x5)

| Value | Description                                                    |
|-------|----------------------------------------------------------------|
| 0x01  | Valid Card Authentication Completed                            |
| 0x02  | Card and Password Authentication Completed                     |
| 0x03  | Card and Password Authentication Failed                        |
| 0x04  | Card and Password Authentication Timed Out                     |
| 0x05  | Card and Password Authentication Timed Out                     |
| 0x06  | No Permission                                                  |
| 0x07  | Invalid Card Swiping Time Period                               |
| 0x08  | Expired Card                                                   |
| 0x09  | Card No. Not Exist                                             |
| 0x0a  | Anti-passing Back Authentication Failed                        |
| 0x0b  | Interlocking Door Not Closed                                   |
| 0x0c  | Card Not in Multiple Authentication Group                      |
| 0x0d  | Card Not in Multiple Authentication Duration                   |
| 0x0e  | Multiple Authentications: Super Password Authentication Failed |
| 0x0f  | Multiple Authentication Completed                              |
| 0x10  | Multiple Authenticated                                         |
| 0x11  | Open Door with First Card Started                              |
| 0x12  | Open Door with First Card Stopped                              |
| 0x13  | Remain Open Started                                            |
| 0x14  | Remain Open Stopped                                            |
| 0x15  | Door Unlocked                                                  |
| 0x16  | Door Locked                                                    |
| 0x17  | Exit Button Pressed                                            |
| 0x18  | Exit Button Released                                           |

|      |                                                                   |
|------|-------------------------------------------------------------------|
| 0x19 | Door Open (Contact)                                               |
| 0x1a | Door Closed (Contact)                                             |
| 0x1b | Door Abnormally Open (Contact)                                    |
| 0x1c | Door Open Timed Out (Contact)                                     |
| 0x1d | Alarm Output Enabled                                              |
| 0x1e | Alarm Output Disabled                                             |
| 0x1f | Remain Closed Started                                             |
| 0x20 | Remain Closed Stopped                                             |
| 0x21 | Multiple Authentications: Remotely Open Door                      |
| 0x22 | Multiple Authentications: Super Password Authentication Completed |
| 0x23 | Multiple Authentications: Repeated Authentication                 |
| 0x24 | Multiple Authentications Timed Out                                |
| 0x25 | Doorbell Ring                                                     |
| 0x26 | Fingerprint Matched                                               |
| 0x27 | Fingerprint Mismatched                                            |
| 0x28 | Card and Fingerprint Authentication Completed                     |
| 0x29 | Card and Fingerprint Authentication Failed                        |
| 0x2a | Card and Fingerprint Authentication Timed Out                     |
| 0x2b | Card and Fingerprint and Password Authentication Completed        |
| 0x2c | Card and Fingerprint and Password Authentication Failed           |
| 0x2d | Card and Fingerprint and Password Authentication Timed Out        |
| 0x2e | Fingerprint and Password Authentication Completed                 |
| 0x2f | Fingerprint and Password Authentication Failed                    |
| 0x30 | Fingerprint and Password Authentication Timed Out                 |
| 0x31 | Fingerprint Not Exists                                            |
| 0x32 | Card Platform Authentication                                      |
| 0x33 | Call Center                                                       |
| 0x34 | Fire Relay Closed: Door Remains Open                              |
| 0x35 | Fire Relay Opened: Door Remains Closed                            |
| 0x36 | Access Granted by Face and Fingerprint                            |

|      |                                                                   |
|------|-------------------------------------------------------------------|
| 0x37 | Access Denied by Face and Fingerprint                             |
| 0x38 | Access Timed Out by Face and Fingerprint                          |
| 0x39 | Access Granted by Face and PIN                                    |
| 0x3a | Access Denied by Face and PIN                                     |
| 0x3b | Access Timed Out by Face and PIN                                  |
| 0x3c | Access Granted by Face and Card                                   |
| 0x3d | Access Denied by Face and Card                                    |
| 0x3e | Access Timed Out by Face and Card                                 |
| 0x3f | Access Granted by Face, PIN, and Fingerprint                      |
| 0x40 | Access Denied by Face, PIN, and Fingerprint                       |
| 0x41 | Access Timed Out by Face, PIN, and Fingerprint                    |
| 0x42 | Access Granted by Face, Card, and Fingerprint                     |
| 0x43 | Access Denied by Face, Card, and Fingerprint                      |
| 0x44 | Access Timed Out by Face, Card, and Fingerprint                   |
| 0x45 | Employee ID and Fingerprint Authentication Completed              |
| 0x46 | Employee ID and Fingerprint Authentication Failed                 |
| 0x47 | Employee ID and Fingerprint Authentication Timed Out              |
| 0x48 | Employee ID and Fingerprint and Password Authentication Completed |
| 0x49 | Employee ID and Fingerprint and Password Authentication Failed    |
| 0x4a | Employee ID and Fingerprint and Password Authentication Timed Out |
| 0x4b | Face Authentication Completed                                     |
| 0x4c | Face Authentication Failed                                        |
| 0x4d | Employee ID and Face Authentication Completed                     |
| 0x4e | Employee ID and Face Authentication Failed                        |
| 0x4f | Employee ID and Face Authentication Timed Out                     |
| 0x50 | Face Recognition Failed                                           |
| 0x51 | First Card Authorization Started                                  |
| 0x52 | First Card Authorization Ended                                    |
| 0x53 | Lock Input Short Circuit Attempts Alarm                           |
| 0x54 | Lock Input Open Circuit Attempts Alarm                            |
| 0x55 | Lock Input Exception Alarm                                        |
| 0x56 | Contact Input Short Circuit Attempts Alarm                        |
| 0x57 | Contact Input Open Circuit Attempts Alarm                         |

|      |                                                                              |
|------|------------------------------------------------------------------------------|
| 0x58 | Contact Input Exception Alarm                                                |
| 0x59 | Exit Button Input Short Circuit Attempts Alarm                               |
| 0x5a | Exit Button Input Open Circuit Attempts Alarm                                |
| 0x5b | Exit Button Input Exception Alarm                                            |
| 0x5c | Unlocking Exception                                                          |
| 0x5d | Unlocking Timed Out                                                          |
| 0x5e | Unauthorized First Card Opening Failed                                       |
| 0x5f | Call Elevator Relay Open                                                     |
| 0x60 | Call Elevator Relay Closed                                                   |
| 0x61 | Auto Button Relay Open                                                       |
| 0x62 | Auto Button Relay Closed                                                     |
| 0x63 | Button Relay Open                                                            |
| 0x64 | Button Relay Closed                                                          |
| 0x65 | Employee ID and Password Authentication Completed                            |
| 0x66 | Employee ID and Password Authentication Failed                               |
| 0x67 | Employee ID and Password Authentication Timed Out                            |
| 0x68 | Human Detection Failed                                                       |
| 0x69 | Person and ID Card Matched                                                   |
| 0x70 | Person and ID Card Mismatched                                                |
| 0x71 | Blocklist Event                                                              |
| 0x72 | Valid Message                                                                |
| 0x73 | Invalid Message                                                              |
| 0x75 | Authentication Failed: Door Remain Closed or Door in Sleeping Mode           |
| 0x76 | Authentication Failed: Authentication Schedule in Sleeping Mode              |
| 0x77 | Card Encryption Verification Failed                                          |
| 0x78 | Anti-passing Back Server Response Failed                                     |
| 0x82 | Open Door via Exit Button Failed When Door Remain Closed or in Sleeping Mode |
| 0x84 | Door Linkage Open Failed During Door Remain Close or Sleeping                |
| 0x85 | Tailgating                                                                   |

|      |                                                                                        |
|------|----------------------------------------------------------------------------------------|
| 0x86 | Reverse Passing                                                                        |
| 0x87 | Force Accessing                                                                        |
| 0x88 | Climb Over                                                                             |
| 0x89 | Passing Timed Out                                                                      |
| 0x8a | Intrusion Alarm                                                                        |
| 0x8b | Authentication Failed When Free Passing                                                |
| 0x8c | Barrier Obstructed                                                                     |
| 0x8d | Barrier Restored                                                                       |
| 0x8e | Failed to Update Local Face Modeling by Device                                         |
| 0x8f | Overstay                                                                               |
| 0x90 | Allowlist Authentication Succeeded                                                     |
| 0x91 | Authenticating Allowlist Failed                                                        |
| 0x92 | Face Picture Collecting Event (No Authentication, Uploaded during Remote Verification) |
| 0x93 | Card Collecting Event (No Authentication, Uploaded during Remote Verification)         |
| 0x94 | Failed Attempts of Authentication via Password Reached Limit                           |
| 0x95 | ID Card Collecting Event (No Authentication, Uploaded during Remote Verification)      |
| 0x96 | Authentication via Password Failed                                                     |
| 0x97 | Passwords Mismatched                                                                   |
| 0x98 | Employee ID Not Exists                                                                 |
| 0x99 | Combined Authentication Completed                                                      |
| 0x9a | Combined Authentication Timed Out                                                      |
| 0x9b | Authentication Type Mismatched                                                         |
| 0x9c | Authenticated via QR Code                                                              |
| 0x9d | Authentication via QR Code Failed                                                      |
| 0x9e | Authenticated via Householder                                                          |
| 0x9f | Authenticated via Bluetooth                                                            |
| 0xa0 | Authentication via Bluetooth Failed                                                    |
| 0xa1 | Verifying Passport Failed                                                              |
| 0xa2 | Authentication Failed: Invalid M1 Card                                                 |
| 0xa3 | Verifying CPU Card Encryption Failed                                                   |
| 0xa4 | Disabling NFC Verification Failed                                                      |
| 0xa5 | LoRa Module Online                                                                     |

|      |                                                            |
|------|------------------------------------------------------------|
| 0xa6 | LoRa Module Offline                                        |
| 0xa7 | MQTT Connection Status                                     |
| 0xa8 | EM Card Recognition Disabled                               |
| 0xa9 | M1 Card Recognition Disabled                               |
| 0xaa | CPU Card Recognition Disabled                              |
| 0xab | ID Card Recognition Disabled                               |
| 0xac | Importing Key to Card Failed                               |
| 0xad | Local Upgrade Failed                                       |
| 0xae | Remote Upgrade Failed                                      |
| 0xaf | Extension Module is Remotely Upgraded                      |
| 0xb0 | Upgrading Extension Module Remotely Failed                 |
| 0xb1 | Fingerprint Module is Remotely Upgraded                    |
| 0xb2 | Upgrading Fingerprint Module Remotely Failed               |
| 0xb3 | Dynamic Verification Code Authenticated                    |
| 0xb4 | Authentication with Verification Code Failed               |
| 0xb5 | Password Authenticated                                     |
| 0xb6 | Consumption Timed Out                                      |
| 0xb7 | Refund Timed Out                                           |
| 0xb8 | Consumption Amount Exceeded Limit                          |
| 0xb9 | Consumption Times Reached Limit                            |
| 0xba | Consumption Confirmation Timed Out                         |
| 0xbb | Number of Blocklists Reached Limit                         |
| 0xbc | Verifying Desfire Card Encryption Failed                   |
| 0xbd | Desfire Card Reading Disabled                              |
| 0xbe | Access Granted by Iris                                     |
| 0xbf | Access Denied via Iris                                     |
| 0xc0 | Iris Anti-Spoofing Detection Failed                        |
| 0xc1 | Number of People Exceeds 90% of Capacity                   |
| 0xc2 | Local Attendance Records Exceeded Limit                    |
| 0xc3 | Authentication of Dynamic Authentication Code Expired      |
| 0xc4 | Meeting Not Checked In                                     |
| 0xc5 | Meeting Check-In                                           |
| 0xc6 | Meeting Late                                               |
| 0xc9 | Deleting Multi-Door Interlocking Failed                    |
| 0xca | Authentication Failed: Fingerprint Recognition Not Enabled |
| 0xcb | Authentication Failed: Face Capture Disabled               |

|                |                                                                                                           |
|----------------|-----------------------------------------------------------------------------------------------------------|
| 0xcc           | Open Door During Live View                                                                                |
| 0xcd           | Restore Card Reader to Factory Settings                                                                   |
| 0xce           | Card Reader ID Conflict                                                                                   |
| 0xcf           | FeliCa Card Recognition Disabled                                                                          |
| 0xd0           | Authentication Failed Due to Abnormal Features (e.g., Not Wearing Mask or Hard Hat, Abnormal Temperature) |
| 0xd1           | Non Meeting Participant Check-In                                                                          |
| 0xd2           | Meeting Participant Check-In In Vacant Status                                                             |
| 0xd3           | Duplicate Check-In by Meeting Participant                                                                 |
| 0xd4           | Person Authentication Times Reached Limit                                                                 |
| 0xd5           | Upgrading Face Modeling Failed Due to Incompatible Version                                                |
| 0xd6           | Upload Device Unlocking Record Event                                                                      |
| 0xd7           | Door Not-Opened Alarm                                                                                     |
| 0xd8           | Door Not-Closed Alarm                                                                                     |
| 0xd9           | Verifying QR Code Secret Key Failed                                                                       |
| 0xda           | Passing Event                                                                                             |
| 0xdb           | Person and Social Security Card Matched                                                                   |
| 0xdc           | Person and Social Security Card Mismatched                                                                |
| 0xdd           | Wearing Mask                                                                                              |
| 0xdf           | Captured Picture Too Small                                                                                |
| 0xe0           | Access Module Upgraded                                                                                    |
| 0xe1           | Upgrading Access Module Failed                                                                            |
| 0xe2           | Access Granted by Employee ID                                                                             |
| 0xe3           | Access Granted by NFC                                                                                     |
| 0xe4           | Access Denied by NFC                                                                                      |
| 0xe5           | Unlock by Public Password Event                                                                           |
| 0xe6           | Card Reader Upgraded                                                                                      |
| 0xe7           | Upgrading Card Reader Failed                                                                              |
| 0x500 to 0x53f | Access Control: Custom Event 1 to Custom Event 64                                                         |
| 0x540          | Electrostatic Discharge Testing Passed                                                                    |
| 0x541          | Electrostatic Discharge Testing Not Passed (Door Not Opened)                                              |
| 0x542          | Electrostatic Discharge Testing Not Passed (Door Opened)                                                  |
| 0x543          | Electrostatic Discharge Testing Timed Out                                                                 |
| 0x544          | Remotely Import Person Data                                                                               |
| 0x545          | Remotely Export Person Data                                                                               |
| 0x600          | Smart Lock: Open Door with Fingerprint                                                                    |
| 0x601          | Smart Lock: Open Door with Password                                                                       |
| 0x602          | Smart Lock: Open Door by Card Swiping                                                                     |
| 0x603          | Smart Lock: Open Door by Center                                                                           |
| 0x604          | Smart Lock: Open Door with App                                                                            |
| 0x605          | Smart Lock: Open Door with Key                                                                            |
| 0x606          | Smart Lock: Open Door with Keyfob                                                                         |

|       |                                                                     |
|-------|---------------------------------------------------------------------|
| 0x607 | Smart Lock: Open Door with Temporary Password                       |
| 0x608 | Smart Lock: Open Door by Bluetooth                                  |
| 0x609 | Smart Lock: Open Door by Multi-Factor Authentication                |
| 0x700 | Voiceprint Anti-Spoofing Detection Failed                           |
| 0x701 | Voiceprint Authentication Failed                                    |
| 0x702 | Channel Upgrading                                                   |
| 0x703 | Channel Learning                                                    |
| 0x704 | Device Self-Testing                                                 |
| 0x705 | Motor Self-Testing                                                  |
| 0x706 | Barrier Angle Adjusting                                             |
| 0x707 | Access Granted by Palmprint and Palm Veins                          |
| 0x708 | Access Denied by Palmprint and Palm Veins                           |
| 0x709 | Palmprint and Palm Veins Anti-Spoofing Detection Failed             |
| 0x800 | Security Area Is Not Clear                                          |
| 0x801 | Anti-Pinch area Is Not Clear                                        |
| 0x802 | Motor Brake Is Operating                                            |
| 0x803 | Infrared Self-Test Failed                                           |
| 0x804 | Motor Studying Failed                                               |
| 0x805 | Do Not Open Barrier When Lane Is Not Clear                          |
| 0x806 | Exception Occurred In Motor Drive Board                             |
| 0x807 | Exception Occurred In Motor Encoder                                 |
| 0x808 | Motor Is Over Current                                               |
| 0x809 | Motor Is Over Voltage                                               |
| 0x80a | Motor Is Under Voltage                                              |
| 0x80b | Exception Occurred In Motor                                         |
| 0x80c | Permission Authentication Is Intercepted                            |
| 0x80d | Access Granted by Keyfob                                            |
| 0x80e | Access Denied via Keyfob                                            |
| 0x80f | Invalid Face Recognition Angle                                      |
| 0x810 | Secondary Authentication of Large Consumption Failed                |
| 0x811 | Secondary Authentication of Similar Consumer Failed                 |
| 0x812 | Door Offline                                                        |
| 0x813 | Door Interlocking Delaying                                          |
| 0x814 | Passing Allowed (Door Not Used)                                     |
| 0x815 | Lock When Failed Attempts to Authenticate via Card No. Exceed Limit |
| 0x816 | Secure Door Control Unit Not Matched                                |
| 0x817 | Exceptional IR Auto Shield                                          |
| 0x818 | Auto-Restore Exceptional IR                                         |
| 0x819 | Incorrect Cabinet User Type for Article Deposit                     |

# Event Linkage Types

For event card linkages, if the linkage type is event, four major event linkage types are available: 0-device event linkage, 1-alarm input event linkage, 2-access control point (e.g., doors, elevators, etc.) event linkage, and 3-authentication unit (e.g., card reader, fingerprint module, etc.) event linkage. Each major event linkage type corresponds multiple minor types of event linkage, see details in the following content.

## Device Event Linkage

| Value | Description                                       |
|-------|---------------------------------------------------|
| 0     | Access Controller Tampering Alarm                 |
| 1     | No Memory Alarm                                   |
| 2     | Network Disconnected                              |
| 3     | Network Connected                                 |
| 4     | Low Battery Voltage                               |
| 5     | Battery Fully Charged                             |
| 6     | AC Power Off                                      |
| 7     | AC Power On                                       |
| 8     | SD Card Full Alarm                                |
| 9     | Capture Linkage Event Alarm                       |
| 10    | Low Face Picture Quality                          |
| 11    | Low Fingerprint Picture Quality                   |
| 12    | Low Battery Voltage                               |
| 13    | Battery Fully Charged                             |
| 14    | Fire Input Short Circuit Attempts Alarm           |
| 15    | Fire Input Open Circuit Attempts Alarm            |
| 16    | Fire Input Alarm Restored                         |
| 17    | RS485 Loop of Main Access Controller Disconnected |
| 18    | RS485 Loop of Main Access Controller Connected    |
| 19    | Distributed Access Controller Offline             |
| 20    | Distributed Access Controller Online              |

| Value | Description                                                      |
|-------|------------------------------------------------------------------|
| 21    | Downstream RS485 Loop of Distributed Access Control Disconnected |
| 22    | Downstream RS485 Loop of Distributed Access Control Connected    |
| 23    | Distributed Elevator Controller Online                           |
| 24    | Distributed Elevator Controller Offline                          |
| 25    | Fire Button Pressed                                              |
| 26    | Fire Button Released                                             |
| 27    | Maintenance Button Pressed                                       |
| 28    | Maintenance Button Released                                      |
| 29    | Panic Button Pressed                                             |
| 30    | Panic Button Released                                            |
| 32    | Communication with Anti-passing Back Server Failed               |
| 33    | Communication with Anti-passing Back Server Restored             |
| 34    | Remotely Armed                                                   |
| 35    | Remotely Disarmed                                                |
| 36    | Motor or Sensor Exception                                        |
| 37    | CAN Bus Exception                                                |
| 38    | CAN Bus Restored                                                 |
| 39    | Too High Pedestal Temperature                                    |
| 40    | Active Infrared Intrusion Detector Exception                     |
| 41    | Active Infrared Intrusion Detector Restored                      |
| 42    | Communication with Light Board Failed                            |
| 43    | Communication with Light Board Restored                          |
| 44    | Communication with IR Adaptor Failed                             |
| 45    | Communication with IR Adaptor Restored                           |
| 46    | Lane Controller Tampering Alarm                                  |
| 47    | Lane Controller Tampering Alarm Restored                         |
| 48    | Lane Controller Fire Input Alarm                                 |
| 49    | Lane Controller Fire Input Alarm Restored                        |
| 50    | Staying Event                                                    |

| Value | Description                                                 |
|-------|-------------------------------------------------------------|
| 51    | No Memory for Unreported and Access Granted Events          |
| 52    | Fire Input Alarm                                            |
| 53    | No-Mask Alarm                                               |
| 54    | Upload Fire Alarm Matrix                                    |
| 55    | Lock Health Information Exception                           |
| 56    | Unlock Health Information Exception                         |
| 57    | Upload Network Camera Event                                 |
| 58    | Optional Board Offline                                      |
| 59    | Restore Optional Board                                      |
| 60    | Access Module Fire Input Short Circuit Alarm                |
| 61    | Restore Access Module Fire Input                            |
| 62    | Access Module Tempering Alarm                               |
| 63    | Restore Access Module Tempering Alarm                       |
| 64    | Panic Alarm                                                 |
| 65    | Consultation Calling                                        |
| 66    | Main Station Calling                                        |
| 67    | VoIP Calling                                                |
| 68    | Terminal Zone Alarm                                         |
| 69    | Terminal Tempering Alarm                                    |
| 70    | Terminal: Sudden Increase/Decrease of Sound Intensity Alarm |

### Alarm Input Event Linkage

| Value | Description                       |
|-------|-----------------------------------|
| 0     | Zone Short Circuit Attempts Alarm |
| 1     | Zone Open Circuit Attempts Alarm  |
| 2     | Zone Exception Alarm              |
| 3     | Zone Alarm Restored               |
| 4     | Alarm Input Alarm                 |
| 5     | Alarm Input Alarm Restored        |
| 6     | I/O Port Short Circuit Alarm      |

### Access Control Point Event Linkage

| Value | Description                       |
|-------|-----------------------------------|
| 0     | Open Door with First Card Started |

| Value | Description                                                        |
|-------|--------------------------------------------------------------------|
| 1     | Open Door with First Card Ended                                    |
| 2     | Remain Open Started                                                |
| 3     | Remain Open Ended                                                  |
| 4     | Remain Closed Started                                              |
| 5     | Remain Closed Ended                                                |
| 6     | Door Unlocked                                                      |
| 7     | Door Locked                                                        |
| 8     | Exit Button Pressed                                                |
| 9     | Exit Button Released                                               |
| 10    | Door Open (Contact)                                                |
| 11    | Door Closed (Contact)                                              |
| 12    | Door Abnormally Open (Contact)                                     |
| 13    | Door Open Timed Out (Contact)                                      |
| 14    | Door Remotely Open                                                 |
| 15    | Door Remotely Closed                                               |
| 16    | Remain Open Remotely                                               |
| 17    | Remain Closed Remotely                                             |
| 18    | Card Not in Multiple Authentication Group                          |
| 19    | Card Not in Multiple Authentication Duration                       |
| 20    | Multiple Authentication Mode: Super Password Authentication Failed |
| 21    | Multiple Authentication Mode: Remote Authentication Failed         |
| 22    | Multiple Authentication Completed                                  |
| 23    | Multiple Authentication: Remotely Open Door                        |
| 24    | Multiple Authentication: Super Password Authentication Completed   |
| 25    | Multiple Authentication: Repeated Authentication Failed            |
| 26    | Multiple Authentication Timed Out                                  |
| 27    | Remote Capture                                                     |
| 28    | Doorbell Ring                                                      |
| 29    | Secure Door Control Unit Tampering Alarm                           |

| Value | Description                                    |
|-------|------------------------------------------------|
| 30    | Center Event                                   |
| 31    | First Card Authentication Started              |
| 32    | First Card Authentication End                  |
| 33    | Lock Input Short Circuit Attempts Alarm        |
| 34    | Lock Input Open Circuit Attempts Alarm         |
| 35    | Lock Input Exception Alarm                     |
| 36    | Contact Input Short Circuit Attempts Alarm     |
| 37    | Contact Input Open Circuit Attempts Alarm      |
| 38    | Contact Input Exception Alarm                  |
| 39    | Exit Button Input Short Circuit Attempts Alarm |
| 40    | Exit Button Input Open Circuit Attempts Alarm  |
| 41    | Exit Button Input Exception Alarm              |
| 42    | Unlocking Exception                            |
| 43    | Unlocking Timed Out                            |
| 44    | Unauthorized First Card Opening Failed         |
| 45    | Call Elevator Relay Open                       |
| 46    | Call Elevator Relay Closed                     |
| 47    | Auto Button Relay Open                         |
| 48    | Auto Button Relay Closed                       |
| 49    | Button Relay Open                              |
| 50    | Button Relay Closed                            |
| 51    | Visitor Calling Elevator                       |
| 52    | Resident Calling Elevator                      |
| 53    | Valid Message                                  |
| 54    | Invalid Message                                |
| 55    | Tailgating                                     |
| 56    | Reverse Passing                                |
| 57    | Force Collision                                |
| 58    | Climbing Over                                  |

| Value | Description                             |
|-------|-----------------------------------------|
| 59    | Passing Timed Out                       |
| 60    | Intrusion Alarm                         |
| 61    | Authentication Failed When Free Passing |
| 62    | Barrier Obstructed                      |
| 63    | Barrier Restored                        |
| 64    | Door Closed via Keyfob                  |
| 65    | Door Opened via Keyfob                  |
| 66    | Remain Open via Keyfob                  |

### Authentication Unit Event Linkage

| Value | Description                                   |
|-------|-----------------------------------------------|
| 0     | Duress Alarm                                  |
| 1     | Card Reader Tampering Alarm                   |
| 2     | Valid Card Authentication Completed           |
| 3     | Card and Password Authentication Completed    |
| 4     | Card and Password Authentication Failed       |
| 5     | Card and Password Authentication Timed Out    |
| 6     | Card Authentication Attempts Reach Limit      |
| 7     | No Permission for Card                        |
| 8     | Invalid Card Swiping Time Period              |
| 9     | Expired Card                                  |
| 10    | Card No. Not Exist                            |
| 11    | Anti-passing Back Authentication Failed       |
| 12    | Interlocking Door Not Closed                  |
| 13    | Fingerprint Matched                           |
| 14    | Fingerprint Mismatched                        |
| 15    | Card and Fingerprint Authentication Completed |
| 16    | Card and Fingerprint Authentication Failed    |
| 17    | Card and Fingerprint Authentication Timed Out |

| Value | Description                                                            |
|-------|------------------------------------------------------------------------|
| 18    | Card, Fingerprint, and Password Authentication Completed               |
| 19    | Card and Fingerprint Authentication Failed                             |
| 20    | Card and Fingerprint Authentication Timed Out                          |
| 21    | Fingerprint and Password Authentication Completed                      |
| 22    | Fingerprint and Password Authentication Failed                         |
| 23    | Fingerprint and Password Authentication Timed Out                      |
| 24    | Fingerprint Not Exist                                                  |
| 42    | Employee ID and Fingerprint Authentication Completed                   |
| 43    | Employee ID and Fingerprint Authentication Failed                      |
| 44    | Employee ID and Fingerprint Authentication Timed Out                   |
| 45    | Employee ID, Fingerprint, and Password Authentication Completed        |
| 46    | Employee ID, Fingerprint, and Password Authentication Failed           |
| 47    | Employee ID, Fingerprint, and Password Authentication Timed Out        |
| 52    | Employee ID and Password Authentication Completed                      |
| 52    | Employee ID and Password Authentication Failed                         |
| 53    | Employee ID and Password Authentication Timed Out                      |
| 57    | Authentication Failed When Door Remain Closed or Door in Sleeping Mode |
| 58    | Authentication Failed When Authentication Schedule in Sleeping Mode    |
| 59    | Card Encryption Verification Failed                                    |
| 60    | Anti-passing Back Server Response Failed                               |
| 61    | Password Mismatched                                                    |
| 62    | Employee ID Not Exist                                                  |
| 63    | Combined Authentication Completed                                      |
| 64    | Combined Authentication Timed Out                                      |
| 65    | Authentication Type Mismatched                                         |
| 67    | Maximum Password Authentication Failure Attempts                       |
| 68    | Password Authenticated                                                 |
| 69    | Password Authentication Failed                                         |

| Value | Description                                                  |
|-------|--------------------------------------------------------------|
| 70    | QR Code Authenticated                                        |
| 71    | QR Code Authentication Failed                                |
| 72    | Resident Authorization Authenticated                         |
| 73    | Bluetooth Authenticated                                      |
| 74    | Bluetooth Authentication Failed                              |
| 75    | Authentication Failed: Invalid M1 Card                       |
| 76    | Verifying CPU Card Encryption Failed                         |
| 77    | Disabling NFC Verification Failed                            |
| 78    | EM Card Recognition Disabled                                 |
| 7     | M1 Card Recognition Disabled                                 |
| 80    | CPU Card Recognition Disabled                                |
| 81    | ID Card Recognition Disabled                                 |
| 82    | Importing Key to Card Failed                                 |
| 83    | Verifying Desfire Card Encryption Failed                     |
| 84    | Desfire Card Reading Disabled                                |
| 85    | Access Granted by Iris                                       |
| 86    | Access Denied by Iris                                        |
| 87    | Iris Anti-Spoofing Detection Failed                          |
| 88    | FeliCa Card Recognition Disabled                             |
| 89    | QR Code Recognized                                           |
| 90    | Voiceprint Anti-Spoofing Detection Failed                    |
| 91    | Voiceprint Authentication Failed                             |
| 92    | Electrostatic Discharge Testing Passed                       |
| 93    | Electrostatic Discharge Testing Not Passed (Door Opened)     |
| 94    | Electrostatic Discharge Testing Not Passed (Door Not Opened) |
| 95    | Electrostatic Discharge Testing Timed Out                    |
| 96    | Person and Social Security Card Matched                      |
| 97    | Person and Social Security Card Mismatched                   |
| 98    | Access Granted by Palmprint and Palm Veins                   |
| 99    | Access Denied by Palmprint and Palm Veins                    |
| 100   | Blocklist Event                                              |