Waveform-Based Timing Correction for TOF-PET

Research Progress Report

Alessandro Falcetta

10-12-2026

Abstract

Accurate coincidence timing is essential for time-of-flight positron emission tomography. This study investigates machine-learning corrections to leading-edge timing using waveforms from two amplification stages and two readout boards, comparing different estimators, detector-shared formulations, and waveform windows.

Waveform-based correction improves first-stage coincidence timing resolution (CTR) by over 20%, reaching approximately 25% with extended windows. Linear models perform competitively with neural networks, while detector-shared estimators retain most of the achievable correction. Wider windows reveal useful timing information beyond the leading edge. Second-stage signals with Machine Learning correction achieve corrected CTRs of approximately 53 ps.

1 Introduction

Positron emission tomography (PET) detects pairs of annihilation photons to reconstruct radiotracer distributions. Time-of-flight (TOF) information uses the difference between photon arrival times to constrain the annihilation position along the line joining the detectors and can improve image signal-to-noise performance. The precision of this information depends on the coincidence timing resolution (CTR), conventionally expressed as the full width at half maximum (FWHM) of the time-difference distribution [1].

A leading-edge discriminator (LED) assigns an arrival time when a pulse crosses a fixed amplitude threshold. Variations in pulse amplitude and rising-edge shape shift the crossing time, producing time walk. Digitized waveforms retain information about these variations, which machine learning (ML) can exploit to estimate event-specific timing corrections.

Waveform-based approaches include direct TOF estimation and correction of conventional timing measurements. Berg and Cherry demonstrated direct TOF estimation from detector waveform pairs using a convolutional neural network (CNN), improving CTR by 20% relative to LED, from 231 to 185 ps [2]. Onishi et al. combined LED with a CNN trained using waveforms acquired at a single source position, improving timing resolution while avoiding the position-dependent bias associated with direct TOF estimation [3]. Feng et al. explored convolutional features combined with transformer-based attention to capture local and global temporal information [4]. For bismuth germanate (BGO) detectors, Loignon-Houle et al. compared LED, a two-threshold time-walk correction and CNN-based timing, showing that performance gains and timing-distribution tails depend on detector characteristics [5].

An open question is whether waveform samples beyond the rising edge improve ML-based LED timing corrections, and which temporal regions contribute most. Previous CNN studies have primarily examined short windows near the rising edge [3, 5]. We propose an investigation of the temporal sensitivity of ML-based timing corrections, using a wide waveform window and explainable ML methods to identify which regions of the waveform are most relevant to the predictions. This analysis can potentially inform the design of future readout electronics and data acquisition systems, even without capturing complete waveforms in clinical settings.

The analog readout chain is another determinant of timing performance. Amplification can change signal amplitude, bandwidth, noise and rise time, affecting both LED timing and the waveform features accessible to ML. Pourashraf et al. compared front-end readout configurations for silicon photomultiplier (SiPM)-based TOF-PET detectors, reporting a best CTR of 99 ± 2 ps, more than 20 ps better than two alternative configurations [6]. These results highlight the importance of the readout electronics and motivate investigating whether ML corrections can further improve the timing performance of the second amplification-stage output.

Building on previous waveform-based timing studies, this work investigates how different ML approaches exploit detector signals to correct leading-edge timing, rather than focusing exclusively on achieving the lowest CTR. By comparing multiple estimator families and temporal windows, we aim to characterize the timing information available across the waveform and assess the potential of both conventional and dedicated high-gain readouts.

A further objective is to investigate the scalability of ML-based timing calibration. Training a separate model for every detector pair would become impractical in complex PET systems. We therefore introduce detector-shared estimators, which apply the same correction function to both detector waveforms, enforcing antisymmetry under detector exchange. Comparing these models with unconstrained estimators allows us to assess whether detector-specific relationships are necessary or whether general waveform characteristics are sufficient for effective timing correction.

Although complete waveform acquisition may not be practical in clinical systems, this analysis provides a way to investigate which signal characteristics ML models exploit and which temporal regions are most relevant to their predictions. The two electronics boards are evaluated independently using control, development, and blind acquisitions, with temporal sensitivity analysis complementing the timing-performance evaluation.

2 Experimental setup and datasets

2.1 Detector modules and acquisition

Two opposing detector modules consist of silicon photomultipliers (SiPMs) coupled to $2 \times 2 \times 3\,\mathrm{mm}^3$ lutetium–yttrium oxyorthosilicate (LYSO) crystals, with a ^{22}Na source positioned centrally between them. The University of Chicago (UC) and Fondazione Bruno Kessler (FBK) electronic boards use the same crystals and SiPMs but different analog front-end electronics.

The two-stage readout chain is shown in Figure 1. Its first stage produces a relatively long signal suitable for energy estimation and conventional timing. The second provides additional amplification and a sharper signal optimized for timing. This dedicated stage requires a separate 5 V supply, adding hardware and integration challenges that make it difficult to deploy in clinical PET systems. The two outputs are referred to as *energy* and *timing*, respectively.




Figure 1: Two-stage readout chain. Energy and timing waveforms are sampled from successive amplification stages of the same SiPM pulse.

The energy signal is acquired without amplitude clipping, and its maximum is used for photopeak selection. For the high-gain timing signal, the oscilloscope's narrower vertical range emphasizes the rising edge while clipping the pulse peak, following a strategy also used by Onishi et al. [3]. In these acquisitions, the energy waveform is cleaner and more stable but exhibits greater time walk, while the timing waveform is more susceptible to noise and pulse-shape variations.

2.2 Acquisitions and scientific roles

Each coincidence event contains four simultaneous waveforms: first-stage outputs on channels 1 and 2, and second-stage outputs on channels 3 and 4. The 100 ns records are sampled at $80\,\mathrm{GS\,s^{-1}}$ with a SiPM bias of 48 V.

For each board, three independent acquisitions are used: *calibration* to determine preprocessing and LED selection criteria, *train* for model training and selection, and *test* for final evaluation. Each calibration dataset contains approximately 20,000 raw coincidence events, while the train and test sets contain approximately 100,000 events each, before event selection. The two boards are analyzed independently.

Figures 2 and 3 show an example of the energy and timing waveforms from a coincidence event acquisition. Both detector signals are shown for each amplification stage. These are raw waveforms before event selection or preprocessing.




Figure 2: UC raw waveforms: first-stage (energy) and second-stage (timing) signals from both detectors in one event.




Figure 3: FBK raw waveforms: first-stage (energy) and second-stage (timing) signals from both detectors in one event.

3 Methods

3.1 Event selection and LED calibration

Only photopeak events are retained, based on the maximum amplitudes of both first-stage (energy) waveforms. Acceptance intervals are obtained from iterative Gaussian fits to the photopeaks in the calibration acquisition and applied to both waveform modes. For timing-mode analysis, time-over-threshold (ToT) selection additionally rejects short, spurious crossings associated with noise and signal oscillations. Events with excessive pre-pulse baseline fluctuations or baseline samples near the acquisition limits are excluded. All selection criteria are established from calibration data only.

For each waveform, the baseline is estimated from the pre-pulse region and subtracted before timing extraction. The leading-edge discriminator (LED) time is defined as the crossing of a fixed voltage threshold by the baseline-corrected waveform. Because the crossing generally occurs between digitized samples, its time is estimated by linear interpolation between the two samples bracketing the threshold.

For each waveform mode, the LED threshold is chosen on the calibration acquisition to minimize coincidence timing resolution (CTR), subject to a minimum fraction of valid coincidences within the prescribed time range. A fixed channel-pair timing offset is subsequently estimated from the calibration LED residuals. Both the threshold and offset remain unchanged during training and testing.

3.2 Timing-error model and learning target

The goal is to correct waveform-dependent errors in a conventional LED measurement, rather than estimate an unconstrained time of flight directly. For a coincidence event, let $\Delta t_{\mathrm{LED}} = t_{1,\mathrm{LED}} - t_{2,\mathrm{LED}}$. We model this measurement as

$$\Delta t_{\mathrm{LED}} = \tau + C + \delta(s_1, s_2) + \epsilon, \tag{1}$$

where τ is the true time of flight and C is the fixed channel-pair offset. The quantities s_1 and s_2 denote the local waveform segments of detectors 1 and 2, respectively. The term $\delta(s_1, s_2)$ represents the waveform-dependent timing error, while ϵ accounts for residual unpredictable variation. The waveform-dependent component δ is the quantity we aim to estimate and correct using ML.

Writing $\widehat{C}$ for the fixed offset estimated during calibration, the supervised target is

$$y = \Delta t_{\mathrm{LED}} - \tau - \widehat{C}, \tag{2}$$

and the corrected time difference is

$$\widehat{\Delta t} = \Delta t_{\mathrm{LED}} - \widehat{C} - h_\theta(s_1, s_2). \tag{3}$$

The final residual relative to true TOF is:

$$r = \widehat{\Delta t} - \tau = y - h_\theta(s_1, s_2). \tag{4}$$

This formulation separates waveform-dependent timing errors, which can potentially be corrected, from unpredictable noise. The source is positioned centrally between the detectors, giving $\tau = 0$. Any positioning error would introduce a constant offset, which can be absorbed into the calibration term without affecting CTR.

3.3 ML window

For each detector waveform, the LED crossing is first identified and used as a local time reference, with the crossing assigned to $t = 0$. The waveform segment provided to the ML model is then extracted relative to this detector-specific reference time, rather than at a fixed position in the acquisition record. In other words, each input window is centered on the same local signal feature even if the absolute acquisition times of the two detector pulses differ. The waveforms are also normalized using fixed channel-specific amplitude limits. This preprocessing removes the absolute acquisition time from the model input while preserving the waveform shape around the timing feature.

Two LED-relative input windows are considered. The short, Onishi-inspired window extends from −1.5 to +2 ns with respect to the LED crossing and is designed to retain only the local rising-edge region used for timing estimation in previous waveform-based work [3]. The wide window instead extends from −2 to +30 ns and therefore includes a substantially larger portion of the subsequent waveform. This second configuration is used to test whether timing correction benefits from information occurring beyond the immediate LED-crossing region.

Table 1: Waveform windows relative to the LED crossing and number of retained samples after constant-sample removal.

Board	Signal	Onishi-inspired	Wide
UC	Energy	279	2559
UC	Timing	136	991
FBK	Energy	279	2559
FBK	Timing	138	1944

Before constant-sample removal, the short and wide windows contain 279 and 2559 samples per detector, respectively. For clipped timing signals, sample positions that are constant across the training population are removed, since they do not carry discriminative information. The resulting input sizes are reported in Table 1. No samples are removed from the energy waveforms. Events are excluded when a valid coincidence is not available or when the requested LED-relative window cannot be fully extracted.

3.4 Detector-shared and direct corrections

Previous waveform-based timing studies have primarily used direct estimators, which predict the timing correction from the pair of detector waveforms [2, 3]. These models can learn detector-specific relationships without imposing constraints on how the correction changes when the detector inputs are exchanged.

While effective in a two-detector setup, training a separate model for every detector pair would be difficult to scale to a complete PET system. This motivates a detector-shared formulation, in which the correction is expressed as the difference between two evaluations of the same function:

$$h_\theta(s_1, s_2) = g_\theta(s_1) - g_\theta(s_2). \tag{5}$$

The shared function g_θ estimates a waveform-dependent timing contribution for each detector independently. This formulation enforces detector-exchange antisymmetry: swapping the inputs reverses the correction sign, while identical inputs yield zero correction. It also offers a potentially more scalable approach, since the same model can be applied to different physical instances of the same detector type, without requiring parameters specific to each detector pair.

To characterize how the choice of estimator affects waveform-based timing correction, we consider model families with different inductive biases. Linear ridge regression provides a simple and stable baseline. MiniRocket provides an efficient time-series-specific representation. MLPs provide a general nonlinear estimator without explicitly exploiting temporal locality, whereas CNNs incorporate local waveform structure and are included both as a standard time-series architecture and because of their successful use in previous waveform-based timing studies [3, 5]. Locally connected networks retain the local receptive-field structure of CNNs while allowing the learned response to depend on absolute temporal position, which is relevant here because the waveforms are aligned to the LED crossing. Table 2 summarizes

the resulting estimators, while implementation details are provided in the appendix.

3.5 Model comparison and training protocol

The independent calibration, training and test acquisitions serve distinct roles, as summarized in Figure 4. Calibration fixes event selection, LED thresholds and timing offsets. Model fitting and selection use only the training set; the test set is reserved for final evaluation.

The models are trained to predict the LED timing error using a standard regression objective, the mean squared error (MSE):

$$\mathrm{MSE} = \frac{1}{N}\sum_{i=1}^{N}\left[y_i - h_\theta(s_{1,i}, s_{2,i})\right]^2. \tag{6}$$

Model selection is performed through grid search with three-fold cross-validation on the training acquisition, using mean validation CTR as the primary performance criterion. The selected model is then refitted on the full training dataset. The independent test acquisition is subsequently used to compare the observed performance of the tested estimators. Model-specific training procedures and exceptions are detailed in Appendix A.

3.6 Timing performance and independent evaluation

All configurations are evaluated against LED on the same selected test events. CTR is defined as the full width at half maximum (FWHM) of the timing-residual distribution and computed using histogram-based method F1 of Rainio et al. [7]. Identical histogram settings are used for LED and corrected residuals within each mode. The fixed bin widths are 10 ps for energy and 5 ps for timing.

Root mean squared error (RMSE) relative to true TOF complements CTR because it captures both residual dispersion and systematic bias. In particular, $\mathrm{MSE} = \mathrm{Var}(r) + [\mathbb{E}(r)]^2$; a reduction in RMSE need not imply a comparable narrowing of the central timing peak. Both metrics are therefore needed to characterize the effects of calibration and waveform-based correction.

Fixed preprocessing and the fitted model are applied to the independent test acquisition. Test-event bootstrap resampling provides uncertainties on CTR and RMSE without retraining; these estimates are conditional on the selected fitted model. Within-board comparisons use matched test events and joint resampling to assess paired model differences.

3.7 Temporal sensitivity analysis

Preliminary XAI approach. The temporal-sensitivity analysis is still under validation and should be interpreted as exploratory.

To investigate which parts of each waveform influence the predicted correction, temporal occlusion is applied to the fitted models on test events. Consecutive groups of samples are replaced by the detector-specific mean waveform evaluated at the same sample positions. For detector c, the reference waveform is computed over the selected control events as

$$\mu_{c,j} = \frac{1}{N_{\mathrm{ctrl}}}\sum_{i=1}^{N_{\mathrm{ctrl}}} s_{c,i,j}, \tag{7}$$

where $s_{c,i,j}$ is sample j of detector c for control event i. The mean waveforms are computed in the same normalized representation, input window, and sampling grid used by the model, separately for each board and amplification stage. Once computed, the replacement values remain fixed for all test events.

Let G_k denote a consecutive group of sample positions and $h_\theta(s_1, s_2)$ the predicted timing correction. Occluding G_k replaces

$$s_{c,i,j} \leftarrow \mu_{c,j}, \qquad j \in G_k. \tag{8}$$

For direct estimators, one detector input is perturbed at a time. The importance of group G_k for detector $c \in \{1, 2\}$ is

$$I_{k,c} = \frac{1}{N}\sum_{i=1}^{N}\left|h_\theta\left(s_{1,i}^{(k,c)}, s_{2,i}^{(k,c)}\right) - h_\theta(s_{1,i}, s_{2,i})\right|, \tag{9}$$

where only detector c is modified within G_k.

For shared estimators, the same group is replaced simultaneously in both detector inputs, yielding a single joint importance score,

$$I_k = \frac{1}{N}\sum_{i=1}^{N}\left|h_\theta\left(s_{1,i}^{(k)}, s_{2,i}^{(k)}\right) - h_\theta(s_{1,i}, s_{2,i})\right|. \tag{10}$$

The importance therefore measures the average absolute change in the predicted correction when the event-specific waveform structure in a given temporal interval is replaced by its control-population mean. The resulting profiles should be interpreted as perturbation sensitivity rather than as a direct measure of causal or independent timing information.

Formulation	Code	Estimator	Correction structure
Direct	D-LIN	Linear ridge	Joint linear regression on concatenated waveforms.
	D-MLP	Dense MLP	Joint nonlinear regression on concatenated waveforms.
	D-CNN	Independent CNN	Separate detector-specific CNN scorers; output difference.
	D-ONI	Onishi-inspired CNN	Paired waveforms fused by convolution for joint regression.
	D-MR	MiniRocket + ridge	Multivariate features of the waveform pair; ridge regression.
Shared	S-LIN	Linear ridge	Linear regression on the difference of waveform samples.
	S-MLP	Dense MLP	Common nonlinear detector scorer; output difference.
	S-LCM	Locally connected MLP	Common position-specific local scorer; bounded output difference.
	S-CNN	Temporal CNN	Common convolutional detector scorer; output difference.
	S-MR	MiniRocket + ridge	Common waveform feature transform; feature difference and ridge regression.

Table 2: Waveform-based timing estimators implemented in the benchmark. Model codes are used throughout the results tables. Direct estimators do not enforce detector-exchange antisymmetry; shared estimators use a common detector-level function or feature transform to enforce it.




Figure 4: Schematic overview of the experimental protocol. The calibration acquisition is used to determine fixed event-selection and LED-calibration criteria. Model selection and fitting are performed on the independent training acquisition. Final performance is assessed on the independent test acquisition.

4 Results

The aim of the model comparison is not to establish a definitive ranking of estimator architectures. Performance differences can also reflect the specific hyperparameter search and the characteristics of each dataset. The results are therefore interpreted primarily in terms of recurring behavior across different boards, waveform modes, and input windows.

4.1 University of Chicago board

4.1.1 Energy waveforms

Energy-waveform corrections reduce the test CTR from the LED reference of approximately 142 ps to 110.5 ps with the short Onishi-inspired window and 105.3 ps with the wide window (Tables 3 and 4; Figures 10a and 10b). The Onishi-inspired paired CNN gives the lowest observed test CTR for the short window, while several shared and direct estimators fall within the same few-picosecond performance range. With the wide window, direct linear ridge gives the lowest observed CTR, again with several other estimators nearby. The relevant trend is the improvement obtained by extending the waveform window rather than the exact ordering of the leading models. Most models show lower CTR and RMSE with the longer window, although the magnitude of the improvement differs by architecture. The independent temporal CNN is a notable exception to the relatively close model agreement in the short-window comparison and remains among the weaker results in the wide-window setting.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	141.9 ± 1.9	142.2 ± 1.7	68.1 ± 1.1
D-ONI	111.0 ± 1.3	110.5 ± 1.2	57.0 ± 1.3
S-MR	111.8 ± 3.3	112.0 ± 1.2	57.4 ± 1.3
S-CNN	113.1 ± 1.6	112.5 ± 1.2	57.6 ± 1.3
D-MR	111.3 ± 3.4	112.5 ± 1.4	57.6 ± 1.3
S-LIN	n/a	112.5 ± 1.2	58.2 ± 1.3
S-LCM	112.9 ± 2.8	112.6 ± 1.2	58.0 ± 1.3
D-LIN	n/a	112.7 ± 1.1	57.6 ± 1.3
S-MLP	112.8 ± 1.4	113.2 ± 1.3	58.4 ± 1.3
D-MLP	112.9 ± 1.0	113.6 ± 1.2	58.0 ± 1.3
D-CNN	112.8 ± 1.3	125.2 ± 1.4	63.1 ± 1.2

Table 3: UC energy onishi: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	141.5 ± 1.7	142.2 ± 1.7	68.0 ± 1.1
D-LIN	n/a	105.3 ± 1.1	54.8 ± 1.4
D-ONI	107.3 ± 2.9	107.3 ± 1.2	55.7 ± 1.4
S-LIN	n/a	107.4 ± 1.3	55.4 ± 1.3
S-LCM	107.8 ± 1.0	107.5 ± 1.3	55.5 ± 1.3
S-CNN	105.2 ± 0.5	108.0 ± 1.2	55.6 ± 1.3
S-MLP	106.3 ± 1.9	108.2 ± 1.3	55.6 ± 1.4
D-MR	108.5 ± 1.9	109.0 ± 1.2	56.5 ± 1.3
S-MR	109.8 ± 0.3	109.0 ± 1.4	56.4 ± 1.4
D-MLP	131.0 ± 3.9	115.6 ± 1.3	58.7 ± 1.3
D-CNN	128.0 ± 9.3	123.5 ± 1.6	62.4 ± 1.2

Table 4: UC energy wide: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	57.6 ± 0.6	57.1 ± 0.7	36.6 ± 1.7
S-MLP	57.3 ± 1.5	56.3 ± 0.7	36.4 ± 1.7
S-LIN	n/a	56.4 ± 0.6	36.3 ± 1.6
D-ONI	56.9 ± 0.3	56.5 ± 0.7	36.7 ± 1.7
S-LCM	57.0 ± 0.9	56.6 ± 0.7	36.4 ± 1.7
D-LIN	n/a	56.7 ± 0.6	36.2 ± 1.7
D-CNN	57.6 ± 0.4	56.7 ± 0.7	36.6 ± 1.7
S-CNN	57.5 ± 1.1	56.8 ± 0.6	36.3 ± 1.7
D-MLP	57.5 ± 0.4	56.9 ± 0.7	36.6 ± 1.7
S-MR	57.1 ± 0.3	57.3 ± 0.6	35.3 ± 1.2
D-MR	68.8 ± 2.8	64.9 ± 0.7	38.0 ± 1.2

Table 5: UC timing onishi: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

4.1.2 Timing waveforms

The timing-waveform LED reference is approximately 57.1 ps. With the short window, most estimators remain close to this reference, and the lowest observed test CTR is 56.3 ps. With the wide window, the minimum decreases to 52.9 ps, and several linear, MiniRocket-based and shared estimators lie between approximately 53 and 54 ps (Tables 5 and 6; Figures 10c and 10d). Thus, extending the timing input produces a clearer improvement in CTR than the small short-window corrections. The short-window direct MiniRocket result is an outlier, with a test CTR exceeding the LED reference. RMSE changes are generally smaller than the corresponding CTR changes.

4.1.3 Temporal sensitivity: wide window

Preliminary XAI results. The temporal-sensitivity analysis is still under validation and should be interpreted as exploratory.

The temporal-occlusion maps for the lowest-test-CTR wide-window estimators are shown in Figures 5 and 6. A model-specific XAI comparison is not reported because the predictions produced by the different competitive estimators are highly correlated and their temporal occlusion profiles show similar qualitative features. We therefore use the lowest-CTR estimator for each waveform mode as a representative example.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	57.9 ± 0.9	57.1 ± 0.7	36.6 ± 1.7
D-MR	54.1 ± 0.3	52.9 ± 0.8	35.6 ± 1.7
S-MR	54.9 ± 1.3	53.5 ± 0.8	35.4 ± 1.6
D-LIN	n/a	53.5 ± 0.7	35.4 ± 1.7
S-LIN	n/a	53.7 ± 0.7	35.5 ± 1.7
S-CNN	54.8 ± 0.8	54.5 ± 0.6	35.6 ± 1.7
D-MLP	55.1 ± 1.3	54.9 ± 0.6	35.9 ± 1.8
D-ONI	55.0 ± 0.4	55.0 ± 0.6	35.8 ± 1.7
S-LCM	54.3 ± 0.6	55.4 ± 0.5	36.0 ± 1.7
S-MLP	54.9 ± 1.2	55.8 ± 0.6	36.0 ± 1.7
D-CNN	57.6 ± 1.6	56.9 ± 0.7	36.6 ± 1.7

Table 6: UC timing wide: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.




Figure 5: UC energy waveforms, wide window: temporal occlusion sensitivity of the estimator with the lowest observed test CTR (direct linear ridge), shown against the two detector waveforms. Colors indicate normalized sensitivity to local occlusion, not causal attribution.

For energy waveforms, the largest sensitivity is concentrated in the early post-crossing portion of the rising pulse, approximately 1–4 ns after the LED reference, with weaker sensitivity over the later waveform. In timing mode, the dominant sensitivity remains close to the LED crossing and to the end of the clipped plateau, while a smaller response is visible around the late structure at approximately 20–22 ns. This late response is present in both detector inputs but is substantially weaker than the dominant early regions. These profiles quantify changes in model predictions under replacement by the control-mean waveform and should therefore be interpreted as perturbation sensitivity rather than causal attribution.

4.2 Fondazione Bruno Kessler board

4.2.1 Energy waveforms

For FBK energy waveforms, the LED reference is approximately 147.3 ps. The lowest observed short-window CTR




Figure 6: UC timing waveforms, wide window: temporal occlusion sensitivity of the estimator with the lowest observed test CTR (direct MiniRocket), shown against the two detector waveforms.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	145 ± 3	147.3 ± 1.8	70.9 ± 1.0
D-ONI	114.9 ± 1.5	115.4 ± 1.2	60.6 ± 1.2
S-LIN	n/a	115.9 ± 1.3	62.8 ± 1.2
D-LIN	n/a	116.2 ± 1.5	61.4 ± 1.2
D-MR	115.9 ± 2.3	116.4 ± 1.2	60.8 ± 1.2
S-LCM	117.3 ± 2.4	116.5 ± 1.4	62.0 ± 1.0
S-CNN	116.9 ± 0.1	116.7 ± 1.4	61.8 ± 1.1
D-MLP	118.6 ± 1.7	117.7 ± 1.2	61.5 ± 1.1
D-CNN	123.9 ± 4.5	117.7 ± 1.2	61.2 ± 1.2
S-MLP	116.9 ± 1.9	119.0 ± 1.4	62.8 ± 1.2
S-MR	116.8 ± 0.8	120.4 ± 1.1	61.5 ± 1.1

Table 7: FBK energy onishi: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

is 115.4 ps, with linear and nonlinear estimators occupying a similar performance range (Table 7; Figure 10e). The wide-window minimum is 111.0 ps, obtained with direct MiniRocket, while several other estimators remain around 114–116 ps (Table 8; Figure 10f). The shared temporal CNN is a marked wide-window outlier: despite a validation CTR of approximately 115 ps, the final refit provides essentially no improvement over LED on the independent test set. Neural-network optimization is non-convex and stochastic, so different weight initializations, minibatch sequences, or changes in the fitting population can lead the same architecture and hyperparameters to different fitted solutions. The observed discrepancy is therefore consistent with an unstable final optimization, although the present analysis does not isolate its specific cause. As with UC, the strongest wide-window results improve over the short-window minimum, but individual architectures do not all benefit equally.

4.2.2 Timing waveforms

In FBK timing mode, the LED reference is about 62.0 ps. Short-window test CTRs range from approximately 57.7 ps to values close to LED, whereas the wide-window comparison

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	145 ± 1	147.3 ± 1.6	70.9 ± 1.1
D-MR	111.9 ± 0.2	111.0 ± 1.2	58.6 ± 1.0
D-LIN	n/a	114.4 ± 1.1	59.9 ± 1.3
S-LCM	114.7 ± 0.7	114.9 ± 1.2	60.1 ± 1.3
D-ONI	114.1 ± 0.9	115.3 ± 1.4	59.4 ± 1.1
S-LIN	n/a	115.9 ± 1.2	60.2 ± 1.3
S-MLP	115.3 ± 0.8	115.9 ± 1.4	60.3 ± 1.2
D-MLP	119.6 ± 2.4	116.9 ± 1.3	60.9 ± 1.1
S-MR	117.0 ± 1.6	117.9 ± 1.4	59.6 ± 1.1
D-CNN	131.6 ± 3.4	130.6 ± 1.2	65.2 ± 1.1
S-CNN	115.0 ± 0.2	147.3 ± 1.7	70.9 ± 1.1

Table 8: FBK energy wide: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	62.0 ± 0.3	62.0 ± 0.8	42.3 ± 1.7
S-CNN	57.7 ± 2.0	57.7 ± 0.8	41.4 ± 1.7
S-MR	56.8 ± 0.7	58.0 ± 0.7	41.3 ± 1.8
D-LIN	n/a	58.1 ± 0.6	41.4 ± 1.5
S-LIN	n/a	58.2 ± 0.6	41.4 ± 1.9
D-ONI	56.9 ± 1.5	58.3 ± 0.5	41.4 ± 1.7
S-MLP	58.1 ± 1.8	58.8 ± 0.6	41.6 ± 1.8
D-MR	57.4 ± 2.1	59.1 ± 0.6	41.3 ± 1.7
S-LCM	57.9 ± 1.4	59.5 ± 0.6	41.7 ± 1.8
D-MLP	60.6 ± 1.9	61.8 ± 0.7	42.3 ± 1.7
D-CNN	61.5 ± 0.5	62.0 ± 0.8	42.3 ± 1.6

Table 9: FBK timing onishi: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.

reaches a minimum of 54.4 ps (Tables 9 and 10; Figures 10g and 10h). The leading wide-window results are obtained with linear ridge and MiniRocket-based estimators; several shared models are also competitive. Conversely, some neural estimators provide little additional narrowing of the timing distribution in this configuration. The wider window produces a lower best CTR and a modest reduction in best RMSE.

4.2.3 Temporal sensitivity: wide window

Preliminary XAI results. The temporal-sensitivity analysis is still under validation and should be interpreted as exploratory.

As for the UC board, the XAI discussion focuses on representative models rather than on a separate analysis of every estimator. The outputs of the competitive models are highly correlated, and their temporal occlusion maps are qualitatively similar, indicating that the main sensitive waveform regions are largely model-independent within the tested estimator set. Figures 7 and 8 therefore show the estimators with the lowest observed test CTR for the energy and timing waveforms, respectively.

The FBK energy map concentrates its largest sensitivity in the early post-crossing evolution of the pulse, with the exact maximum differing between the two detector inputs and much weaker sensitivity at later times. The timing map shows a more detector-dependent pattern. For detector 1,

Model	CV CTR [ps]	Test CTR [ps]	Test RMSE [ps]
LED	62.2 ± 1.3	62.0 ± 0.8	42.3 ± 1.7
D-LIN	n/a	54.4 ± 0.7	40.3 ± 1.6
D-MR	54.4 ± 0.7	55.1 ± 0.6	40.2 ± 1.7
S-MR	55.2 ± 1.8	55.9 ± 0.6	40.4 ± 1.8
S-LIN	n/a	55.9 ± 0.5	40.4 ± 1.9
S-MLP	55.8 ± 1.1	56.3 ± 0.6	40.9 ± 1.8
S-CNN	55.8 ± 0.2	57.5 ± 0.7	40.8 ± 1.7
S-LCM	56.4 ± 1.4	57.6 ± 0.6	41.1 ± 1.9
D-ONI	58.1 ± 3.5	61.8 ± 0.8	42.3 ± 1.7
D-CNN	62.1 ± 1.3	61.9 ± 0.8	42.3 ± 1.6
D-MLP	61.9 ± 1.3	62.0 ± 0.7	42.3 ± 1.7

Table 10: FBK timing wide: validation CTR (mean ± fold SD), independent-test CTR and RMSE (estimate ± bootstrap SD). Models are ranked by unrounded test CTR; codes are defined in Table 2. LED has no outer CV; ridge uses internal LOOCV.




Figure 7: FBK energy waveforms, wide window: temporal occlusion sensitivity of the estimator with the lowest observed test CTR (direct MiniRocket), shown against the two detector waveforms.

the strongest sensitivity remains close to the LED crossing, whereas for detector 2 the largest response occurs around 20–21 ns, coincident with the sharp late waveform structure. The corresponding late region is also visible, although less strongly, for detector 1.

The additional shared MiniRocket map in Figure 9 provides a formulation-level comparison. Its dominant response is again located near the LED crossing, while the strongest secondary maximum appears around 8–9 ns. Later intervals around 20–27 ns retain lower but non-negligible sensitivity.

Taken together, the maps show that sensitivity to later waveform structure is not confined to a single estimator, although the relative importance of the individual late regions depends on the model formulation and detector input. The occlusion analysis measures changes in model predictions under replacement by the control-mean waveform and does not by itself establish the physical origin, causal role, or independent information content of the highlighted signal regions.




Figure 8: FBK timing waveforms, wide window: temporal occlusion sensitivity of the estimator with the lowest observed test CTR (direct linear ridge), shown against the two detector waveforms.




Figure 9: FBK timing waveforms, wide window: shared MiniRocket temporal occlusion sensitivity, included as an additional model comparison rather than the lowest-observed-CTR estimator. The lower panel displays the normalized sensitivity profile, with the dominant response near the LED crossing, the strongest secondary maximum around 8–9 ns, and lower sensitivity over later intervals.

4.3 Comparison across waveform modes

Across both boards, the dedicated second-stage timing signals provide substantially better timing resolution than the first-stage energy signals, both before and after waveform-based correction. In the wide-window comparisons, the minimum energy CTRs are 105.3 and 111.0 ps for UC and FBK, respectively, compared with 52.9 and 54.4 ps for timing waveforms (Tables 4, 6, 8, and 10). Importantly, waveform-based correction still provides an additional improvement when applied to the timing-optimized second-stage signal. The two boards reach a similar corrected timing performance despite their different LED references and front-end implementations.

5 Conclusions

5.1 CTR improvement

Waveform-based correction substantially improved leading-edge timing on the first-stage energy signals of both boards. The test CTR was reduced by more than 20% even with the short Onishi-inspired window, with reductions reaching approximately 25% when the wider window was used. The strong performance of the Onishi-inspired CNN in the short-window energy comparisons is consistent with previous waveform-based LED correction studies [3, 5].

5.2 Shared detector-level models

The detector-shared formulation retained essentially the same useful timing correction as the direct formulation without using separate detector-specific scoring functions. Across boards, waveform modes, and windows, shared estimators generally remained in the same performance range as the leading direct estimators. The small few-picosecond differences between the best shared and direct results are not interpreted as evidence that either formulation is intrinsically superior, since such differences may depend on the detector and acquisition setup. The main result is that most of the achievable waveform-based correction can be retained with a shared detector-level model.

5.3 Model comparison

CNN and MLP approaches did not provide a systematic advantage over simpler estimators, despite the successful application of CNNs in previous waveform-based timing studies [3, 5]. Across the tested configurations, linear ridge regression and MiniRocket features followed by ridge regression reached the same overall performance range as the neural models. Because the leading estimators often differ by only a few picoseconds, their exact ordering is not considered a general property of the model families and may change with detector and acquisition conditions. The broader result is that much of the waveform-dependent timing correction can be captured without requiring end-to-end nonlinear neural networks. The marked FBK energy-wide shared-CNN failure also highlights a practical advantage of the ridge-based estimators: for fixed input features, ridge regression has a convex objective and is not subject to the initialization-dependent optimization of the neural models. Together with their competitive timing performance, this makes the ridge-based approaches particularly attractive for this correction task.

5.4 Window length and XAI

Extending the waveform window consistently improved the achievable timing resolution on both boards, with a particularly important effect on the timing signals, where short windows provided limited correction.

Preliminary XAI results. The temporal-sensitivity analysis is still under validation and should be interpreted as exploratory. Temporal occlusion analysis showed that energy-channel models relied primarily on the region around the LED crossing, while timing-channel models were also sensitive to later waveform structures. This was especially evident for the FBK board, where a pronounced secondary sensitivity peak appeared around 20 ns. These findings support the usefulness of waveform information beyond the rising edge.

5.5 Final considerations

Despite ML correction, the second-stage timing signals achieved approximately twice the timing resolution of the first-stage energy signals, highlighting that waveform-based correction cannot fully compensate for differences in analog readout quality. Nevertheless, ML consistently improved LED timing, with both boards reaching similar corrected CTRs of approximately 53–54 ps despite different amplification electronics and LED thresholds. This convergence suggests that the remaining timing uncertainty may be dominated by physical effects common to the detectors that cannot be recovered from the available waveform information, although this hypothesis requires further investigation.

References

[1] Suleman Surti. Update on time-of-flight PET imaging. *Journal of Nuclear Medicine*, 56(1):98–105, 2015. doi: 10.2967/jnumed.114.145029.

[2] Eric Berg and Simon R. Cherry. Using convolutional neural networks to estimate time-of-flight from PET detector waveforms. *Physics in Medicine & Biology*, 63 (2):02LT01, 2018. doi: 10.1088/1361-6560/aa9dc5.

[3] Yuya Onishi, Fumio Hashimoto, Kibo Ote, and Ryosuke Ota. Unbiased TOF estimation using leading-edge discriminator and convolutional neural network trained by single-source-position waveforms. *Physics in Medicine & Biology*, 67(4):04NT01, 2022. doi: 10.1088/1361-6560/ac508f.

[4] Xuhui Feng, Amanjule Muhashi, Yuya Onishi, Ryosuke Ota, and Huafeng Liu. Transformer-CNN hybrid network for improving PET time of flight prediction. *Physics in Medicine & Biology*, 69:115047, 2024. doi: 10.1088/1361-6560/ad4c4d.

[5] Francis Loignon-Houle, Nicolaus Kratochwil, Maxime Toussaint, Carsten Lowis, Gerard Ariño Estrada, Antonio J. Gonzalez, Etiennette Auffray, and Roger Lecomte. Improving timing resolution of BGO for TOF-PET:

a comparative analysis with and without deep learning. *EJNMMI Physics*, 12:2, 2025. doi: 10.1186/s40658-024-00711-6.

[6] Shirin Pourashraf, Andrea Gonzalez-Montoro, Min Sun Lee, Joshua W. Cates, Jun Yeon Won, Jae Sung Lee, and Craig S. Levin. Investigation of electronic signal processing chains for a prototype TOF-PET system with 100-ps coincidence time resolution. *IEEE Transactions on Radiation and Plasma Medical Sciences*, 6(6):690–696, 2022. doi: 10.1109/TRPMS.2021.3124756.

[7] Oona Rainio, Johanna Hällilä, Jarmo Teuho, and Riku Klén. Methods for estimating full width at half maximum. *Signal, Image and Video Processing*, 19:289, 2025. doi: 10.1007/s11760-025-03820-6.

[8] Gamaleldin Elsayed, Prajit Ramachandran, Jonathon Shlens, and Simon Kornblith. Revisiting spatial invariance with low-rank local connectivity. In *Proceedings of the 37th International Conference on Machine Learning*, volume 119 of *Proceedings of Machine Learning Research*, pages 2868–2879. PMLR, 2020.

[9] Angus Dempster, Daniel F. Schmidt, and Geoffrey I. Webb. MiniRocket: A very fast (almost) deterministic transform for time series classification. In *Proceedings of the 27th ACM SIGKDD Conference on Knowledge Discovery & Data Mining*, pages 248–257, 2021. doi: 10.1145/3447548.3467231.

A Model architectures and training settings

The following implementation details complement the model overview in Table 2. The complete configured search spaces are summarized in Table 11.

Linear ridge regression. The direct estimator uses independent weights on the concatenated detector waveforms and an intercept. The shared estimator applies common weights to the sample-wise waveform difference, without an intercept:

$$h(s_1, s_2) = \mathbf{w}^T(s_1 - s_2) = \mathbf{w}^T s_1 - \mathbf{w}^T s_2. \quad (11)$$

Ridge regularization limits sensitivity to highly correlated samples and is selected by internal leave-one-out cross-validation minimizing mean squared error (MSE).

Convolutional neural networks. The Onishi-inspired direct CNN combines the detector dimension in the first convolution and predicts a joint correction. The independent CNN uses separately parameterized detector scorers, whereas the shared CNN uses one common scorer for both detector signals. CNNs are included because temporal filters exploit local waveform structure and have been successfully applied to waveform timing [3, 5].

Multilayer perceptrons. The direct dense MLP performs nonlinear regression on concatenated waveforms. The shared MLP applies the same nonlinear scorer to both detector signals and subtracts the outputs,

$$h_\theta(s_1, s_2) = g_\theta(s_1) - g_\theta(s_2). \quad (12)$$

The shared locally connected MLP preserves temporal neighborhoods without sharing filters across positions, providing an intermediate assumption between dense and convolutional processing [8].

MiniRocket feature regression. MiniRocket is an efficient, largely deterministic convolutional feature transformation for time series [9]. The direct model transforms the waveform pair jointly; the shared model applies the same univariate transform to both detector signals and regresses on their feature difference.

Training settings. Dense MLPs, the locally connected MLP and temporal CNNs use at most 300 epochs, an internal holdout fraction of 0.2 for early stopping, patience of 10 epochs, a minimum loss improvement of 0.1 ps, gradient clipping at 10, and a gradient-stop threshold of 10^{-6} with patience 4. The Onishi-inspired CNN uses a fixed 100-epoch schedule with learning-rate reductions at epochs 30 and 60. Neural and MiniRocket hyperparameters are selected using mean held-out CTR in the three common outer folds; linear ridge uses internal leave-one-out cross-validation on MSE.


Code	Architecture / feature space	Learning rate / regularization	Batch size	Optimizer / selection
S-MLP	Hidden widths: 16; 128; 128–64; 16–16–16	10^{-2}, 10^{-3}, 10^{-4}, 10^{-5}	32	Nesterov SGD
D-MLP	Hidden widths: 16; 128; 128–64; 16–16–16	10^{-2}, 10^{-3}, 10^{-4}, 10^{-5}	32	Adam
S-LCM	Dense 128; local kernels 3,3; strides 1,1; bound 500 ps	10^{-2}, 10^{-3}, 10^{-4}, 10^{-5}	32, 128	Adam
S-CNN / D-CNN	Channels 16,32; kernels 5,3; dense 64	10^{-3}, 10^{-4}, 10^{-5}	32, 128	Adam
D-ONI	Channels 32,64; kernels 5,3; dense 256	10^{-3}, 10^{-4}, 10^{-5}	32, 128	Adam; fixed 100 epochs
S-LIN / D-LIN	Linear waveform samples	50 log-spaced ridge strengths from 10^{-8} to 10^{3}	–	Leave-one-out CV; MSE
S-MR / D-MR	10000 requested MiniRocket features	11 log-spaced ridge strengths from 10^{-1} to 10^{6}	–	Outer CV; mean CTR

Table 11: Configured model search spaces. Model codes are defined in Table 2. Neural models use ReLU activations. Shared and direct variants use the same search space where grouped in one row; formulation-specific details are described in the text.


Software. Implementation uses PyTorch 2.2, scikit-learn 1.4, sktime 0.35, NumPy 1.26, SciPy 1.11, Matplotlib 3.8 and pandas 2.1 as declared minimum versions.

B Independent-test CTR comparisons


Figure 10 collects the model-wise independent-test CTR comparisons for both boards, waveform modes and input windows. Numerical results and uncertainty estimates are reported in Section 4.




(a) UC energy, Onishi-inspired.




(b) UC energy, wide.




(c) UC timing, Onishi-inspired.




(d) UC timing, wide.




(e) FBK energy, Onishi-inspired.



(f) FBK energy, wide.



(g) FBK timing, Onishi-inspired.



(h) FBK timing, wide.

Figure 10: Independent-test CTR comparisons. The dashed line denotes the LED reference and error bars indicate bootstrap standard deviations.