

DPhil Thesis Draft



Alessandro Lodi
Trinity College
University of Oxford

A thesis submitted for the degree of
Doctor of Philosophy
Michaelmas 2021

Contents

List of Figures	vii
Abbreviations	ix
1 Introduction	1
1.1 Motivation	1
1.2 Graphene	1
1.2.1 crystal structure	1
1.2.2 band dispersion	3
1.2.3 thermal conductivity	4
1.2.4 graphene as electrode material	5
1.2.5 Graphene Transistors	5
1.3 Carbon-based Field Effect Transistor	8
1.3.1 crystal structure	8
1.3.2 Carbon Nanotube Field-Effect Transistors	9
1.4 Graphene Nanoribbons	14
1.5 Delocalised π -electron Systems	15
2 Foundations	17
2.1 Charge Transport In Zero-Dimensional Objects	17
2.2 Charge Transport in One-Dimensional Objects	17
2.3 Thermoelectric Phenomena in Zero-Dimensional Structures	18
2.4 Density Functional Theory	18
2.5 Non-Equilibrium Green Function Theory	18
3 Instrumentations	19
3.1 Room Temperature DC Measurements	19
3.2 Dipstick DC Measurements	19
3.3 Cryogenic DC Measurements	19
3.4 Cryogenic AC Measurements	20
3.5 Thermoelectric Measurements	20

4	Fabrication	21
4.1	General Fabrication Procedure	21
4.1.1	Graphene Preparation and Wet Transferring	21
4.2	Graphene Nanogaps	22
4.3	Chip Design	22
4.3.1	2T Design	22
4.3.2	3T Design	22
4.3.3	Thermoelectric Device	22
4.4	Deposition Process and Related Phenomna	22
5	Room Temperature Graphene Nanoribbon Single-Electron Transistor	23
5.1	Introduction	23
5.2	Sample Preparation and Characterisation	23
5.3	Electrical Transport Measurements	24
5.4	Summary	24
6	Chemical Doping of the Bandgap for Cove Graphene Nanoribbons	25
6.1	Introduction	25
6.2	Sample Preparation and Characterisation	25
6.3	<i>Ab-initio</i> Experiments	25
6.4	Electrical Transport Measurements	26
6.5	Summary	26
7	Thermocurrent Spectroscopy of cove Graphene Nanoribbons	27
7.1	Introduction	27
7.2	Sample Preparation and Characterisation	27
7.3	Electrical Transport Measurements	28
7.4	Summary	28
8	Transport Spectroscopy of Biaryl-linked Dy–Tb Porphyrin	29
8.1	Introduction	29
8.2	Sample Preparation and Characterisation	29
8.3	Electrical Transport Measurements	30
8.4	Summary	30
9	Conclusions and Outlook	31
9.1	Conclusions	31
9.2	Outlook	31

Appendices

A	Review of Cardiac Physiology and Electrophysiology	35
A.1	Anatomy	35
A.2	Mechanical Cycle	38
A.3	Electrical Cycle	39
A.4	Cellular Electromechanical Coupling	41
	References	43

List of Figures

Abbreviations

CNT carbon nanotube. 8, 9, 10

CNTFET carbon nanotube field-effect transistor. 9, 12, 14

DIBL drain induced barrier lowering. 12

EOT effective oxide thickness. 13, 14

FET field-effect transistor. 9

MOSFET metal–oxide–semiconductor field-effect transistor. 13

MW multi-walled. 8

SB Schottky barrier. 9

SS Sub-threshold swing. 12, 13, 14

SW single-walled. 8

1

Introduction

1.1 Motivation

Motivation

1.2 Graphene

1.2.1 crystal structure

Graphene has a hexagonal structure where the carbon atoms are hybridised sp^2 , as detailed by the Pauling theory on chemical bonds. Based on the experimental evidence collected in the last 20 years, the model that seems to best describe the proprieties of graphene is the band-structure Wallace model, which dates back in 1947, and describes graphene as a semimetal with a linear dispersion of the electronic excitations. In the International Table of Crystallography, graphene is included in the symmorphic space group #191, with symmetry D_6^1h ($P6/mmm$). The triangular lattice is obtained by considering two atoms per unit cell having the respective lattice vectors:

The carbon atoms in graphene form a two-dimensional hexagonal crystal with two atoms per unit cell, as shown in figure.

$$\mathbf{a}_1 = \frac{a}{2}(3, \sqrt{3}), \quad \mathbf{a}_2 = \frac{a}{2}(3, -\sqrt{3}), \quad (1.1)$$

with $a \approx 1.42 \text{ \AA}$ be the carbon-carbon bond length. Each atom belonging to one sublattice, called sublattice A, has three first neighbours belonging to the other sublattice, called sublattice B. With respect to one atom chosen from sublattice A as origin, the position of these first three neighbours in real space are given by:

$$\boldsymbol{\delta}_1 = \frac{a}{2}(1, \sqrt{3}), \quad \boldsymbol{\delta}_2 = \frac{a}{2}(1, -\sqrt{3}), \quad \boldsymbol{\delta}_3 = -a(1, 0), \quad (1.2)$$

The reciprocal-lattice vectors are then given

$$\mathbf{b}_1 = \frac{2\pi}{3a}(1, \sqrt{3}), \quad \mathbf{b}_2 = \frac{2\pi}{3a}(1, -\sqrt{3}), \quad (1.3)$$

In order to define the vertices of the Brillouin zone one has to apply the Bragg condition:

$$2\mathbf{k} \cdot \mathbf{G} = 0 \quad (1.4)$$

where

$$\mathbf{G} = n\mathbf{b}_1 + m\mathbf{b}_2, \quad (1.5)$$

The first amongst these are:

$$\begin{array}{lll} n = \pm 1, & m = 0, & \mathbf{G} = \pm \mathbf{b}_1, \\ n = 0, & m = \pm 1, & \mathbf{G} = \pm \mathbf{b}_2, \\ n = \pm 1, & m = \pm 1, & \mathbf{G} = \pm(\mathbf{b}_1 + \mathbf{b}_2), \end{array}$$

and all these vectors have the same modulus $|\mathbf{G}| = \frac{4\pi}{3a}$. By applying Bragg's condition in the first of the three cases we get:

$$\sqrt{3}k_x + k_y = \mp \frac{4\pi}{3a}, \quad (1.6)$$

which gets satisfied by the points:

$$K \equiv \mp \frac{2\pi}{3a} \left(\frac{1}{\sqrt{3}}, 1 \right) \quad (1.7)$$

For the second case one gets:

$$\mp (\sqrt{3}k_x - k_y) = \frac{4\pi}{3a}, \quad (1.8)$$

which gives the points:

$$K' \equiv \pm \frac{2\pi}{3a} \left(\frac{1}{\sqrt{3}}, -1 \right) \quad (1.9)$$

The third and last case gives the point:

$$M \equiv \pm \left(0, \pm \frac{2\pi}{3a} \right) \quad (1.10)$$

1.2.2 band dispersion

The electronic structure of graphene can be model with a tight-binding hamiltonian. Following the second quantization formalism ($\hbar = 1$ units), the hamiltonian can be written as:

$$H = -t \sum_{\langle ij \rangle, \sigma} \left(a_{\sigma,i}^\dagger b_{\sigma,j} + \text{H.c.} \right) - t' \sum_{\langle\langle ij \rangle\rangle, \sigma} \left(a_{\sigma,i}^\dagger a_{\sigma,j} + b_{\sigma,i}^\dagger b_{\sigma,j} + \text{H.c.} \right), \quad (1.11)$$

The notation $\langle ij \rangle$ means that the sum runs over pairs of electrons which are nearest neighbour; similarly, the notation $\langle\langle ij \rangle\rangle$ specify a summation over the next nearest neighbours; the operators $a_{i,\sigma}^\dagger$ ($a_{i,\sigma}$) and $b_{i,\sigma}^\dagger$ ($b_{i,\sigma}$) creates (annihilates) an electron with spin σ ($\sigma = \uparrow, \downarrow$) for atoms on sublattice A and B, respectively. The value of t which reproduces best experimental result is $t \approx 2.8$ eV and quantify the nearest-neighbour hopping energy; similarly, t' denotes the next nearest-neighbour hopping energy. The dispersion energy computed from this model reads:

$$E_{\pm}(\mathbf{k}) = \epsilon_p - t' f(\mathbf{k}) \pm t \sqrt{3 + f(\mathbf{k})}, \quad (1.12)$$

with $f(\mathbf{k})$ defined as:

$$f(\mathbf{k}) = 2 \cos(\sqrt{3}k_y a) + 4 \cos\left(\frac{\sqrt{3}}{2}k_y a\right) \cos\left(\frac{3}{2}k_x a\right). \quad (1.13)$$

Therefore, it is possible to identify an upper (π^*) band associated with the plus sign and a lower (π) band described by the minus sign; these are symmetric with respect to the single-particle zero energy. The experimental estimate reported for next nearest-neighbour hopping energy is $t' \approx 0.1\text{eV}$ thus the asymmetry introduced is small. It is worthwhile to notice that the function $3 + f(\mathbf{k})$

If the system is not doped, there is one electron per carbon atom, so two electrons per cell: it follows that the lower band is full and the upper band is empty the upper one is empty. The system is therefore a semi-metal. The peculiarities of the dispersion in graphene become apparent when analysing their trend near the point $\mathbf{K}$ and $\mathbf{K}'$. By taking the positive components for the $\mathbf{K}$ as define in Eq. 1.7 and expanding the Eq. 1.12 as $\mathbf{k} = \mathbf{K} + \mathbf{q}$, with $|\mathbf{q}| \ll |\mathbf{K}|$, one gets:

$$E_{\pm}(\mathbf{q}) = \epsilon_p \pm \frac{3at}{2}|\mathbf{q}| \quad (1.14)$$

which is linear in $\mathbf{q}$. For intrinsic graphene, at $T = 0\text{K}$ $E_F = \epsilon_p$. The Fermi velocity is defined by the usuale relation $v_F = \frac{1}{\hbar} \left(\frac{dE}{d\mathbf{k}} \right)$, and in graphene $v_F \simeq 1 \times 10^6 \text{m s}^{-1}$.

A difference arises in the density of the states, when we limit ourselves to consider those near the Fermi energy. In the case of a two-dimensional electron gas, it is constant. On the contrary for graphene, the density of states per unite cell is:

$$\rho(E) = \frac{2A_{\text{cell}}}{\pi} \frac{|E|}{v_F^2} \quad (1.15)$$

If the graphene is charge-neutral, the DOS has two Van Hove singularities at $\omega_{\text{VH}} = \pm 1\text{eV}$ [1]. This behaviour is in stark constrat with the DOS of carbon nanotubes and clean graphene nanoribbons, as they show $1/\sqrt{E}$ singularities due to the 1D nature, which imposes a quantization perpendicular to the ribbon or tube longitudinal direction.

1.2.3 thermal conductivity

Thermal Properties of graphene

1.2.4 graphene as electrode material

can be used as electrode material

1.2.5 Graphene Transistors

The first graphene field-effect transistor (GFET) was the one reported by the Manchester group in 2004 where a scotch-taped exfoliated flake of graphene was deposited on top of 300 nm of SiO₂ acting as a back-gate [2]. The resulting output characteristics displayed were characteristics of an ambipolar device, with linear relation between the current and the drain-source voltage, without any saturation regime reached for the charge carrier [3] (Fig. ??): this behaviour agrees with the semi-metal nature of graphene and indicates that transistor functionality was exclusively limited by inevitable contact resistances [4]. As for any transistor, the charge carriers can be varied by sweeping the gate voltage, which distinguishable branches of the gate-transfer characteristic; the charge neutrality point (Dirac point) is where they touch each other. Large positive gate voltages promote an electron accumulation in the channel (n-type channel), and large negative gate voltages lead to a p-type channel [5, 6].

Hysteresis between the forward and reverse sweeps have been reported depending on the sweeping rate and range [7], and attributed mainly to charge trapping in silanol groups (Si–OH), mediated and assisted by surface-bound H₂O molecules [8]. Despite the usefulness for its proof-of-concept purposes, back-gate devices suffered from parasitic capacitances, making impossible further integration with other components. Alternatives geometries have since then been explored, in order to increase the carriers mobility, to decrease contact resistances and parasitic capacitances, and to avoid Schottky barriers formation between the graphene and the semiconductor. Top-gate devices have been the first to chronologically appear in the literature. Back then in 2007, Lemme and co workeres used a stack of SiO₂ (20 nm), Ti (10 nm), and Au (100 nm) as top gate for modulating the current inside a large-area graphene channel transistor obtained by the exfoliation method [9]. Whilst the gate characteristics exhibit a similar trend of the characteristics

	Direct Gap			Indirect Gap		
	InP	Si	Ge	GaAs	InAs	Graphene
a_{lattice} (Å)	5.87	5.43	5.65	5.65	6.06	2.46
E_g (eV)	1.35	1.12	0.66	1.42	0.36	0
μ (cm ² V ⁻¹ s ⁻¹) at 300 K	2800	1400	3900	4600	16,000	200,000
v_{sat} (10 ⁷ cm s ⁻¹)	2.2	1	0.6	2.2	4.0	>5
DOS (m^*/m_0)	0.077	1.08	0.56	0.067	0.023	0
ϵ_r	12.4	11.9	16.0	13.1	14.6	2.4
κ (W m ⁻¹ K ⁻¹)	68	150	60.2	46	27	5000

Table 1.1: Differences between the main semiconductors used in modern digital electronics and graphene.

(the top gate reduces the back-gate current modulation, lowering the drain current by one order of magnitude) and the hysteresis, weak current saturation at high drain-source bias have been reported [10]. This effect seem due to a partial charge pinning at the contacts at high back-gate voltages [11] and carrier drift velocity eventually saturating due to optical-phonon scattering [12]. Top-gated graphene MOSFET with CVD and epitaxial graphene have been also made [13, 14]; SiO₂, Al₂O₃, and HfO₂ have been used as top-gate dielectric.

However, despite the improvements obtained with a top gate, most graphene MOSFETs with large-area (gapless) graphene channels show on-off switching ratios of less than 10 at room temperature [15], much too little for complex logic circuits.

In 2012, Mehr *et al.* proposed a vertical arrangement of emitter, base, and collector similar to the original vacuum triode, where graphene plays the base role and electrons travel vertically rather than transversely. When the device is in the ON state, the electrons tunnel with a Fowler-Nordheim tunnelling mechanism:

$$I \propto \left(\frac{V_{sd}}{d}\right)^2 \exp\left\{-\frac{\alpha d}{V_{sd}}\right\}, \quad (1.16)$$

through the emitter–base layer (of thickness d); ON/OFF ratios of the order of 10^4 have been demonstrated using graphene between two h-BN layers [16] and using WeS₂–graphene [17] heterostructures.

Solution methods have also been explored, in which graphene is dropcasted on top of a semiconducting wafer, and then spin-coated [18]. The main difficulties arise when attempting to quantify the structure and the quality of the deposited graphene, and not many methods can guarantee a good dispersion in organic solvents [19]. Simpler ways to obtain graphene oxide in solution have been reported [20], but once deposited, graphene oxide needs to be reduced for obtaining pure graphene – low mobility values (up to, at best, $1000 \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$) caused by defects during the fabrication steps have discouraged further investigations along this direction.

Yet in spite of the very different dc behavior compared to the most used semiconductors in digital electronics, graphene FETs have reported good performance in terms of high-frequency applications. This comparison is made by measuring each system’s frequency response, its output signal strength when it is given a particular input signal: features such as ballistic transport, linear current-voltage characteristics, high transconductance, and very high ($> 10^8 \text{ A cm}^{-2}$) sustainable currents are all ideal features for analog/RF applications [12, 21]. The primary means of estimating frequency response is through the cutoff frequency: it is a fundamental property indicating how quickly a signal can travel from the gate to the drain of the device. The frequency response depends inversely on the length of the gate, and proportionally to the transconductance, which is loosely proportional to mobility. Thus, to make faster devices, we can either reduce the gate length or use higher mobility materials [15].

The first graphene MOSFET with a cutoff frequency f_T in the gigahertz range has been reported in late 2008 [21]. In 2009, graphene MOSFETs with 350-nm gates and a cutoff frequency of 50 GHz have been presented [22]; in early 2010, a graphene MOSFET with a 240-nm gate showing an f_T of 100 GHz has been

reported [14], soon followed by a 144-nm gate graphene MOSFET with f_T ¼ 300 GHz later that year [23]. Finally, in 2012, a graphene MOSFET with a 40-nm-long gate showing 350-GHz f_T [24] and a 67-nm gate graphene MOSFET with an f_T of 427 GHz have been reported [25]. Graphene RF MOSFETs have successfully been realized using exfoliated (e.g., [23] and [22]), epitaxial (e.g., [14] and [10]), and CVD ([26]) graphene. Fig. ?? shows the cutoff frequency of the best graphene MOSFETs reported, together with the f_T performance of competing RF FET types. The record f_T data of the competing FETs are 688 GHz for a 40-nm GaAs mHEMT[27] and 644 GHz for a 30-nm InP HEMT [28], 485 GHz for a 29-nm Si MOSFET [29], and 153 GHz for a 100-nm carbon nanotube MOSFET [30]. Worthwhile to mention also the results obtained by Han *et al.* [31] in 2014, when they implemented a high-performance three-stage graphene integrated circuit using Si fabrication steps and CVD graphene: the reported performance for f_T and $f_{\max}$ were ranging from 8 to 10 GHz and from 8.5 to 13.5 GHz.

1.3 Carbon-based Field Effect Transistor

1.3.1 crystal structure

This crystalline form of carbon can be considered as a rolled up sheet of graphene and comes in two major flavours: single-walled (SW) and multi-walled (MW). Carbon nanotubes (CNTs) display an electronic band gap which depends on the chirality and the diameter of the nanotube [32]. Having defined two unit vectors in the real space, $\mathbf{a}_1$ and $\mathbf{a}_2$, a CNT can be described by the linear combination of these with integers coefficients (m, n). Based on the values of m and n , CNTs can be metallic, quasi-metallic ($m - n$ is a multiple of 3, with $m \cdot n \neq 0$ and $m \neq n$), and semiconducting for the majority of the remaining cases – exceptions due to the curvature (spin–orbit couplings) in small-diameter tubes are also known [33]. Thus, a quantization of the electronic states in the circumferential direction is resulted when the nanotube diameter d_{CNT} is between 0.8 and 2.5 nm. Each of these substates is called subband and are determined by the periodic boundary condition. Having defined a circumferential wave vector $\mathbf{k}_c$ such that $\mathbf{k}_c \cdot \mathbf{c} = k_c |\mathbf{c}| = k_c \pi d_{\text{CNT}} = 2\pi\nu$,

for ν integer, it is possible from this relation to draw parallel lines in the first Brillouin zone of graphene. If the subband intersect one of the $\mathbf{K}$ points, then the resulting nanotube will have no energy gap and thus exhibit metallic properties (this condition is realised by having $m = n$ for the coefficients of the chiral vector). If none of the subbands pass through $\mathbf{K}$ then the resulting CNT will be semiconducting, having a E_g proportional to the smallest distance between a $\mathbf{K}$ point and the subband lines:

$$E_g = 2 \left(\frac{\partial E}{\partial k} \right) \frac{k_c}{3} = \frac{2}{3} \hbar v_F \frac{2\pi}{|c|} = \frac{4}{3} \hbar v_F \frac{1}{d_{\text{CNT}}} \approx \frac{0.7}{d_{\text{CNT}}} \quad (1.17)$$

where $v_F = 8 \times 10^5 \text{ m s}^{-1}$ is the Fermi velocity, E_g is expressed in eV, and d_{CNT} is expressed in nm.

1.3.2 Carbon Nanotube Field-Effect Transistors

General Operation

The modulation of a CNT channel by a gate-induced field was realised in the 1998 by the group of Cees Dekkar. These early field-effect transistors (FETs) were fabricated by using doped silicon substrate as a gate to modulate the energy bands, separated from the nanotube by thermally-grown SiO_2 oxide acting as dielectric. For contacting the nanotube, metal contacts were employed.

Since then, a great variety of carbon nanotube field-effect transistor (CNTFET) structures and geometries have been demonstrated, and can be essentially classified in devices with or without a spacer. where the spacer length L_{spr} is the distance between the gated channel and the source/drain metal contacts. Given that the nanotubes are intrinsically semiconducting, in spacer-less devices charge carriers are not induced in the channel by the gate-field but are injected from the contacts: the role of the gate is to lower the thermal barrier in the channel, thus allowing a tunnelling through the Schottky barrier (SB) at the source. In this scenario, a critical role for the CNTFET performance is played by the metal work function ϕ^{M} .

CNTFETs with spacers, on the other hand, are less limited by the injection at the junction source–CNT, as they are regulated by the modulating effect played by in the channel as in conventional. Since the carrier barrier injection at the drain is large,

device with spacers have been proved to be more resistant to ambipolar conduction. In Table 1.2 an overview of gated-spacer (top and bottom) devices is reported.

Contacts

One of the principal issues when study the interface metal–CNT is the role played by carbon and metal atoms at the interface. Solid-state semiconductors have dangling bonds at the surface, leading to Fermi level pinning, meaning that the variation of the band bending is independent of the work function of the metal, even when this is large. Since the ideal structure of CNTs has no open bonds, no pinning of the metal Fermi level to mid-gap states occurs, thus legitimating the study of different work functions for maximising performance and tuning polarity. Many metals have been studied for contacting CNTs. Interestingly, it has been demonstrated that Pd ($\phi^{\text{Pd}} = 5.22 - -5.60$) builds an almost ideal *p*-channel contact to the valence band of CNTs. Despite having a larger workfunction ($\phi^{\text{Pt}} \approx 5.65$ eV) than Pd, Pt provides very poor contacts due to the physical wetting of the metal on the nanotube.

<i>Device type</i>	$I_{\text{on}}/I_{\text{off}}$	SS (mV/dec)	g_{mt} ($\mu\text{S cm}^{-1}$)	L_{ch} (nm)	f_T [f_{max}] (GHz)	Ref.
Bottom gate	10^4	94	~ 40	9	—	[34]
	10^5	~ 85	40	15	—	[35]
	10^5	~ 85	20	20	—	[35]
	10^5	60	20	200	—	[36]
	10^5	~ 63	—	200	—	[37]
	10^4	80	50	240	—	[38]
	—	—	143	800	[1]	[39]
	10^4	—	—	1,500	1.5 – 3.0	[40]
	—	70	$12^\dagger$	$2,000^1$	—	[41]
	10^8	—	—	$< 10,000^1$	—	[42]
	—	—	- 500	—	30	[43]
Top gate	10^6	—	20^2	80	—	[44]
	2	—	~ 50	100	25	[45]
	50	—	310	100	~ 70 [80]	[46]
	—	—	0.3	210	—	[47]
	10^5	—	33.5	85,000	—	[48]

Table 1.2: Figures of merit for a few CNFET reported in literature. S : subthreshold swing; g_m : intrinsic transconductances; L_{ch} : channel length; μ : carriers mobility

† Normalized by the tube width.

1 Referred to the gated length of a nanotube.

2 For the n-type transistor, whereas 10 μS were measured for the p-type.

<i>Device type</i>	I_{on} (A)	I_{off} (A)	$I_{\text{on}}/I_{\text{off}}$	g_{mt} (μS)	SS (mV/dec)
Conventional	1.41×10^{-5}	4.06×10^{-10}	3.4×10^4	29	99.6
Partial S/D-doped	1.50×10^{-5}	2.33×10^{-8}	6.4×10^2	63.6	93.1
Schottky-Barrier	3.26×10^{-6}	2.31×10^{-8}	1.41×10^2	19.6	109.8
Tunnel	5.53×10^{-6}	1.16×10^{-8}	4.76×10^2	13	107.9

Table 1.3: Comparative simulation for the four major type of CNFETs as reported in [49]. These results are obtained by setting $V_{\text{sd}} = 0.5$ V.

***n*-Type CNTFETs**

In a *n*-type CNTFETs the injection of electrons is favoured over the holes. Given that $\phi^{\text{CNT}} \approx 4.7$ eV and with an average $E_g \approx 0.6$ eV, it is possible to configure *n*-type channel with nanotube by either doping the spacer region or by using a metal with lower work function. One of the main drawbacks of doping is the challenge to keep it under control: instability in air, low consistency, variability to temperature variations, are amongst the most frequent scenarios. The other issue in working with low work function metals as contacts is the high tendency to oxidize. A simple and effective workaround to this is to use high work function metals to cap the contact metals, passivating the contact surface tendency to destabilise in air. One example of high performance *n*-type device was obtained by using Y contacts, achieving an Sub-threshold swing (SS) of 73 mV/dec, mobility of $5100 \text{ cm V}^{-2} \text{ s}^{-1}$, and drain induced barrier lowering (DIBL) of 105 mV V^{-1} [50].

Scaling

While Si technology was for long time questioned whether it could work below 10-nm of channel length, recent impressive technological developments from the industry have proved not only its feasibility but also a widespread commercial application (currently modern laptop employ the 5-nm technology). Nevertheless, the interest in Si scalability has been always a crucial starting point for exploring different technologies and materials capable of overcoming short-channel effects (threshold voltage roll-off, off-state leakage current, channel length modulation are just a few of the problematics).

In carbon nanotubes transistors a crucial and important – but somehow overlooked difference – is the difference between the two critical lengths for scaling, which are the contact length (L_c) and the channel length (L_{ch}). Aggressive scaling for the channel length generally leads to lose control of the band bending through the gate: intuitively, by shrinking the channel length the electric field generated by the source contact will be felt more and more by the charge carriers. The argument here is that carbon nanotubes offer, however, a good enough platform for such

scaling given by the ultrathin hollow structure (recall an effective wall thickness about $d_{\text{CNT}} \approx 0.68 \text{ \AA}$). On the other hand, this could be a double edge-sword. The effective carrier mass in nanotubes is $m_{\text{CNT}}^* = (0.228 \pm 0.129)m_0$ [51], thus potentially leading to tunnelling current from source to drain: this effect can be appreciate by an increase in the SS and the OFF current.

One of the first few systematic study on channel length scaling effects was conducted by Franklin *et al.* in 2010 through a series of measurements on nanotubes with relatively small diameters ($1.1 \text{ nm} < d_{\text{CNT}} < 1.3 \text{ nm}$) by using local bottom gates covered with 2 nm effective oxide thickness (EOT) of HfO_2 [52]. A consistent trend was observed when the channel length was scaled down more than two orders of magnitude (from 3 μm to 15 nm), both in the values of V_{th} and SS ($-0.5 \pm 0.2 \text{ V}$ and 90 mV/dec, respectively). The authors reported also encouraging figures on the transconductance g_m .

In a standard metal–oxide–semiconductor field-effect transistor (MOSFET), the transconductance is the change in the drain current divided by the amount varied in the gate/source voltage V_{gs} when the drain/source voltage (V_{ds}) is kept constant. Typical values of g_m for a small-signal field effect transistor are between 1 and 30 $\text{mS}\mu\text{m}^{-1}$. In a n-channel (nMOS) FET with threshold voltage V_{th} , the drain current at a certain V_{gs} in saturation mode (so when $V_{\text{th}} > V_{\text{gs}} - V_{\text{sd}}$) is given by:

$$I_{\text{sd}} = \frac{1}{2}\mu_n C_{\text{ox}} \frac{W}{L} (V_{\text{gs}} - V_{\text{th}})^2, \quad (1.18)$$

where μ_n is the electron mobility, C_{ox} is the gate oxide capacitance, W and L are the gate width and length, respectively. It is possible to work out the value of g_m by using the Shichman–Hodges model and assuming that the threshold voltage V_{th} is a device constant, such that $V_{\text{ov}} = V_{\text{gs}} - V_{\text{th}}$:

$$g_m = \frac{\partial I_{\text{sd}}}{\partial V_{\text{gs}}} = \frac{2 I_{\text{sd}}}{V_{\text{ov}}}, \quad (1.19)$$

Here V_{ov} is the so called *overdrive voltage* and has the physical meaning of being the voltage above the threshold voltage of the MOSFET. It is useful in the designing

phase of a transistor and elegantly links the drain current with a voltage: in fact, by rearranging Eq. 1.18 and identify $k_n = \mu_n C_{\text{ox}} \frac{W}{L}$ one gets:

$$I_{\text{sd}} = \frac{1}{2} k_n V_{\text{ov}}^2 \implies V_{\text{ov}} = \sqrt{\frac{2I_{\text{sd}}}{k_n}} \quad (1.20)$$

The usefulness for this equation is that the relation expressed in terms of overdrive voltage rather than threshold voltage holds both in the n and in the p case. Some reference numbers: V_{ov} is typically set at about 70–200 mV for the 65 nm technology node (with $I_{\text{sd}} = 1.13 \text{ mA } \mu\text{m}^{-1}$ of width) with value of $g_m \approx 11 - 32 \text{ mS } \mu\text{m}^{-1}$. In their work, Franklin *et al.* achieved transconductance peak up to $40 \text{ } \mu\text{S } \mu\text{m}^{-1}$ for a CNTFET with 15 nm of channel length, corresponding to values of g_m between approximately $91 - 110 \text{ } \mu\text{S } \mu\text{m}^{-1}$, thus meeting the requirements for being compatible with the Si technology.

The first CNTFET in which L_{ch} was scaled below 10 nm came two years later, again by Franklin *et al.* [34]. By using a CNT with $d_{\text{CNT}} \approx 1.3 \text{ nm} \pm 0.2 \text{ nm}$ and $E_g \approx 0.62 \text{ eV} \pm 0.1 \text{ eV}$ contacted through local bottom gates, they manage to scale down the $L_{\text{ch}} = 9 \text{ nm}$. The EOT was reduced to $\approx 0.65 \text{ nm}$ to achieve a better electrostatic coupling with the nanotube.

The authors reported an increase on the minimum current as L_{ch} decreases from 320 nm to 9 nm, attributed to a back-injection of the carriers into the conduction band from the drain, while the on-current approached the ballistic value for $L_{\text{ch}} \leq 41 \text{ nm}$ [52]. Impressive switching behaviour, with SS about 94 mV/dec, was measured, thus far outperforming any silicon-based of that time. based on previous results [52], the authors claimed the possibility of lowering the SS and the off-current at minimal cost to I_{on} by reducing the diameter of the nanotubes.

1.4 Graphene Nanoribbons

The scientific interest for graphene nanoribbons started in the physics community. Although this may appear irrelevant at the first glance, we will see that this actually had an impact over the last twenty years of progress in the field. The physics

community was looking for a way to open a bandgap in graphene. As mentioned in Sec. 1.1, graphene is a semi-metal, therefore unsuitable for all those semiconducting applications where the conduction paths for the charge carriers are well defined.

The first class of methods for synthesising graphene nanoribbons are methods that involve cutting or producing rectangular shapes from the graphene lattice through macroscopic methods. For this reason, they are also known as *top-down* approaches. Although they have seen an improvements in recent years, common drawbacks for this class of methods are a random distribution in the widths, a non-atomical control of the edge structures, and non-negligible impurity concentrations left after the process.

Kim and co-workers synthesized GNRs by employing the electron-beam lithography and etching technique [53]. The widths of GNRs obtained by this technique were scattered over a broad range, and most of the edges were extremely rough. An 8 nm GNR FET showed a dramatically improved on/off ratio of about 160.

Nanocutting of graphene is another promising method of GNR synthesis. In 2008, Strachan *et al.* used thermally activated Fe nanoparticles as chemical scissors to cut graphene sheet along a specific crystallographic direction [53, 54]. Later, Ni and other catalysts were employed as well. The carbon-carbon bond breaking is driven by the combustion reaction $\text{Ni} + \text{C}_{\text{graphene}} + 2\text{H}_2 \uparrow \longrightarrow \text{Ni/Fe} + \text{CH}_4 \uparrow$ catalysed by the nanoparticles, thus producing hydrocarbon compounds. One of the reason that have discouraged these synthetic way is the random width distribution obtained: this is likely to be a consequence of the change in direction when nanoparticles encounter defects or edges.

It will be interesting to discuss the $E_g \propto 1/W$ relation as the model used for describing gnr is the particle in the box, but in the toy model (particle in a box) as a relation of the kind $E_g \propto 1/W^2$.

1.5 Delocalised π -electron Systems

Porphyrin

2

Foundations

Contents

1.1	Motivation	1
1.2	Graphene	1
1.2.1	crystal structure	1
1.2.2	band dispersion	3
1.2.3	thermal conductivity	4
1.2.4	graphene as electrode material	5
1.2.5	Graphene Transistors	5
1.3	Carbon-based Field Effect Transistor	8
1.3.1	crystal structure	8
1.3.2	Carbon Nanotube Field-Effect Transistors	9
1.4	Graphene Nanoribbons	14
1.5	Delocalised π-electron Systems	15

2.1 Charge Transport In Zero-Dimensional Objects

quantum dots transport physics

2.2 Charge Transport in One-Dimensional Objects

nanowires transport physics

2.3 Thermoelectric Phenomena in Zero-Dimensional Structures

What are the necessary changes that one has to take into account when dealing also with other extensive variable such as a temperature gradient

2.4 Density Functional Theory

What are the relevant parameters/quantities that we are interested to calculate ab initio Why we opted for a pseudopotential such as SIESTA rather than others (quantum espresso). Explain why calculating the isolated gas phase all-electron electronic structure is legit for a qualitative see how the electron density is distributed over the system.

Remember also to emphasise the difference from stricly and non-stricly localised functions used for computing the electronic properties: when the functions are stricly localised they are zero outside a given radius from the atom they are associated with and so the radius is a key quality determined parameter for the basis set

2.5 Non-Equilibrium Green Function Theory

This section is needed to explain formally the results from transiesta and TB-trans calculations

3

Instrumentations

Contents

2.1	Charge Transport In Zero-Dimensional Objects	17
2.2	Charge Transport in One-Dimensional Objects	17
2.3	Thermoelectric Phenomena in Zero-Dimensional Structures	18
2.4	Density Functional Theory	18
2.5	Non-Equilibrium Green Function Theory	18

3.1 Room Temperature DC Measurements

Describe here the probe station setup]

3.2 Dipstick DC Measurements

Describe here the dipstick used for both liquid N₂ and liquid He

3.3 Cryogenic DC Measurements

Describe here the delft box. Describe how the delft box modular structure enables to adapt two and multi-terminal DC measurements

3.4 Cryogenic AC Measurements

Describe here the delft box + lock-in setup and why it is so complicated to set it usepackage

3.5 Thermoelectric Measurements

Describe here the setup used for the thermoelectric devices and why it needs a dedicated section Describe also here from a setup point of view which complications have raised during the setup (direct lines instead of dc lines, the need to use nano-D connectors and to design the a new pcb board).

4

Fabrication

Contents

3.1	Room Temperature DC Measurements	19
3.2	Dipstick DC Measurements	19
3.3	Cryogenic DC Measurements	19
3.4	Cryogenic AC Measurements	20
3.5	Thermoelectric Measurements	20

4.1 General Fabrication Procedure

The steps are well known: chip preparation, e-beam, development, metal deposition and lift-off, graphene transfer old process, graphenea graphene

4.1.1 Graphene Preparation and Wet Transferring

Initially the graphene was transferred on top of the substrate through the wet transfer method. The graphene was supplied by Graphene ain 5 x 5 cm2 rectangles, with a PMMA front-layer and a back-layer of partially removed graphene. Before transfer, the back-layer had to be fully removed via etching, and the remaining stack appropriately sized for the substrates for this work. The graphene arrived in a vacuum-sealed pack, which had to be transported to the cleanroom before

being opened and the following preparation steps initiated. Figure 6.2 depicts the main stages involved in preparing the graphene for transfe

4.2 Graphene Nanogaps

Here three methods have been exploited: standard feedback electroburning, gate-dependent electroburning, and lithographic patterning of graphene nanogap

4.3 Chip Design

Here the designs for the different chips that have been used. Give a proper credit to Dr. Alex Gee for the fabrication of thermoelectric and the common gate ones.

4.3.1 2T Design

How convenient and 'quick' is the usage of a backgate device. List, as usual, pro and cons

4.3.2 3T Design

Why the need to use 3T over 2T

Local Gates from Waterloo

Give proper credit

Interconnected Drain and Gate

The one I made and also made with the help of Alex

4.3.3 Thermoelectric Device

Common and different features of the thermoelectric

4.4 Deposition Process and Related Phenomna

Why it has been important to try different deposition techniques How this has been qualitatevely addressed.

5

Room Temperature Graphene Nanoribbon Single-Electron Transistor

Contents

4.1	General Fabrication Procedure	21
4.1.1	Graphene Preparation and Wet Transferring	21
4.2	Graphene Nanogaps	22
4.3	Chip Design	22
4.3.1	2T Design	22
4.3.2	3T Design	22
4.3.3	Thermoelectric Device	22
4.4	Deposition Process and Related Phenomna	22

5.1 Introduction

A brief intro why single-electron transistors with gnr are interesting A brief intro to what we are gonna do/measure in this chapter

5.2 Sample Preparation and Characterisation

How the sample it has been prepared (lot of crossreference with previous chapters)
Explained why the scarcity of characterisation checks is intrinsically scarce in molecular electronics.

5.3 Electrical Transport Measurements

What type of experiments have been performed and which tricks have been used in triton to do so. What are the evolution in temperature of the zero-bias, low-bias and high bias conductance. Look at the dependence in temperature and explain possible interpretations: why it is not a Luttinger Liquid (the gnr has a bandgap) and what possible phonon modes are responsible at some point for desctructing the

5.4 Summary

6

Chemical Doping of the Bandgap for Cove Graphene Nanoribbons

Contents

5.1	Introduction	23
5.2	Sample Preparation and Characterisation	23
5.3	Electrical Transport Measurements	24
5.4	Summary	24

6.1 Introduction

A brief intro on how why it is important to study this

6.2 Sample Preparation and Characterisation

How the sample it has been prepared (lot of crossreference with previous chapters)
Explained why the scarcity of characterisation checks i s intrinsically scarce in
molecular electronics.

6.3 *Ab-initio* Experiments

What DFT and NEGF have been used and for what.

6.4 Electrical Transport Measurements

Explain how the calculations have initially suggested the comparison between the base case and the methoxy groups, as they have the largest bandgap distance.

6.5 Summary

7

Thermocurrent Spectroscopy of covalently Functionalized Graphene Nanoribbons

Contents

6.1	Introduction	25
6.2	Sample Preparation and Characterisation	25
6.3	<i>Ab-initio</i> Experiments	25
6.4	Electrical Transport Measurements	26
6.5	Summary	26

7.1 Introduction

A brief intro on how why it is important to study this what has been done.

7.2 Sample Preparation and Characterisation

How the sample it has been prepared (lot of crossreference with previous chapters)

Explained why the scarcity of characterisation checks is intrinsically scarce in molecular electronics.

7.3 Electrical Transport Measurements

Explain how the calculations have initially suggested the comparison between the base case and the methoxy groups, as they have the largest bandgap distance.

7.4 Summary

8

Transport Spectroscopy of Biaryl-linked Dy–Tb Porphyrin

Contents

7.1	Introduction	27
7.2	Sample Preparation and Characterisation	27
7.3	Electrical Transport Measurements	28
7.4	Summary	28

8.1 Introduction

A brief intro on how why it is important to study this

8.2 Sample Preparation and Characterisation

How the sample it has been prepared (lot of crossreference with previous chapters)

Explained why the scarcity of characterisation checks i s intrinsically scarce in
molecular electronics.

8.3 Electrical Transport Measurements

Explain how the calculations have initially suggested the comparison between the base case and the methoxy groups, as they have the largest bandgap distance.

8.4 Summary

9

Conclusions and Outlook

Contents

8.1	Introduction	29
8.2	Sample Preparation and Characterisation	29
8.3	Electrical Transport Measurements	30
8.4	Summary	30

9.1 Conclusions

Here the final conclusions

9.2 Outlook

Appendices

Cor animalium, fundamentum est vitæ, princeps omnium, Microcosmi Sol, a quo omnis vegetatio dependet, vigor omnis & robur emanat.

The heart of animals is the foundation of their life, the sovereign of everything within them, the sun of their microcosm, that upon which all growth depends, from which all power proceeds.

— William Harvey [55]



Review of Cardiac Physiology and Electrophysiology

Appendices are just like chapters. Their sections and subsections get numbered and included in the table of contents; figures and equations and tables added up, etc. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Sed et dui sem. Aliquam dictum et ante ut semper. Donec sollicitudin sed quam at aliquet. Sed maximus diam elementum justo auctor, eget volutpat elit eleifend. Curabitur hendrerit ligula in erat feugiat, at rutrum risus suscipit. Pellentesque habitant morbi tristique senectus et netus et malesuada fames ac turpis egestas. Integer risus nulla, facilisis eget lacinia a, pretium mattis metus. Vestibulum aliquam varius ligula nec consectetur. Maecenas ac ipsum odio. Cras ac elit consequat, eleifend ipsum sodales, euismod nunc. Nam vitae tempor enim, sit amet eleifend nisi. Etiam at erat vel neque consequat.

A.1 Anatomy

Lorem ipsum dolor sit amet, consectetur adipiscing elit. Donec accumsan cursus neque. Pellentesque eget tempor turpis, quis malesuada dui. Proin egestas, sapien sit amet feugiat vulputate, nunc nibh mollis nunc, nec auctor turpis purus sed metus. Aenean consequat leo congue volutpat euismod. Vestibulum et vulputate

nisl, at ultrices ligula. Cras pulvinar lacinia ipsum at bibendum. In ac augue ut ante mollis molestie in a arcu.

Etiam vitae quam sollicitudin, luctus tortor eu, efficitur nunc. Vestibulum maximus, ante quis consequat sagittis, augue velit luctus odio, in scelerisque arcu magna id diam. Proin et mauris congue magna auctor pretium id sit amet felis. Maecenas sit amet lorem ipsum. Proin a risus diam. Integer tempus eget est condimentum faucibus. Suspendisse sem metus, consequat vel ante eget, porttitor maximus dui. Nunc dapibus tincidunt enim, non aliquam diam vehicula sed. Proin vel felis ut quam porta tempor. Vestibulum elit mi, dictum eget augue non, volutpat imperdiet eros. Praesent ac egestas neque, et vehicula felis.

Pellentesque malesuada volutpat justo, id eleifend leo pharetra at. Pellentesque feugiat rutrum lobortis. Curabitur hendrerit erat porta massa tincidunt rutrum. Donec tincidunt facilisis luctus. Aliquam dapibus sodales consectetur. Suspendisse lacinia, ipsum sit amet elementum fermentum, nulla urna mattis erat, eu porta metus ipsum vel purus. Fusce eget sem nisl. Pellentesque dapibus, urna vitae tristique aliquam, purus leo gravida nunc, id faucibus ipsum magna aliquet ligula. Lorem ipsum dolor sit amet, consectetur adipiscing elit. Proin sem lacus, rutrum eget efficitur sed, aliquam vel augue. Aliquam ut eros vitae sem cursus ultrices ut ornare urna. Nullam tempor porta enim, in pellentesque arcu commodo quis. Interdum et malesuada fames ac ante ipsum primis in faucibus. Curabitur maximus orci purus, ut molestie turpis pellentesque ut.

Donec lacinia tristique ultricies. Proin dignissim risus ut dolor pulvinar mollis. Proin ac turpis vitae nibh finibus ullamcorper viverra quis felis. Mauris pellentesque neque diam, id feugiat diam vestibulum vitae. In suscipit dui eu libero ultrices, et sagittis nunc blandit. Aliquam at aliquet ex. Nullam molestie pulvinar ex vitae interdum. Praesent purus nunc, gravida id est consectetur, convallis elementum nulla. Praesent ex dolor, maximus eu facilisis at, viverra eget nulla. Donec ullamcorper ante nisi. Sed volutpat diam eros. Nullam egestas neque non tortor aliquet, sed pretium velit tincidunt. Aenean condimentum, est ac vestibulum mattis, quam

augue congue augue, mattis ultrices nibh libero non ante. Lorem ipsum dolor sit amet, consectetur adipiscing elit.

Aenean volutpat eros tortor, non convallis sapien blandit et. Maecenas faucibus nulla a magna posuere commodo. Nullam laoreet ante a turpis laoreet malesuada. Phasellus in varius sem. Vestibulum sagittis nibh sed tincidunt blandit. Donec aliquam accumsan odio sit amet lacinia. Integer in tellus diam. Vivamus varius massa leo, vitae ullamcorper metus pulvinar sed. Maecenas nec lorem ornare, elementum est quis, gravida massa. Suspendisse volutpat odio ex, ac ultrices leo ultrices vel. Sed sed convallis ipsum. Pellentesque euismod a nulla sed rhoncus. Sed vehicula urna vitae mi aliquet, non sodales lacus ullamcorper. Duis mattis justo turpis, id tempus est tempus eu. Curabitur vitae hendrerit ligula.

Curabitur non pretium enim, in commodo ligula. Etiam commodo eget ligula a lacinia. Vestibulum laoreet ante tellus, vel congue sapien ornare in. Donec venenatis cursus velit vitae pulvinar. Pellentesque habitant morbi tristique senectus et netus et malesuada fames ac turpis egestas. Suspendisse in metus lectus. Pellentesque gravida dolor eget finibus imperdiet. Duis id molestie tortor. Mauris laoreet faucibus facilisis. Aliquam vitae dictum massa, sit amet dignissim lacus.

Fusce eleifend tellus id ex consequat maximus. Donec ultrices ex ut turpis ornare, non molestie mi placerat. Nulla sit amet auctor nunc, sit amet euismod elit. Phasellus risus tellus, condimentum a metus et, venenatis tristique urna. Cras mattis felis eget ipsum fermentum egestas. Ut augue odio, venenatis id convallis vel, congue quis augue. Maecenas sed maximus est, posuere aliquet tortor. Ut condimentum egestas nisi eu porttitor. Ut mi turpis, posuere id lorem vel, elementum tempor arcu.

Morbi nisl arcu, venenatis non metus ac, ullamcorper scelerisque justo. Nulla et accumsan lorem. Mauris aliquet dui sit amet libero aliquet, in ornare metus porttitor. Integer ultricies urna eu consequat ultrices. Maecenas a justo id purus ultricies posuere sed et quam. Cum sociis natoque penatibus et magnis dis parturient montes, nascetur ridiculus mus. Sed eleifend risus quis aliquet gravida. Nullam ac erat porta est bibendum dictum in a dolor. Nam eget turpis viverra, vulputate

lectus eget, mattis ligula. Nam at tellus eget dui lobortis sodales et ut augue. In vestibulum diam eget mi cursus, ut tincidunt nulla pellentesque.

Aliquam erat volutpat. Sed ultrices massa id ex mattis bibendum. Nunc augue magna, ornare at aliquet gravida, vehicula sed lorem. Quisque lobortis ipsum eu posuere eleifend. Duis bibendum cursus viverra. Nam venenatis elit leo, vitae feugiat quam aliquet sed. Cras velit est, tempus ac lorem sed, pharetra lobortis ipsum. Donec suscipit gravida interdum. Nunc non finibus est. Nullam turpis elit, tempus non ante.

A.2 Mechanical Cycle

Lorem ipsum dolor sit amet, consectetur adipiscing elit. Aenean tellus est, suscipit sed facilisis quis, malesuada at ipsum. Nam tristique urna quis quam iaculis, et mattis orci pretium. Praesent euismod elit vel metus commodo ultrices. Vestibulum et tincidunt ex, in molestie ex. Donec ullamcorper sollicitudin accumsan. Etiam ac leo turpis. Duis a tortor felis. Nullam sollicitudin eu purus ac hendrerit. Nam hendrerit ligula libero, eget finibus orci bibendum a. Aenean ut ipsum magna.

Ut viverra, sapien sed accumsan blandit, nisi sem tempus tellus, at suscipit magna erat ornare nunc. Proin lacinia, nisi ut rutrum malesuada, nibh quam pellentesque nunc, sit amet consectetur purus felis ac tortor. Suspendisse lacinia ipsum eu sapien pellentesque mattis. Mauris ipsum nunc, placerat non diam vel, efficitur laoreet nunc. Sed lobortis, ipsum eget gravida facilisis, sem nulla viverra mi, in placerat eros sem viverra lacus. Aliquam porta aliquet diam vel commodo. Nulla facilisi. Duis erat libero, lobortis vel hendrerit vitae, sagittis id dui. Nulla pretium eros nec quam tincidunt, vel luctus mi aliquam. Integer imperdiet purus in est tristique venenatis. Ut pellentesque, nunc vitae iaculis ultricies, urna turpis dignissim risus, a laoreet felis magna nec erat.

Quisque sollicitudin faucibus ligula, et egestas nibh dictum sit amet. Proin eu mi a lectus congue pretium eu quis arcu. Suspendisse vehicula libero eu ipsum aliquam, vel elementum nibh mattis. Sed sed sapien vitae turpis tristique pulvinar a ut metus. Etiam semper gravida est, mollis gravida est porta ac. Proin eget tincidunt

erat. Maecenas ultrices erat eget purus ultricies, ut lacinia arcu dictum. Nam et nisi sit amet ex congue mattis vel eget lorem. Aliquam erat volutpat. Pellentesque porttitor nibh vitae elementum consectetur. Aenean et est lobortis, congue sapien non, ullamcorper sapien. Ut facilisis sem non dapibus vehicula.

Mauris euismod odio dolor, sit amet gravida mauris placerat et. Curabitur nec dolor non nibh molestie lobortis dignissim non ante. Nullam rutrum lobortis ultrices. Aenean ex erat, elementum sed maximus id, posuere id quam. Proin rutrum ex elit, pretium aliquam risus finibus at. Aenean egestas orci velit, sed aliquet sapien condimentum a. Duis consequat, arcu eu viverra venenatis, dolor lorem gravida lectus, non aliquet nisi sem at augue. Donec laoreet blandit luctus. Aenean vehicula nisl vel faucibus luctus. Sed ut semper velit, vitae laoreet magna. Sed at interdum magna.

Sed iaculis faucibus odio, eu aliquam purus efficitur vel. Cras at nulla ac enim congue varius ut et nulla. Integer blandit mattis augue.

A.3 Electrical Cycle

Lorem ipsum dolor sit amet, consectetur adipiscing elit. In faucibus condimentum rhoncus. Ut dictum nisl id risus gravida lobortis. Sed vehicula mollis tellus ut varius. Fusce eget egestas dui, et commodo dui. Proin sollicitudin interdum tempus. Nullam in elit a enim fringilla bibendum. Vestibulum sodales pellentesque condimentum. Nulla facilisi. Nunc et dolor in nulla eleifend dictum at vel ligula. Aliquam ut velit non elit ullamcorper porta ac et ex. Fusce ornare magna non nunc vestibulum, eget molestie quam dictum. In interdum aliquam odio, in posuere tellus convallis quis. Curabitur non diam elit. Proin vulputate orci diam, a tincidunt ante luctus eu. Ut a viverra ligula. Curabitur pulvinar tempus tellus eget suscipit.

Aliquam posuere massa at ante dapibus congue. Curabitur ullamcorper tortor eget consectetur aliquet. Mauris tempor magna id mauris fringilla, a varius erat blandit. Nam eleifend ullamcorper placerat. Phasellus augue tortor, volutpat bibendum lorem nec, fringilla volutpat nisl. Mauris cursus urna metus, vel eleifend orci iaculis ut. Sed sit amet scelerisque massa, quis consequat dui. Donec

semper sem dui, ac placerat velit egestas vel. Nulla facilisi. Quisque tellus eros, sagittis malesuada augue ut, faucibus dictum nulla. Vestibulum non dapibus erat, ut consequat libero. Ut turpis mi, dapibus commodo libero lobortis, maximus vestibulum lectus. Vestibulum sit amet sapien dapibus, tincidunt leo in, suscipit arcu. Sed in erat bibendum, laoreet eros eu, pellentesque justo. Nulla sodales purus neque, eget maximus ipsum consequat at. Maecenas a nisl sagittis, tempus ipsum sed, dictum mauris.

Suspendisse posuere odio lacus, at auctor tortor vehicula sed. Phasellus suscipit ornare enim vitae placerat. Sed viverra purus vel sapien tempor, quis iaculis erat laoreet. Aenean vel nunc vestibulum, ornare nunc ac, mollis urna. Aenean ultrices felis ipsum, ac semper est ullamcorper in. Donec in justo varius, egestas tortor ut, venenatis augue. Duis mattis, ligula quis lacinia fringilla, tellus neque accumsan ipsum, vitae tempor metus elit vel nibh. Curabitur porttitor urna nec sapien tempor, et porttitor velit malesuada.

Suspendisse aliquam nisl quis placerat vulputate. Proin dapibus ipsum ac ante sagittis, volutpat auctor sem dapibus. Nam in facilisis odio. Integer ante mauris, eleifend et pulvinar in, venenatis quis ligula. Phasellus posuere sollicitudin tortor eget euismod. Maecenas mollis tortor eget justo vulputate sagittis. Etiam hendrerit massa quis ex molestie sodales. Quisque facilisis erat lacus, id convallis sem suscipit bibendum. Integer dui urna, pharetra sed porta sed, bibendum ut odio. Donec placerat at lectus egestas consequat. Sed id rhoncus est, vitae vulputate sapien. Fusce tempus quam lorem, id ornare turpis sodales sed. Integer aliquet urna eget condimentum consequat. Vestibulum quis dui vel ligula posuere luctus id nec turpis.

Nam vitae placerat lacus. Mauris scelerisque interdum volutpat. Nunc aliquet tristique enim, sit amet molestie felis ullamcorper vitae. Nullam sollicitudin orci orci, in condimentum tellus consectetur in. Nam id justo justo. Fusce eget finibus est. Proin id tortor nec quam cursus vehicula. Aliquam ultrices eros eros, a tincidunt elit eleifend auctor.

Nullam consectetur dapibus ligula sit amet efficitur. Nunc non posuere sapien. Vivamus dui nisl, aliquam id ipsum non, pulvinar ornare neque. Nunc rhoncus

pretium congue. Fusce id laoreet enim. Cras sed massa in eros bibendum auctor in nec sem. Nam commodo, velit id porta consequat, mi arcu gravida lorem, ut aliquam elit ante quis dui. Quisque in massa sed nibh blandit dictum.

Vestibulum molestie consectetur porttitor. Donec tincidunt vel orci at pharetra. Nullam id felis sit amet nulla tempus lacinia. Integer egestas ullamcorper massa, ut ultricies diam congue sit amet. Cras sit amet velit at nibh vehicula finibus a et lorem. Cras odio metus, venenatis ut ultrices non, ornare ac orci. Morbi et nulla dui. Mauris dictum molestie nibh, eu efficitur lorem accumsan quis.

A.4 Cellular Electromechanical Coupling

Lorem ipsum dolor sit amet, consectetur adipiscing elit. Nullam vitae consectetur metus, ac maximus ex. Quisque vitae ex eu lectus ultricies consequat vel non lorem. Etiam odio ipsum, tempus ut lobortis in, molestie ac leo. Vivamus mollis feugiat bibendum. Vestibulum eget venenatis quam. Aenean faucibus, massa sed ullamcorper porta, arcu nunc iaculis velit, quis consectetur purus neque placerat nibh. Vestibulum elit nunc, dignissim vulputate venenatis et, sodales non massa. Proin leo ligula, vehicula eu aliquam varius, posuere a dolor. Donec iaculis auctor neque, sit amet gravida libero porta vel. Vivamus consequat elementum lacus, at bibendum mauris egestas nec. Fusce fermentum diam eu dolor ornare, vitae vestibulum leo interdum. Morbi luctus libero quis dictum laoreet. Etiam semper porta ante, vel ullamcorper enim sodales quis.

Nullam eu nisi faucibus, fermentum ex auctor, tempor arcu. Phasellus condimentum erat mi, condimentum malesuada ligula congue venenatis. Nullam gravida imperdiet urna quis cursus. Ut tempus nec purus eget posuere. Cras non nulla sit amet justo aliquet pellentesque nec sed eros. Nam aliquam nisl urna, in placerat magna gravida venenatis. Donec interdum vel magna ullamcorper molestie. Nunc felis neque, rhoncus fringilla faucibus sit amet, ultrices sed magna. Maecenas malesuada hendrerit diam in ultrices. Nam libero urna, volutpat ut auctor eget, interdum sed odio. Vestibulum suscipit mauris nec augue ornare, ut eleifend nulla gravida. Proin imperdiet, mauris quis consectetur porta, leo dui convallis leo,

id lobortis massa diam eu libero. Aenean hendrerit vel ante aliquam venenatis. Pellentesque bibendum pretium odio, ut sagittis lectus feugiat a. Donec porttitor vulputate lacus.

Nunc volutpat efficitur lacus in aliquet. Nullam non iaculis diam, at ultrices diam. Proin vehicula vulputate cursus. Morbi tempus sapien id urna lobortis interdum. Maecenas elementum sagittis elementum. Donec at sodales velit, a posuere tortor. Nulla id hendrerit tortor. Sed semper velit in magna sagittis pulvinar. Nulla nec arcu molestie, ultricies sapien sit amet, sollicitudin nisi. Donec nisi massa, suscipit ut dignissim quis, lacinia id leo.

Suspendisse ut mi metus. Morbi tincidunt ligula in porttitor consectetur. Integer eu urna urna. Suspendisse potenti. Mauris sit amet felis eu diam auctor ullamcorper. Morbi in porta nisi. Nam ante tortor, venenatis vitae tempor sed, sagittis vitae velit. In semper orci sit amet nisi ullamcorper varius. Aenean dignissim ultrices imperdiet. Maecenas lacinia enim id neque porttitor iaculis. Curabitur laoreet ante ut urna dignissim, id sollicitudin metus consectetur. Aenean massa ipsum, auctor vel ante vel, blandit dignissim libero. Fusce interdum ac magna et interdum.

*The first kind of intellectual and artistic personality
belongs to the hedgehogs, the second to the foxes ...*

— Sir Isaiah Berlin [56]

References

- [1] Cristina Bena and Steven A Kivelson. “Quasiparticle scattering and local density of states in graphite”. In: *Physical Review B* 72.12 (2005), p. 125432.
- [2] Kostya S Novoselov et al. “Electric field effect in atomically thin carbon films”. In: *science* 306.5696 (2004), pp. 666–669.
- [3] Yu-Ming Lin et al. “Operation of graphene transistors at gigahertz frequencies”. In: *Nano letters* 9.1 (2008), pp. 422–426.
- [4] SA Thiele, JA Schaefer, and Frank Schwierz. “Modeling of graphene metal-oxide-semiconductor field-effect transistors with gapless large-area graphene channels”. In: *Journal of Applied Physics* 107.9 (2010), p. 094505.
- [5] Phaedon Avouris. “Graphene: electronic and photonic properties and devices”. In: *Nano letters* 10.11 (2010), pp. 4285–4294.
- [6] A. H. Castro Neto et al. “The electronic properties of graphene”. In: *Rev. Mod. Phys.* 81.1 (Jan. 2009), pp. 109–162. URL: <http://link.aps.org/doi/10.1103/RevModPhys.81.109>.
- [7] Haomin Wang et al. “Hysteresis of electronic transport in graphene transistors”. In: *ACS nano* 4.12 (2010), pp. 7221–7228.
- [8] P Joshi et al. “Intrinsic doping and gate hysteresis in graphene field effect devices fabricated on SiO₂ substrates”. In: *Journal of Physics: Condensed Matter* 22.33 (2010), p. 334214.
- [9] Max C Lemme et al. “A graphene field-effect device”. In: *IEEE Electron Device Letters* 28.4 (2007), pp. 282–284.
- [10] JS Moon et al. “Epitaxial-graphene RF field-effect transistors on Si-face 6H-SiC substrates”. In: *IEEE Electron Device Letters* 30.6 (2009), pp. 650–652.
- [11] Antonio Di Bartolomeo et al. “Charge transfer and partial pinning at the contacts as the origin of a double dip in the transfer characteristics of graphene-based field-effect transistors”. In: *Nanotechnology* 22.27 (2011), p. 275702.
- [12] Inanc Meric et al. “Current saturation in zero-bandgap, top-gated graphene field-effect transistors”. In: *Nature nanotechnology* 3.11 (2008), p. 654.
- [13] Jakub Kedzierski et al. “Epitaxial graphene transistors on SiC substrates”. In: *IEEE Transactions on Electron Devices* 55.8 (2008), pp. 2078–2085.
- [14] Y-M Lin et al. “100-GHz transistors from wafer-scale epitaxial graphene”. In: *Science* 327.5966 (2010), pp. 662–662.
- [15] Frank Schwierz. “Graphene transistors”. In: *Nature nanotechnology* 5.7 (2010), p. 487.

- [16] L Britnell et al. “Field-effect tunneling transistor based on vertical graphene heterostructures”. In: *Science* 335.6071 (2012), pp. 947–950.
- [17] Thanasis Georgiou et al. “Vertical field-effect transistor based on graphene–WS 2 heterostructures for flexible and transparent electronics”. In: *Nature nanotechnology* 8.2 (2013), p. 100.
- [18] Li-Hong Liu et al. “A simple and scalable route to wafer-size patterned graphene”. In: *Journal of materials chemistry* 20.24 (2010), pp. 5041–5046.
- [19] Zhengzong Sun, Dustin K James, and James M Tour. “Graphene chemistry: synthesis and manipulation”. In: *The Journal of Physical Chemistry Letters* 2.19 (2011), pp. 2425–2432.
- [20] Chuc Van Nguyen et al. “Effect of glass surface treatments on the deposition of highly transparent reduced graphene oxide films by dropcasting method”. In: *Colloids and Surfaces A: Physicochemical and Engineering Aspects* 498 (2016), pp. 231–238.
- [21] Inanc Meric et al. “RF performance of top-gated, zero-bandgap graphene field-effect transistors”. In: *2008 IEEE International Electron Devices Meeting*. IEEE. 2008, pp. 1–4.
- [22] Yu-Ming Lin et al. “Development of graphene FETs for high frequency electronics”. In: *2009 IEEE International Electron Devices Meeting (IEDM)*. IEEE. 2009, pp. 1–4.
- [23] Lei Liao et al. “High-speed graphene transistors with a self-aligned nanowire gate”. In: *Nature* 467.7313 (2010), p. 305.
- [24] Yanqing Wu et al. “State-of-the-art graphene high-frequency electronics”. In: *Nano letters* 12.6 (2012), pp. 3062–3067.
- [25] Rui Cheng et al. “High-frequency self-aligned graphene transistors with transferred gate stacks”. In: *Proceedings of the National Academy of Sciences* 109.29 (2012), pp. 11588–11592.
- [26] Yanqing Wu et al. “High-frequency, scaled graphene transistors on diamond-like carbon”. In: *Nature* 472.7341 (2011), p. 74.
- [27] Dae-Hyun Kim, Berinder Brar, and Jesús A Del Alamo. “ $f_T = 688$ GHz and $f_{max} = 800$ GHz in $L_g = 40$ nm In 0.7 Ga 0.3 As MHEMTs with $g_{m_max} > 2.7$ mS/ μ m”. In: *2011 International Electron Devices Meeting*. IEEE. 2011, pp. 13–6.
- [28] Dae-Hyun Kim and Jesús A Del Alamo. “30-nm InAs PHEMTs With $f_T = 644$ GHz and $f_{max} = 681$ GHz”. In: *Institute of Electrical and Electronics Engineers*. 2010.
- [29] Sungjae Lee et al. “Record RF performance of 45-nm SOI CMOS technology”. In: *2007 IEEE International Electron Devices Meeting*. IEEE. 2007, pp. 255–258.
- [30] Mathias Steiner et al. “High-frequency performance of scaled carbon nanotube array field-effect transistors”. In: *Applied Physics Letters* 101.5 (2012), p. 053123.
- [31] Shu-Jen Han et al. “Graphene radio frequency receiver integrated circuit”. In: *Nature communications* 5 (2014), p. 3086.
- [32] Mildred S Dresselhaus et al. “Carbon nanotubes”. In: *The physics of fullerene-based and fullerene-related materials*. Springer, 2000, pp. 331–379.

- [33] Edward A Laird et al. “Quantum transport in carbon nanotubes”. In: *Reviews of Modern Physics* 87.3 (2015), p. 703.
- [34] Aaron D Franklin et al. “Sub-10 nm carbon nanotube transistor”. In: *Nano letters* 12.2 (2012), pp. 758–762.
- [35] Aaron D Franklin and Zhihong Chen. “Length scaling of carbon nanotube transistors”. In: *Nature nanotechnology* 5.12 (2010), p. 858.
- [36] Ralf Thomas Weitz et al. “High-performance carbon nanotube field effect transistors with a thin gate dielectric based on a self-assembled monolayer”. In: *Nano letters* 7.1 (2007), pp. 22–27.
- [37] Yu-Ming Lin et al. “High-performance carbon nanotube field-effect transistor with tunable polarities”. In: *IEEE Transactions on Nanotechnology* 4.5 (2005), pp. 481–489.
- [38] Ali Javey et al. “High-field quasiballistic transport in short carbon nanotubes”. In: *Physical Review Letters* 92.10 (2004), p. 106804.
- [39] N Chimot et al. “Gigahertz frequency flexible carbon nanotube transistors”. In: *Applied Physics Letters* 91.15 (2007), p. 153111.
- [40] Michael Schröter et al. “CNTFET-based RF electronics—State-of-the-art and future prospects”. In: *2016 IEEE 16th Topical Meeting on Silicon Monolithic Integrated Circuits in RF Systems (SiRF)*. IEEE. 2016, pp. 97–100.
- [41] Ali Javey et al. “High- κ dielectrics for advanced carbon-nanotube transistors and logic gates”. In: *Nature materials* 1.4 (2002), p. 241.
- [42] Vladimir Derenskyi et al. “Carbon nanotube network ambipolar field-effect transistors with 108 on/off ratio”. In: *Advanced Materials* 26.34 (2014), pp. 5969–5975.
- [43] A Le Louarn et al. “Intrinsic current gain cutoff frequency of 30 GHz with carbon nanotube transistors”. In: *Applied physics letters* 90.23 (2007), p. 233108.
- [44] Ali Javey et al. “High performance n-type carbon nanotube field-effect transistors with chemically doped contacts”. In: *Nano letters* 5.2 (2005), pp. 345–348.
- [45] Yuchi Che et al. “T-gate aligned nanotube radio frequency transistors and circuits with superior performance”. In: *ACS nano* 7.5 (2013), pp. 4343–4350.
- [46] Yu Cao et al. “Radio frequency transistors using aligned semiconducting carbon nanotubes with current-gain cutoff frequency and maximum oscillation frequency simultaneously greater than 70 GHz”. In: *ACS nano* 10.7 (2016), pp. 6782–6790.
- [47] Fumiyuki Nihey et al. “A top-gate carbon-nanotube field-effect transistor with a titanium-dioxide insulator”. In: *Japanese journal of applied physics* 41.10A (2002), p. L1049.
- [48] Pak Heng Lau et al. “Fully printed, high performance carbon nanotube thin-film transistors on flexible substrates”. In: *Nano letters* 13.8 (2013), pp. 3864–3869.
- [49] Amandeep Singh, Mamta Khosla, and Balwinder Raj. “Comparative analysis of carbon nanotube field effect transistors”. In: *2015 IEEE 4th Global Conference on Consumer Electronics (GCCE)*. IEEE. 2015, pp. 552–555.

- [50] Li Ding et al. “Y-contacted high-performance n-type single-walled carbon nanotube field-effect transistors: scaling and comparison with Sc-contacted devices”. In: *Nano letters* 9.12 (2009), pp. 4209–4214.
- [51] Jose M Marulanda and Ashok Srivastava. “Carrier density and effective mass calculations in carbon nanotubes”. In: *physica status solidi (b)* 245.11 (2008), pp. 2558–2562.
- [52] Aaron D Franklin and Zhihong Chen. “Length scaling of carbon nanotube transistors”. In: *Nature nanotechnology* 5.12 (2010), p. 858.
- [53] Liang Ma, Jinlan Wang, and Feng Ding. “Recent Progress and Challenges in Graphene Nanoribbon Synthesis”. In: *ChemPhysChem* 14.1 (2013), pp. 47–54.
- [54] Sujit S. Datta et al. “Crystallographic Etching of Few-Layer Graphene”. In: *Nano Letters* 8.7 (2008), pp. 1912–1915. URL: <http://arxiv.org/pdf/0806.3965v1.pdf>.
- [55] William Harvey. *Exercitatio Anatomica de Motu Cordis et Sanguinis in Animalibus*. Latin. 1st. Frankfurt: Sumptibus Guiljelmi Fitzeri, 1628.
- [56] Isaiah Berlin. *The Hedgehog and the Fox: An Essay on Tolstoy’s View of History*. English. Ed. by Henry Hardy. 2nd. Princeton University Press, June 2013.