Fast Stop aktiv	186	

Communication error messages:

Screen messages	ID	Description
Comm err w -I	116	Communication error between LC100-C and the LC100-I board.
Comm err w -K/K2	117	Communication error between LC100-C and the LC100-K board.
Comm err w -E(0)	118	Communication error between LC100-C and the LC100-E board with address 0.
Comm err w -E(1)	119	Communication error between LC100-C and the LC100-E board with address 1.
Comm err w -C(A)	120	Communication error between LC100-C and the LC100-C board of elevator „A" in duplex mode.
Comm err w -C(B)	121	Communication error between LC100-C and the LC100-C board of elevator „B" in duplex mode.
Comm err w -C(C)	122	Communication error between LC100-C and the LC100-C board of elevator „C" in duplex mode.
Comm err w -C(D)	123	Communication error between LC100-C and the LC100-C board of elevator „D" in duplex mode.
WDT RESET	124	Indicates a reset of the processor in the event of a unforeseen flow of the program code.
Comm err w -E(2)	146	Communication error between LC100-C and the LC100-E board with address 2.
Comm err w -E(3)	147	Communication error between LC100-C and the LC100-E board with address 3.
Comm err w -E(4)	148	Communication error between LC100-C and the LC100-E board with address 4.
Comm err w -E(5)	149	Communication error between LC100-C and the LC100-E board with address 5.
Comm err w -E(6)	150	Communication error between LC100-C and the LC100-E board with address 6.
Comm err w -E(7)	151	Communication error between LC100-C and the LC100-E board with address 7.
Comm err w -VFD	152	Communication error between LC100-C and the LC100-VFD board.
Comm err w -VFX	153	Communication error between LC100-C and the LC100-VFX board.
Comm err w -SR2	154	Communication error between LC100-C and the LC100-SR2 board.
Error on ANTS	161	Communication error between LC100-C and the LC100-B2/ANTS board.
Comm err w VF7-A	172	Communication error between LC100-C and the door VF7 – A.
Comm err w VF7-B	173	Communication error between LC100-C and the door VF7 – B.
Comm err w -ADL	183	Communication error between LC100-C and the LC100-B2/ADL inverter.
Comm err w -V3	184	Communication error between LC100-C and the LC100-V3 card.