NEIL ARMSTRONG
MICHAEL COLLINS
EDWIN ALDRIN

Apollo 11 Mission Overview

Relatório Intermédio

Palavras Chave

texto livro, arquitetura, história, construção, materiais de construção, saber tradicional.

Resumo

Um resumo é um pequeno apanhado de um trabalho mais longo (como uma tese, dissertação ou trabalho de pesquisa). O resumo relata de forma concisa os objetivos e resultados da sua pesquisa, para que os leitores saibam exatamente o que se aborda no seu documento.
Embora a estrutura possa variar um pouco dependendo da sua área de estudo, o seu resumo deve descrever o propósito do seu trabalho, os métodos que você usou e as conclusões a que chegou.
Uma maneira comum de estruturar um resumo é usar a estrutura IMRaD. Isso significa:

- Introdução
- Métodos
- Resultados
- Discussão

Veja mais pormenores aqui:
`https://www.scribbr.com/dissertation/abstract/`

Keywords

textbook, architecture, history, construction, construction materials, traditional knowledge.

Abstract

An abstract is a short summary of a longer work (such as a thesis, dissertation or research paper).
The abstract concisely reports the aims and outcomes of your research, so that readers know exactly what your paper is about.
Although the structure may vary slightly depending on your discipline, your abstract should describe the purpose of your work, the methods you've used, and the conclusions you've drawn.
One common way to structure your abstract is to use the IMRaD structure. This stands for:

- Introduction
- Methods
- Results
- Discussion

Check for more details here:
`https://www.scribbr.com/dissertation/abstract/`

Contents

1 Introduction **5**
- 1.1 Background . . . 5
- 1.2 Problem Statement . . . 5
- 1.3 Objectives . . . 5
- 1.4 Significance of the Study . . . 5
- 1.5 Scope . . . 5
- 1.6 Work Breakdown Structure (WBS) . . . 5

2 Literature Review **6**
- 2.1 Influence of IMPs on LDH growth . . . 6
  - 2.1.1 Pre-Treatment . . . 7
- 2.2 Equivalent Circuit Models for EIS . . . 8
  - 2.2.1 Randles Equivalent Circuit (REC) . . . 8
  - 2.2.2 More advanced circuits . . . 10

3 Methodology **12**
- 3.1 Determine ECM for EIS . . . 12
- 3.2 Pre-treatments . . . 14

4 Results **15**

5 Discussion **16**

6 Conclusion & Future Work **17**

Bibliography **18**

List of Figures

List of Tables

Chapter 1

Introduction

1.1 Background

Context or background of the project.

1.2 Problem Statement

Clearly state the problem that you will address in your project.

1.3 Objectives

Clearly state the objectives or goals of your project.

1.4 Significance of the Study

Explain the importance of your project.

1.5 Scope

Define the scope of your project through requirements and allocate priorities in accordance with the relevance and uncertainty of each one.

1.6 Work Breakdown Structure (WBS)

Define the WBS, including Work Packages (WPs), tasks, Gantt Chart, indentifying risks and mitigation strategy.

Chapter 2

Literature Review

2.1 Influence of IMPs on LDH growth

AC46000 contains a diverse range of intermetallic particles (IMPs), including copper-rich phases such as Al_2Cu and Al_7Cu_2Fe, iron-rich phases such as Al_5FeSi and $Al_{15}(Fe, Mn)_3Si_2$, and eutectic silicon particles. To assess the influence of these IMPs on LDH growth and corrosion behavior, it is important to consider their electrochemical potential relative to the aluminium matrix [7, 9].

The copper-rich phases are strongly cathodic relative to the Al matrix, with Al_2Cu exhibiting a potential difference of approximately +400 mV [7]. This drives intense localized micro-galvanic coupling, promoting rapid oxygen reduction and a sharp rise in local pH. In the context of LDH growth, these conditions trigger the preferential and rapid precipitation of thick, "flower-like" LDH islands directly over the cathodic sites [3]. This localized growth is sustained by the anodic dissolution of the surrounding aluminium matrix, commonly referred to as trenching [2]. The trenching process generates voids at the periphery of the intermetallic particles where LDH flakes fail to nucleate [2]. These uncoated gaps compromise the corrosion resistance of the substrate, as chloride ions and other aggressive species can readily penetrate the exposed defects and initiate pitting corrosion [2]. The resulting inhomogeneous LDH film also reduces the adhesion of subsequently applied polymer coatings or paints [2], and in severe cases extensive trenching can render the intermetallic particles prone to detachment, further undermining the integrity of overlying layers [2].

The iron-rich phases are also strongly cathodic, approximately +300 mV above the aluminium matrix [7], and the galvanic coupling they generate similarly leads to inhomogeneous LDH growth and increased susceptibility to corrosion.

Although eutectic silicon particles are likewise cathodic, with a potential

difference of approximately +250 mV relative to the Al matrix, they are electrochemically inert and do not act as nucleation sites for LDH. Since they provide no source of the metal cations (Al^{2+}/Al^{3+}, Mg^{2+}) required for LDH formation, no coating growth is triggered at these sites [7, 6].

2.1.1 Pre-Treatment

Given the detrimental influence of these IMPs on LDH growth homogeneity and overall coating quality, their removal from the alloy surface prior to conversion coating is essential. To this end, various pre-treatment strategies have been developed, but the most widely adopted approach consists of a multistep procedure comprising degreasing, alkaline etching, and acid pickling, applied sequentially [13].

Degreasing constitutes the first pre-treatment step, with the primary objective of removing surface contamination, most notably oils and lubricants introduced during the manufacturing process. This step is critical to ensure full surface wettability, thereby guaranteeing that subsequent processing stages act uniformly across the substrate [13].

The second step, alkaline etching, is aimed at dissolving the native oxide layer that forms spontaneously on aluminium surfaces, as well as removing surface-exposed intermetallic particles. The cathodic IMPs act as highly active sites for oxygen reduction, generating a localised rise in pH at their immediate vicinity. This accelerates the anodic dissolution of the surrounding aluminium matrix, progressively undermining the mechanical support of the particles [15]. As the matrix recedes, scallop-shaped voids form at the particle periphery, eventually causing the IMPs to detach from the surface, a process known as selective dealloying [15, 8]. Since many of the constituent alloying elements released during this process are insoluble in alkaline media, they accumulate on the surface as a loosely adherent residue known as smut, the removal of which necessitates a subsequent acid pickling step [13, 15, 8].

Nitric acid (HNO_3) is widely used for desmutting because it naturally passivates the aluminum matrix while acting as a powerful oxidant [8]. It successfully targets and dissolves the dealloyed metallic smut, including copper, iron, and manganese residues. Despite this, Nitric acid alone is ineffective against silicon-rich intermetallic residues [4]. To remove these, fluorides (such as hydrofluoric acid or ammonium bifluoride) must be added to the pickling bath [1, 12]. The fluoride ions dissolve the silica and complex the remaining silicon remnants so they can be washed away [1, 12].

2.2 Equivalent Circuit Models for EIS

2.2.1 Randles Equivalent Circuit (REC)

Determining an appropriate equivalent circuit model (ECM) for electrochemical impedance spectroscopy (EIS) spectra is among the most critical steps in impedance analysis, as it enables the deconvolution of overlapping electrochemical processes and their quantification through physically meaningful parameters. One of the most widely used models is the Randles equivalent circuit, which consists of a solution resistance (R_s) in series with a parallel combination of a charge-transfer resistance (R_ct) and a double-layer capacitance (C_dl), as represented in [REFERENCIAR FIGURE] [5, 11].

Before discussing each circuit element individually, it is necessary to introduce the concept of the time constant, as it underpins the physical interpretation of the impedance response. A time constant (τ) defines the characteristic duration required for a given electrochemical process to relax from a transient state towards a new equilibrium [5]. In an electrical equivalent circuit, it is defined as the product of a resistance and a capacitance ($\tau = RC$), and governs the rate at which the system responds to an applied perturbation [11]. Because an electrochemical interface involves multiple concurrent processes (such as charge transfer, ionic diffusion, and intermediate adsorption) each process is characterised by its own distinct time constant [5]. For instance, the kinetic time constant of an interface is given by $\tau_k = R_\mathrm{ct}C_\mathrm{dl}$ [11]. In the frequency domain, each time constant manifests as a characteristic angular frequency ($\omega_c = \frac{1}{RC}$), which marks the transition between different impedance regimes — for example, from a capacitively controlled response to a diffusion-dominated one [11, 5]. Their resolution in the impedance spectrum is therefore a prerequisite for the unambiguous assignment of ECM elements to specific interfacial processes.

R_s, also referred to as the ohmic or uncompensated resistance, quantifies the resistive potential drop occurring between the working electrode and the reference electrode [14, 11]. Its magnitude is governed by the specific conductivity of the bulk electrolyte and the cell geometry [14]. In a Nyquist representation, R_s is readily identified as the high-frequency intercept of the impedance data with the real axis, corresponding to the condition under which the reactive elements of the circuit are effectively short-circuited and the purely resistive contribution dominates the response.

R_ct is the real component of the Faradaic impedance governing the transfer of electrons across the electrode/electrolyte interface to or from electroactive species in solution [11]. As a strictly kinetic parameter, its value is inversely proportional to the heterogeneous rate constants of the electrode reactions, and it is sometimes referred to as polarisation

resistance in the context of Faradaic processes [11, 5]. This inverse relationship extends directly to the corrosion rate: according to the Stern–Geary relationship, the instantaneous corrosion current density i_{corr} is obtained by dividing a proportionality constant B by R_{ct} [10]:

$$i_{\text{corr}} = \frac{B}{R_{\text{ct}}} \tag{2.1}$$

Consequently, a higher R_{ct} reflects slower interfacial kinetics, a lower corrosion current density, and therefore improved corrosion protection [10]. In the Nyquist plot, R_{ct} manifests as the diameter of the semicircle observed in the high-frequency to mid-frequency range, a feature arising directly from its coupling with C_{dl} to form the kinetic time constant $\tau_k = R_{\text{ct}} C_{\text{dl}}$ [5, 11].

C_{dl} is the capacitance that inherently forms at the electrode/electrolyte interface as a consequence of the charge separation between ionic species in solution and charges within the electrode, as described in section [REFERENCIAR SECÇÃO DA DOUBLE LAYER] [10, 14]. While liquid electrodes can behave as nearly ideal capacitors, solid electrodes invariably exhibit frequency dispersion due to surface heterogeneities, roughness, porosity, and non-uniform current distributions [11, 5]. To account for this non-ideal behaviour, the double layer at solid electrodes is most accurately represented by a constant phase element (CPE) rather than an ideal capacitor [5, 11, 14].

From a corrosion monitoring perspective, C_{dl} is a particularly sensitive indicator of coating degradation and the onset of localised pitting, often preceding any macroscopic visual evidence of corrosion [10]. As a protective coating degrades or delaminates, the electrolyte gains direct access to the underlying metal substrate, initiating underfilm corrosion [10]. The measured capacitance at defect sites scales directly with the delaminated area. Consequently, progressive coating breakdown exposes an increasingly large area of bare metal, driving C_{dl} proportionally higher [10]. This area dependence is readily understood through the expression for a planar capacitor:

$$C = \frac{\epsilon \epsilon_0 A}{d} \tag{2.2}$$

where ϵ is the relative permittivity of the interfacial medium, ϵ_0 is the permittivity of free space, A is the effective interfacial area, and d is the charge separation distance. Additionally, as localised corrosion progresses, for instance through pitting, the electrode surface becomes increasingly rough and geometrically complex, further enlarging the effective interfacial area and driving C_{dl} to higher values [11, 10].

2.2.2 More advanced circuits

While the simple Randles circuit provides an adequate description of a bare metal undergoing a single-step charge transfer reaction, real-world systems exhibit multiple time constants that cannot be captured by a single RC network. To model these more complex responses, advanced equivalent circuits are constructed by combining multiple resistor–capacitor (RC) or resistor–constant phase element (R-CPE) sub-networks.

When a system displays two distinct time constants, which typically manifest as two partially or fully resolved semicircles in the Nyquist plot, the two most common topologies are the series (Voigt-type) configuration [FIGURE X] and the nested (ladder) configuration [FIGURE Y]. In the series configuration, each RC sub-network represents a physically distinct and sequential process that operates independently of the others [11, 10]. The nested configuration, by contrast, is generally preferred in corrosion science for the description of defective or porous protective coatings, where simultaneous and spatially overlapping processes occur [10]. In this topology, the outer RC network represents the macroscopic response of the coating itself which can be characterised by the film capacitance and the film resistance. The inner nested RC network on the other hand describes the actively corroding metal/electrolyte interface at the base of the pores, represented by the double-layer capacitance and the charge-transfer resistance [10].

It is important to note, however, that despite their distinct physical interpretations, a series Voigt circuit and a nested ladder circuit can be mathematically equivalent, producing identical impedance values and indistinguishable complex plane plots [11]. The selection of the nested topology must therefore be justified by the physical reality of the system under investigation rather than by mathematical preference alone [11].

In this nested configuration, the outer time constant is associated with the response of the protective film such as an externally applied organic coating, a native oxide layer, or a conversion coating like an LDH film.

The film resistance, R_{film} plays an analogous role to R_{ct} in the sense that both manifest as semicircle diameters in the Nyquist plot and both inversely reflect the degree of protection afforded at their respective interface. However, while R_{ct} is a kinetic parameter governing the rate of electron transfer across the electrode/electrolyte interface, R_{film} is an ionic transport parameter [10]. It represents the resistance to ionic current flow both through the bulk of the film itself and through any microscopic pores and defects connecting the bulk electrolyte to the metal/film interface [10]. Just as a high R_{ct} indicates sluggish interfacial reaction kinetics, a high R_{film} restricts ionic transport across the film and is therefore directly associated with superior corrosion protection [11, 10].

The film capacitance, C_{film}, is equally informative and serves as a

sensitive early indicator of coating degradation, often responding before any macroscopic evidence of corrosion becomes apparent. Its evolution is most directly governed by water uptake: upon immersion in an electrolyte, water progressively penetrates the pores of the coating [11]. Since water possesses a substantially higher dielectric constant (approximately 80) relative to that of a typical coating, its ingress causes a measurable increase in C_{film} [14, 11]. Monitoring this increase is of practical importance, as water uptake is frequently a precursor to active substrate corrosion [10]. More generally, a progressive increase in C_{film} over time is indicative of ongoing coating degradation and a reduction in protective performance.

Chapter 3

Methodology

3.1 Determine ECM for EIS

Determining an appropriate equivalent circuit model (ECM) for electrochemical impedance spectroscopy (EIS) spectra is among the most important steps in impedance analysis, as it enables the deconvolution of overlapping electrochemical processes and their quantification through physically meaningful parameters, such as charge transfer resistance (R_{ct}), film resistance (R_{film}), and double-layer capacitance (C_{dl}).

Despite its centrality to the analysis, ECM identification remains a laborious task. Commercial software packages such as ZView and Gamry Echem Analyst rely on nonlinear least-squares (NLLS) fitting routines, most commonly the Levenberg-Marquardt algorithm, which are inherently sensitive to the choice of initial parameter estimates. While heuristic approaches exist to guide these estimates, such as reading characteristic resistances from the diameters of semicircular arcs in the Nyquist representation or extracting time constants from Bode phase plots, the process remains largely manual and iterative, demanding considerable operator experience to avoid convergence to local minima or physically unreasonable solutions.

In response to these limitations, a number of open-source, programmatic alternatives have been developed, predominantly in Python. Among these, `impedance.py` provides a flexible framework for ECM fitting and validation. More recently, tools such as `AutoECM` and `AutoEIS` have incorporated machine learning methodologies into the workflow. AutoECM employs supervised classification models such as Random Forest, XGBoost (XGB), and convolutional neural network (CNN) architectures. These are trained on libraries of previously validated circuit-spectrum pairs to predict candidate ECMs for new datasets. AutoEIS, by contrast, adopts a probabilistic framework grounded in Bayesian inference, enabling uncertainty quantification in both circuit structure selection and parameter

estimation. A notable limitation shared by both tools, however, is the apparent discontinuation of active maintenance by their respective developers. As a consequence, dependency incompatibilities with more recent versions of core scientific Python libraries have rendered them largely non-functional in current environments.

Given this landscape, `impedance.py` emerges as the most viable open-source option. In its standard implementation, it operates analogously to commercial software: the user must supply the impedance dataset, an *a priori* circuit string, and initial parameter guesses. Two optional fitting configurations are available. The first, `weight_by_modulus`, applies the modulus of the complex impedance as a frequency-dependent weighting factor which ensures that data points spanning several decades of impedance magnitude contribute proportionally to the objective function. The second, `global_opt`, invokes a basin-hopping algorithm, which combines stochastic perturbation of parameter coordinates with local minimization and a Metropolis-type acceptance criterion to escape local minima. Importantly, `global_opt` is incompatible with `weight_by_modulus` and given that EIS datasets span several decades in frequency, commonly from 10 mHz to 100 kHz, and correspondingly large ranges in impedance magnitude, modulus weighting is generally considered essential to prevent low-frequency, high-impedance data from disproportionately dominating the fit residuals.

To overcome the dependence on user-supplied initial guesses while retaining the precision of local optimization, a hybrid fitting framework was developed building upon impedance.py and the Differential Evolution (DE) algorithm. DE is a stochastic, population-based global optimization metaheuristic well-suited to high-dimensional, non-differentiable, and multimodal objective functions. The algorithm evolves a population of candidate solutions across successive generations through three operators: mutation, which generates trial vectors via linear combinations of population members; crossover, which probabilistically exchanges parameter values between candidate and trial vectors; and selection, which retains whichever vector yields a lower objective function value. Crucially, DE requires no gradient information and treats the cost function as a black box, making it particularly appropriate for the complex, rugged parameter landscapes characteristic of multi-element ECM fitting.

In the proposed workflow, the user supplies only physically motivated bounds for each circuit element rather than precise initial estimates. The DE algorithm then explores this parameter space to identify the order of magnitude and approximate value of each component. To accelerate convergence, given that circuit element values typically span many orders of magnitude, the optimization is performed in logarithmic space, transforming the search domain such that each decade is treated uniformly. This logarithmic reparameterization substantially improves the efficiency of

the population-based search and reduces sensitivity to the scale disparity between, for example, charge-transfer resistances on the order of kilohms and double-layer capacitances on the order of microfarads. Once the DE stage yields a sufficiently accurate global estimate, the resulting parameter vector is passed as the initial condition to the Levenberg-Marquardt local optimizer within `impedance.py`, with `weight_by_modulus` activated, to refine the solution and obtain statistically meaningful parameter estimates together with their associated uncertainties.

3.2 Pre-treatments

As previously discussed, the presence of intermetallic phases (IMPs) on the surface of the aluminum alloy can negatively affect LDH growth and must therefore be removed prior to coating. Two different pre-treatment procedures were tested: a chemical treatment and an industrial treatment.

The first procedure consisted of cleaning at room temperature for 120 s in a 0.1 M NaOH solution, followed by etching for 480 s in a 0.1 M HNO_3 solution. Each step was followed by rinsing with deionized water and final drying in air.

The second procedure consisted of cleaning in Metaclean T2001 (alkaline cleaner based on metal silicates with complexing and surface-active agents) at approximately 65 °C for 25 min, followed by rinsing with deionized water. The specimens were then etched in TurcoLiquid Aluminetch N2 (sodium hydroxide and phosphate-based solution) at 65 °C for 45 s, rinsed with deionized water, and desmutted in TurcoLiquid Smutgo NC (based on ferric sulfate, nitric acid, sodium hydrogendifluoride, and sulfuric acid) at 30 °C for approximately 5 min, before a final rinse with deionized water and drying in air.

Chapter 4

Results

Present the results of your project clearly and concisely, using tables and figures where necessary.

Chapter 5

Discussion

Interpret the results and discuss their implications. Compare your findings with previous research. Discuss any limitations of your study.

Chapter 6

Conclusion & Future Work

Sum up the main findings and their importance, and discuss how they have the WBS going forward.

Bibliography

[1] Albert L. Askin and Paul B. Schultz. Method for desmutting aluminum alloys having a highly reflective surface. US Patent 5,417,819, May 1995. Assigned to Aluminum Company of America.

[2] A. C. Bouali, M. Serdechnova, K. A. Yasakau, A. Lutz, G. Wiese, H. Terryn, M. G. S. Ferreira, and M. L. Zheludkevich. The Role of Cu-Based Intermetallic on the Direct Growth of a ZnAl LDH Film on AA2024. *Journal of The Electrochemical Society*, 169(8):081501, 2022.

[3] Yanhui Cao, Shenao Wang, Congshu Huang, Jingjing Wang, Haixia Qi, Lieji Yang, Hui Li, Dajiang Zheng, and Changjian Lin. Study on the influence mechanism of intermetallic compounds (IMCs) in aluminum alloy AA7075 on the growth behavior and corrosion resistance of layered double hydroxide films. *Corrosion Science*, 265:113809, 2026.

[4] C. M. Cotell, J. A. Sprague, and F. A. Smidt. *Surface Engineering of Aluminum and Aluminum Alloys*, pages 784–804. ASM International, 1994.

[5] Sutanu Das, Ankita Banerjee, Upendranath Nandi, and Aswini Ghosh. Critical review on the analysis of electrochemical impedance spectroscopy data. *Journal of Applied Physics*, 138(12):125002, 2025.

[6] Rubén del Olmo, Reynier I. Revilla, Francesco Andreatta, and Iris De Graeve. Layered double hydroxides on additively manufactured Al–Si alloy: Growth mechanism, microstructure and corrosion performance. *Applied Surface Science*, 710:163891, 2025.

[7] Senka Gudić, Ladislav Vrsalović, Jure Krolo, Aleš Nagode, Ivana Dumanić Labetić, and Branimir Lela. Corrosion Behaviour of Recycled Aluminium AlSi9Cu3(Fe) Machining Chips by Hot Extrusion and Thixoforming. *Sustainability*, 16(4):1358, 2024.

[8] Zelong Jin, Changrun Cai, Yudie Yuan, DaeHoon Kang, John Hunter, and Xiaorong Zhou. The behaviour of AA5754 and AA5052 aluminium alloys in alkaline etching solution: Similarity and difference. *Materials Characterization*, 168:110534, 2020.

[9] Justyna Kasińska, Dana Bolibruchová, and Marek Matejka. The Influence of Remelting on the Properties of AlSi9Cu3 Alloy with Higher Iron Content. *Materials (Basel)*, 13(3):575, 2020.

[10] Robert G. Kelly, John R. Scully, David W. Shoesmith, and Rudolph G. Buchheit. *Electrochemical Techniques in Corrosion Science and Engineering*. Marcel Dekker, Inc., New York, NY, 2002.

[11] Andrzej Lasia. *Electrochemical Impedance Spectroscopy and its Applications*. Springer New York, New York, NY, 2014.

[12] Eul-Kyu Lee. Surface treatment composition and method for removing Si component and reduced metal salt produced on the aluminum die cast material in etching process. US Patent 7,405,189, Jul 2008. Assigned to Cheon Young Chemical Co., Ltd.

[13] Mariana Paz Martínez-Viademonte, Shoshan T. Abrahami, Theodor Hack, Malte Burchardt, and Herman Terryn. A Review on Anodizing of Aerospace Aluminum Alloys for Corrosion Protection. *Coatings*, 10(11):1106, 2020.

[14] Metrohm Autolab. Electrochemical Impedance Spectroscopy Part 3 - Data Analysis. EC Application Note AN-EIS-003, Metrohm AG, 2021.

[15] K. J. H. Nelson, A. E. Hughes, R. J. Taylor, B. R. W. Hinton, L. Wilson, and M. Henderson. Characterisation of aluminium alloys after $HNO_3/HF - NaOH - HNO_3/HF$ pretreatment. *Materials Science and Technology*, 17(10):1211, 2001.