Let $Q = \min(s^{0.1}, 2^{\sqrt{\log n}})$, $k = k = Q^2 n/s$.
$\varepsilon \leftarrow \varepsilon/10$.
Sample $j_1, \ldots, j_a \sim \mathcal{D}$, where $\mathcal{D}$ is as in Theorem 7.
Sample $j_{u+1}, \ldots, j_{u+v} \in [N]$ uniformly randomly.
For each $1 \le t \le u+v$, set $P_0^t, P_1^t \leftarrow 0$.
while there exists t such that $P_0^t, P_1^t \le (1-\varepsilon)k/2$ **do**
    Read next copy $y^{(i)}$, and perform smooth local decoding on $y^{(i)}$ as in Theorem 7, $u+v$ times in parallel, to get confidences p_0^t, p_1^t for each index j_t.
    For each t, set $P_0^t \leftarrow P_0^t + p_0^t$ and $P_1^t \leftarrow P_1^t + p_1^t$.
For each t, let b_t be such that $P_{b_t}^t > (1-\varepsilon)k/2$.
while there are bits remaining to output **do**
    Read the next copy $y^{(i)}$, keeping a counter c tracking how many $u < t \le u+v$ satisfy $y_t^{(i)} = b_t$. ▷ *We will prove that the copies will not run out before decoding is complete.*
    In parallel with the above, perform local list decoding with advice as in Theorem 7 using $y_{j_t} = b_t$ for $1 \le t \le u$, in parallel for the next $r = s(n)/Q^2$ bits that have not yet been output.
    if $c < (1/2 - \varepsilon)v$ **then**
        Output the decoded bits.