

# DISCRETE

EE23BTECH11006 - Ameen Aazam\*

**Question :** Consider a carrier signal which is amplitude modulated by a single-tone sinusoidal message signal with a modulation index of 50%. If the carrier and one of the sidebands are suppressed in the modulated signal, the percentage of power saved (rounded off to one decimal place) is ....

(GATE EC 2021)

**Solution:** The percentage modulation,

Parameters	Values	Description
$m$	50%	Percentage modulation
$P_t$		Total power of the modulated AP
$P_c$		Power of the carrier signal
$P_s$		Saved power

TABLE 0  
PARAMETERS

$$m = 50\% \quad (1)$$

$$= 0.5 \quad (2)$$

The total power is due to the carrier and the two sidebands,

$$P_t = P_c \left[ 1 + \frac{m^2}{2} \right] \quad (3)$$

Now as the carrier signal and one of the sidebands are suppressed then total saved power,

$$P_s = P_c \left[ 1 + \frac{m^2}{4} \right] \quad (4)$$

So percentage power saved,

$$\%Powersaved = \frac{P_s}{P_t} \times 100\% \quad (5)$$

$$= \frac{P_c \left[ 1 + \frac{m^2}{4} \right]}{P_c \left[ 1 + \frac{m^2}{2} \right]} \times 100\% \quad (6)$$

$$= \frac{1 + \frac{1}{16}}{1 + \frac{1}{8}} \times 100\% \quad (7)$$

$$= 94.44\% \quad (8)$$

Hence, the percentage power saved is 94.4%.