RP2350 CONNECT — REV A — 85 x 70 mm, 6-layer PCB

16MB flash + 8MB PSRAM (shared QMI bus, GPIO0 CS1)

Wi-Fi / BLE: ESP32-C3-WROOM-02-N4

USB-C: USB 2.0 FS sink, independent 5.1k CC resistors

External 1.1V core; VREG_FB=GND, VREG_LX=NC

microSD SPI1 on switched rail; enable after USB enumeration

12MHz crystal + per-pin supply bypass

Qwiic / STEMMA QT: 3.3V I2C

USB_EN1/2 reset LOW: USB100; radio and SD reset OFF

Firmware: USB500 after enumeration, handle USB suspend; set VREG.HIZ

LiPo 4.2V, protected pack +10k NTC; pin1=BAT+, 2=GND, 3=NTC

3.3V buck-boost; nominal 66uF output

RGB: dedicated 5V boost + AHCT level buffer

Sockets expose user GPIO and power-control signals

PCB features: four 2.7mm mounting holes and three 1mm fiducials; no purchased parts

All fitted parts assembled by PCBWay. Battery, microSD media and cables are external. See README and fab instructions.

| | |
|---|---|
| Sheet: / | |
| File: rp2350-connect.kicad_sch | |
| **Title:** | |
| Size: A2 | Date: |
| KiCad E.D.A. 10.99.0-unknown | **Rev:** |
| | Id: 1/1 |