

Product technical specifications and specifications

Item		Item description
Input	Rated volt.,frequency	3 phase 380V, 50Hz/60z
	Allowed volt.range	3 phase 380V: 320-460V
Output	Voltage	0-input voltage
	Frequency	0~599Hz
	Over loading capacity	P type: 18.5kW and below: 120% of rated current for 1 minute 22kW-75kW: 115% of rated current for 1 minute 90kW and above: 110% of rated current for 1 minute
		G type: 150% of rated current for 1 minute
Control performance	Control mode	1. Without PG vector control(support synchronous motor and asynchronous motor) 2. PG vector control(support synchronous motor and asynchronous motor) 3. V/F control
	Speed control precision	±0.5% rated synchronous speed(without PG vector control) ±0.3% rated synchronous speed(PG vector control) ±1% rated synchronous speed(V/F control)
	Speed regulation range	1:2000(PG vector control) 1:200(without PG vector control) 1:50(V/F control)
	Starting torque	1.0Hz: 150% rated torque(V/F control) 0.25Hz: 150% rated torque(without PG vector control) 0Hz: 180% rated torque(PG vector control)
	Speed fluctuation	±0.3% rated synchronous speed(without PG vector control) ±0.1% rated synchronous speed(PG vector control)
	Torque response	≤20ms(without PG vector control) ≤10ms(PG vector control)
	Frequency precision	Digital setting: max.frequency×±0.01%,; Analog setting: max.frequency×±0.5%,
	Freq. resolution	Analog setting
		Digital setting
		External pulse
	Torque boost	Automatic torque boost Manual torque boost 0.1-30.0%
	V/F curve (volt. Frequency characteristics)	Setting rated frequency at the range of 5-599Hz, by choosing constant torque, degressive torque 1, degressive torque 2, degressive torque 3, self-defined V/F, V/F separation, total 6 kinds of curve
	Acceleration/Deceleration curve	Two modes: straight line acceleration and deceleration, S curve acceleration and deceleration; 15 kinds of acceleration and deceleration time, time unit(0.01s, 0.1s, 1s) for option, max. time for 1000 minutes
	Brake	Power consumption brake
		DC brake
	Jog	Jog frequency range: 0Hz - upper limit frequency; jog acceleration and deceleration time 0.1 - 6000.0 seconds for setting
	Multi-section speed run	Realized by inbuilt PLC or control terminal; with 15 section speed, each section speed with separately acceleration and deceleration time; with inbuilt PLC can achieve reserve when power down
	Inbuilt PID controller	Convenient to make closed-loop control system
	Automatic voltage(AVR)	Automatically keep output voltage constant, when the power grid voltage fluctuation
	Automatic current limiting	Current limited automatically under run mode in avoid of inverter over-current frequently to trip
	Carrier modulation	Modulate carrier wave automatically according to the load characteristic
	Speed tracking restart	Make rotating motor smoothly start without shocking
Running function	Running command specified channel	Keypad specified, control terminal specified, communication specified, can switch through various means
	Running frequency specified channel	Main & auxiliary specified to a realize one main adjusting and one fine control Digital specified, analog specified, pulse specified, pulse width specified, communication specified and others, which can be switched by many means at any time
	Binding function	Run command channel and frequency specified channel can bind together randomly and switch synchronously