




Research Notes

Problem framing, goal association, assumptions and associated research papers



PROJECT
Node v0

Document ID	NT-N-M-H-001	Revision	A
Status	Exploratory Draft	Date	2026-07-9
Stage	Preliminary Research	Owner	Robotics Systems Engineering
Author	NervTech Research	Class	INTERNAL

Research Question
Which motor housing architecture will fulfill NT-N-G1, NT-N-G2 and NT-N-G7?

Abstract
This document collates and analyses multiple research papers and notes for fulfilling Node v0 design goals. Its intended purpose is to isolate observations, assumptions, risks, and design direction before committing to a detailed technical design.

Keywords: integrated actuator, mechanical design, motor housing, robotics, research notes

CONTENTS

1	Research Snapshot	2
2	Problem Framing	2
3	Preliminary Direction	2
4	Assumptions	2
5	Frameless BLDC Architecture	3
6	Existing Motor Integration Guidelines	4
6.0.1	Bearings	4
6.0.2	Stator Mounting	5

1 RESEARCH SNAPSHOT

Research Snapshot

Problem	Build motor housing to maximise thermal and electromagnetic performance of the actuator, while reducing size and weight.
Key Finding	The highest leverage early decision is the actuator architecture, because it constrains torque density, controllability, thermal behaviour, and manufacturability.
Main Uncertainty	The true operating envelope is still uncertain: load profile, duty cycle, heat rejection, encoder resolution, and gearbox backlash all need validation.
Next Step	Prototype the smallest credible bench rig and measure torque, speed, temperature rise, backlash, and closed-loop response.

2 PROBLEM FRAMING

Research Question – System Direction

What outrunner BLDC motor housing architectures minimises thermal resistance ($^{\circ}\text{C}/\text{W}$), magnetic flux leakage and Air Gap instability ($\pm \text{mm}$)?

3 PRELIMINARY DIRECTION


This research document will collate results from multiple research papers and notes to inform the design of a motor housing for Node v0. The goal is to identify the most promising motor housing architecture that meets the specified design goals (NT-N-G1, NT-N-G2, NT-N-G7). A preliminary frameless outrunner BLDC motor has been selected, informed by cost and performance requirements.

4 ASSUMPTIONS

- The frameless outrunner BLDC architecture will provide the highest torque density and lowest thermal resistance for the Node v0 actuator.
- Aluminium provides the best balance of thermal conductivity, weight, and manufacturability for the motor housing.

5 FRAMELESS BLDC ARCHITECTURE

The selected frameless outrunner BLDC was the SteadyWin WK8115 model with the following dimensions:



更新于2025. 7. 10

Figure 1: SteadyWin WK8115 Dimensions

The magnetic, thermal and electrical properties of the motor are taken from the manufacturer as follows:

规格型号	wk1105	wk2205	wk2806	wk3505	wk3510	wk4310	wk4315	wk5215	wk5225	wk6010	wk6025	wk8110	wk8115	wk10025
额定电压 (V)	12	12	12	12	12	16	16	24	24	24	36	24	48	48
额定电流 (A)	0.59	0.66	0.81	0.79	0.53	0.79	0.59	1.12	1.28	1.19	1.78	1.75	6.5	4
堵转电流 (A)	0.92	1	1.22	1.2	0.8	1.2	0.9	1.69	1.94	1.8	2.67	3	10	11.2
额定扭矩 (N.M)	0.01	0.04	0.06	0.07	0.11	0.21	0.28	0.76	1.26	0.73	1.77	1.6	2.16	6
堵转扭矩 (N.M)	0.02	0.07	0.1	0.12	0.19	0.32	0.42	1.24	1.92	1.21	2.83	2.68	5.83	8.9
额定转速 (rpm)	7000	5500	2060	1890	945	585	425	390	313	280	227	186	1800	190
最高转速 (rpm)	8700	7200	2570	2160	1250	875	608	565	455	410	315	312	2280	310
绕组匝数 (T)	50	65	60	40	160	160	160	50	80	50	30	30	30	20
相间电阻 (Ω)	12.5	8	5	6.5	8.8	10.9	15.2	14.8	11.8	11.9	10.1	3	0.4	2.5
相间电感 (mH)	1.15	1.45	1.51	2.35	3.95	4.74	6.56	7.8	11.31	13.03	10.07	31.5	0.2	66
转速常数 (rpm/V)	108	100	121	74	45	33	23	12	12	11	7	11	37	12
扭矩常数 (N.M/A)	0.01	0.06	0.07	0.09	0.2	0.27	0.47	0.68	0.98	0.61	1.63	1.13	0.58	0.76
转子惯量 (gcm ²)	15	42	51	56	81	202	268	667	933	748	1645	2860	1500	4656
极对数	6	7	7	11	11	14	14	11	11	14	14	21	21	21
工作温度范围 (°C)	-20~80													
最高退磁温度 (°C)	120													

Figure 2: SteadyWin WK8115 Specifications

Figure 1 will inform the tolerances and mechanical design of the Node v0 motor housing, while Figure 2 will inform the thermal and electromagnetic characteristics of the Node v0 actuator.

6 EXISTING MOTOR INTEGRATION GUIDELINES

Several motion control companies provide mounting and installation guidelines for frameless BLDC motors, which can be applied to the Node v0 motor housing design.

Note:

It should be noted that many of these guidelines are for inrunner motors, however the engineering concepts can be transferred between inrunner and outrunner geometries.

6.0.1 Bearings

Bearings in the motor housing are critical for maintaining air gap stability and therefore electromagnetic performance [1]. Kollmorgen notes that concentricity requirements are noted on the motor datasheet, and should be considered when "sizing and selecting bearings for appropriate radial and preload forces to achieve desired motor running gap clearance and total runout". While the WK8115 datasheet is vague on concentricity requirements, it does show an air gap of 0.75 mm, and a tolerance stack of ± 0.07 mm.

According to the Maccon Frameless BLDC mounting guide, "the defined manufacturing tolerances in your design should ensure a minimum gap greater than the half nominal air gap", which is 0.375 mm [2]. However, to maximise electromagnetic performance, the air gap should be as consistent as possible, and therefore the concentricity of the bearing stack should be designed to maintain the minimum gap with a factor of safety of 1.5, ensuring a minimum air gap of 0.5625 mm. This would require the bearing stack to have a minimum tolerance of ± 0.1175 mm. According to Maxon, a tolerance class of P5 is recommended for frameless BLDC motors, which is on the scale of micrometers and would therefore be sufficient to maintain the minimum air gap with a factor of safety of 1.5. [3]

Bearings should also be chosen for the lowest possible friction and high quality lubricant, to reduce motor losses and heat generation. To do a bearing selection, the expected radial and axial loads on the motor housing must be calculated. This will be done in the technical design phase; for now, bearings requirements are being defined based on their effect on air gap stability.

6.0.2 Stator Mounting

The stator mounting technique is critical for proper thermal management of the motor, and its tolerance will also affect the air gap stability of the motor. Both Kollmorgen and Maccon note 3 techniques for stator mounting: adhesive bonding, shrink fitting and axial clamping [1, 2].

Axial Clamping

Securing the stator within 2 "bells", or end caps, puts axial load on the stator and counters torque generated from the rotor via friction. This is shown for inrunner architectures in the following figures:




Figure 3: Axial Clamping of Stator [4]




Figure 4: Axial Clamping of Stator [2]

According to Kollmorgen, axial clamping is recommended for "low torque applications" [1]. Furthermore, Kollmorgen do not recommended it for "high shock/vibration applications ... or for peak torques greater than 50 N-m without special design considerations". Geometrically, axial clamping is easier to integrate into housing for inrunner motors vs outrunner motors, making it less suitable for the Node v0 actuator. Axial clamping also requires a high degree of concentricity between the two end caps, which is difficult to achieve in a small form factor.

Since the outrunner stators are located inside the rotor, the end caps would be end caps attached to cylindrical tube-like locating features. This would reduce the bore diameter of the housing to include machine screws. This concept is shown in the following figure:



Figure 5: Axial Clamping of Stator in Outrunner Architecture

An advantage of axial clamping is high thermal efficiency, as the stator is in direct contact with the end caps, which can be designed to act as heat sinks.

Shrink Fitting

Shrink fitting for inrunner motors involved heating the motor housing to expand the bore, and then inserting the stator. As the housing cools, it contracts and applies a radial load on the stator. According to Kollmorgen, "aluminium or steel housings may be used effectively to shrink fit stators across a broad peak torque range, generally from <1 N-m up to thousands of N-m" [1]. The Mabuchi and Maccon installation guides offer some notes for motor housing design if using shrink fitting. Mabuchi mention that the housing must meet certain prerequisites for shrink fitting [4]:

- "The housing has a thickness that corresponds to the torque" transmitted by the stator.
- "The housing has a suitable surface roughness for shrink fit fixing".

Maccon also notes that [2]:

- "Different materials have different thermal expansion coefficients. This means that you are limited in the operating/storage temperature when using different materials for stator and housing".
- "All mechanical parts have tolerances. When you determine the gap you should always calculate the worst case".

Since the procured outrunner motor has a peak transmitted torque of 5.83 N-m, shrink fitting may be an overengineered solution, since it requires consideration of thermal expansion coefficients during operation and stress analysis of the stator to ensure it does not fracture under the radial load. Furthermore, as will be seen in the next section, adhesive bonding may also provide suitable thermal management if the adhesive is chosen with consideration of its thermal conductivity.

Adhesive Bonding

Adhesive bonding is the simplest method of stator mounting, and is suitable for low torque applications. Kollmorgen notes that "motors in the general peak torque range up to 750 N-m may have the stator bonded in place using a structural epoxy, such as Hysol® EA934NA, 3M™ Scotchweld™ 2214 or other similar adhesives" [1]. Adhesive bonding provides the advantage of being easy to implement, however comes at the disadvantage of not having easy disassembly.

Kollmorgen, while coming from the perspective of inrunner stators, notes that the stator housing should be designed with "a small shoulder for axial positioning at one end" and that the shoulder "should generally clear the maximum outer diameter of the winding end turn by no less than 1 mm at all circumferential points" [1].

For outrunner motor architectures, the stator would be mounted on a cylindrical locating feature, and the shoulder would be a small lip on the cylindrical feature that has the width of the outer laminated edge of the stator and allows enough axial clearance for the winding width.

Mabuchi notes that if the temperature rises when curing adhesive bonding, it should not "exceed the heat resistance of the windings" [4]. This aligns with recommendations from Kollmorgen. For recommended gaps for proper adhesion, all manuals point to the datasheets of the adhesives. Kollmorgen notes, as a rule of thumb, that "if using thick structural epoxy, [the] inner diameter of the housing cup should be approximately 0.051 mm - 0.102 mm larger than the maximum outer diameter of the stator", but follows this with pointing to the datasheet of the adhesive for more specific recommendations [1]. Small grooves are also recommended as adhesive reservoirs for structural epoxies, but "are considered optional features per the user's discretion" [1].

All manuals note that bonding surfaces should be thoroughly cleaned and degreased prior to bonding, to ensure the optimal adhesion.

REFERENCES

- [1] Kollmorgen Corporation (2020) *Mounting and Installation Guidelines for BLDC Motors*, Kollmorgen Technical Documentation.
- [2] Maccon Corporation (2019) *Frameless BLDC Motor Mounting Guide*, Maccon Technical Documentation.
- [3] Maxon Corporation (2020) *Frameless BLDC Motor Selection Guide*, Maxon Technical Documentation.
- [4] Mabuchi Motor Corporation (2018) *BLDC Motor Mounting and Installation Guide*, Mabuchi Technical Documentation.