

SMARTLINK AC1200 Wi-Fi Router

Installation Guide — Initial Setup & Network Configuration

1. Before You Begin

Before installing the router, confirm that you have the router, supplied power adapter, Ethernet cable, and an active Internet connection from your modem, ONT, or ISP Ethernet outlet. Keep the router near a power socket and place it in an open, elevated location. Avoid enclosed cabinets, direct sunlight, water, and sources of strong electromagnetic interference. For initial configuration, keep a phone, tablet, or computer nearby.

2. Physical Connections

Step	Connection	Action
1	WAN / Internet	Connect the Ethernet cable from the modem/ONT or ISP outlet to the router's WAN/Internet port.
2	LAN	For wired setup, connect a computer to LAN 1–4 using an Ethernet cable.
3	Power	Connect the supplied power adapter and switch the router on.
4	Startup	Wait approximately 1–2 minutes for the router to initialize before configuring it.

3. Connect to the Router

- **Wi-Fi method:** On your phone/computer, open Wi-Fi settings and select the default SSID printed on the router label.
- **Wired method:** If using a computer, connect it to any LAN port and wait for the Ethernet connection.
- **Credentials:** Enter the default Wi-Fi password printed on the router label. Change it during configuration.
- **Management page:** Open a browser and enter the local router address shown on the device label or setup documentation.

4. Internet Setup Wizard

1. Sign in to the router administration page using the default administrator credentials supplied with the device.
2. Select the Internet/WAN connection type. Use Automatic/DHCP when instructed by the ISP; select PPPoE or another method only when ISP credentials/settings are provided.
3. Enter the required ISP username/password or network parameters if requested.
4. Wait for the router to test the WAN connection. A successful test should show an active Internet/WAN status.
5. Create a unique Wi-Fi network name (SSID) and a strong Wi-Fi password. Use separate names for 2.4 GHz and 5 GHz if desired.
6. Enable WPA2 or WPA3 security where supported. Avoid open/unsecured Wi-Fi for normal use.
7. Save or apply the configuration and allow the router to restart if requested.

5. Recommended Configuration

Setting	Recommended Action
Wi-Fi Security	Use WPA2/WPA3 with a strong password; do not share the administrator password.
SSID	Use a recognizable network name without unnecessary personal information.
Administrator Password	Change the default administrator password immediately after setup.
Firmware	Check for an official firmware update after the Internet connection is working.
Guest Network	Enable a separate guest network when visitors need Internet access without access to the main LAN.

6. Installation Troubleshooting

Problem	Action
No Internet after setup	Check that the cable is connected to WAN, not LAN. Restart the modem/ONT and router. Verify the selected WAN type and ISP credentials.
Internet LED is red	Inspect the WAN cable, check the modem/ONT status, confirm ISP service, and review WAN status in the router interface.
Cannot open setup page	Confirm you are connected to the router, disable an active VPN temporarily, check the gateway/router address, and try another browser/device.
Wi-Fi network not visible	Confirm Wi-Fi is enabled, move closer to the router, restart the router, and check whether the SSID is hidden.
Setup stops or fails	Reconnect cables, restart the router, retry the wizard, and verify that all required ISP information is correct.

7. Final Installation Check

Confirm that the Power indicator is on, the Internet/WAN status is connected, both required Wi-Fi bands are available, and at least one device can browse the Internet. Test a wired LAN connection if required. Record the new Wi-Fi and administrator credentials in a secure location. Never perform a factory reset unless you are prepared to repeat the Internet and wireless configuration.

Support Reference: This is a synthetic installation guide created for the TechSupport RAG demonstration. It is intended as a realistic retrieval source and does not represent a real commercial router's official manual.