




Build Gesture-controlled Devices

Introduction to the course:	Build hand gesture-based devices that can be used as alternate control devices for PC mouse or to navigate a mobility device.
What does this course aim to achieve?	• Learn about alternate PC control • Learn about inertia measurement sensors, HID devices, and how to convert a normal microcontroller to a PC HID device. • Learn more about the people with limited hand movements and their requirements. • Learn about Bluetooth wireless communication • Learn about IMU sensors, Motor controller boards, and Bluetooth modules. • Learn about AT commands and configuration • Learn how gestures can be converted to mobility
What is being built in this course:	1) A wearable gesture-controlled mouse that helps to access a Windows PC without a mouse/keyboard. The microcontroller mimics an HID device and does the mouse movements. 2) A wearable hand gesture device that includes a gyro sensor & microcontroller, which converts gyro values to corresponding motor movements and sends the data to an RC car via Bluetooth
How is it being tested:	1) Different people will have different comfortable hand positions; the device can adjust to that position with the click of a calibration switch. Activities are given to adjust sensitivity values and also to look for better positions for the sensor and right-click/left-click buttons 2) The Controllability of the RC car can be corrected by changing the sensitivity value as per individual preference. If the movements are beyond the possible correction values, the sensors/Car setup/wiring needs to be reconfigured/tested
Course Prerequisites	• Basic C/C++ programming skill • Basic understanding of sensors and other electronics • Build a club project on maze solving robot

Build a Gesture controlled Mouse for PC





Index

Prerequisite

Aim

Concept

Components

Connections

Components in detail

Implementing the gesture project

Activities

Prerequisite

Topic	Resources
Understanding Gyro Sensor & HID	HID
AT Command	Link

Aim

Build a hand gesture-based device for people with limited hand motor movements that can control the mouse pointer of a PC.

Concept

In this project, we will create a gesture-based device that mimics mouse actions and controls a Windows PC. This device can be used by persons with hand impairments who cannot use a conventional mouse to control the PC. The wearable gesture device could communicate with the PC which can in turn communicate with apps and avail many services such as communication software or accessing the internet for healthcare, food delivery, etc.



Here we will be using an ESP32 module as an HID device.

HID (Human Interface Device)

A human interface device, often known as a HID, is a kind of computer hardware that is typically used by people and that receives input from people and provides outputs to people in many forms.

The USB-HID specification is most frequently used when the term "HID" is used. Mouse, Keyboards & Joysticks are all part of HID Devices.

Components


1. ESP 32 Module
2. MPU6050 sensor
3. Small breadboard (170points)

4. Button module
5. Long wires
6. Jumper wires
7. USB cables

Note: All the components above are reusable for other projects



Esp 32 Module



MPU6050 sensor



Push Button



Jumper Wires



USB




Breadboard


Connections

Circuit Diagram

- NOTE: Before starting the connections, verify using a multimeter that all the wires are working. Also ensure that the connections are strong, else the setup may not work.



Orientation of MPU6050 sensor



Since we are using only y and z axis values for this project. Orient the sensor in such a way that it is perpendicular to the breadboard as shown in the above picture.

Detailed Connection Steps

Stick the small breadboard to the wristband you have in this orientation

MPU6050 sensor

(MPU to ESP32)

- VCC to V5
- GND to GND
- SCL to G22
- SDA to G21

Button module

(Buttons to ESP32)

Left Button


- VCC to V5
- GND to GND
- OUT to G12

Right Button

- VCC to V5
- GND to GND
- OUT to G14

Components in detail

1) MPU6050 Sensor Module



MPU6050 sensor module is complete 6-axis Motion Tracking Device. It combines 3-axis Gyroscope, 3-axis Accelerometer and Digital Motion Processor all in small package.


NOTE: Also, the sensor has an additional feature of on-chip Temperature sensor. It has I2C bus interface to communicate with the microcontrollers.

It has Auxiliary I2C bus to communicate with other sensor devices like 3-axis Magnetometer, Pressure sensor etc.

If the 3-axis Magnetometer is connected to the auxiliary I2C bus, then the MPU6050 can provide complete 9-axis Motion Fusion output.

3-Axis Gyroscope

The MPU6050 consists of a 3-axis Gyroscope with Micro Electromechanical System (MEMS) technology. It is used to detect rotational velocity along the X, Y, Z axes as shown in below figure.



When the gyros are rotated about any of the sense axes, the Coriolis Effect causes a vibration that is detected by a MEM inside MPU6050.

The resulting signal is amplified, demodulated, and filtered to produce a voltage that is proportional to the angular rate.


This voltage is digitized using 16-bit ADC to sample each axis.

The full-scale range of output are +/- 250, +/- 500, +/- 1000, +/- 2000.

It measures the angular velocity along each axis in degrees per second unit.

3-Axis Accelerometer

The MPU6050 consists of a 3-axis Accelerometer with Micro Electromechanical (MEMs) technology. It is used to detect angle of tilt or inclination along the X, Y and Z axes as shown in below figure.



Acceleration along the axes deflects the movable mass.

This displacement of moving plate (mass) unbalances the differential capacitor which results in sensor output. Output amplitude is proportional to acceleration.

16-bit ADC is used to get digitized output.

The full-scale range of acceleration are $\pm 2g$, $\pm 4g$, $\pm 8g$, $\pm 16g$.

It is measured in g (gravity force) units.

When the device is placed on a flat surface it will measure $0g$ on the X and Y axis and $+1g$ on the Z axis.

The MPU-6050 module has 8 pins as listed below:

1. **INT**: Interrupt digital output pin.
2. **AD0**: I2C Slave Address LSB pin. This is 0th bit in 7-bit slave address of device. If connected to VCC then it is read as logic

one and slave address changes.

3. **XCL**: Auxiliary Serial Clock pin. This pin is used to connect other I2C interface enabled sensor SCL pin to MPU-6050.

4. **XDA**: Auxiliary Serial Data pin. This pin is used to connect other I2C interface enabled sensor SDA pin to MPU-6050.

5. **SCL**: Serial Clock pin. This pin to connected to microcontrollers SCL pin.

6. **SDA**: Serial Data pin. This pin is connected to microcontrollers SDA pin.

7. **GND**: Ground pin. This requires a ground connection.

8. **VCC**: Power supply pin. This requires a +5V DC supply.

For detailed theory refer to this [Link](#)

2) Button module





Features

- Interface: Standard electronic block (GND, VCC, SIG)
- Working voltage: 2 - 5.5 Volt DC
- Working Current: 0.55mA (MAX)
- Output: Digital level (press high, release low)



G. Implementing the gesture project

Downloads & Installation

Download the project zip file from the build club website and unzip it on your computer.

Steps to install libraries

1. Unzip the *.zip file
2. Go to the extracted folder > libraries
3. Copy the **MPU6050** and **ESP32_BLE_Mouse** folder under the libraries folder.
4. Paste it under your **Documents > Arduino > Libraries**

The ***mouse.ino*** turns an ESP32 device with an MPU6050 sensor into a Bluetooth Low Energy (BLE) mouse. It uses gyroscope data from the MPU6050 to control cursor movement and includes functionality for left and right mouse clicks using physical buttons connected to the ESP32.

```
#include <Wire.h>
#include <MPU6050.h>
#include <BleMouse.h>

// Initialize MPU6050 and BleMouse objects
MPU6050 mpu;
BleMouse bleMouse;

// Define pin numbers for left and right mouse buttons
const int leftButtonPin = 12;
const int rightButtonPin = 14;

// Variables to store accelerometer and gyroscope readings
int16_t ax, ay, az;
int16_t gx, gy, gz;

// Adjust this value to change mouse sensitivity
float sensitivity = 0.2;

void setup() {
  /*
  Setup function:
  - Initializes serial communication
  - Initializes I2C communication
  - Initializes the MPU6050 sensor
  - Sets up button pins as inputs
  - Starts the Bluetooth Low Energy (BLE) mouse functionality
  */
  Serial.begin(9600);
  Wire.begin();

  mpu.initialize();
```

```
pinMode(leftButtonPin, INPUT);
pinMode(rightButtonPin, INPUT);

bleMouse.begin();
Serial.println("Bluetooth Mouse started");
}

void loop() {
  /*
  Main loop function:
  - Checks if BLE is connected
  - Reads sensor data and calculates mouse movement
  - Checks button states and performs clicks
  - Includes a small delay to prevent overwhelming the BLE stack
  */
  if(bleMouse.isConnected()) {
    // Read accelerometer and gyroscope values
    mpu.getMotion6(&ax, &ay, &az, &gx, &gy, &gz);



    // Calculate mouse movement based on gyroscope data
    int mouseX = -gy / 200 * sensitivity;
    int mouseY = gx / 200 * sensitivity;

    // Move the mouse if there's significant movement
    if(abs(mouseX) > 0 || abs(mouseY) > 0) {
      bleMouse.move(mouseX, mouseY);
    }

    // Check button states and perform clicks
    if(digitalRead(leftButtonPin) == HIGH) {
      bleMouse.click(MOUSE_LEFT);
      Serial.println("Left Button Clicked");
      delay(1000); // Debounce delay
    }

    if(digitalRead(rightButtonPin) == HIGH) {
      bleMouse.click(MOUSE_RIGHT);
      Serial.println("Right Button Clicked");
      delay(1000); // Debounce delay
    }
  }
}
```

```
delay(10); // Small delay to prevent overwhelming the BLE stack
}
```




Activities

1. Try changing the sensitivity value and find out a value suitable for each of your teammates. Try opening multiple apps in PC
2. Interchange the sensor and button positions and check whether the sensitivity is suitable for people with limited hand movements.



3. Try to position the sensors and buttons, so that it can be operated by single hand.
4. Make a video presenting the build of a gesture device, how you completed the activities and challenges. Share it with the Build Club Community on the Discord Server!

Build a Gesture-controlled Micro Mouse





Index

Aim

Concept

Components

Connections

Components in detail

Implementing the gesture project

Activities

Aim

Build a hand gesture-based device to wirelessly control a robot car (Micro Mouse).

Concept

This project will enable you to control a robot car (Micro Mouse) wirelessly with ESP32 module. The hand movements will be captured by a wearable hand gesture device and the data will be sent to the Micro Mouse wirelessly. The Micro Mouse will move according to the hand movements.

The project can be later converted to control real vehicles or to assist people in wheelchairs. The conventional joystick-controlled powered wheelchairs can be replaced, and the hand gesture device can be used as an alternative drive control for powered wheelchairs



Here we are using a gyro sensor to detect the orientation of the hand, and the data is transmitted to an ESP32 Bluetooth transmitter. The Bluetooth receiver then receives

the hand data which is converted to corresponding motor movements on the Micro Mouse side.


Components

1. ESP 32 Module
2. MPU6050 sensor
3. Small breadboard (170 points)
4. 2 Wheel Smart Car Robot Chassis Kit
5. Jumper wires
6. USB cables
7. L298 Dual Motor driver board


Note: All the components above are reusable for other projects



Esp 32 Module



MPU6050 sensor



MicroMouse Kit



Jumper Wires



USB



Breadboard




L298 Dual Motor driver board

Connections

Circuit Diagram

- NOTE: Before starting the connections, verify using a multimeter that all the wires are working. Also ensure that the connections are strong, else the setup may not work.

Connection diagram for the Wrist side




Detailed Connection Steps


MPU to ESP32

- VCC to V5
- GND to GND
- SDA to G21
- SCL to G22

Stick the small breadboard to the wrist band you have, in this Orientation.



Connection diagram for the Micro mouse/Car side



Detailed Connection Steps

L298N to ESP32

- IN 1 to G13
- IN 2 to G12
- IN 3 to G14
- IN 4 to G27
- GND to GND

Motor Left to L298N

- +ve to Out 1
- -ve to Out 2

Motor Right to L298N


- +ve to Out 3
- -ve to Out 4


12v adapter to L298N

- +ve to 12v
- -ve to GND

Step 1

Take the L298 Motor driver board and screw it on the main acrylic sheet as shown below:






Step 2

Insert screws on the main acrylic sheet in order to mount the ESP32 module. The holes should be chosen in such a way that it matches the holes on the ESP32 module.

Step 3

Place a double sided tape on Micro mouse frame as below




Step 4

Mount the ESP32 module assembly on this double side tape

Components in detail

L293D Dual motor driver module

L298 Based Motor Driver Module is a high power motor driver perfect for driving DC Motors and Stepper Motors. It uses the popular L298 motor driver IC and has the onboard 5V regulator which it can supply to an external circuit. It can control up to 4 DC motors, or 2 DC motors with directional and speed control



Implementing the gesture Micro mouse project

Receiver part (Micro Mouse /Car side)

The **receiver.ino** code sets up a Wi-Fi server to control a robot's motors based on received commands. The robot has two motors, A and B, which can move forward, backward, turn left, or turn right

Block 1: Including Libraries and Defining Constants

This block includes the necessary libraries and defines the constants for Wi-Fi credentials, server port, and motor pins.

Explanation:

1. Includes the necessary Wi-Fi library.
2. Defines Wi-Fi credentials and the server port.

3. Defines the GPIO pins used to control motors A and B.
4. Creates a Wi-Fi server on the specified port.

####Make sure you enter your WIFI SSID and PASSWORD####

```
#include <WiFi.h> // Include the Wi-Fi library

// Wi-Fi credentials
const char* ssid = ""; // SSID of the Wi-Fi network
const char* password = ""; // Password of the Wi-Fi network
const int serverPort = 8080; // Port number for the Wi-Fi server

// Motor A pins
const int motor1Pin1 = 13; // Pin 1 for motor A
const int motor1Pin2 = 12; // Pin 2 for motor A

// Motor B pins
const int motor2Pin1 = 14; // Pin 1 for motor B
const int motor2Pin2 = 27; // Pin 2 for motor B

WiFiServer server(serverPort); // Create a Wi-Fi server on the specified port
```

Block 2: Setting Up the Wi-Fi Connection and Motor Pins

Explanation:

1. Starts serial communication at a baud rate of 115200 for debugging purposes.
2. Sets the motor pins as outputs to control the motors.
3. Begins Wi-Fi connection with the specified SSID and password.
4. Waits until the Wi-Fi connection is established.
5. Prints the IP address once connected.
6. Starts the Wi-Fi server.

```
void setup() {
```

```
Serial.begin(115200); // Start serial communication for debugging

// Set motor pins as outputs
pinMode(motor1Pin1, OUTPUT);
pinMode(motor1Pin2, OUTPUT);
pinMode(motor2Pin1, OUTPUT);
pinMode(motor2Pin2, OUTPUT);

// Connect to Wi-Fi
WiFi.begin(ssid, password); // Begin Wi-Fi connection
while (WiFi.status() != WL_CONNECTED) { // Wait until connected
    delay(1000); // Wait for 1 second
    Serial.println("Connecting to WiFi...");
}
Serial.println("Connected to WiFi");
Serial.print("IP address: ");
Serial.println(WiFi.localIP()); // Print the IP address of the connected device

server.begin(); // Start the server
}
```

Block 3: Handling Client Connections and Reading Commands

Explanation:

1. Listens for incoming client connections.
2. If a client connects:
 - While the client is connected:
 - If there's data available from the client:
 - Reads the command from the client.
 - Converts the command to an integer.
 - Prints the received command for debugging.
 - Controls the motors based on the command.
3. Stops the client connection after processing the command.

```
void loop() {  
  WiFiClient client = server.available(); // Listen for incoming clients  
  
  if (client) { // If a client connects  
    while (client.connected()) { // While the client is connected  
      if (client.available()) { // If there's data to read from the client  
        String commandStr = client.readStringUntil('\n'); // Read the command  
        int command = commandStr.toInt(); // Convert the command to an integer  
        Serial.println("Command received: " + commandStr);  
  
        // Control motors based on the command  
        controlMotors(command);  
      }  
    }  
    client.stop(); // Close the connection after processing the command  
  }  
}
```

Block 4: Controlling the Motors Based on Commands

Explanation:

1. Defines the `controlMotors` function, which takes an integer command as input.
2. Uses a switch-case structure to control the motors based on the command:
 - 0: Calls ***stopMotors*** to stop the motors.
 - 1: Calls ***turnLeft*** to turn left.
 - 2: Calls ***turnRight*** to turn right.
 - 3: Calls ***moveForward*** to move forward.
 - 4: Calls ***moveBackward*** to move backward.
 - Default: Prints an error message and stops the motors for invalid commands.

Call the functions for motor movement in the below code accordingly

```
void controlMotors(int command) {  
  switch (command) {  
    case 0:  
      stopMotors(); // Stop the motors  
      break;  
    case 1:  
      // call left function here  
      break;  
    case 2:  
      // call right function here  
      break;  
    case 3:  
      // call forward function here  
      break;  
    case 4:  
      // call backward function here  
      break;  
    default:  
      Serial.println("Invalid command"); // Print an error message for invalid  
      commands  
      stopMotors(); // Stop the motors for safety  
      break;  
  }  
}
```

Block 5: Defining Motor Control Functions

Explanation:

1. Defines the moveForward function to set the pins to move the motors forward.
2. Defines the moveBackward function to set the pins to move the motors backward.
3. Defines the turnRight function to set the pins to turn the motors right.
4. Defines the turnLeft function to set the pins to turn the motors left.
5. Defines the stopMotors function to set all motor pins LOW, stopping the motors.



The diagram above shows the pin states for Motor A and Motor B for each function (***moveForward***, ***moveBackward***, ***turnRight***, ***turnLeft***, and ***stopMotors***). Each function is represented with its corresponding pin states for both motors.

To write the code for each action, follow these steps:

1. Create a function for each action (***moveForward***, ***moveBackward***, ***turnRight***, ***turnLeft***, ***stopMotors***).
2. Within each function, set the pin states for Motor A and Motor B according to the diagram.
3. Use `digitalWrite()` to set the pin states (HIGH or LOW) for each motor's pins.
4. Use ***moveForward()*** as an example to write other functions.

```
// Function to move forward
```

```
void moveForward() {  
  digitalWrite(motor1Pin1, HIGH);  
  digitalWrite(motor1Pin2, LOW);  
  digitalWrite(motor2Pin1, HIGH);  
  digitalWrite(motor2Pin2, LOW);  
}  
  
// Function to move backward  
void moveBackward() {  
  //write robot backward action here  
}  
  
// Function to turn right  
void turnRight() {  
  //write robot right action here  
}  
  
// Function to turn left  
void turnLeft() {  
  //write robot left action here  
}  
  
// Function to stop motors  
void stopMotors() {  
  //write robot stop action here  
}
```

Upload and Run the Code

Uploading your code to an ESP32 module using the Arduino Integrated Development Environment (IDE). Here are the steps to upload code to your Arduino:

1. Connect Your Arduino Board:

Use a USB cable to connect your ESP32 Module to your computer. The Arduino IDE should recognize the connected board automatically.

2. Open the Arduino IDE:

Launch the Arduino IDE on your computer.

3. Select Your Arduino Board:

In the Arduino IDE, go to **Tools > Board** and select the board **ESP32 > ESP32 Dev Module**

4. Select the Correct Port:

Go to **Tools > Port** and select the COM port that your Arduino is connected to. This might be labeled as something like "COM3" or "COM4" on Windows, or "/dev/tty.usbmodem" on macOS.

5. Verify Your Code:

Click the Verify button (a checkmark icon) to compile your code. This will check for any errors in your code.

6. Upload Your Code:

- Once the code is verified, click the Upload button (an arrow icon) to upload the code to your Arduino board.
- The IDE will compile the code again and then upload it to the esp32 module. You will see the RX and TX LEDs on the board blink during this process.

7. Monitor Output:

If your sketch includes serial communication, you can open the Serial Monitor by going to **Tools > Serial Monitor** or clicking the magnifying glass icon in the upper right corner of the Arduino IDE. This allows you to see output from your Arduino board.

Transmitter part (Wrist side)

The **transmitter.ino** code reads data from an MPU6050 sensor, calculates the pitch and roll of the device, and sends corresponding commands to a robot via Wi-Fi.

This block sets up the MPU6050 sensor and connects to the Wi-Fi.

Explanation of Block 1:

1. **Includes necessary libraries** for MPU6050, sensors, Wire (I2C communication), and Wi-Fi.
2. **Defines Wi-Fi credentials** and the robot's IP and port.
3. **Initializes the MPU6050 sensor** and sets its accelerometer and gyroscope ranges.
4. **Connects to the specified Wi-Fi network.**

####Make sure you enter your WiFi SSID, Password and IP Address of the Robot ####

####Copy the IP address of the robot on receiver part from the serial monitor####

####Copy the setup() function and paste it in your file inside the setup() function####

```
#include <Adafruit_MPU6050.h>
#include <Adafruit_Sensor.h>
#include <Wire.h>
#include <WiFi.h>

const char* ssid = "YOUR_WIFI_SSID_HERE";
const char* password = "YOUR_WIFI_PASSWORD_HERE";
const char* robotIP = "YOUR_ROBOT_IP_ADDR_HERE"; // Set this to your robot's IP
address
const int robotPort = 8080;

Adafruit_MPU6050 mpu;
WiFiClient client;

void setup() {
  Serial.begin(115200);
  Wire.begin();

  // Initialize MPU6050
  Serial.println("Initializing MPU6050...");
```

```

if (!mpu.begin()) {
  Serial.println("Failed to find MPU6050 chip");
  while (1) {
    delay(10);
  }
}
Serial.println("MPU6050 Found!");

// set accelerometer range to +-8G
mpu.setAccelerometerRange(MPU6050_RANGE_8_G);

// set gyro range to +- 500 deg/s
mpu.setGyroRange(MPU6050_RANGE_500_DEG);

// set filter bandwidth to 21 Hz
mpu.setFilterBandwidth(MPU6050_BAND_21_HZ);

// Connect to Wi-Fi
WiFi.begin(ssid, password);
while (WiFi.status() != WL_CONNECTED) {
  delay(1000);
  Serial.println("Connecting to WiFi...");
}
Serial.println("Connected to WiFi");
}

```

Block 2: Reading Sensor Data and Sending Commands

This block reads data from the MPU6050 sensor, calculates pitch and roll, determines the command to send, and sends it to the robot.

Explanation of Block 2:

1. **Reads acceleration and gyroscope data** from the MPU6050 sensor.
2. **Calculates pitch and roll** angles based on the acceleration data.
3. **Determines a command to send** based on the pitch and roll values:
 - Pitch > 15: command = 0

- Pitch < -15: command = 2
 - Roll > 15: command = 4
 - Roll < -15: command = 3
 - Otherwise: command = 1
4. **Attempts to connect to the robot's IP and port**, sends the command, and then stops the connection.
 5. **Prints the command** to the Serial Monitor for debugging.
 6. **Waits for a short period** before the next loop iteration.

####Copy the loop () function and paste it inside the loop() function on your code####

```
void loop() {  
  // Read acceleration data  
  sensors_event_t a, g, temp;  
  mpu.getEvent(&a, &g, &temp);  
  
  // Calculate pitch and roll  
  float pitch = atan2(a.acceleration.x, sqrt(a.acceleration.y * a.acceleration.y +  
a.acceleration.z * a.acceleration.z)) * 180.0 / M_PI;  
  float roll = atan2(a.acceleration.y, a.acceleration.z) * 180.0 / M_PI;  
  
  // Determine command to send  
  int command;  
  if (pitch > 15) {  
    command = 0;  
  } else if (pitch < -15) {  
    command = 2;  
  } else if (roll > 15) {  
    command = 4;  
  } else if (roll < -15) {  
    command = 3;  
  } else {  
    command = 1;  
  }  
}
```

```
// Send command to robot
if (client.connect(robotIP, robotPort)) {
  client.println(command);
  client.stop();
  Serial.println("Command sent: " + command);
} else {
  Serial.println("Connection to robot failed");
}

delay(100); // Adjust delay as needed
}
```

Finally, upload the code to your ESP32 module. After the project has been successfully built, you can use the gesture controller to operate the robot. This innovative setup allows you to control the robot's movements simply by using your hand gestures. The gesture controller interprets your motions and translates them into commands, enabling a seamless and intuitive way to interact with your robotic project.

Activities

1. Try to move the Micro mouse between tables/paths
2. Make a video presenting the build of the gesture device, and how you completed the activities and challenges. Share it with the Build Club Community on the Discord Server!