



	1	2	3	4	5	6	7	8	
A	SAM CPU replacement board, draft 0.2, drawn from docs/ARCHITECTURE.md. Licence: CERN-OHL-S v2. A Raspberry Pi 4 on the 40-pin header J21 runs PinMAME + ppuc (HDMI stays on the Pi). The RP2354B drives the original IO power driver board on J9 and scans the switches. Connector names and pinouts follow the original CPU/Sound board 520-5246-00. Each connector sits on the same page as the circuit that drives or reads it. Signals between pages use global labels; the numbers in brackets next to a label list the other pages it goes to.								
B	Power Power: +5 V mux (external / J11), 3.3 V, 4.5 V, supply monitors File: power.kicad_sch		MCU and Pi RP2354B SAM IO controller and Raspberry Pi 4 header File: mcu.kicad_sch		IO bus J9: bus to the IO power driver board (IO board J1) File: io_bus.kicad_sch				
C	Switch columns Switch matrix columns: 74HC595, strobe drivers, J1 File: sw_columns.kicad_sch		Switch rows 1-8 Switch matrix returns 1-8: J6, LM339 front end, 74HC165 File: sw_rows_1.kicad_sch		Switch rows 9-16 Switch matrix returns 9-16: J12, LM339 front end, 74HC165 File: sw_rows_9.kicad_sch				
D	Dedicated switches 1-16 Dedicated switches D1-D16 (J2, J3) and coin door memory protect File: sw_dedicated_1.kicad_sch		Dedicated switches 17-24 Dedicated switches D17-D24 (J13) and DIP switches File: sw_dedicated_2.kicad_sch		Display and GI J5 original DMD driver and J18 GI dimmer header File: display_gi.kicad_sch				
E	Audio Audio: Pi I2S -> PCM5102A -> 2 x TDA2030A on +-12 V -> J10 File: audio.kicad_sch								
F								Stern SAM CPU PPUC (CERN-OHL-S v2) Sheet: / File: sam_cpu.kicad_sch Title: SAM CPU replacement board Size: A3Date: 2026-10-06Rev: 0.2 KiCad E.D.A. 10.0.6Id: 1/11	
	1	2	3	4	5	6	7	8	

J11 keeps the original CPU board pinout (IO board J16 harness): +5 V, +−12 V and ground.
External +5 V on J17 has priority: U2 turns the J11 path off whenever +5V_EXT is present (EXT_PRESENT high).
LTC4412 + AO3401A ideal diodes stand in for the TPS2121 of ARCHITECTURE.md 9.3 (library part, about 4 A per path).
JP1 (bridged by default) disconnects the J11 +5 V completely: leaving J17 unplugged forces J11.


External +5 V (J17, priority)




IO board power (J11)




3.3 V



Supply monitors (RP2354B ADC)



4.5 V for the switch matrix



Stern SAM CPU PPUC (CERN-OHL-S v2)

Sheet: /Power/
File: power.kicad_sch

Title: Power: +5 V mux (external / J11), 3.3 V, 4.5 V, supply monitors


Size: A3 Date: 2026-10-06

KiCad E.D.A. 10.0.6

Rev: 0.2

Id: 2/11

GPIO map: ARCHITECTURE.md 9.2. PIO0 bus on GPIO0–15, PIO1 switch chain on GPIO16–20, PIO2 DMD on GPIO21–27, GPIO31 coin door memory protect.
Core supply from the internal switching regulator: VREG_LX -> L1 -> DVDD (1.1 V); VREG_AVDD through 33 R / 4.7 uF. Check against the RP2350 hardware guide.
Raspberry Pi 4 on the 40-pin header J21 (HDMI stays on the Pi). The Pi is powered from the board +5 V; never plug the Pi USB-C supply at the same time.



ARCHITECTURE.md 3.1–3.2. The doc calls this connector J1 (its name on the IO board); on the CPU board it is J9. Both buffers are off at power-up (BUS_OE_N pulled high) and NBRESET is held low until the firmware releases it. 33 R series resistors on the J9 side for the ribbon cable. Unused 74AHCT541 inputs tied low.

A

B

C

D

E

F

A


B

C

D

E

F



Stern SAM CPU PPUC (CERN-OHL-S v2)


Sheet: /IO bus/
File: io_bus.kicad_sch

Title: J9: bus to the IO power driver board (IO board J1)


Size: A3	Date: 2026-10-06	Rev: 0.2
KiCad E.D.A. 10.0.6		Id: 4/11

Id: 5/11

Per return (ARCHITECTURE.md 5.2–5.3): series diode from the connector, 1 k pull-up to +4.5 V, 220 R + 100 nF, LM339 against VREF (2.25 V). Output 1 = open, 0 = closed, as the ROM expects. Connector pin order follows the original drawing: check it with a meter.



Per return (ARCHITECTURE.md 5.2–5.3): series diode from the connector, 1 k pull-up to +4.5 V, 220 R + 100 nF, LM339 against VREF (2.25 V). Output 1 = open, 0 = closed, as the ROM expects. Connector pin order follows the original drawing; check it with a meter.



Stern SAM CPU PPUC (CERN-OHL-S v2)

Sheet: /Switch rows 9-16/
File: sw_rows_9.kicad_sch

Title: Switch matrix returns 9-16: J12, LM339 front end, 74HC165

Size: A3


Date: 2026-10-06

Rev: 0.2

KiCad E.D.A. 10.0.6


Id: 7/11

Per input (ARCHITECTURE.md 5.2–5.3): 1.5 k pull-up to +4.5 V (switch wetting current) and the original 39 k + 47 pF filter, plus 68 k to ground so the 3.3 V 74HC165 sees 2.8 V (open) or 0 V (closed). Connector pin to D-number order follows the original drawing: check it with a meter. Memory protect (J2 pin 10) uses the same filter with the original 4.7 k pull-up and goes straight to RP2354B GPIO31.




Stern SAM CPU PPUC (CERN-OHL-S v2)	
Sheet: /Dedicated switches 1-16/	
File: sw_dedicated_1.kicad_sch	
Title: Dedicated switches D1-D16 (J2, J3) and coin door memory protect	
Size: A3	Date: 2026-10-06
KiCad E.D.A. 10.0.6	Rev: 0.2
	Id: 8/11

Per input (ARCHITECTURE.md 5.2–5.3): 1.5 k pull-up to +4.5 V (switch wetting current) and the original 39 k + 47 pF filter, plus 68 k to ground so the 3.3 V 74HC165 sees 2.8 V (open) or 0 V (closed). Connector pin to D-number order follows the original drawing: check it with a meter. The 8 DIP switches are read through the last 74HC165 of the chain (U14), whose serial input is tied low.




J5 pinout read from the original drawing (ARCHITECTURE.md 8): signals on odd pins, ground on even pins. Confirm with a meter (Q18).
The 100 k pull-downs keep the DMD lines low while the RP2354B boots.
J18 is the default GI dimmer link of ARCHITECTURE.md 10.2: +5 V, GND, GI_PWM, GI_SPARE.

Original DMD (J5)



GI dimmer board link (J18)



Same structure as the original (DAC + two TDA2030A on +-12 V, speakers on J10). Volume stays digital (ROM / PinMAME).
Gain: $22k / 4.7k$ input divider $\times (1 + 22k / 1k) =$ about 4 overall. Starting values, to check on the bench.

