# Project planning report

Saved project inputs and selected calculation results

2026-10-25 13:38:28.169011+00:00

## Project

This report presents saved project inputs and the original results of the selected calculations. Country-specific requirements, electrical design and installation checks remain open. It does not approve the complete installation.

| | |
|---|---|
| Project | Berlin · Beispielprojekt · PV und Speicher |
| Project reference | c7795bc2c1e14e389622015c809ace45 |
| Input revision | 20 |

## Site and project inputs

| | |
|---|---|
| Location | Berlin · Beispielstandort |
| Country | DE |
| Time zone | Europe/Berlin |
| Project note | Interaktives Beispiel mit echten JRC-Wetterdaten und nachgewiesenen Trina-Moduldaten; Dachgeometrie und Verbrauch sind Beispielannahmen. |

## Equipment checks

Country requirements are not assessed by the selected calculations.

| | |
|---|---|
| Assessment status | Further checks required |

## Converter output

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 10 kW |
| Source document · Page 2 | 10000 W<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Grid phases

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 3 |
| Requirement | 3 |

## PV input power

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 20 kWp |
| Requirement | 11.04 kWp |
| Source document · Page 2 | 20000 Wp<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## PV strings and inputs

| | |
|---|---|
| Assessment status | Further checks required |

## Required accessory

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | SAJ BC2-HV1 |

## Manufacturer pairing

| | |
|---|---|
| Assessment status | Further checks required |

## Module count

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 4 |

## Parallel arrangement

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 1 |

## Battery voltage

| | |
|---|---|
| Assessment status | Checked requirements met |
| Source document · Page 2 | 180~800 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |
| Source document · Page 2 | 89.6-115.2 / 179.2-230.4 / 268.8-345.6 / 358.4-460.8 / 448-576.0 V<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Sales unit

| | |
|---|---|
| Assessment status | Checked requirements met |
| Source document · Page 2 | battery_module<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Usable energy

4.5 × 4 = 18 kWh

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 18 kWh |
| Requirement | 18 kWh |
| Source document · Page 2 | 4.5 kWh<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Continuous AC discharge power

| | |
|---|---|
| Assessment status | Further checks required |
| Requirement | 10 kW |

## Battery discharge path

| | |
|---|---|
| Assessment status | Further checks required |

## Components and manufacturer conditions

The H2 T3 ships with a smart meter, three current transformers and a 10 m meter communication cable (H2 manual, section 2.2 Unpacking, PDF p. 36 English / p. 7 German).

SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and the B2 manual (V1.2, PDF p5) says the B2 can only be used as such a set: the control module is an article of its own.

SAJ's Configuration Instructions V1.0 (Section 2) give the H2 series system as H2 + BC2 + BU2. SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and SAJ's B2 manual (V1.2, PDF p5) says the B2 can only be used as a set with SAJ's H2 high voltage series storage inverter. The listing does not cover the one-module B2-5.0, whose operating voltage lies below the H2 T3's battery voltage range.

One BU2-5.0 module alone operates at 89.6 to 115.2 V (SAJ's B2 datasheet gives this for the one-module B2-5.0), below the H2 T3's battery voltage range of 180 to 800 V; two modules operate at 179.2 to 230.4 V.

| | |
|---|---|
| Source document · Page 36 | https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf |
| Source document | https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf<br>https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf |
| Source document | https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf |
| Source document · Page 2 | https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |
| Source document · Page 37 | https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf |

## Provisional bill of materials

This provisional list comes from the selected saved equipment result. Quantities are shown only where established. It is not a complete installation bill of materials. Further components and open requirements need project-specific assessment.

| Quantity | Product | Reference |
|---|---|---|
| 1 | SAJ H2-10K-T3 | DLK-SAJ-H210KT3 |
| 1 | SAJ BC2-HV1 | DLK-SAJ-BC2HV1 |
| 4 | SAJ BU2-5.0-HV1 | DLK-SAJ-BU250HV1 |

## Energy scenario and selected equipment

These checks compare the saved scenario parameters with the equipment selected for this calculation. They do not establish manufacturer performance.

4.5 × 4 = 18 kWh

| | |
|---|---|
| Assessment status | Further checks required |
| Model | SAJ BU2-5.0-HV1 |
| Model | SAJ BC2-HV1 |
| Model | SAJ H2-10K-T3 |
| Module count | 4 |

| | |
|---|---|
| Parallel arrangement | 1 |
| Usable energy · Source document · Page 2 | 4.5 kWh<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

| Check | Assessment status | Result | Requirement |
|---|---|---|---|
| Usable energy | Checked requirements met | 18 kWh | 18 kWh |
| Continuous AC discharge power | Further checks required | — | 10 kW |
| Scenario operating mode | Checked requirements met | — | — |
| Storage losses and operating conditions | Further checks required | — | — |
| Converter ports and system topology | Further checks required | — | — |

## Energy scenario

PV generation and curtailment are calculated at the DC bus; load supply and grid flows are calculated on the AC side. Storage results use the saved loss assumptions.

Battery temperature is a fixed scenario condition used to check the documented charging and discharging temperature ranges. It is not inferred from outdoor weather. This model uses fixed loss assumptions and does not simulate temperature changes.

| | |
|---|---|
| Simulated load demand | 1.103 kWh |
| PV generation (DC) | 9.634 kWh |
| Grid import | 0 kWh |
| PV export | 0 kWh |
| PV curtailment (DC) | 0 kWh |
| Unserved simulated load | 0 kWh |
| Solar share of gross demand | 100 % |
| PV used or stored on site | 100 % |
| Calculated intervals | 2 |
| Battery temperature for this scenario | 20 °C |

## Saved calculation references

| | |
|---|---|
| Data source | Beispielannahme · kein externer AC-Hilfsverbrauch |
| Data source | Declared reference assumptions: DC/DC 98% each way, storage 99% each way, forward inverter 96%, fixed battery temperature 20 °C, zero internal and DC auxiliary demand and standing loss. No reverse charging. These are scenario assumptions, not manufacturer performance data. |
| Data source | Beispielverbrauch · 6.000 kWh pro Jahr |
| Data source | JRC PVGIS typical meteorological year |
| Calculation reference | 4a89969354884bb79292f9ca000574c4 · Input revision 20 |