

# ECE 240 Formula Sheet

By Benjamin Kong & Lora Ma

## 1. Time-domain signals

A continuous-time signal takes the form

$$x(t + nT) = x(t) \quad n \in \mathbb{Z}.$$

A signal  $z(t) = \alpha x(t + aT_1) + \beta x(t + bT_2)$  will be periodic if

$$\frac{T_1}{T_2} = \frac{a}{b}$$

for some  $a, b \in \mathbb{Z}$ .

Let  $x(t)$  be some signal.

- The *total energy* is given by

$$E = \lim_{T \rightarrow \infty} \int_{-L}^L |x(t)|^2 dt.$$

- The *average power* is given by

$$P = \lim_{T \rightarrow \infty} \frac{1}{2L} \int_{-L}^L |x(t)|^2 dt.$$

- If  $x(t)$  is periodic,

$$P = \frac{1}{T} \int_0^T |x(t)|^2 dt.$$

$E$  finite  $\rightarrow$  **Energy signal**  $\rightarrow P = 0$ .

$E$  infinite and  $P$  finite  $\rightarrow$  **Power signal**.

Periodic signal  $\rightarrow$  **Power signal**.

Let  $x(t)$  be some signal.

- A *time shift* is represented by

$$x(t - t_0).$$

- A *reflection* is represented by

$$x(-t).$$

The *unit step signal* is defined as

$$u(t) = \begin{cases} 1 & t > 0, \\ 0 & t < 0. \end{cases}$$

A *rectangular pulse* is represented as

$$\text{rect}\left(\frac{t}{T}\right) = u\left(t + \frac{T}{2}\right) - u\left(t - \frac{T}{2}\right).$$

A *ramp signal* is represented as

$$r(t) = tu(t) = \begin{cases} t & t \geq 0, \\ 0 & t < 0. \end{cases}$$

The *unit impulse*  $\delta(t)$  (Dirac delta function) is defined as

$$\int_{t_1}^{t_2} x(t)\delta(t) dt = x(0) \quad t_1 < 0 < t_2.$$

It has the following properties:

- $\delta(t) = 0$  for  $t \neq 0$ ,

- $\int_{-\infty}^{\infty} \delta(t) dt = 1$ ,
- $\delta(-t) = \delta(t)$ , and
- $\delta(0) = \infty$ .

Some  $p(t)$  can be used as a model of a delta function if

- $p(t)$  is even,
- $\lim_{\epsilon \rightarrow 0^+} p(t) = +\infty$  for  $t = 0$ ,
- $\lim_{\epsilon \rightarrow 0^+} p(t) = 0$  for  $t \neq 0$ , and
- $\int_{-\infty}^{\infty} p(t) dt = 1$  for all  $\epsilon > 0$ .

If these conditions are satisfied, then

$$\lim_{\epsilon \rightarrow 0^+} p(t) = \delta(t).$$

The *sifting property* is represented as

$$\int_{t_1}^{t_2} x(t)\delta(t - t_0) dt = \begin{cases} x(t_0) & t_1 < t_0 < t_2, \\ 0 & \text{otherwise.} \end{cases}$$

If  $x(t)$  is continuous at  $t = t_0$ , the *sampling property* states that

$$x(t)\delta(t - t_0) = x(t_0)\delta(t - t_0).$$

The *scaling property* states that

$$\delta(at + b) = \frac{1}{|a|} \delta\left(t + \frac{b}{a}\right) \quad a \neq 0.$$

The derivative of  $\delta(t)$  is defined as

$$\int_{t_1}^{t_2} x(t)\delta'(t - t_0) dt = -x'(t_0) \quad t_1 < t_0 < t_2.$$

It has the following properties:

- $x(t) * \delta'(t) = \int_{-\infty}^{\infty} x(\tau)\delta'(t - \tau) d\tau = x'(t)$ ,
- $x(t)\delta'(t - t_0) = x(t_0)\delta'(t - t_0) - x'(t_0)\delta(t - t_0)$ ,
- $\int_{-\infty}^t \delta'(\tau - t_0) d\tau = \delta(t - t_0)$ , and
- $\delta'(-t) = -\delta'(t) \rightarrow \int_{-\infty}^{\infty} \delta'(t) dt = 0$ .

## Continuous-time systems