

CHIPOWER PRODUCT CATALOG

■ ULTRA-SMALL STEP-UP DC-DC CONVERTER & CONTROLLER

Part NO.	Iout(Typ.)	Isw	Vin	Vout	Eff	Fsw & Mode	EXT	Enable	Typical Feature	Packages
CE8301A/C	400mA	0.8A	0.9~6V	1.9~5.5V	85%	100kHz@PFM		C:√	Ultra Low Iq=5μA	SOT89-3/5, SOT23-3/5, TO-92
CE8301B/D	1A	-	0.9~6V	1.9~5.5V	85%	100kHz@PFM	√	D:√	High Current	SOT89-3/5, SOT23-3/5, TO-92
CE8303A/C	500mA	1A	0.9~6V	1.8~5.5V	87%	300kHz@PFM		C:√	Low Output Noise	SOT89-3/5, SOT23-3/5, TO-92
CE8303B/D	2A	-	0.9~6V	1.8~5.5V	87%	300kHz@PFM	√	D:√	High Current	SOT89-3/5, SOT23-3/5, TO-92
CE8304	20mA@12V	0.4A	2.0~5.5V	Vin~28V	89%	1MHz@PFM		√	Adjustable Highvoltage Output Low Iq=20μA	DFN2X2-6, SOT23-5/6
CE8401A/B	300mA	1A	0.9~6V	1.8~5.0V	95%	400kHz@PFM		B:√	Sync, Low Iq=15μA	SOT89-3, SOT23-3/5, SOT23, TO-92
CE8400	500mA	1.1A	0.9~5V	2.5~5.25V	95%	600KHz@PWM		√	Sync. Rectifier	SOT23-6
CE8406	500mA	1.2A	0.5~4.5V	2.5~5.25V	95%	600KHz@PWM		√	Sync, True Output Load Disconnect when Shutdown	SOT23-6
CE8405	500mA	1A	0.9~5V	1.8~5.0V	95%	500KHz@PWM/PFM		√	Sync, Low Iq, True Output Load Disconnect when Shutdown	SOT23-6
CE8407	100mA	400mA	0.9~5V	1.8~5.5V	0.96	PFM		√	Sync, Low Iq	SOT23-6, SC70-6
CE9908A/B	1A	-	0.9~6V	Adj.	85%	100kHz@PFM	√	B:√	Adjustable Output	SOT23-5, SOT89-5

■ STEP-DOWN DC-DC CONVERTER

Part NO.	Iout(Typ.)	Isw	Vin	Vout	Eff	Fsw & Mode	Recommended Inductor(μH)	Typical Feature	Packages
CE8503	800mA	1.5A	2.0~6.5V	0.6~5.0V/Adj.	96%	1.5MHz@PFM/PWM	1.5~3.3	Sync.Hiccup-Mode Output Undervoltage Protection	SOT23-5

■ ULTRA-SMALL HIGH-PRECISION VOLTAGE DETECTOR & RESET IC

Part NO.	Vin	Detection Voltage	Output Forms	Quiescent Current	Accuracy	Delay	Packages
CE8803	0.7~6.0V	0.9~2.0V	CMOS/Nch	1μA	±2%/±1%	Ultra Low Detect Voltage, No Delay	SOT89-3, SOT23-3, SOT23-5, SOT343(SC-82), TO-92
CE8808	0.95~7.0V	1.5~6.0V	CMOS/Nch	1μA	±2%/±1%	No Delay	SOT89-3, SOT23-3, SOT23-5, SOT343(SC-82), TO-92
CE8809	0.95~7.0V	1.5~6.0V	CMOS/Nch	1μA	±2%/±1%	200ms(Typ.), 50~400ms Selectable	SOT89-3, SOT23-3, SOT23-5/6, SOT343(SC-82), TO-92
CE8810	0.95~7.0V	1.5~6.0V	CMOS/Nch	1μA	±2%/±1%	200ms(Typ.),50~400ms Selectable,Active-High Output	SOT89-3,SOT23-3,SOT23-5/6,SOT343(SC-82),TO-92
CE8818	0.7~7.0V	0.8~5.0V	CMOS/Nch	1μA	±2%/±1%	External Delay Capacitor	SOT23-5,SOT343(SC-82)

■ CMOS LOW DROPOUT LINEAR REGULATOR

Part NO.	Vin	Vout	Iout(Typ.)	Quiescent Current	Accuracy	Enable	Typical Feature	Packages
CE6200A/B	2.0~6.0V	1.0~5.0V	500mA	50μA	±2%/±1%	B:√	High PSRR(75dB@1kHz), Low Noise	SOT23-3/5, SOT-353(SC70-5), SOT89-3/5, DFN1X1-4, FBP1x1-4
CE6204A/B	1.8~6.0V	0.85~5.0V	500mA	45μA	±2%	B:√	High PSRR,Low Noise,with OTP	SOT23-3/5,SOT-353(SC70-5),SOT89-3/5
CE6205A/B	1.8~6.0V	1.05~5.0V	500mA	50μA	±2%/±1%	B:√	High PSRR, Low Noise, Low dropout	SOT23-3/5, SOT-353(SC70-5), SOT89-3/5, DFN1X1-4
CE6210A/B	2.0~6.0V	1.1~5.0V	1000mA	80μA	±2%/±1%	B:√	High Speed, High PSRR	SOT23-5, SOT89-3/5, SOT-223
CE6218E	2.0~6.0V	0.9~5.0V	300mA	5μA	±2%/±1%	√		SOT23-5
CE6219P	2.0~6.0V	0.9~5.0V	300mA	5μA	±2%/±1%			SOT23-3/5,SOT89-3,TO-92
CE6230A/B	2.0~7.0V	1.2~5.0V	500mA	5μA	±2%/±1%	B:√	High PSRR@Low Current Consumption	SOT23-3/5,, SOT89-3/5,TO-92,SC70-5 DFN1X1-4, FBP1x1-4
CE6206	2.0~7.0V	1.2~5.0V	300mA	5μA	±2%/±1%	B:√	High PSRR@Low Current Consumption	SOT23-3/5,, SOT89-3/5,TO-92,SC70-5 DFN1X1-4, FBP1x1-4

CE6232A/B	1.8~8.0V	1.2~5.0V	500mA	0.8μA	±2%/±1%	B:√	High PSRR & Low Noise@Ultral Low Current Consumption	SOT23-3/5, SOT89-3/5,TO-92, DFN1X1-4 FBP1×1-4
CE6233A/B	1.8~6.0V	1.0~5.0V	300mA	0.8μA	±2%/±1%	B:√	High PSRR@Low Current Consumption	DFN1X1-4
CE6260A/B	2.0~6.0V	0.9~5.0V	500mA	5μA	±2%/±1%	B:√	High PSRR@Low Current Consumption	SOT23-3/5, SOT89-3/5
CE6275A	2.0~30V	2.8~5.0V	150mA	2.5μA	±2%/±1%		High Voltage Input	SOT89-3, SOT23-3/5, TO-92
CE6301A/B	2.5~18.0V	1.2~5.0V	300mA	2.0μA	±2%/±1%	B:√	High PSRR & Low Noise@ Low Current Consumption	SOT89-3/5, SOT23-3/5, TO-92
CE6311A/B	2.5~18.0V	1.2~5.0V	500mA	2.5μA	±2%/±1%	B:√	High PSRR & Low Noise@ Low Current Consumption	SOT89-3/5, SOT23-3/5, TO-92
CE6303A/B	2.5~28V	1.2~12.0V	300mA	1.8μA	±2%/±1%	B:√	High PSRR & Low Noise@ Low Current Consumption	SOT89-3/5,SOT23-3/5,TO-92
CE6375A	2.5~36V	1.8~12V	250mA	2μA	±2%/±1%		High PSRR & Low Noise@ Low Current Consumption	SOT89-3, SOT23-3/5, TO-92,SOP8-PP
CE6300	1.8~7.0V	0.6~5.5V	500mA	45μA	±2%	√	Adjustable Output, High PSRR(70dB@1kHz), Low Noise	SOT23-5/6, SOT-353(SC70-5), DFN2X2-6
CE6601A/B	2.5~60V	1.2~12V	150mA	3μA	±2%/±1%	B:√	High Voltage Input	SOT89-3/5,SOT23-3/5,SOT223,TO-92

■ BATTERY CHARGER

Part NO.	Vin	Vfloat	Typical Feature	Cell Chemistry	Control Topology	Packages
CE3102X	4.25V~6.5V	4.2V	120mA Li-Ion/Li-polymer Battery Charger, Without Trickle Charge, 0.2C Charge Termination	Li-Ion/Li-polymer	Linear	SOT23-5,TDFN1.8X2.0-6
CE3150A	4.5V~6.5V	4.2V/4.35V	800mA Li-Ion/Li-polymer Battery Charger	Li-Ion/Li-polymer	Linear	SOT23-5, SOT89-5
CE3158	4.0V~6.5V	3.9V	500mA LiFePO4 Battery Charger	LiFePO4	Linear	SOT23-5
CE3154	4.5V~6.5V	4.2V/4.35V	800mA Li-Ion/Li-polymer Battery Charger	Li-Ion/Li-polymer	Linear	SOT23-5/6, SOT89-5, TDFN1.8X2.0-6
CE3168	4.5V~24.0V	4.2V/4.35V	600mA Li-Ion/Li-polymer Battery Charger, With 0.3C Trickle Charge, 0.3C Charge Termination, And 6.5V OVP	Li-Ion/Li-polymer	Linear	SOT23-5,SOT23-6
CE3169	4.5V~24.0V	4.2V/4.35/4.4V	600mA Li-Ion/Li-polymer Battery Charger, With 0.3C Trickle Charge, 0.3C Charge Termination, And 6.5V OVP	Li-Ion/Li-polymer	Linear	TDFN2.0X2.0-8
CE3211	4.5V~6.5V	4.2V/4.35V	1A Li-Ion/Li-polymer Battery Charger	Li-Ion/Li-polymer	Linear	SOP8-PP(ESOP8)
CE3213	4.5V~6.5V	4.2V/4.35V	1A Li-Ion/Li-polymer Battery Charger	Li-Ion/Li-polymer	Linear	DFN3X3-6
CE3221	4.5V~24.0V	4.2V/4.35V	1.2A Li-Ion/Li-polymer/LiFePO4 Battery Charger, With 6.5V OVP	Li-Ion/Li-polymer	Linear	SOP8-PP(ESOP8) DFN3*3-10,DFN2*3-10

■ USB FIXED & ADJUSTABLE CURRENT LIMITED LOAD SWITCH

Part NO.	Vin	Quiescent Current	Current Limit	RDS(ON)	Typical Feature	Packages
CE1610	2.5V~5.5V	9μA	Adj. 1A@RSET=6.8kΩ	145mΩ	Adjustable Current-Limited	SOT23-5
CE1615	2.5V~5.5V	9μA	Adj. 1.6A@RSET=6.8kΩ	145mΩ	Adjustable Current-Limited	SOT23-5

■ USB DEDICATED CHARGING PORT CONTROLLER

Part NO.	Number of Controller	Charging Schemes (DCP_AUTO)			1.2V mode (D+/D- shorted and bias to 1.2V)	BC1.2 and YD/T 1591-2009 mode (D+/D- shorted)	Packages
		Divider 1 (D+/D- = 2.0V/2.7V)	Divider 2 (D+/D- = 2.7V/2.0V)	Divider 3 (D+/D- = 2.7V/2.7V)			
CE1501	Single	Yes	Yes	No	Yes	Yes	SOT23-5/6
CE1502	Dual	Yes	Yes	No	Yes	Yes	SOT23-6

■ HALL SWITCH

Part NO.	Vin	Features	Iddavg	Top	Tp	Packages
CE1001	1.8V~5.5V	CMOS High Sensitivity	3μA	100μs	140ms	SOT23-3, TO-92S
CE1003	2.3V~5.5V	CMOS High Sensitivity	5μA	50μs	50ms	SOT23-3/5, TO-92S
CE1014	2.3V~5.5V	Transmission Gate Output	30μA	50μs	7ms	SOT23-5

■ CHARGE PUMP (INDUCTORLESS) DC-DC CONVERTER							
Part NO.	Features		Vin	Vout	Accuracy	Typical Feature	Packages
CE7660	Charge Pump DC-DC Voltage Converter		2.5~10V	Adj.	99.90%		SOP8, DIP8
■ LED DRIVER							
Part NO.	Vin	Power Output		Shutdown Current	Typical Feature		Packages
CE9401	0.9V~6.0V	Output Current 1A(Typ.)		<1μA	3W Boost WLED Driver,Vomax=5V		SOT23-6, SOP8-PP(ESOP8), DFN3X3-10
CE9910	2.5V~6.0V	Output Current 1A(Typ.)		<1μA	3W PWM Synchronous Step-Down WLED driver		SOT23-5
■ AUDIO POWER AMPLIFIER							
Part NO.	Vin	Power Output	External RF	PSRR		Shutdown Current	Packages
CE0030A	2.2V~5.0V	1W@(5.0V&1%THD)		83dB@217Hz (VDD>3V)		0.01μA	DICES, SOP8, SOP8-PP, DIP8
CE0030/B	2.4V~6.8V	1W@(5.0V&1%THD)		83dB@217Hz (VDD>3V)		0.01μA	DICES, SOP8, SOP8-PP, DIP8
CE0031A	2.0V~6.8V	1.6W@(5.0V&1%THD)	√	70dB@1kHz (VDD=5V)		0.1μA	SOP8, SOP8-PP, MSOP8, MSOP8-PP
CE0032A	2.0V~6.8V	1.6W@(5.0V&1%THD)	√	70dB@1kHz (VDD=5V)		0.1μA	SOP8