*

Inhaltsverzeichnis

1 Intro

How to prepare and create an SD-Card or USB Stick Boot-Image for RasPi 2 or 3

to be able to run the AS Software.

Basic Elements: Linux is ArchLinuxArm because it has most flexibility and newest drivers.

The Installation is with Xorg and jre for JavaFX. All activations are made with SYSTEMD.

Watchmen is running in parallel to GUI. (Simple WebServer for system analysis)

Hardware: RasPi 2 or 3 with Touch Screen 800x480 and USB Audio Interface.

Audio Interfaces are more stable in arch linux than in raspbian (why)

Symtom: audacity sometimes stopps recording in raspbian.

Arch is a pure systemd system.

2 Image prepare

2.1 Parting

Plan: part1 256M part2 7G

Part1:

Part 1Sector Start 2048

Size Part1[sectors]: (256 * 1024 * 1024 – 2048 * 512) / 512 = 522240

Part 2:

Start Part2[Sectors]: 256 * 2^20 / 512 = 524288

Size Part2[Sectors]: 7 * 2^30 /512 = 14680064

dd size: (7 * 2^30 + 256 * 2^20) / 2^20 = 7424

TRAP: Knoppix background file system vFat does not allow 7G Filesize

UNTRAP: use with overlay .. allowes big files inside knoppix (not at mouunt system)

2.2 bootline

For USB Stick .. change bootdrive to sda1 (ala?)

2.3 Extending config.txt

Remove black borders

disable_overscan=1

For hifiberry amp and amp+

dtoverlay=hifiberry-amp

For Hifiberry amp2

dtoverlay=hifiberry-daclpus

For Touchscreen

```
max_usb_current=1
hdmi_force_hotplug=1
config_hdmi_boost=7
hdmi_group=2
hdmi_mode=1
hdmi_mode=87
hdmi_drive=1
hdmi_cvt 800 480 60 6 0 0 0
```

Uart

```
enable_uart=1
```

3 Creating

TRAP: ArchLinux requires bigger first partition than Raspbian.

tar -xvzf <file.tar.gz> -C <destination>

??? -p preserve file attributes

Use script

age.sh

to get the ala archieve file

TRAP: use rpi-2 image for raspi 3 too

Use script

make_image.sh

To create an image for arch linux

change config.txt for USB Stick usage

TODO every script mount and unmount losetup

4 First Install and Update

After starting image … log into arch linux with putty

Login as alarm; su to root (both name = passwd) (no root on ssh)

```
loadkeys de
```
at Terminal usage.

Two commands by install advise

```
pacman-key --init
pacman-key --populate archlinuxarm
```

Init the update system

```
pacman -Sy
pacman -Su
```

Special tool found necessary

```
pacman -S mc
```

nstall xorg in arch with optional lxde

    pacman -S xorg
    pacman -S xterm
    pacman -S lxde
    pacman -S xorg-xinit
start with

    startx startlxde

PROBLEM: xorg istall is incomplete; after 2nd reboot sd card is corrupted and usb does not start
maybe: arch linux runs only from sd card

SUXXESS:

Everything from SD Card; not USB Stick

    pacman -S xf86-video-fbdev
File

    ~/.xinitrc
contains

    startlxde
start with

    startx
you should see running lxde

5 Run Tests

5.1 Audio Test

Install audacity

    pacman -S audacity
Audio Interfaces are not visible

must install

    pacman -S alsa-lib
then audio interfaces are visible in audacity

    pacman -S alsa-utils
then alsamixer is avaiable

5.2 Ensemble8

Test with bellsoft jre 9.....

Must run as root or problem with input

Bellsoft 11.0.2 lite does not contain FX

Must run big

Error message

    JavaFX detected no fonts! Please refer to release notes for proper font configuration

Check with

/usr/share/fonts

contains something

fc-list

shows many fonts

Adding lib/fonts with lucidia from other jdk goes to next step

Hint

https://www.raspberrypi.org/forums/viewtopic.php?t=71111

https://wiki.openjdk.java.net/display/OpenJFX/Font+Setup

Next

glGetError 0x505 == out of memory reported by the opengl gpu driver.

gpu_mem=256

Suxessful start script from ssh terminal

DISPLAY=:0.0 j9/bin/java -Dprism.useFontConfig=false -jar Ensemble8.jar

Mouse input on Ensemble8 … No keyboard input ???

--- no keyboard ??? … Start command:

j11b/bin/java -Dprism.useFontConfig=false -jar Ensemble8.jar

5.3 Standard Java Demos

Test mit:

jre8-openjdk

Standard Java Demos

krötenlangsam

alle Bellsoft stürzen ab

Cross Test

jre-openjdk

was 11 ist

Stürzt auch ab

11er Demos holen:

Aus zulu package (Azul Zulu)

Bellsoft J11b mit 11er Demo … geht so

-Xcomp

extem lange ladezeiten; dann nett

jre-openjdk mit 11er Demo: Zuckt ruckelt aber dann schnell

jre8-openjdk: -Xcomp : magic switch no effect

jre11-openjdk ohne magic switch etwas langsamer aber startet viel schneller

Ensble8 and bellsoft jre11 **ohne** X: surprise runs too … without keyboard

can only be stopped with a

```
killall java
```

5.4 Sun/Oracle jre

Access download requires name password !

https://docs.oracle.com/javase/8/embedded/develop-apps-platforms/jrecreate.htm

Use Script

```
ejdk.sh
```
to builsd sun jre.

Loading time and execution speed

BOOAAAAAHHHH

5.5 Sun with gluon 6

https://stackoverflow.com/questions/38359076/how-can-i-get-javafx-working-on-raspberry-pi-3

Combine sun jre with gluon 6 (Problem armv7 arm v6 ?????)

```
armv6hf-sdk/rt/lib/ext/jfxrt.jar --> jre/lib/ext/
armv6hf-sdk/rt/lib/arm/* --> jre/lib/arm/
armv6hf-sdk/rt/lib/javafx.platform.properties --> jre/lib/
armv6hf-sdk/rt/lib/javafx.properties --> jre/lib/
armv6hf-sdk/rt/lib/jfxswt.jar --> jre/lib/
```
exactly same problem as bellsoft11: no keyboard and block cursor after scrollbar usage

different failure message because of fonts

Start script Error message no Fonts

```
gluon/bin/java -jar Ensemble8.jar
```
starts:

```
gluon/bin/java -Dprism.useFontConfig=false -jar Ensemble8.jar
```
Lucidia fonts was already in sunjre.

5.6 Cross check Raspbian

With installed oracle jre … good performance

Ensemble8 with Liberica jre same symtoms … no keyboard and scrollbar cursor disappear

6 Prep 4 X

For german kezboard and Timezon the File

~/.xinitrc

must contain

```
setxkbmap de &
timedatectl set-timeyone Europe/Berlin &
startlxde
```

7 Add JRE

8 Other Linux commands

```
netstat -a -tcp
ps -aux
ip link show
```
CAN-Bus
```
ip link add type vcan
ip link add dev vcan42 type vcan
ip link del vcan42
```
Geht bei Raspi

9 Links

9.1 alarm

http://archlinuxarm.org

https://archlinuxarm.org/platforms/armv8/broadcom/raspberry-pi-3

Hints about X Server

https://wiki.archlinux.org/index.php/xorg

9.2 OpenJDK

https://wiki.openjdk.java.net/display/OpenJFX/Monocle

https://wiki.openjdk.java.net/display/OpenJFX/Font+Setup

https://wiki.openjdk.java.net/display/OpenJFX/OpenJFX+on+the+Raspberry+Pi

https://wiki.openjdk.java.net/display/OpenJFX/Platforms

https://wiki.openjdk.java.net/display/OpenJFX/Touch+screen+calibration+on+embedded+platforms

https://openjfx.io/javadoc/11/

9.3 Liberica jre

Company

https://www.bell-sw.com/

List of all releases

https://github.com/bell-sw/Liberica/releases/

9.4 Azul Zulu

https://www.azul.com/downloads/zulu/

https://www.azul.com/downloads/zulu/zulufx/

kein arm

9.5 Other

https://www.b4x.com/android/forum/threads/raspberry-pi-b4j-ui-applications-with-liberica-jdk.92950/

9.6 Hints

WorkEnvironement/Doc/Javarpi2_alarm.odt