



Exide Industries Limited
 Survey No. 246,
 Chichurakanapalli,
 Sevaganapalli Panchayath,
 Hosur Taluk, Krishnagiri Dist.,
 Tamilnadu Pin - 635 103.
 email: exidecorp@exide.co.in
 visit @ : www.exideindustries.com
 Ph : 09994458251-252,
 Fax : 04344-258255

**CONSTANT POWER DISCHARGE RATINGS IN WATTS PER BATTERY FOR EP PLUS
 AND NXT RANGE AT 27 Deg C**

Date : 20.08.2018

ECV (V)	BATTERY TYPE	DISCHARGE TIME IN MINUTES													
		10	15	20	30	45	60	90	120	180	240	300	360	480	600
10.8	18	376	299	248	184	167	164	83	71	50	41	34	30	23	19
	26	637	497	408	293	189	185	120	114	76	62	52	45	36	30
	28	643	502	412	296	191	187	121	115	77	63	53	46	36	30
	34	728	567	467	346	244	239	157	147	32	69	58	50	40	33
	42	980	763	629	475	299	293	194	180	124	101	84	73	58	48
	55	1192	929	766	579	401	393	254	243	162	132	110	96	76	63
	65	1590	1240	1022	772	479	470	300	292	191	156	130	113	90	74
	75	1788	1389	1150	864	537	526	347	328	216	178	150	131	104	84
	84	1862	1448	1196	900	594	582	388	362	238	196	165	144	114	92
	100	2323	1810	1491	1125	696	682	462	423	294	240	200	174	138	114
	120	2788	2172	1789	1350	834	818	554	508	353	288	240	209	166	137
	130	2839	2212	1822	1375	904	886	601	550	382	312	260	226	179	148
10.5	150	3485	2715	2237	1688	1043	1023	693	635	441	360	300	261	207	171
	160	3569	2780	2291	1728	1113	1091	739	677	470	384	320	278	221	182
	200	4646	3620	2982	2250	1391	1364	924	846	588	480	400	348	276	228
	18	399	310	255	189	172	169	89	72	52	42	35	31	24	20
	26	671	517	422	303	193	189	129	116	80	65	53	47	37	30
	28	678	522	426	306	195	191	130	117	80	65	54	47	37	31
	34	752	590	482	357	249	244	168	149	88	72	59	52	41	34
	42	1001	794	650	491	305	299	208	183	129	105	86	76	59	49
	55	1218	967	792	598	411	403	272	247	168	137	113	99	78	64
	65	1625	1290	1056	798	493	483	322	296	199	162	133	117	92	76
	75	1828	1445	1185	893	551	541	371	333	227	186	154	135	106	87
	84	1901	1505	1233	930	611	599	416	368	243	199	165	144	113	93
10.2	100	2370	1879	1537	1163	717	703	495	431	306	249	205	180	141	117
	120	2844	2255	1844	1395	860	844	594	517	367	299	246	216	169	140
	130	2896	2296	1878	1421	932	914	644	560	398	324	267	234	183	152
	150	3555	2819	2306	1744	1076	1055	743	646	459	374	308	270	212	176
	160	3640	2886	2361	1786	1147	1125	792	689	490	398	328	288	226	187
	200	4739	3758	3074	2325	1434	1406	990	861	612	498	410	360	282	234
	18	421	321	262	194	174	171	95	73	54	44	36	32	25	20
	26	705	536	436	313	197	193	137	117	83	67	55	48	37	31
	28	712	541	440	316	199	195	139	118	84	68	55	49	38	32
	34	777	612	498	369	254	249	180	151	89	72	58	52	40	33
	42	1022	825	671	507	311	305	222	185	134	108	88	78	61	50
	55	1244	1005	817	617	421	413	290	250	175	142	116	102	79	66
10.2	65	1660	1340	1090	823	506	496	343	300	207	168	137	121	94	78
	75	1867	1500	1220	921	566	555	396	337	239	194	158	140	108	90
	84	1941	1561	1270	960	628	616	444	373	253	205	167	148	114	95
	100	2416	1948	1583	1200	738	724	528	438	318	258	210	186	144	120
	120	2899	2338	1899	1440	886	869	634	526	382	310	252	223	173	144
	130	2952	2381	1934	1466	960	941	686	570	413	335	273	242	187	156
	150	3624	2922	2375	1800	1108	1086	792	657	477	387	315	279	216	180
	160	3711	2992	2432	1843	1182	1158	845	701	509	413	336	298	230	192
	200	4832	3896	3166	2400	1477	1448	1056	876	636	516	420	372	288	240

Points to be noted during Battery Sizing Calculation:

- Battery sizing to be done as per IEEE 485 Standard.
- Above wattage chart states the maximum wattage a single battery can deliver at 100% state of charge. Appropriate losses through UPS, cabling, heat, etc (Minimum of 10-15%) must be considered when battery sizing are done with single or parallel strings.
- Design margin and ageing factor must be considered for all battery sizing and it is mandatory to consider these factors in case of any sizing which includes site acceptance tests.
- Batteries will be at 90% state of charge when delivered from factory. 100% of capacity will be achieved with minimum 10 cycles of charge-discharge at full depth or under continuous float operation for 3 to 6 months.
- Minimum backup time of 10 minutes to be considered for battery sizing. Sizing for less than 10 minutes is not recommended.
- In case of any critical applications, battery sizing shall be vetted by EXIDE representative.

For EXIDE Industries Limited, Hosur.

Head Technical.
 VRLA Division, Hosur.

Regd. Office : Exide House, 59E, Chowringhee Road, Kolkata - 700 020. Ph: (033) 2283-2120/33/36/50
 Fax (033) 2283-2632/37, email: contact@exide.co.in, www.exideindustries.com
 CIN: L31402WB1947PLC014919

