

AIRSTREET · DESIGN DECISIONS REGISTER

AirStreet design decisions register

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	AST-DEC-001	Version	0.1
Status	Draft	Date	2026-09-30
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/airstreet		
Source	docs/06-design-decisions.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.1	2026-09-30	Amish Chadha	Register opened with the open decisions from REVIEW.md, the decision records and the build plan work

AirStreet design decisions register

Every design decision still to be made, and every decision made, in one place. Each decision is argued in full in its decision record under `docs/decisions/` ; this register is the index Amish works from. The build plan (`docs/05-build-plan.md`) describes the design as it stands and does not list open decisions.

■ Open decisions

#	Decision needed	Options	Recommendation	Affects in the build	Source
1	Design for construction as a whole: the changes that make the node buildable (adapter plates, 140° V-saddles, bands in saddle grooves, cross arm, two-part pod, cable entries, shield spacers and probe tube)	Accept; or ask for changes	Accept	The whole build plan	AST-DDR-003, Table 1
2	Mass on the pole: 3.84 kg (4.00 kg with FieldNode's sun shield) against R13's 3.5 kg	(a) raise the R13 limit to 4.0 kg, pole owner to confirm the load; (b) lighten (saddles at 40 % infill, 40 x 4 mm rail, 1.5 mm shield plates, windows in the adapter plates) to about 3.6 kg, still over; (c) both	(c)	Rail, plates and printed parts; first check "Mass"	AST-DDR-003, A1
3	Sensor head parts cost \$303.00 against the \$285 budget_usd	(a) raise budget_usd to \$305; (b) keep \$285 and recover \$18 with the open two-channel NO2 front end (PCB work, on hold with TRL 4); (c) cheaper band hardware and fixings at purchase	(a) for the prototype, (b) as the route back under \$285	Nothing in the build; the purchase list	AST-DDR-003, A2
4	Antenna whip 15 mm from the pod's drip lid (23 mm in the concept)	(a) accept and check the radio link with the pod fitted at TRL 4; (b) move the pod 8 mm further left	(a)	Pod position on the cross arm	AST-DDR-003, A3
5	First partner, city and reference station for co-design and collocation	Open; no recommendation made	None yet	Not part of the TRL 3 build; sets the radio band and the first site	AST-DDR-001, O1
6	FieldNode to accept its enclosure, plate clips and sun shield on AirStreet's two adapter plates in place of its back plate	Agree with FieldNode; or restore FieldNode's back plate (heavier)	Agree with FieldNode	Sections 3.3 and 3.5 of the build plan	AST-DDR-002 N2, AST-DDR-003
7	FieldNode to keep port B's 5 V supply on at all times for the NO2 bias, and to allow a 5 min interval on a private gateway	Agree with FieldNode	Agree	Pod wiring and FieldNode's firmware (not part of the TRL 3 build)	AST-DDR-002
8	Port pin assignment of FieldNode's two M12 ports	Agreed between FieldNode and the projects that use it	None yet (FieldNode's decision)	Pod wiring, section 3.10	FND-DDR-001, O2
9		Follows decision 5	None yet		

#	Decision needed	Options	Recommendation	Affects in the build	Source
	Radio band and antenna for the pilot region			FieldNode's antenna	FND-DDR-001, O1

■ To confirm when parts are bought

#	What to confirm	Why it matters	Source
1	The band roll and housings close round both an 80 mm and a 200 mm pole with the saddle, and the band maker's torque for about 1,000 N of preload	The slip and twist checks assume 1,000 N per band	AST-CAL-001 [F7], [G2]
2	The NO2 front end board's size and mounting holes (model: 86 x 55 mm, holes 76 x 43 mm apart) and how the B4 sensor connects to it	They set the back wall bosses and the lead length to the sensor	AST-DDR-003, P8
3	The particle sensor's interface select pin and logic levels on its datasheet	Sets the terminal block wiring	Build plan section 3.10
4	Heat-set insert sizes (M5 and M3) and the hole size their maker gives	The printed holes are drawn 6.8 and 4.0 mm	AST-DWG-102, 106, 109
5	The M8 4-pin socket's panel hole and the M16 glands' hole size	The pod's printed holes are 8.2 and 16.2 mm	AST-DWG-106
6	FieldNode's enclosure lug kit positions match FieldNode's back plate pattern	The adapter plates copy that pattern	FND-DDR-003
7	The FieldNode panel's frame has a flat back lip at least 12 mm wide	FieldNode's panel clips bolt through it	FND-DDR-003

■ Decisions made

Date	Decision	Decided by	Record
2026-09-25	TRL 2 review items D1 to D9: budget covers the sensor head only; pitch wording; NO2 collocation plan; NO2-B43F class sensor; ISB class front end bought first; SPS30 class particle sensor; 3.0 m inlets; 5 min records with raw signals; open data	Amish: "i accept all your recommendations, go with them across all repos."	AST-DDR-001, AST-DDR-002
2026-09-25	<code>budget_usd</code> \$285 for the sensor head; FieldNode back plate left off with the enclosure and bracket on the AirStreet rail; frontal area limit 0.15 m²; R3 (WHO guideline) withdrawn and kept as research; 60 s particle run; 5 min records on a private gateway and 15 min on The Things Network; FieldNode sun shield at sites above 45 °C; pre-collocated pod exchange for service	Amish, same instruction: go with recommendation	AST-DDR-002, N1 to N7