BUILD PLAN SKETCH, PLAN NOT YET BUILT

VoidScope · github.com/BoujeeEnjinia1701/voidscope

REV	DESCRIPTION	DATE	BY
P1	Making sketch for the prototype build plan	2026-10-24	AC
P2	VDS-DDR-003: steerable camera tip	2026-10-24	AC

TOP VIEW

Scale 1:5; looking down (along -Z)

FRONT VIEW

Scale 1:5; looking at the front (along +Y)

RIGHT VIEW

Scale 1:5; looking at the right side (alo

WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

Make four. Cut 1,050 mm, square, from 38.1 x 1.47 mm tube.
Deburr inside and out; the inside edge must not cut the cable.
Scribe a straight line along the tube: the button line (+Y).
Back end, sections 1 to 3: drill 8.5 mm on the button line,
30 mm from the end. This takes the next section's button.

Back end, section 4: no button hole; the tail cap pins go in
4.0 mm holes top and bottom, 20 mm from the end (step 2);
two 4 mm housing holes on top, 10.5 mm off centre,
332 and 368 mm from the back end.
Front end: the coupler pin holes, 4.0 mm top and bottom 30 mm
from the end, are drilled through with the coupler fitted.
Depth marks every 100 mm from the tip, section number at each
end, paint marker under clear heat-shrink.
Check: the next coupler slides in by hand with no rock.

VOIDSCOPE

github.com/BoujeeEnjinia1701/voidscope

VoidScope rod section (make 4): making sketch

DRAWING NO.	REV	SHEET	SIZE
VDS-DWG-101	P2	1 of 1	ANSI B

SCALE	UNITS	PROJECTION	DATE	DRAWN
1:5	mm		2026-10-24	Amish Chadha

MATERIAL / NOTES

6061-T6 drawn tube 38.1 x 1.47 mm (1.5 x 0.058 in)

Licensed CERN-OHL-S-2.0 · Design Molecule Lab · designmolecule.com

Generated from cad/src; do not edit by hand